Scan-path methods ease sequential-logic test

> Boards let IBM PCs emulate fax machines

New core materials help power-supply designers

ADEE preview

ELECTRONIC TECHNOLOGY FOR ENGINEERS AND ENGINEERING MANAGERS

Graphics ICs help the artist's muse take flight your test programs.

They're backed by strong factory support. From applications engineering and customer service. To a manufacturing group that hits over 98% of its committed first ship dates.

And we work closely with our distributors to help them work for you, too. With prototypes when you need them. Complete PAL and PROM programming services. Plus volume inventory levels.

So if your present supplier's idea of service and support is a hotline and a datasheet, consider

the alternative.

Monolithic Memories.

Where we're all pulling for you.

Now, it's your turn to drop us a line. Tell us in a sentence or two what service and support mean to you. And we'll send you a free full-size poster of the photo below.

Monolithic Memories, 2175 Mission College Blvd., Santa Clara, CA 95054. Attn: Literature

Dept., MS 09-14.

PAL is a registered trademark of Monolithic Memories, Inc. © 1986, Monolithic Memories, Inc.

Monolithic MM Memories CIRCLE NO 96



Like right about now.


Advanced products require advanced service and support. Unfortunately, they don't always go hand in hand.

Unless, of course, you go with Monolithic Memories.

First, we have some of the brightest Field Application Engineers this side of M.I.T. They know our PAL, PROM and advanced logic ICs inside and out.

What's more, they all have four to eight years of system design experience. And it shows.

Our FAEs will show you how to use our circuits and software to your best advantage. Troubleshoot your design problems. Even help you debug



Sometimes you need more than just a hotline.

See pages 16-17.

INTERSIL



ast Cost Resistors.



al Film Resistors give you a lot just a competitive selling price.

general purpose resistors. We guaran- CHECK THIS LINEUP tee our CCF-50 and CCF-55 commercial products will perform as specified without costly in-plant verification. And, we guarantee shipment will be made on our confirmed date. ZIP costs ou you no more, plus it has helped us forge disciplines that are the basis of "just in time" and quality "partnerships" now in place with major resistor users

Think it over and call Dale if you're ready to take a closer look at reducing resistor costs. We have the products and programs to help you get it done.

For more information, contact your Dale representative or phone 402-371-0080, Dale Electronics, Inc., 2300 Riverside Blvd., Norfolk, NE 68701.

Ultra Precision, tolerances to .01%, TC's to ±5 PPM/°C, matched sets available, Model PTF

Established Reliability, MIL-R-55182 (RNC), MIL-R-39017 (RLR) and MIL-R-122.

Military, MIL-R-10509 (RN), MIL-R-22684 (RL).

General Purpose, 1%, 2%, 5%, Model CCF.

Special Purpose, ultra high voltages, values and frequencies in a wide range of carbon film and metal oxide

models.

CLE NO 41

nationwide.

Your Best Source for SMD Test Accessories is POMONA ELECTRONICS

PATCH CORD; SMD GRABBER™ BOTH ENDS: MODEL 5301 SMD TEST TWEEZER™ TO BNC MALE: MODEL 5142 (SHOWN). TO TWO SINGLE STACKING BANANA PLUGS: MODEL 5143

DO-IT-YOURSELF SMD GRABBER™: MODEL 5243








SMD MICROTIP™ TEST PROBE TO SINGLE STACKING BANANA PLUG: MODEL 5144





Pomona Electronics
1500 E. Ninth St., Pomona, CA 91766
Tel: (714) 623-3463

68 PIN PLCC QUAD CLIP™ TEST CLIP: MODEL 5060





CABLE ASSEMBLY; SMD GRABBER™ TEST CLIPS TO BNC MALE: MODEL 5304



SOIC CLIP™ TEST CLIP: MODEL 5250 (8 PIN); 5251 (14 PIN); 5252 (16 PIN) SHOWN; 5253 (20 PIN); 5254 (24 PIN)



MOLDED BREAKOUT; SMD GRABBER" TEST CLIPS TO FEMALE BNC: MODEL 5305





Filts \$995

dc to 3GHz

- less than 1dB insertion loss over entire passband
- greater than 40dB stopband rejection
- 5 section, 30dB per octave roll-off
- VSWR less than 1.7 (typ)
- over 100 models, immediate delivery
- meets MIL-STD-202
- rugged hermetically sealed package (0.4 x 0.8 x 0.4 in.)
- BŇČ, Type N, SMÁ available

setting higher standards

Mini-Circuits

finding new ways ..

P.O. Box 166, Brooklyn, New York 11235 (718) 934-4500 Domestic and International Telexes: 6852844 or 620156

LOW PASS	Model	*LP-	10.7	50	70	100	150	200	300	450	550	600	750	850	1000
Min. Pass Band				48	60								700	780	900
Max. 20dB Stop Frequency (MHz)			19	70	90	147	210	290	410	580	750	840	1000	1100	1340
Prices (ea.): P	Prices (ea.): P \$9.95 (6-49), B \$24.95 (1-49), N \$27.95 (1-49), S \$26.95 (1-49)														

HIGH PASS	Model *HP-	50	100	150	200	300	400	500	600	700	800	900	1000
Pass Band (MHz	start, max.	41	90	133	185	290	395	500	600	700	780	910	1000
	end, min.	200	400	600	800	1200	1600	1600	1600	1800	2000	2100	2200
Min. 20dB Stop Frequency (MHz)		26	55	95	116	190	290	365	460	520	570	660	720

Prices (ea.): P \$12.95 (6-49), B \$27.95 (1-49), N \$30.95 (1-49), S \$29.95 (1-49)

*Prefix P for pins, B for BNC, N for Type N, S for SMA exal

example: PLP-10.7

CIRCLE NO 89

C105 REV. B





dc to 2000 MHz amplifier series

SPECI	FICATIONS	
Model	Frequency	

Model	Frequency MHz	Gain, dB (min.)	Max. Power dBm (typ)	NF dB (typ)	Price Ea.	\$ Qty.
MAR-1	DC-1000	13	0	5.0	0.99	(100
MAR-2	DC-2000	8.5	+3	6.5	1.50	(25)
MAR-3	DC-2000	8	+8	6.0	1.70	(25)
MAR-4	DC-1000	7	+11	7.0	1.90	(25)
MAR-7	DC-2000	8.5	+4	5.0	1.90	(25)
MAR-8	DC-1000	21	+ 10	3.5	2.20	(25)

designers amplifier kit, DAK-1

5 of each model, total 30 amplifiers only \$49.99


Unbelievable, until now...tiny monolithic wideband amplifiers for as low as 99 cents. These rugged 0.085 in.diam.plastic-packaged units are 50ohm input/output impedance, unconditionally stable regardless of load*, and easily cascadable. Models in the MAR-series offer from 7 to 21dB gain, 0 to +11dBm output, noise figure as low as 3.5dB (5.5dB typical), and up to DC-2000MHz bandwidth. *3:1 load VSWR for the MAR-8

Also, for your design convenience, Mini-Circuits offers chip coupling capacitors at 12 cents each*

Size (mils)	Tolerance	Temperature Characteristic	Value
80 × 50 80 × 50	5% 10%	NPO X7R	10, 22, 47, 68, 100, 470, 680, 1000 pf
120 × 60	10%	X7R	2200, 4700, 6800, 10,000 pf .022, .047, .068, .1μf

* MINIMUM ORDER 50 PER VALUE

Typical Biasing Configuration



finding new ways ... setting higher standards



P.O. Box 166, Brooklyn, New York 11235 (718) 934-4500 Domestic and International Telexes: 6852844 or 620156



ELECTRONIC TECHNOLOGY FOR ENGINEERS AND ENGINEERING MANAGERS



On the cover: Powerful graphics-processor ICs can amplify an artist's skills. The Superset system used to produce this issue's cover incorporates the TMS34061 video system controller; in the future, such systems will employ graphics engines like those discussed in this issue's Special Report (pg 112). Those engines will lower the systems' cost, but they won't do away with the need for artistic talent, as Regional Editor Margery Conner notes in this issue's Editorial (pg 47). The cover image and the wire-frame image on pg 113 were recorded on a Matrix OCR-Z film recorder. (Photo courtesy David Hamby Design, Torrance, CA)

DESIGN FEATURES

Special Report: Graphics engines

112

By offloading pixel-manipulation chores from a host CPU, graphics engines can provide higher resolution, more colors, and faster response in your graphics applications. Graphics engines also handle displaymemory access and generate CRT control signals.—Margery Conner, Regional Editor

CMOS ADC achieves reliable 12-bit resolution

131

It's not easy to achieve maximum performance from a 12-bit ADC. Conversion results can be quite misleading if you fail to adjust the converter's endpoints prior to operation. Such adjustments usually require that you calculate the overall converter error budget by combining offset, gain, and linearity errors into a total error spec.—John Reidy and John Wynne, Analog Devices

Interface various IC technologies to CMOS arrays

153

163

Many times you have no choice as to what device types your CMOS designs must work with. You need not despair: The key to interfacing devices made from dissimilar technologies lies in a simple analysis of each technology's voltage and current requirements.—Mark Stansberry, National Semiconductor Corp

Partition custom ICs along technology lines

Implementing analog circuitry on custom ICs can be a difficult task because such circuitry often uses a wide variety of device technologies. To divide your circuitry into the functional blocks appropriate for each IC technology, you must first know your system's requirements and the strengths and weaknesses of the various technologies.—Karl J Huehne, United Technologies Microelectronics Center

Designer's Guide to EDIF—Part 4

171

As you learned in the first three parts of this series, your CAE system can communicate with all CAE systems, ASIC foundries, and testers that can understand the Electronic Design Interchange Format (EDIF) data standard. To create a program that translates your system's data into and out of EDIF, get started with the simple programming steps described here in part 4.—Esther Marx, Hart Switzer, and Mike Waters, Motorola Inc

Continued on page 7



♥BPA ABP



EDN (ISSN 0012-7515) is published 45 times a year, biweekly with one additional issue in January, February, March, August, and December, two additional issues in April, June, July, September, and November, and three additional issues in May and October by Cahners Publishing Co, a Division of Reed Publishing USA, 275 Washington Street, Newton, MA 02158. William M Platt, President; Terrence M McDermott, Executive Vice President, Jerry D Neth, Vice President of Publishing Operations; J J Walsh, Financial Vice President Magazine Division; Thomas J Dellamaria, Vice President Production & Manufacturing; Frank Sibley, Group Vice President. Copyright 1987 by Reed Publishing USA, a division of Reed Holdings Inc; Saul Goldweitz, Chairman; Ronald G Segel, President and Chief Executive Officer, Robert L Krakoff, Executive Vice President. Circulation records maintained at Cahners Publishing Co, 270 St Paul St, Denver, CO 80206. Second class postage paid at Denver, CO 80202 and additional mailing offices. Postmaster: Send address changes to EDN, 270 St Paul St, Denver, CO 80206.

WHEN BUYING SWITCHES REMEMBER THREE THINGS.




53

67

79

89





Placing a multiplexer in front of each flip-flop sets the stage for scan-path testing. You can now find tools that allow you to implement the scan-path technique without sacrificing circuit performance and die size (pg 67).

TECHNOLOGY UPDATE

Add-in facsimile boards enable users of PCs to transfer CAE graphics in real time

With the advent of compression/expansion processor ICs, manufacturers of add-in boards for IBM PCs are now making fax expansion boards that permit you to use a PC as a fax machine to send graphics over the phone lines.—Chris Terry, Associate Editor

Scan-path tools speed the conversion of your design into a testable chip

You could employ scan-path design methodology to make your large chips (10,000 to 20,000 gates) more testable. But manually designing the additional test logic can lead to many other problems. Automated scan-path design tools, however, can speed the design process while minimizing die size increases and system performance losses.

—Chris Everett, Regional Editor

Magnetic materials provide the final piece to the high-frequency switching-supply puzzle

The magnetic materials used to construct a supply's transformer core are the limiting factor of high-frequency designs. The most recent introductions from magnetic-materials makers, however, provide acceptably low losses at moderately high frequencies.—Charles H Small, Associate Editor

ADEE West '87

Catch up on developments in computer-aided design at ADEE '87 in Anaheim, CA.—Joan Morrow, Assistant Managing Editor

PRODUCT UPDATE

Floating-point chip set	95
Low-cost digital pattern generator	99
Compact magnetic rotary encoder	100
20-nsec cache RAM	103
Voice-compression chip	104

DESIGN IDEAS

Linear load dissipates constant power	179
Bounds checker has DSP applications	180
PLD controls a RAM-based LIFO memory	180
MAC functions as a counter or divider	184
Pulse-delay circuit has dual-edge trigger	186

Continued on page 9

Advertising and editorial offices: 275 Washington St, Newton, MA 02158. Phone (617) 964-3030. Subscription offices: 270 St Paul St, Denver, CO 80206. Phone (303) 388-4511. EDN is circulated without charge to those qualified. Subscription to others: US, \$95/year, \$6/copy; Canada and Mexico, \$110/year, \$8/copy; Europe Air Mail, \$135/year, \$10/copy; all other nations Air Mail, \$200/year. Special issue prices may vary. Send requests for qualification forms and/or change of address to subscription office.

You've got to be pretty dense to send your PCB design to Forest Grove.

If you're working with high circuit densities, you need the exceptional prototype capabilities of our new Forest Grove, Oregon plant. We specialize in dense multi-layer and surface mount PCBs, using technologies refined and perfected by our own engineers.

Your blind and buried vias, fine line circuits, all your space-saving concepts will be faithfully

translated through our highly automated and rigorously controlled processes.

We also know all the ways to close the space between you and us. Our computer interface to your CAD system gets us off to a fast start. And from there, we go out of our way to make sure you get your prototype in a hurry — no matter where you are.

When it comes to PCB designs, it's smart to be dense. And we have the technology to prove it. So send your most sophisticated design to Forest Grove today. When you see your prototype tomorrow, you'll know it was well worth the trip. Call 1-800-222-2600 ext. 216 in the U.S., or 1-800-338-8800

ext. 216 in Canada.





	VP/Publisher	
F	Warren Dickson	

VP/Associate Publisher/Editorial Director Roy Forsberg

Editor Jonathan Titus

Managing Editor Rick Nelson

Assistant Managing Editor Joan Morrow

Special Projects Gary Legg

Home Office Editorial Staff 275 Washington St, Newton, MA 02158 (617) 964-3030

Tom Ormond, Senior Editor
Deborah Asbrand, Associate Editor
Joanne Clay, Associate Editor
Tarlton Fleming, Associate Editor
Eva Freeman, Associate Editor
Clare Mansfield, Associate Editor
Dave Pryce, Associate Editor
Charles Small, Associate Editor
Charles Small, Associate Editor
George Stubbs, Associate Editor
Chris Terry, Associate Editor
Jim Wiegand, Associate Editor
Valerie Lauzon, Staff Editor
Helen McElwee, Staff Editor
Cynthia B Rettig, Staff Editor
Steven Paul, Production Editor

Editorial Field Offices Margery S Conner, Regional Editor Newbury Park, CA: (805) 499-7901

Bob Cushman, Special Features Editor Port Washington, NY: (516) 944-6524

Chris Everett, Regional Editor San Jose, CA: (408) 296-0868

Steven H Leibson, Regional Editor Boulder, CO: (303) 494-2233

J D Mosley, Regional Editor Arlington, TX: (817) 465-4961 David Shear, Regional Editor San Jose, CA: (408) 296-0868

Maury Wright, Regional Editor San Diego, CA: (619) 748-6785

Peter Harold, European Editor 0603-630782 (St Francis House, Ougans Rd

(St Francis House, Queens Rd, Norwich, Norfolk NR1 3PN, UK) Contributing Editors

Robert Pease, Bob Peterson, Don Powers, Bill Travis

Editorial Services Kathy Leonard, Office Manager Loretta Curcio, Nancy Weiland, Sharon Gildea

Art Staff

Kathleen Ruhl, Art Director Chin-Soo Chung, Graphic Designer Deborah Queally, Graphic Designer

Production/Manufacturing Staff
William Tomaselli, Production Supervisor
Donna Pono, Production Manager
Beth Ann Cooper, Production Assistant
Andrew A Jantz, Production Assistant
Diane Malone, Composition

Graphics Director Norman Graf

VP/Production/Manufacturing Wayne Hulitzky

Director of Production/Manufacturing John R Sanders

Director of Research Deborah Virtue

Marketing Communications
Janice Molinara, Manager
Jennifer Ware, Communications Manager
John Bartlett, Marketing Projects Manager
Corie Rand, Promotion Coordinator
Anne Foley, Promotion Assistant

EDITORIAL

47

We have previously contested the suggestion that computers and software can make it unnecessary for humans to master basic writing skills. This issue's cover story, on graphics ICs, makes a similar warning appropriate for graphics-arts skills.

NEW PRODUCTS

Integrated Circuits	. 190
CAE & Software Development Tools	. 198
Computers & Peripherals	.204
Components & Power Supplies	
Test & Measurement Instruments	

PROFESSIONAL ISSUES

227

A study in contrasts: US engineers recall their visit to Japan.—Deborah Asbrand, Associate Editor

LOOKING AHEAD

241

Annual growth rate is 10.2% for rectifier market . . . Molecular electronic devices to be commercial by 2000.

DEPARTMENTS

News Breaks
News Breaks International
Signals & Noise
Calendar
Reader's Choice
Leadtime Index
Literature
Career Opportunities
Business/Corporate Staff
Advertisers Index

Cahners Publishing Company ☐ A Division of Reed Publishing USA ☐ Specialized Business and Consumer Magazines for Building & Construction ☐ Interior Design ☐ Electronics & Computers ☐ Foodservice & Lodging ☐ Manufacturing ☐ Book Publishing & Libraries ☐ Medical & Health Care ☐ Child Care/Development

At last, the ordinary microprocessor can take its rightful place in history.





It had to happen—the conventional microprocessor has had its day. Relegated to the ranks of yesterday's devices by the new transputer family from INMOS. It's history in the making.

The IMS T414 transputer is a fast, easy-to-use VLSI component, integrating a 32-bit processor, four intertransputer communication links, 2K bytes Static RAM, 32-bit memory interface and DRAM controller. All on a single CMOS chip—offering execution rates up to 10 MIPs.

While transputers excel in single-processor systems, their real power can be unleashed by connecting any number of transputers together via the high-speed serial links. Multi-transputer systems can deliver the performance you need today, and can be easily expanded in the future as your processing requirements increase.

And there's more. Programming multiprocessor systems has never been easier. The Transputer Development System (TDS) supports C, Fortran, Pascal and OCCAM, providing a complete software development environment, and is available for a number of popular hosts. Software developed on the TDS can be executed on one or more transputers, enabling cost-performance tradeoffs to be made.

INMOS transputers are available now and have already found their way into companies who are evaluating, prototyping and manufacturing transputer-based systems. Applications include supercomputers, DSP, graphics, robotics, AI, distributed control systems, PC's, engineering workstations and many others.

Write or phone for more information on the transputer family and start making history yourself.

	TRANSPUTER PRODUCTS
IMS T414	32 bit Transputer—2Kbyte —4 links
IMS T212	16 bit Transputer–2Kbyte —4 links
IMS M212	16 bit Disc Processor – 1 Kbyte — 2 links
	DEVELOPMENT TOOLS
IMS D701-2	IBM PC—Transputer Development System.
IMS D600	VAX/VMS—Transputer Development System.
, , , , , , , , , , , , , , , , , , ,	EVALUATION BOARDS
IMS B002-2	Double Eurocard + IMS T414 + 2Mbyte DRAM + 2 x RS232.
IMS B003-1	Double Eurocard + 4 x IMS T414 + 4 x 256Kbyte DRAM.
IMS B004-2	IBM PC Format + IMS T414 + 2Mbyte DRAM.
IMS B006-2	Double Eurocard + 9 x IMS T212 + 128Kbyte SRAM.
IMS B007-1	Double Eurocard + IMS T414 + 0.5Mbyte DRAM + 0.5Mbyte Video RAM
	HIGH PERFORMANCE VLSI MEMORIES
	4K CMOS SRAM, 20-55ns, 16K CMOS SRAM, 25-45ns
	64K CMOS SRAM, 35-70ns

THE TRANSPUTER

PARALLEL PROCESSING, UNPARALLELED POTENTIAL.



INMOS, P.O. Box 16000, Colorado Springs, CO 80935, Tel. (303) 630-4000;
 Bristol, England, Tel. 454-616616; Paris, France, Tel. (14) 687-2201;
 Munich, Germany, Tel. (089) 319-1028; Tokyo, Japan, Tel. 03-505-2840.

CIRCLE NO 83

HP's integrated CAE/CAD

The HP DesignCenter offers integrated CAE/CAD software tools that accelerate the design process from idea to test. These tools, which run on the HP 9000 Series 300 technical workstations, improve productivity and communication throughout the product development process. So engineers can design faster and get products to market quickly.

Analog and digital design on one system

Both digital and analog designers can use the same HP design capture system,

helping you to maximize return from your CAE/CAD investment. The system offers a number of features that help speed design, including a consistent environment of component libraries and schematics; hierarchical design entry; integrated documentation; on-line electrical rule checking; automatic component selection; and links between external design tools and design capture.

Faster microprocessor software development


You get HP computeraided software engineering. And some of the most advanced hardware and software integration tools available, including real-time emulation for over 40 processors. These tools let engineers tap the power of HP's microprocessor development environment to speed product development.

There's even a link to design capture from microprocessor system development so engineers can transfer programs directly to simulation, reducing both simulation setup time and the possibility of manual-entry errors.

Advanced PCB design tools for a head start in manufacturing

HP's automated printed circuit design system helps

Accelerate your product from idea to design and



turn engineering ideas into finished printed-circuit boards quickly. And gives you the assurance that boards will match the approved design from engineering and be practical to manufacture.

You get a link from schematic capture to PCB design for highest design integrity, and system features that optimize designs for your actual manufacturing environment. The result is reduced manufacturing costs, higher yield, and improved reliability.

You can also transfer netlist and part information from PCB design to HP's board test system, ending manual-entry hassles and errors

HP DesignCenter:our commitment to CAE/CAD


THE THETHE

HP's CAE/CAD tools are part of HP DesignCenter... a powerful product development environment that unites the activities of electronic, mechanical, and software engineers through integrated systems, software, and support.

For all the facts, call your local HP sales office listed in the telephone directory white pages. Or call 1-800-447-3282 (in Colorado call 590-5540 collect) for free literature on our CAE/CAD solutions.




development test.



DS15611A

13

You are only nine chapters away from understanding Semicustom IC design



earn how to design a semicustom IC with A Designer's Guide to Semicustom Integrated Circuits. Based on EDN's own design experience, this nine-chapter booklet outlines the complete procedure used to design, fabricate, and test EDN 1, a chip with a 1200 equivalent-gate complexity. You'll not only learn the steps to take when creating ICs, but also the design/cost analyses and vendor-interface methods that lead to successful semicustom chips.

Mail coupon to: Semicustom IC Reprints EDN Magazine Cahners Building	NAME			
275 Washington Street Newton, MA 02158-1630	TITLE			
Please send copies of A Designer's Guide to Semicustom In-	TITLE			
tegrated Circuits (96 pages) \$6.95 UPS \$\subseteq \\$8.96 non USA \$\langle \{\text{Page} \text{kdraft apply}\right)}\$	COMPANY			
(Bank draft only) Check or money order made out to EDN REPRINTS must accompany	ADDRESS			
each order. No COD. Mass residents add 5% sales tax.	CITY	STATE	ZIP	
Please print clearly. This is your mailing label.			EDN 3487	

In Power IN-CAR SECRETS Success in the car industry means keeping a step ahead. Today we deliver the power for tomorrow's in-car innovations. Compact, reliable, high-speed power converters run autonavigation, communication, test and instrumentation systems... Market leaders in telecomms, aerospace, computers and many other industries are ahead of their competition using In Power expertise. Are You? For the secret of success, contact: In Power Ballysimon Road Limerick Ireland Tel: International +353 61 49677 Fax: (G3)+353 61 42730 Tix: 70322 IPKO EI

Anything's possible with Great Engineering.



Why is Intersil's new high-voltage monolithic multiplexer better? We'll give you a hint.

You guessed it, leakage.

If you've worked with other high-voltage 8-channel multiplexers, you've seen how poor leakage current specs can cause serious signal errors.

You also may have learned that patching up the problem can mean some pretty extensive (and expensive) corrective circuitry

expensive) corrective circuitry.

Now, thanks to Intersil, you can get the multiplexer performance you need without do-it-yourself repairs. Just switch to our new IH9108 8-Channel High-Voltage Multiplexer with Latches.

In its military version, drain on-leakage is 25% lower, drain off-leakage 40% lower and source off-leakage 60% lower than competitive devices.

That reduces the major cause of multiplexer

error by 25% over competition.

To go along with its extremely low leakage numbers (0.5 nA, typical) the IH9108's breakdown voltage is greater than 120V. Typical ON resistance is a mere 35 ohms.

You also get true bi-directional switch action over the full analog signal range. And microprocessor interfacing is simple with on-board data latches and control pins.

All of which makes the IH9108 ideal for microprocessor-based instrumentation, ultrasound medical equipment and process control systems.

For complete details about the IH9108 and a free sample, call Intersil toll-free at

1-800-443-7364, ext. 81.

(In New York State, 1-800-243-7364, ext. 81.)
Or for on-line information on your ASCII terminal
or PC, dial 1-800-345-7335 (in CT 203-852-9201).
You'll need a 300 or 1200-baud modem (EVEN or
IGNORE parity, 7 data bits, 1 stop bit). At "Enter
Response Code," type GEIHVMUX.


The new IH9108 multiplexer from Intersil. Not the first product of its kind to hit the market.

Just the best.

Intersil, Inc., A Division of GE/RCA Solid State, 10600 Ridgeview Court, Cupertino, CA 95014.



CIRCLE NO 76



NEWS BREAKS

EDITED BY JOAN MORROW

IBM PC COPROCESSOR BOARD PROVIDES TERMINAL EMULATION

The PC4100 graphics coprocessor board enables your IBM PC to run software written for the Enhanced Graphics Adapter (EGA) and the Color Graphics Adapter (CGA), as well as the Tektronix 4107 and 4105 color graphics terminals. Based on the programmable TMS34010 graphics engine, the board, from Tektronix Inc (Wilsonville, OR), has a resolution of 640×480 pixels in its initial version; a future version will have a resolution of 1024×768 pixels. In addition to its display memory, the board contains 1M bytes of RAM, which the TMS34010 can use for display list storage. (For more information on graphics engines, see the Special Report starting on pg 112.) The board requires the PLOT 10 PC-07 and PLOT 10 PC-05 software packages to emulate the 4107 and 4105 terminals, respectively. Available at the end of this month, the PC4100 board will cost less than \$2000, the PLOT 10 PC-07 will be less than \$1000, and the PLOT 10 PC-05 will be less than \$500.—Margery S Conner

WINDOWING-STANDARD PROPOSALS EMERGING SLOWLY

On January 15, eleven companies announced support of X Window, a windowing system for multitasking computers developed by MIT. The companies include Adobe Systems Inc (Palo Alto, CA); Apollo Computer Inc (Chelmsford, MA); Data General Inc (Westborough, MA); Digital Equipment Corp (Maynard, MA); Hewlett-Packard Co (Palo Alto, CA); and Masscomp (Westford, MA). The support consists of the companies' promotion of X Window as the industry standard for graphics information display in networked systems; intercompany cooperation on X Window enhancements; pursuit of formal standardization by international standards organizations; and incorporation of X Window into new products. MIT supplies source code for the price of the media; X Window is an open, nonproprietary specification.

Sun Microsystems (Mountain View, CA), which introduced its News (network extensible window system) windowing specification for multitasking screen displays last year, plans to license source code to commercial vendors for \$25,000 starting this month. Like X Window and the company's NFS file-interchange specification, Sun has placed the News specification in the public domain. Any company can implement News with proprietary software without paying a license fee. News, based on a subset of Adobe Systems' Postscript graphics description language, currently runs on Sun's 3/200 Series workstations, as does X Window. The company claims that News is a superset of X Window and that News therefore can run X Window-compatible applications.—Steven H Leibson

IN-PACKAGE TRIM TECHNIQUE IMPROVES OFFSET-VOLTAGE SPECS

A proprietary in-package trim technique allows Motorola (Tempe, AZ) to adjust the offset voltage of a quad op amp to 10 μ V. The op amps are trimmed at the final test stage after they are packaged, thus, claims Motorola, avoiding the degradation in the offset spec commonly associated with the packaging process. The technique involves applying a current pulse to the trim resistors, which diffuses metal into the dielectric material of the IC and consequently reduces the resistance of the trim.—Jim Wiegand

STD BUS-BASED PERSONAL COMPUTER IS IBM PC/XT COMPATIBLE

The STD Bus-based System 2 from Pro-Log Corp (Monterey, CA, (408) 372-4593) offers IBM PC compatibility at the operating-system, BIOS, and chip-hardware levels. For example, some communication software written for the IBM PC will only work with a serial port implemented with an 8250; the System 2 employs this UART. The personal

EDN March 4, 1987

NEWS BREAKS

computer runs Microsoft's MS-DOS version 3.2, and it is rugged enough for industrial applications. You can also purchase the Model 7350 graphics/keyboard card that offers IBM PC-compatible CGA (Color Graphics Adapter), EGA (Enhanced Graphics Adapter), and monochrome operating modes. It interfaces to the standard IBM PC keyboard. With one $3\frac{1}{2}$ -in. floppy-disk drive, the NEC V20 μ P, and 128k bytes of CMOS static RAM, the system sells for \$1595.—Maury Wright

2400-BPS MODEMS SPORT ADAPTIVE ECHO CANCELLATION

Both internal (IBM PC bus) and external versions of Bizcomp Corp's (Sunnyvale, CA) 2400-bps Intellimodem 2400 cost \$599. They provide adaptive echo cancellation, a feature the company claims improves sensitivity by a factor of four over competing adaptive equalization designs. Rather than relying on band-splitting filters to remove echos from the telephone line, the Intellimodem 2400 predicts the echo, inverts the predicted signal, and injects the resulting waveform into the line, thus cancelling the predicted echo signal through destructive interference. The modems also feature Hayes-compatible command sets and an internal expansion bus for future hardware enhancements.—Steven H Leibson

CMOS CONTROLLER CHIP HANDLES X.25 PACKET SWITCHING

The MK5025 from Thomson Components-Mostek Corp (Carrollton, TX, (214) 466-6000) uses on-chip DMA control with buffer management to transmit and receive X.25 packets through separate circulator queues, thus offloading your host CPU of all link-level operations. The device lets you achieve data rates to 7M bps. Manufactured in a 1.5- μ m CMOS double-level metal process, the 5025 provides link-level data-communication control, a self-test feature, and loop-back test facilities. The chip includes programmable timers and counters and handles HDLC frame formatting—including zero-bit insertion and deletion, FCS generation and detection, and frame delimiting by flags. You can select the FCS as either 16 or 32 bits. A programmable option lets you manipulate XID, TEST, and UI frames. Packaged in a 48-pin DIP, the 5025 costs \$55 (1000).—J D Mosley

MAP MODEM CARD PLUGS INTO IBM PC BUS

Compatible with existing Manufacturing Automation Protocol (MAP)/IEEE-802.4 network controllers, the M8024-P modem from Fairchild Data Corp (Scottsdale, AZ) plugs directly into an IBM PC or compatible computer's card slot and attaches to the MAP network through a rear-panel F connector. You can obtain the modem with either a standard, 40-pin connector compatible with network controllers from Industrial Networking Inc (Santa Clara, CA), or a 37-pin connector compatible with network controllers from Concord Data Systems (Waltham, MA). Beta-site units of the M8024-P will be available in June, and production is slated for August.—Steven H Leibson

BICMOS 16k-BIT TTL-COMPATIBLE STATIC RAMS NOW AVAILABLE

The SSM6167 16k×1-bit and SSM6116 2k×8-bit BiCMOS static RAMs from Saratoga Semiconductor (Cupertino, CA, (408) 973-0945) are both available in two versions. You can order either IC in a standard power version with fast chip select, or in a power-down version that draws 20 mA in standby mode. Both devices come in 20-, 25-, and 35-nsec address access times. The SSM6167 specs 60-mA active power consumption and comes in a 20-pin DIP. The SSM6116 consumes 120 mA when active and comes in a 24-pin DIP. Prices range from \$8.60 to \$38.50 (100).—J D Mosley

The Sine of a Good Generator



Purity • Precision • Speed

- typically 0,0006% (-105 dB) distortion in the audio range
 ±0,1192 mHz frequency accuracy throughout the 0,2 Hz
- to 200 kHz range

 precision attenuator with ±0,026 dB (±0,3%) accuracy
- precision attenuator with ±0,026 dB (±0,3%) accuracy across the entire 100 μV to 5V range
- very fast response time for all functions via IEEE-488 interface
- heterodyne synthesis gives "instantaneous" settling (<0,1 ms) of frequency and amplitude
- memory sweep feature with pre-defined amplitude weighting
- two models: Sine Generator Type 1051 and Sine/Noise Generator Type 1049

Brüel & Kjær

Bruel & Kjaer Instruments, Inc.

HEAD OFFICE: 185 Forest Street, Mariborough, Massachusetts 01752 · (617) 481-7000 · TWX: 710-347-1187 REGIONAL OFFICES: MA (617) 481-7000 ext. 139 · NJ (201) 227-6100 · MD (301) 948-0494 · GA (404) 951-0115 MI (313) 522-8600 · IL (312) 358-7582 · TX (713) 645-0167 · CA (714) 978-8066 · (415) 574-8155 · WA (206) 625-1112

NEWS BREAKS: INTERNATIONAL

X-Y PLOTTER FURNISHES 17.7-IPS PLOTTING SPEED

The SPL-800 from Sekonic Co Ltd (Tokyo, TLX J34376) is an 8-pen X-Y plotter with a 17.7-ips plotting speed in each axis. The 32.3×12.5×41.3-in. device weighs 45 lbs, comes with both RS-232C and IEEE-488 interfaces, and provides 0.001-in. resolution. It also features 18k bytes of storage capacity and software compatibility with HP-GL commands. The plotter costs approximately \$5000.—Joan Morrow

VOICE SCRAMBLER SECURES NETZ-C SPEECH TRANSMISSIONS

Meeting the requirements of the West German NETZ-C cellular-radio standard, the FX304 audio processor from Consumer Microcircuits Ltd (Witham, UK, TLX 99382) allows you to scramble speech transmissions by frequency inversion of the audio band. The IC has two identical channels, which you can use to scramble and unscramble transmitted and received speech signals respectively, permitting full-duplex operation. Each channel has separate control inputs to inhibit the frequency inversion and to disable the channel's output.

Based on switched-capacitor filters and balanced modulators, the device is clocked from a low-cost 4.43-MHz crystal. Unwanted modulation products and baseband breakthrough are at a level of better than -40 dB. The FX304 costs around £8 (1000).—Peter Harold

TWO-CHIP SET SUITS 1553B BUS CONTROLLER/TERMINAL APPLICATIONS

You can configure the MA3690 transceiver and the MA3691 terminal controller ICs from Marconi Electronic Devices Ltd (Lincoln, UK, TLX 56380) to operate together as a bus controller, a remote terminal, or a passive bus monitor in dual-redundant 1553B bus systems. The terminal controller features two modes of operation. In single-shot mode, you can control 1553B bus activity directly from the subsystem's processor; in table-driven mode, the terminal controller has sufficient intelligence to execute a sequence of bus control instructions contained in external ROM or RAM.

The terminal controller also features an extendable no-response timeout and an automatic retry facility to cope with bus errors. Programmable options that modify message sequences, redefine status bits, and alter the way flags are set and cleared allow you to tailor the chip set to suit different interpretations of 1553B bus protocol. Samples of the £890 (100) CMOS SOS chip set, approved to MIL-STD-883C, will be available in the second quarter of this year.—Peter Harold

KYOCERA TO MARKET AIDA'S CAE TOOLS IN JAPAN

Kyocera Corp's LSI Design Div (Tokyo) and Aida Corp (Santa Clara, CA) have entered into a distribution agreement that licenses the Japanese company to market Aida's CAE workstation tools. Kyocera will offer design support and system-level simulation and testability tools. The products will be available in the Tokyo and Osaka design centers.—Joan Morrow

MESSAGE CENTER DISPLAY SYSTEMS


	1 11				<u> </u>			
			97	71	Polling Capability/Real Time Clock	1		
				4/	Enclosed in Metal Housing		1	
					NEMA 12 or 4X Stainless Steel Bezel	1	1	
	\perp	T			115/230 Volt Power Supply Included		\perp	
	L		1	1_	12 Volt Power Supply Required	Te	Sept.	
		7		1_	Four Line x 24 Character Readout	1	<u> </u>	
			4	1.7	Single Line Readout (24 Characters)	Tal	Tal	
		1			64 Canned Messages in EPROM			
		1	Y		256 Canned Messages in CMOS RAM			
	P	1	1	Ÿ.	📗 ½´´ Characters Utilizing Gas Plasma Technology 📗 🦞	1.		
	7		4		RS232/RS422 and 20mA Outputs	1_		
-I					Full and Half Duplex Communication			
Γ	4.	7			Accepts RS422 Serial ASCII Input			A
	2	7	75		Accepts RS232 & 20mA Serial ASCII Input			
		Lag			PC Software Available for Message Programming			
?	19)	9		Accepts Parallel ASCII Input (TTL Logic Levels)		4	94
4	12				Recall Message with +5 to +30VDC Logic			
W 424 1040 V 40	W424 105D 1X5D		W424 1 05B X5B			W424 1058	W424 1053	WAZA 1051
						And the second section of the	the Papers where we will not	the thinks are a second of the

Get our detailed message: Send for specs.



INDUSTRIAL CONTROL PRODUCTS

3600 Sunset Avenue, Waukegan, IL 60087 • (312) 360-3500



crans

over 50 off-the-shelf models...



Having difficulty locating RF or pulse transformers with low droop, fast risetime or a particular impedance ratio over a specific frequency range?...Mini-Circuits offers a solution.

Choose impedance ratios from 1:1 to 36:1, connector or pin versions (plastic or metal case built to meet MIL-T-21038 and MIL-T-55831 requirements*). Ultra-wideband response achieves low droop and fast risetime for pulse applications. Ratings up to 1000M ohms insulation resistance and up to 1000V dielectric voltage. For wide dynamic range applications involving up to 100 mA DC primary current, use the T-H series. Coaxial connector models are offered with 50 and 75 ohm impedance; BNC standard; request other types. Available for immediate delivery with one-year guarantee.

Call or write for 64-page catalog or see our catalog in EBG, EEM, Gold Book or Microwaves Directory.

*units are not QPL listed

finding new ways. setting higher standards

P.O. Box 166, Brooklyn, New York 11235 (718) 934-4500 Domestic and International Telexes: 6852844 or 620156

NISNI CHIDE

NSIN GUIDE						
MCL NO.	NSN					
T1-1	5950-01-128-374					
T2-1	5950-01-106-1218					
T4-1	5950-01-024-762					
TMO4-1	5950-01-067-1012					
TMO4-2	5950-01-091-355					
T9-1	5950-01-105-815					
TMO9-1A	5950-01-098-631					
T16-1	5950-01-094-743					

bent lead version style x 65


T, TH, case W 38, X65 Bent Lead Version TMO, case A 11, † case B 13 FT, FTB, case H 16

formers

3KHz-800 MHz from \$295




			FREQUENCY	INSERTION LOSS			PRICE \$	
case style number	MODEL	$_{ extsf{RATIO}}^{\Omega}$	MHz	3dB MHz	2dB MHz	1dB MHz	Ea	Qty.
see opposite page.	NO.							
A*	T 11-11	1	.05-200	.05-200	.08-150 .01-150	.2-80 .02-50	3.95 5.95	(10-49) (10-49)
PRI SEC	T1-6T NEW	1	.003-300	.003-300 .07-200	.1-100	.5-50	4.25	(10-47)
DDI 3 E-0 SEC	T2-1T	2	.07-200 .01-100	.01-100	.02-50	.05-20	4.25	(10-47)
7 6 2 25	T2.5-6T T3-1T	2.5	.05-250	.05-250	.1-200	.5-70	3.95	(10-49)
\sim	T4-1	4	.2-350	.2-350	.35-300	2-100	2.95	(10-49)
	T4-6T	4	.02-250	.02-250	.05-150	0.1-100	3.95	(10-49)
	T5-1T	5	.3-300	.3-300	.6-200	.5-100	4.25	(10-49)
	T8-1T	8	.03-140	.03-140	.10-90	1-60	6.95	(10-49)
	T43_4T	13	.3-120	.3-120	.7-80	5-20	4.25	(10-49)
	T16-6T NEW	16	.03-75	.03-75	.06-30	.1-20	4.95	(10-49)
	TH 74-1H	4	8-350	8-350	15-300	25-200	4.95	(10-49)
	TMO TMO1-1T	1	.05-200	.05-200	.08-150	.2-80	6.45	(10-49)
	TMO2-1T	2	.07-200	.07-200	.1-100	.5-50	6.75	(10-49)
	† TMO2.5-6T	2.5	.01-100	.01-100	.02-50	.05-20	6.75	(10-49)
	† TMO3-1T	3	.05-250	.05-250	.1-200	.5.70	6.45	(10-49)
	TMO4-1	4	.2-350	.2-350	.35-300	2-100	4.95 6.75	(10-49) (10-49)
	TMO5-1T	5	.3-300	.3-300 .3-120	.6-200 .7-80	5-100 5-20	6.75	(10-49)
	TMO13-1T	13	.3-120	.3-120	.7-00	3-20	0.75	(10-47)
B* NEW	TT TT1-6	1	.004-500	.004-500	.02-200	.1-50	5.95	(10-49)
	TT1.5-1	1.5	.075-500	.075-500	.2-100	.1-50	4.95	(10-49)
PRI SEC	TT2.5-6	2.5	.01-50	.01-50	.025-25	.05-10	5.25	(10-49)
PRI O SEC	TT4-1	4	.05-200	.05-200	.02-50	1-30	4.95	(10-49)
←	TT25-1	25	.02-30	.02-30	.05-20	.1-10	7.95	(10-49)
	TTMO TTMO1-1	1	.005-100	.005-100	.01-75	.05-40	10.95	(10-49)
C	T 11-1	1	.15-400	.15-400	.35-200	2-50	2.95	(10-49)
~ ~	T1-6 NEW	1	.01-150	.01-150	.02-100	.05-50	4.95	(10-49)
0.7 6.0	T1.5-1	1.5	.1-300	.1-300	.2-150	.5-80	3.95	(10-49)
PRI SEC	T1.5-6 NEW	1.5	.02-100	.02-100	.05-50	0.1-25	4.95	(10-49)
مے کے	T2.5-6	2.5	.01-100	.01-100	.02-50	.05-20	3.95	(10-49)
0	T4-6	4	.02-200	.02-200	.05-150	.1-100	3.95 3.45	(10-49) (10-49)
	T9-1	9	.15-200	.15-200	.3-150	2-40 .5-20	3.45	(10-49)
	T16-1	16	.3-120	.3-120	.7-80 .05-10	.5-20 .1-5	5.95	(10-49)
	T36-1	36	.03-20	.03-20				
	TH 11-1H	1	8-300	8-300	10-200	25-100	4.95	(10-49)
	T9-1H	9	2-90	2-90	3-75	6-50	5.45	(10-49)
	T16-1H	16	7-85	7-85	10-65	15-40	5.95	(10-49)
	TMO TMO1-1	1	.15-400	.15-400	.35-200	2-50	4.95	(10-49)
	TMO1.5-1	1.5	.1-300	.1-300	.2-150	.5-80	6.75	(10-49)
	† TMO2.5-6	2.5	.01-100	.01-100	.02-50	.05.20	6.45	(10-49)
	† TMO4-6	4	.02-200	.02-200	.05-150	.1-100	6.45	(10-49)
	TMO6-1	6	.3-200	.3-200	.5-150	5-50 2-40	6.45	(10-49) (10-49)
	TMO9-1	9	.15-200	.15-200	.3-150 .7-80	5-20	6.45	(10-49)
	TMO1.6-1	16	.3-120	.3-120	.7-80			
D	T T2-1	2	.025-600	.025-600	.05-400	.5-200	3.45	(10-49)
	T3-1	3	.5-800	.5-800	.2-400		4.25	(10-49)
200 - 3 F. 320	T4-2	4	.2-600	.2-600	.5-500	.2-250	3.45	(10-49)
PRI 🕽 ⊱ SEC	T8-1	8	.15-250	.15-250	25-200	2-100	3.45	(10-49)
PRI SEC	T14-1	14	.2-150	.2-150	.5-100	2-50	4.25	(10-49)
÷	TMO TMO2-1	2	.025-600	.025-600	.05-400	.5-200	5.95 6.95	(10-49) (10-49)
	TMO3-1	3	.5-800	.5-800 .2-600	2-400 .5-500	2-250	5.95	(10-49)
	TMO4-2	4	.2-600 .15-250	.15-250	.25-200	2-100	5.95	(10-49)
	TMO8-1 TMO14-1	8	.2-150	.2-150	.5-100	2-50	6.75	(10-49)
E 0	FT FT1.5-1	1.5	.1-400	.1-400	.5-200	1-100	29.95	(1-4)
PRI SEC SEC		1	.2-500	.2-500	.5-300	10-100	29.95	(1-4)
~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~ ~	FTB FTB1-1 FTB1-6	1	.01-125	.01-125	.05-50	.1-25	29.95	(1-4)
<u> </u>	■ FTB1-1-75	1	.5-500	.5-500	5-300	10-100	29.95	(1-4)
7	= FIDI-1-73	1 . '	1 .0 000					



^{*} Maximum Amplitude Unbalance 0.1 dB over 1 dB frequency range 0.5 dB over entire frequency range

^{*} Maximum Phase Unbalance 1.0° over 1 dB frequency range 5.0° over entire frequency range



A \$20 BILLION COMPANY INTO A PACKAGE THIS SMALL MEANT LEAVING A FEW THINGS OUT.

And we all benefit. Because what we left out of our 31/2" floppy drive is really still there, in smaller, VLSI packaging. Packaging that allows us to build a drive with fewer components than anyone else. As much as 20% less than most manufacturers. Made possible by the advanced technology of Toshiba engineers.


And that means you get drives of higher reliability. Because when you build a drive with fewer components you end up needing fewer interconnections and using less power. And, as you know, that means higher MTBF, longer product life and, well, you get the idea.

Of course, making a drive this reliable required putting a lot into it when we designed it. Like time. And money. And expertise. In short, whatever it took to produce the best product available in the marketplace.

But then we've always done things that way. Starting with keeping our eyes and ears open so that we know what kinds of disk products you're looking for. And then putting all the resources of our \$20 billion company behind producing those products.

And it works. Just like it's working with our $3\frac{1}{2}$ " floppy product. Not just the best drive but also the most popular one on the market today. It's a true 1"

high, 1 megabyte drive. Weighing less than 1 pound. Offering a choice of CMOS or TTL interfaces. Compatible with 51/4" floppy drives. A



perfect fit for both portable and office PCs. And it's made with the latest in robotics for consistent high quality.

And of course it comes with all the world-class support you've come to expect from Toshiba. Evaluation units when and where you need them. Responsive technical assistance. And a full family of highly reliable products. From the $3\frac{1}{2}$ " and $5\frac{1}{4}$ " floppy drives to $5\frac{1}{4}$ " and 8" Winchesters and a range of optical storage products.

For more information call 408-727-3939. Or write Toshiba America, Inc., Disk Products Division, 3910 Freedom Circle, Suite 103, Santa Clara, CA 95054.

We'll show you how leaving a few things out has made a big improvement in the world of $3\frac{1}{2}$ " drives.

WORLD-CLASS QUALITY. WORLD-CLASS SUPPORT.

TOSHIBA

DISK PRODUCTS DIVISION

© 1986 Toshiba America, Inc.



on VMEbus.
We give you
the choice.
You make the
best decision.

VMEbus has always provided performance, reliability and quality. Now add flexibility from Force.

Upgrade the performance of your software

Bring 32 bit 80386 power to your existing software. Or upgrade your 68000 designs to 25 MHz speeds. Both with no-wait-states. You now have the choice between the two most powerful 32 bit micros on the industry leading VMEbus. Check the best product for your application.


Force 32 bit CPU Availability								
	CPU-20	CPU-21	CPU-24	CPU-25	CPU-386A	CPU-386B		
Processor	68020*	68020*	68020*	68020*	80386*	80386*		
Available frequencies	12.5/16.7/ 20/25	12.5/16.7/ 20/25	12.5/16.7/ 20	12.5/16.7/ 20	12/16/20	12/16/20		
Number of wait states	0	0	1	1	0 (1 at 20 MHz)			
FPU	no	yes	no	yes	no	yes		
MMU	no	no	yes	yes	yes	yes		
Memory capacity	0.5 to 4 MB SRAM		0.5 to 4 MB SRAM		2 to 8 MB DRAM			
EPROM capacity	512 KB	512 KB	64 KB	64 KB	256 KB	256 KB		
Serial I/O channels	3	3	3	3	3	3		



Choices, Tools and Support

Force as the largest independent VMEbus supplier in the world gives you choices and tools including development systems, comprehensive design literature, 50 hardware products, 20 software products, in-plant seminars and prompt support. Industry leading quality levels are assured through functional and incircuit testing and a 48 hour operating burn-in on all products.

Flexibility, Performance, Quality and Support from Force. Today with 1300 customers in 30 countries, Force is your best choice in VME.



Free! Call 1-800-BEST VME

(or 1-800 237-8862 in California) for our new 380 page VME data book and for rapid applications support.

the intelligent choice

FORCE COMPUTERS, INC, Los Gatos, CA 95030, Phone (408) 354-3410 Midwest: Ann Arbor, MI 48108, Phone (313) 769-0840 Southeast: Roswell, GA 30076, Phone (404) 642-9647

Processor Boards

Controller Boards

Memory Boards

O Boards

FORCE COMPUTERS GMBH, 8012 Ottobrunn, Phone (089) 600910 FORCE COMPUTERS FRANCE, 92100 Boulogne, Phone (1) 46203737 FORCE COMPUTERS (UK) LTD, Wendover, Phone (0296) 625456

SIGNALS & NOISE

High specialization leads to stagnation

Dear Editor:

I say a loud "Amen" to the comments of Philip Mandel and Fred Chitayat (Signals & Noise, EDN, November 13, 1986, pg 33). The walls that seem to exist between analog and digital design are artificial.

One example of the falseness of these walls can be found in the design of high-speed digital circuits, where the lessons of analog RF design (about transmission-line effects, for example) very much come into play.

I do believe that putting people into the little boxes of high specialization is a bad trend: Look what has happened to medicine. After a long drift toward extreme specialization, the medical profession is finally starting to recognize the worth of the general practitioner. I wonder how long it will take the engineering profession to wake up.

Has anyone considered that one of the reasons for the high burnout rate of engineers (and also the large number of company-hoppers) may be that the high degree of specialization leads to boredom and stagnation? I can tell you that that was the case for me. That's why I started my own company and why I stay involved in all the aspects of our product design, from the power plug to the output.

Sincerely yours, William H Bowen Chief Engineer Tiger Communications Houston, TX

Technicians should earn associates' degrees

Dear Editor:

Matthew Slate's letter entitled "The technician syndrome" (EDN, November 27, 1986, pg 29) raised some excellent points.

My studies at the University of



"SURE, BUT THOSE AREN'T MY FIGURES. THEY'RE THE FIGURES OF SOMEONE WHO KNOWS WHAT HE'S TALKING ABOUT."

Texas at Dallas covered the future job market and qualifications for technicians. The main problem is that, in the past, many technicians came from poor training programs in the military or in trade schools. Most firms will no longer accept technicians who received their training only in the military, as an article in The Wall Street Journal (October 9, 1985) points out. Further, the book Career Education in Colleges (Harris and Grede, Jossey-Bass Publishers, 1977) states that trade-school programs are of very low quality.

Community colleges now offer associate's degree programs of study in microprocessor systems, laser optics, and robotics. Several studies recommend that firms now require the associate's degree to enter the profession. More technicians should be hired, and their positions should be upgraded to a higher professional level, where their advanced training can be better utilized.


Sincerely yours, Glen Spielbauer Dallas, TX


Multiplexer limits 1's-complement data

Dear Editor:

I'd like to correct two errors that

SPRAGUE POWER ICS





UDN-2998W DUAL FULL-BRIDGE MOTOR DRIVER for 2-Phase Stepper, or Brushless DC Motors


- Load Voltages to 50 V
- Output Current to ±2 A Continuous, or ±3 A Peak
- External Current-Sensing Capability
- Output Enable for External PWM
- Logic-Compatible Inputs
- Internal Thermal Shutdown Protection
- Crossover Current Protection
- Improved Internal Suppression Diodes
- Monolithic Reliability
- 12-Pin Power-Tab SIP
- Clip-On Heat Sink Available

Write for Engineering Bulletin 29319.6 or:

CIRCLE NO 3



POWER MANAGEMENT.



Sprague Power Integrated Circuits offer high performance along with lower component counts, improved reliability and cost economy. This ever-expanding line includes highvoltage (to 200V) or high-current (to 5 A) peripheral power ICs, motor/relay/solenoid drivers, LED/incandescent/VF/PGD display drivers, and BiMOS smart power ICs. Also available are SMPS controllers,

audio power ICs (to 20 W), and power operational amplifiers (to 3.5 A). Sprague Electric Company, a Penn Central unit, World Hdqtrs., Lexington, MA. For additional information, write for Brochures WR-181, WR-189, WR-195, WR-202, and WR-203 to Technical Literature Service, Sprague Electric Co., 41 Hampden Rd., P.O. Box 9102, Mansfield, MA 02048-9102.



High-Tech Take-Away

The portability and low price of our PM 3632 brings logic analysis within reach of every user in industry and education.

But not at any cost in performance. Because this remarkable personal


logic analyzer out-performs all other instruments in its class on the market!

Compare some of the benefits of this 'high-tech take-away' for yourself:

■ 100 MHz acquisition speed, or up to 32 channel data width cover demanding state/time applications in digital systems.

■ Wide ranging microprocessor support (incl. 68000/68010 and 8086/ 8087/8088 16-bit devices) and ROM emulation enhance operational versatility.

■ Powerful triggering and menu-driven operation combined with status display, screen prompts and fingertip control provide easy user access to full-function logic analysis.



Test the difference

Philips, one of the world's largest electronic companies, is a major innovator, manufacturer and user of precision test and measuring instrumentation. So product credibility in technology, usability and reliability is assured.



Test the difference and you'll agree that Philips wins on price and performance!

Write to: Philips I & E, T & M department, Building HKF70, 5600 MD Eindhoven, The Netherlands or call your local supplier. **Austria** (222) 629141-0; **Belgium** (2) 5256692/94; **Denmark** (1) 572222; **Finland** (0) 5257225; France (1) 48301111; Germany (561) 5010; Great Britain (0223) 358866; Ireland (1) 693355; Italy (39) 36351; Netherlands (40) 782808; Norway (2) 680200; Portugal (1) 683121; Spain (1) 4042200; Sweden (8) 7821800; Switzerland (1) 4882211



Test & Measurement PHILIPS

CIRCLE NO 45

SIGNALS & NOISE

crept into the published version of my Design Idea, "Multiplexer limits complement data" (EDN, October 30, 1986, pg 202). First, in an 8-bit, 2's-complement data word, the maximum positive value is only 127, not 128. In the article, therefore, readers should substitute +127 for +128.

Second, Fig 1's circuit works without any modification for 1's complement data as well. The modification explained in the last paragraph is for limiting unsigned (straight positive binary) data.


Sincerely yours, S Murugesan ISRO Satellite Centre Department of Space Government of India Bangalore, India

Productive software

In the paragraph on the Hewlett-Packard DACQ/300 software package in EDN's New Products section (October 2, 1986, pg 267), we erroneously stated that the software can reduce the engineer's program-development time by a factor of 100. Not so. Says H-P: "Would that we could increase our customers' productivity by a factor of 100. Alas, all we can do is reduce the development time by 50%."

YOUR TURN

EDN's Signals and Noise column provides a forum for readers to express their opinions on issues raised in the magazine's articles or on any topic that affects the engineering industry. Send your letters to the Signals and Noise Editor, 275 Washington St, Newton, MA 02158. We welcome all comments, pro or con. All letters must be signed, but we will withhold your name upon request. We reserve the right to edit letters for space and clarity.



TIA GETTIEG MIGENT EE COTT OTO													
Models	+ 5V	- 5V	+ 12V	- 12V	+ 15V	- 15V	+24V	+12V	Total Power	Dimensions L W H			
HX250-3100	40A		10A	3A	1111			1.5	120				
HX250-3200	40A				3A	3A	100	44 Y .					
HX250-4103	40A	3A	10A	3A .					250 Watts	+0.5%			
HX250-4104	40A		3A	3A			5A			10.5" × 5" × 2.5			
HX250-4105	40A		10A	ЗА				ЗА					
HX250-4204	40A				3A	3A	5A						
HX350-3100	65A		10A	5A			1.0		1.				
HX350-3200	65A				5A	5A			350 Watts				
HX350-4103	65A	5A	10A	5A									
HX350-4104	65A		5A	5A			5A	100		11.5" × 5" × 2.5			
HX350-4105	65A		10A	5A				5A					
HX350-4204	654				5Δ	5Δ	5Δ		1				

Single outputs available in 5V, 12V, 15V, 24V and 48V.

- Primary output adjustable +20% to -5%.
- Auxiliary outputs adjustable ±5%.
- · All outputs isolated.
- · Remote inhibit.
- · Current mode control.
- Power fail detect, TTL signal high or low optional.
- Outputs tailored to your specifications.
- Remote sense.
- Extruded aluminum chassis.

855 East Collins Blvd. Richardson, TX 75081 (214) 231-1456 • FAX (214) 680-2457

Toll Free (800) 645-2074



CIRCLE NO 12

Be An Author!

When you write for EDN, you earn professional recognition. And you earn \$75 per published magazine page.

EDN publishes how-to design application information that is read by more than 137,000 electronics engineers and engineering managers worldwide. That's an audience that could belong to you.

If you have an appropriate article idea, please phone Eva Freeman, Associate Editor, at (617) 964-3030, or send a proposal and outline to her at 275 Washington Street, Newton, MA 02158 – 1630. For a FREE EDN Writer's Guide—which includes tips on how to write for EDN and other technical publications—please circle number 800 on the Information Retrieval Service Card.




First in Readership among Design Engineers and Engineering Managers in Electronics




With its 150 MHz bandwidth, 5 ns/div maximum sweep speed and 2-channel simultaneous acquisition, the 2430 displays TTL and ECL signals for risetime and coincidence measurements. (Above) The scope is used in 50 ohm input termination with a 500 ohm probe for an accurate measurement of propagation delay through an ECL inverter



How long does it take a transformer to reach operating voltage? Using DELAY BY EVENTS, the 2430 lets you select the 254th (or any other) switching event of the pulse-width modulator in a high-efficiency power supply.



A new Tek patented feature, SAVE ON DELTA instructs the 2430 to compare incoming acquisitions against a user defined reference and save it in the event of a difference. You can catch intermittent failures automatically and implement automatic tests with improved repeatability.



TEK'S NEW 2430. THE REVOLUTIONARY DIGITAL SCOPE YOU ALREADY KNOW HOW TO USE.

We've expanded the best features of our familiar, industry-standard 2400 Series in a new portable scope that sets some standards of its own. Start with a 150 MHz bandwidth and a 100 MS/sec digitizing rate plus dual channel simultaneous acquisition. It's a powerful combination that enables you to digitize, view and store fast and complex signals.

Add 8-bit vertical resolution, 1K record length per channel and a 0.01% crystal-controlled timebase for making accurate measurements with

ease.

The result: an advanced measurement package with many sophisticated capabilities built in especially for solving tough product design problems.

All-purpose high performance at its affordable best! The 2430 not only handily meets your general purpose measurement needs, it gives you a lot more. With digital



DAC glitches won't escape you with the 2430's enhanced ENVELOPE function. The peak-detecting ENVELOPE mode enables you to catch events as narrow as 2 ns, even with a single acquisition, at any sweep speed.

capabilities come powerful waveform manipulation functions ranging from waveform multiplication to highresolution averaging.

It is also fully programmable via the GPIB. Complete talk/listen capabilities extend the scope's power and make it a valuable systems component for making automatic measurements. You can develop test procedures that can be used later on the manufacturing floor. Plus, the time-consuming task of waveform characterization, analysis and logging is simplified.

In addition, the 2430 can store waveforms and front panel setups in


nonvolatile memory.

The 2430 exhibits unusual power as a troubleshooting tool. The patented peak detection circuit lets you capture glitches as narrow as 2 ns at any sweep speed with confidence—a level of performance available until now in only the most expensive instruments.

The 2430's envelope mode, which automatically captures and updates signal minimums and maximums, allows you to conveniently study signal variations such as jitter, drift and stability. It also monitors signal excursions outside user-defined limits.

Plus, a broad range of pretrigger selections available in all modes makes it possible to examine conditions leading up to an event. The crystal-controlled timebase allows you to delay by time and/or events for precise timing measurements in complex triggering modes. You can even trigger on digital words.

Best of all, we've kept the 2430 easy to use. From the simple, one-level menus for standard functions to the comfortable grouping of the front panel controls, the 2430 was designed to drive like the scopes you already use.



With full programmability you can improve repeatability and throughput—and reduce operator interface requirements.

The enhanced capabilities of the 2430's time and voltage cursors are another convenience, enabling you to make accurate measurements of all essential parameters.

The reliability of the 2430 is underwritten with a 3-year warranty. A variety of low-cost service plans can extend this coverage even further.

Now! See the features you've been looking for in a priced-right, digital scope. Call your Tek sales engineer for a demo. For literature, or to find our sales office nearest you, call the Tek National Marketing Center toll-free, 1-800-426-2200. In Oregon call collect, (503) 627-9000.



Immediate

Apply within. No experience necessary.
That's another wonderful benefit of our exclusive EPLD technology. You can move right into user-programmable logic design. Right now. Because we have a complete family of high density products (from 300 to 2000 gates), plus the easy-to-use development software you need to turn your assignment into a working prototype. In a matter of days. And for a fraction of what you'd expect to invest.

Best of all, you no longer have to enter the frightening realm of gate arrays to get a high level of integration. Just look into our newest family member: the EPI800.


You'll work with 2000 gates. In a tiny J-lead package. Without worrying about speed (it has plenty), power (it desires very little) or noise (it's quite deaf).

What's more, design development is a breeze. Even on the EPI800. With our A+PLUS software and your IBM PC, prototypes can be produced in days. Sometimes hours. Modifications can be made in minutes. And with the software automatically placing your design into the right chip, you don't waste time figuring out what goes where.

One last step. Volume production. Also no problem. Because every one of our EPLDs is available as a One-Time-Programmable (OTP) plastic part. So you can get to market in less time. For a lot less money.

So apply today. We've got immediate openings for your design.

Call (408) 984-2800




3525 Monroe Street Santa Clara, CA 95051

CIRCLE NO 49



A+PLUS is a registered trademark of Altera Corporation. IBM is a registered trademark of International Business Machines Corporation. CHMOS is a patented process of Intel Corporation.

Distributed in U.S. by Alliance, Pioneer, Quality Components, Schweber and Wyle. In Canada by Future. © 1986 Altera Corporation. Openings.









CALENDAR

Hands-on Programming in C, Boston, MA. Integrated Computer Systems, Box 3614, Culver City, CA 90231. (800) 421-8166; in CA, (213) 417-8888. March 17 to 20.

Real-time Operating Systems: A Hands-on Workshop, Palo Alto, CA. Integrated Computer Systems, Box 3614, Culver City, CA 90231. (800) 421-8166; in CA, (213) 417-8888. March 17 to 20.

Computer Graphics '87, Philadelphia, PA. National Computer Graphics Association, 2722 Merrilee Dr, Suite 200, Fairfax, VA 22031. (703) 698-9600. March 22 to 26.

IEEE VLSI Test Workshop, Atlantic City, NJ. Wesley Radcliffe, IBM, East Fishkill Facility, Bldg 321-5E1, Dept 277, Hopewell Junction, NY 12533. (914) 894-4346. March 24 to 25.


Southcon, Atlanta, GA. Electronic Conventions Management, 8110 Airport Blvd, Los Angeles, CA 90045. (213) 772-2965. March 24 to 26.

Hands-on Programming in C, San Diego, CA. Integrated Computer Systems, Box 3614, Culver City, CA 90231. (800) 421-8166; in CA, (213) 417-8888. March 24 to 27.

Internepcon/Semiconductor Korea '87, Seoul, Korea. Cahners Exposition Group, Box 70007, Washington, DC 20088. (301) 657-3090. March 26 to 28.

ADEE West '87, Anaheim, CA. Cahners Exposition Group, 1350 E Touhy Ave, Des Plaines, IL 60017. (312) 299-9311. March 31 to April 2.

Hands-on Programming in C, Washington, DC. Integrated Computer Systems, Box 3614, Culver City, CA 90231. (800) 421-8166; in CA, (213) 417-8888. March 31 to April 3.



MICRO-CAP II. The CAE tool with fully interactive analog simulation for your PC.

Spectrum Software's MICRO-CAP II® is fast, powerful, and feature rich. This fully interactive, advanced electronic circuit analysis program helps engineers speed through analog problems right at their own PCs.


MICRO-CAP II, which is based on our original MICRO-CAP software, is a field-proven, second-generation program. But it's dramatically improved.



Schematic Editor

MICRO-CAP II has faster analysis routines. Better resolution and color. Larger libraries. All add up to a powerful, cost-effective CAE tool for your PC.

The program has a sophisticated integrated schematic editor with a pan capability. Just sketch and analyze. You can step



Transient Analysis

component values, and run worst-case scenarios—all interactively. And a 500-type* library of standard parts is at your fingertips for added flexiblity.

MICRO-CAP II is available for IBM® PCs and Macintosh.™ The IBM version is CGA, EGA, and Hercules® compatible and costs only \$895 complete. An evaluation version is available for \$100. Call or write today for our free brochure and demo disk. We'd like to tell you more about analog solutions in the fast lane.

- Integrated schematic editor
- Fast analysis routines
- High-resolution graphic output
- Standard parts library of 500* types
 - *IBM versions only.

- Transient, AC, DC, and FFT routines
- Op-amp and switch models
- Spec-sheet-to model converter*
- Printer and plotter* hard copy



AC Analysis

Spactrum

1021 S. Wolfe Road, Dept. E Sunnyvale, CA 94087 (408) 738-4387

MICRO-CAP II is a registered trademark of Spectrum Software.

Macintosh is a trademark of McIntosh Laboratory, Inc. and is being used with express permission of its owner

Hercules is a registered trademark of Hercules Computer Technology

IBM is a registered trademark of International Business Machines, Inc.

Parylene 87

TECHNOLOGY UPDATE

April 28-29, 1987 Indianapolis, Indiana

Seminar on the latest parylene conformal coating techniques for circuit boards and other applications. This technology update will include presentations by various industry experts, with a review of parylene properties and application theory.

Military applications—April 28, commercial applications—April 29. Attend one or both sessions at no charge. Please call the Parylene '87 information number—317-842-5399—for details. Register by March 23, 1987.

Sponsored by Union Carbide Corporation and its subsidiary Nova Tran



8031 CASTLETON ROAD INDIANAPOLIS, IN 46250

Copyright @ Nova Tran Corporation

40



CIRCLE NO 10

Looking for a job doesn't have to be one.

EDN's Career Opportunities section keeps you informed of current job openings from coast-to-coast



CALENDAR

Real-time Operating Systems: A Hands-on Workshop, Boston, MA. Integrated Computer Systems, Box 3614, Culver City, CA 90231. (800) 421-8166; in CA, (213) 417-8888. March 31 to April 3.

Defense Communications Agency Forecast to Industry, White Oak, MD. Armed Forces Communications and Electronics Association NOVA Chapter, Computer Sciences Corp, 6565 Arlington Blvd, M/C DCA/AFCEA, Falls Church, VA 22046. April 1 to 2.

Microtronics '87, Hannover, West Germany. Hannover Fairs USA, Box 7066, Princeton, NJ 08540. (609) 987-1202. April 1 to 8.

Invitational Computer Conference, Nashua, NH. B J Johnson & Associates, 3151 Airway Ave, #C-2, Costa Mesa, CA 92626. (714) 957-0171. April 2.

Conference on Human Factors in Computing Systems and Graphics Interface, Toronto, Canada. Wendy Walker, Conference Coordinator, Computer Systems Research Office, University of Toronto, 10 Kings College Rd, Rm 2002, Toronto, Ontario, Canada M5S 1A4. (416) 978-5184. April 5 to 9.

Electro/Mini Micro Northeast, New York, NY. Electronic Conventions Management, 8110 Airport Blvd, Los Angeles, CA 90045. (800) 421-6816; in CA, (800) 262-4208. April 7 to 9.

Nepcon Southeast, Orlando, FL. Cahners Exposition Group, Box 5060, Des Plaines, IL 60017. (312) 299-9311. April 7 to 9.

Annual Electrical Overstress Exposition, San Jose, CA. EOE, 2504 N Tamiami Trail, Nokomis, FL 33555. (813) 966-9521. April 21 to 23.

Thinking of Image Processing on a MicroVAX II? Think Data Translation.



Are we out of our skull? Data Translation's Image Processing boards and software for the MicroVAX II are priced way below the competition's. Yet they offer a wider range of functions.


Since Fred Molinari sets prices, we had his head examined. As you can see, Fred and his skull are doing quite well.

And so is Data Translation. We're selling a lot of Image Processing boards and software for the MicroVAX II, for reasons other than price: • Full-functionality-on-one board

• Real-time processing • Different resolutions for different applications • Standard video, VCR, or slow-scan capability • Application and subroutine library software under MicroVMS.

Simply put, Data Translation has the best values on the widest range of Image Processing boards and software for the MicroVAX II.

Now, can you think of using anyone else's Image Processing products? If so, may we suggest that you have your head examined? **CALL (617) 481-3700**



DATA TRANSLATION

World Headquarters: Data Translation, Inc., 100 Locke Dr., Marlboro, MA 01752 (617) 481-3700 Tlx 951 646
European Headquarters: Data Translation Ltd., 13 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG11 2QZ, England Tlx 849862 (#D)
International Sales Office: Australia (61) 2-662-4295; Belgium (32) 2-7352135; Canada (416) 625-1907; Chile (2) 2-253689; China (408) 727-8222, (86) 8-721-4017; Denmark (45) (02)
187188; England (44) 734-79383; Finland (358)-90-372144; France (33) (1) 69-28-01-73; Greece (30) (3) 152-7039, (30) (1) 361-4300; Hong Kong (852) 3-318585; India (91) 2-231040; Israel
(972) 3-324298; Italy (39) 2-81821; Japan (81) (3) 502-5550, (81) (3) 375-1551, (81) (3) 355-1111; Korea (82) 778-0721; Malaysia (60) 3-36299; Morrocco (21) 9-30-6949; Netherlands (31)
70996360; New Zealand (61) 2-662-4295; Norway (47) (02) 559050; Peru (51) (14) 31-8060; Phillipines (63) 818-0103; Portugal (351) 1545313; Singapore (65) 271-3163; South Africa (27)
12469221; Spain (34) 14558112; Sweden (46) 8-7617820; Switzerland (41) 17231410, (41) 22360830; Taiwan (86) 2-709-1394; West Germany (49) 89809020.

The GE/RCA ASIC cell library:



where best-sellers begin.

With one of the largest standard cell and gate array libraries, and a first-time success rate of virtually 100%, GE/RCA has all the tools you need to design leading-edge products.

The GE/RCA library of hundreds of verified cells and functions is one of the broadest in the industry.

We have cells with effective gate length as small as 1.5μ (.9 μ coming soon). And double-level metal for higher-density chips that handle higher clock speeds.

You can choose from a wide range of Supercells, including core micros, RAMs, analog functions and bit-slice processors. Right now, we're working on new editions, including Advanced CMOS Logic, EPROMs and high-voltage cells. Additionally, we can generate custom cells to meet your requirements.

So you can easily reduce an entire system onto a single ASIC chip, and get the ASIC benefits of smaller power supplies, lower system cost and higher reliability.

Plus a full library of gate arrays.

If your design calls for gate arrays, you can select from a broad line with up to 13,000 gates. With alternate sourcing on the LSI/Toshiba series.

GE/RCA gate arrays have effective gate lengths as small as 1.2μ . And they're compatible with the industry standard.

Writing made easy.

We've made it easy for you to write your best-selling design.

Our designer-friendly software gets you up to speed in as little as the three days it takes to complete our training course.

And our software supports the major workstations in the industry, including Daisy,™ Mentor Graphics,™ Valid,™ P-CAD®

and FutureNet.®

Through the use of Twins, our transparent workstation interface system, you can complete or revise your design at practically any workstation.

We're also in the forefront of silicon compiler technology. So we can offer you the ability to create designs that are heavily BUS-structured, with your ROMs, RAMs, PLAs and ALUs compiled right into the design.

The best editors in the business.

We know how important accurate performance modeling is to you. That's why we've developed the industry's most advanced simulation and parasitic extraction programs, which make it easy to create designs that work. In fact, our first-time success rate is virtually 100%.

And you can count on our ASICs specialists for technical support from design through production. One other thing you can count on with GE/RCA: there are no hidden charges in addition to your NRE.

On the best-seller list for years.

GE/RCA has been the CMOS company since the day we invented the technology. We've produced one best-selling CMOS circuit after another. And built the industry's broadest line of High-Rel CMOS parts, including super radiation-hardened Silicon-on-Sapphire.

With all this behind you, think how easy it could be to design a best-seller.

For more information, call toll-free 800-443-7364, ext. 14. Or contact your local GE/RCA sales office or distributor.

Daisy™ is a trademark of Daisy Systems Corp.
Mentor Graphics™ is a trademark of Mentor Graphics Corp.
Valid™ is a trademark of Valid Logic Systems Inc.
FutureNet® is a registered trademark of FutureNet® La Data I/O Company
P-CAD® is a registered trademark of Personal CAD Systems, Inc.







Finally, graphics to match your imagination.

INTRODUCING THE FIRST EFFECTIVELY PARTITIONED VLSI ARCHITECTURE FOR TRULY FLEXIBLE GRAPHICS SYSTEMS DESIGN

Imagine a graphics architecture so powerful, you can achieve 16K-by-16K resolution. So effective, you can add virtually unlimited planes of color without degrading performance. So flexible, you can integrate it into an existing design or use it to build an entire range of new systems.

That's the Advanced Graphics Chip Set from National Semiconductor.

By using a multiple-chip, modular approach, the Advanced Graphics Chip Set avoids the design compromises and limitations of single chip solutions.

That gives you two unprecedented benefits: *performance* and *flexibility*.

Which means you can design exactly the type of system you need with exactly the level of performance your application demands.

For example, you can integrate part of the chip set with an existing general-purpose microprocessor for a low-end display.

Or you can utilize the chip set's full capabilities for a high-end, high-performance, high-resolution CAE/CAD workstation or laser printer — with virtually unlimited planes of color. Yet with the same high-

THE ADVANCED GRAPHICS CHIP SET

Raster Graphics Processor (RGP). A fully programmable, high-performance microprocessor engine specially tuned for graphics applications. Samples available Second Quarter, 1987.

Bitblt Processing Unit (BPU). A 20-MHz data chip that controls data movements within its dedicated memory plane and between it and other memory planes in a multi-color system. Available now.

Video Clock Generator (VCG). A timing and control generator providing all of the synchronization signals needed by a graphics system, with a pin-programmable pixel frequency of up to 225 MHz. Available now.

Video Shift Register (VSR). A parallel-to-serial shift register capable of serial output shift rates up to 225 MHz. Available now.

All devices available in PLCCs.

speed performance as a black-and-white application.

In fact, you can design an entire range of graphics systems without having to 'reinvent the wheel' each time, by using the same hardware building blocks and the same central software in each of the systems.

THE MULTIPLE-CHIP SECRET

The secret to all this flexibility and performance is our unique multiple-chip, modular approach. Rather than trying to squeeze all the important graphics functions onto a single chip — which would require some significant design and performance

compromises — we've partitioned appropriate functions onto individual building-block ICs. This allows us to optimize the design of each chip, and allows you to optimize your own design for your particular application.

GRAPHICS WITHOUT LIMITS

What matters most about the Advanced Graphics Chip Set, of course, is what it does for *you*. And that answer is clear when you consider its high performance, its modular approach, its open architecture, and its programmability: It gives you graphics without limits. It gives you true design freedom. It gives you the opportunity, for the first time, to design a graphics system "custom fit" to your exact specifications.

So what are you waiting for? If you're tired of those limited single-chip solutions bogging down your designs, take a look at the Advanced Graphics Chip Set. And learn how you can design a graphics system to match your needs... as well as your imagination.

For more information and availabilities, just contact your local National Semiconductor Sales Engineer or write:

National Semiconductor

Advanced Graphics, MS 23-200

P.O. Box 58090

Santa Clara, CA 95052-8090





When it comes to SUDDEN SERVICE Samtec really is a different breed of cat!



WRITE TODAY

for our new 72-page full line catalog. It has been revised and enlarged to include many new products. And it contains complete specification data for fast, easy ordering. Get yours today.













Surface Mount Socket Strips



Dual Terminal Strips



Socket Strips



Terminal Strips

For use on board, board-to-board or cable-to-board, Samtec .025" sq. post interconnects provide reliable, gas-tight connections. A unique snap strip feature allows you to snap most strips to desired lengths. CONNECT TODAY with Samtec SUDDEN SERVICE for all of your .025" sq. post interconnect needs.



HEADQUARTERS:

SAMTEC, Ltd. 35 Deerdykes View, Westfield, Cumbernauld, Scotland G68 9HN Phone: 02367 39292 FAX: 2367 27113 TLX: 776158

WORLDWIDE

HEADQUARTERS: New Albany, IN 47150 USA
Phone: (812) 944-6733 TWX: 810-540-4095 TLX: 333-918

CIRCLE NO 116

EDITORIAL

We still need the artists



This page has previously contested the suggestion that computers and software can make it unnecessary for humans to master basic writing skills (see EDN, October 16, 1986, pg 53). This issue's cover story, on graphics ICs, makes a similar warning appropriate for graphics-arts skills. No matter how powerful today's graphics engines, the artist must possess the same degree of knowledge and the same planning skills as a writer who uses a word processor, or as an electrical engineer who uses CAE tools.

Consider, for example, this issue's cover. To implement the concept of a winged figure bursting out of a graphics-display controller chip, the cover's designer, David Hamby, required five basic shapes—a torso, leg, wing, head, and chip. Although an illustrator could have roughly sketched each shape in a few minutes, Hamby needed to draw each shape to scale in both front and side views. Each view (some of the digitizing sketches drawn by Hamby are reproduced beginning on pg 112) included 3-dimensional digitizing points accurate to ½000th of an inch. The complete design required more than 2400 such points.


You may wonder what advantage lies in generating the illustration with a computer. Although the concept sketch showed the figure in a front view, Hamby thought the front view was a bit boring when he saw the computer display it. By quickly changing software parameters, he was able to rotate the figure and the wings separately from the chip. Likewise, it was fairly easy to change the figure from polished bronze to blued aluminum. At first the wings were orange, which was fine for the bronze figure, but it clashed horribly with the blue. Again, modifying software parameters let Hamby change the color. Hamby was similarly able to adjust the figure to accommodate the wishes of EDN's editorial and art staffs.

Hamby's efforts are something that no computer could duplicate. As Hamby's work shows, a designer's basic skill is a necessary part of using the computer's capabilities.

Margery Conner
Regional Editor

SEE WHAT A DIFFERENCE CMOS MAKES!

CMOS is fast becoming the chosen technology for developing integrated circuits. That's because CMOS ICs are able to implement ultra-complex system-level functions on a chip!



Now you can meet the special challenges posed by this new breed of ICs with *A Designer's Guide to CMOS ICs*. You'll learn the advanced design and fabrication techniques required. Plus the latest linear and digital CMOS ICs available.

Mail coupon to: CMOS IC Reprints EDN Magazine Cahners Building 275 Washington Street Newton, MA 02158-1630	NAME		
Please send copies of A Designer's Guide to CMOS ICs (92 pages)	TITLE		
□ \$6.95 UPS □ \$8.95 non USA (BANK DRAFT ONLY) Check or money order made out to	COMPANY		
EDN REPRINTS must accompany each order. No COD. Mass. residents add 5% sales tax.	ADDRESS		
Please print clearly. This is your mailing label.	CITY	STATE	ZIPEDN 3487



When highs and lows are forecast, DS is the answer.

Few things change as fast as the weather. But when the highs and lows in your digital system are changing at 100MHz, the forecast must be for the new 'DS' ULA* Series from Ferranti.

High speed at low power is provided by the functions featured in the 'DS' Series macro library. A D type flip-flop clocked at 250MHz maintains its clock-to-output delay of 1.5ns yet draws only 170µA.

The interfacing facilities are equally impressive.

Digital I/O macros feature input buffers with delays as low as lns and output buffers with drive capabilities as high as 48mA. The library of linear interfaces spans comparators, schmitt triggers, monostables and a range of oscillators, allowing more of the system to be integrated onto the chip.

The 'DS' Series is supported by ULACAD** software running on workstations and

VAX*** based systems. This opens up access to both the rich macro library for ease of design and silicon compilers for autorouting.

Features include:-

- ☐ system speed to 100MHz
- ☐ complexities to 10,000 gates
- ☐ 48mA output drives on every I/O cell
- ☐ digital and linear macro library
- ☐ complete CAD support
- ☐ silicon compilers

You can see why the advanced performance of the 'DS' Series ULAs means clear skies for your business.



IC Marketing
Ferranti Electronics Limited
Fields New Road Chadderton
Oldham OL9 8NP England
Telephone: 061-624 0515 Telex: 668038
Fax: 061-626 4946

*ULA is a registered Trade Mark of Ferranti plc for semiconductor devices. **ULACAD is a Trade Mark of Ferranti plc.
***VAX is a Trade Mark of the Digital Equipment Corporation.

CIRCLE NO 39




International Addresses:

☐ Ferranti CmbH, West Germany, Munich, Tel: (089)-3609-06-0☐ Ferranti Electronics Benelux, Antwerp, Tel: (0)-3/542.62.73

□ Ferranti Electronics Sweden, Stockholm, Tel: (08)-52 07 20 □ Ferranti Computer Systems (Australia) Pty Limited, Alexandria, Tel: (02)-698 5544 □ Ferranti Wheelock Microelectronics, Aberdeen, Hong Kong, Tel: (5)-538298-9 □ Ferranti Interdesign Inc. USA, California, Tel: (408)-438-2900.

Hewlett-Packard re-invents the calculator.




ENGINEERING RESPONSIBILITY SEPIA SEPIA STANDARD D-00028-40001-1

SYM REVISIONS APPROVED DATE


A AS ISSUED DRE 9/8/86

THE NEW HP-2BC DOES THINGS NO OTHER GALGULATOR CAN, AND IT DOES MORE

THE FIRST CALCULATOR THAT COES SYMBOLIC ALGEBRA




THE FIRST CALCULATOR THAT DOES SYMBOLIC CALCULUS




SCIENTIFIC CALCULATOR THAT ACCEPTS YOUR OWN FORMULAS, THEN SOLVES FOR ANY UNKNOWN



THE FIRST CALCULATOR THAT PERFORMS MATRIX OPERATIONS AS EASILY AS FOUR-FUNCTION MATH



THE FIRST CALCULATOR THAT DOES COMPLEX NUMBER ARITHMETIC AS EASILY AS FOUR-FUNCTION MATH



things than any OTHER CALCULATOR GAN, MORE THAN THE UNIQUE FUNCTIONS displayed on the LEFT, THE HP-28C ALSO BRINGS TOGETHER SUCH FEATURES AS KEYSTROKE PROGRAMMABILITY; RPN LOGIC WITH ALGEBRAIC expression entry: 120 UNIT CONVERSION FACTORS; HEX, OCTAL AND BINARY MATH -- AND CONVERSIONS 1 ADVANCED STATISTICS; AND THE ABILITY TO USE AN OPTIONAL PRINTER VIA INFRARED BEAM. FOR A

DEMONSTRATION,

CALL 1-800-307-4772, EXT, 215 G AND ASK FOR THE NAME OF YOUR NEARBST HP DEALER. THEN SEE QUOD ERAT DEMONSTRANDUM.

Q.E.D.

HEWLETT PACKARD

DO NOT SCALE THIS DRAWING			© 1987 Hewlett-Packard Company			PG12611			SEE NOTE
	ITEM	QTY.	PART	RIPTION	MAT'L-PART N	0.	MAT'L-DWG. NO.	MAT'L-SPEC.	
UNLESS OTHERWISE SPECIFIED, DIMENSIONS ARE IN INCHES.	JERRY STEIGER			4/20/86 DATE	TOPCASE - NUMERIC				
TOLERANCES .XX±.02 .XXX±.005	JERRY STEIGER		4/20/86	00028-40001					
	RELEASE TO PROD.			TITLE					
SEE CORP. STD. 608	SUPERSEDES DWG.			ZX SCALE S	HEET LOF L	D-	-00028-4	0001-1	

TO-3 Power in a Plastic Package

TO-3P

Now power supply OEMs can design out TO-3s and TO-3P bipolars and design in large-die TO-3P HEXFET power MOSFETs that offer the economy of TO-220s and the power handling capability of TO-3s.

Consider this. TO-3P HEXFETs meet or exceed TO-3 specs. Thermal resistance is lower than equivalent die sizes in TO-3s. Leads, too, conform to UL and VDE spacing.

TO-3P HEXFETs also offer an isolated mounting hole to simplify installation, cut hardware costs and assembly time.

Best of all, you can expect the same high quality and reliability all HEXFET power MOSFETs guarantee.

Over thirty TO-3P HEXFET part numbers are ready now to upgrade your design. Voltage ratings range up to 500V, and current up to 41A depending on Rds(on) and die size. For complete data, call (213) 607-8842. Today.



Most HEXFETs now in stock for immediate delivery!



Number 1 in Intern

International Rectifier

WORLD HEADQUARTERS: 233 KANSAS ST., EL SEGUNDO, CA 90245. U.S.A. (213) 772-2000. TWX 910-348-6291, TELEX 472-0403
EUROPEAN HEADQUARTERS: HURST GREEN, OXTED, SURREY RH8 9BB. ENGLAND TELEPHONE (088 33) 3215/4231. TELEX 95219

Power MOSFETs · CMOS Power Ics · Commercial/Custom Power Packages · Schottkys Rectifiers · Thyristors (SCRs) · Diode Bridges · Molded Circuits · Assemblies

TECHNOLOGY UPDATE

Add-in facsimile boards enable users of PCs to transfer CAE graphics in real time

Chris Terry, Associate Editor

With the advent of compression/expansion processor ICs, manufacturers of add-in boards for IBM PCs are now making fax expansion boards that permit you to use your personal computer as a fax machine for sending graphics over the telephone lines.

For more than 10 years, facsimile machines have used compression algorithms that allow the transmission of an 8½×11-in. page of text and images over the PSTN (Public Switched Telephone Network) in less than one minute. These algorithms conform to the CCITT's (Consultative Committee for International Telegraphy and Telephone) set of recommended standards and yield compression ratios between 5:1 and 50:1, depending on image characteristics.

Until recently, though, the hardware capable of performing these image-compression and -expansion algorithms had to be implemented in MSI logic and discrete components. It was complex, expensive, and uneconomical except in dedicated fax machines.

Now, VLSI compression/expansion processors (CEPs) contain all the logic needed to implement the CCITT algorithms in a single chip. All these VLSI CEPs embody CCITT group 3 algorithms, which remove horizontally and (optionally) vertically redundant information and yield a minimum resolution of 100 lines/in. Most CEPs can also perform compression/expansion according to CCITT group 4 algorithms, which provide a 2-D compression mode and a resolution of 400 pixels/in. in both directions.

One-dimensional horizontal com-

pression consists of calculating a line-length value that represents the number of pixels of the same color (black or white) in a scan line across the document. The variable-length Huffman code that the algorithm uses to represent run lengths assumes that each line starts with a white pixel; if, in fact, the line starts with a black pixel, the first code has to be a zero-length line of white pixels.

Two-dimensional compression uses a modified relative-element

code be sent and that the offset distance then be represented as a 1-D Huffman code.

The 2-D algorithm inserts a 1-D Huffman-coded scan line to act as a new reference line at user-specified intervals throughout the document. Thus, if a transmission error occurs in a READ code, its effect is limited to the specified number of scan lines instead of being propagated throughout the document (**Ref 1**).

Several companies are now manufacturing plug-in fax boards based



Model FX-BM88, a plug-in board from Panasonic Industrial, provides fax hardware and software that lets an IBM PC or compatible emulate a group 3 fax machine and communicate with other fax machines. The communications software lets you establish a directory and send images automatically at times that you specify.

address-designate (READ) code, based on the relative position of color changes in the previous scan line, which serves as a reference. When a color change lies exactly below the same color change in the reference line, a single bit serves to encode this fact. If the new color change is no more than three pixels to the left or right of the change in the reference line, the offset is represented by the READ code. If the offset is more than three pixels, the algorithm requires that a special

on these CEP ICs for the IBM PC and compatibles. These fax expansion boards allow the PC to emulate a group 3 fax machine. Three such expansion boards are Gammalink's Gammafax, American Data Technology's Smartfax, and Panasonic's FX-BM88.

The \$995 Gammafax package comes with software that lets you send and receive images over phone lines at rates as fast as 9600 bps. Actually, effective throughput is somewhat less because the software



CALCOMP ELECTROSTATIC PLOTTERS. FOUND IN ALL THE RIGHT PLACES.

Most companies know us for our solid reputation in pen plotters. Yet many leading corporations all around the world also know CalComp for electrostatic plotters. And they select CalComp for good reasons.

CalComp offers a full family of color and monochrome electrostatic plotters with high

resolution image quality—up to 400 dots-per-inch. Our 5700 and 5800 series plotters are self-contained plotting systems without the

need or expense of any add-on controllers.

Also, many Fortune 500 companies are already familiar with our high quality products, responsive sales support and worldwide field service network. After all, we've been in the computer graphics business for over 25 years.

So if you're shopping for the right electrostatic plotter, check the ones found in all the right places. Call 1-800-CALCOMP. Or write CalComp, P.O. Box 3250, Anaheim, California 92803.

CALCOMP

TECHNOLOGY UPDATE

performs extensive error checking, and the hardware continuously adjusts the transmission speed to match the instantaneous capability of the PSTN link. You can expect an average throughput of about 9000 bps between two PC/ATs, or about 4000 bps between two PCs or PC/XTs.

Gammafax's software features allow automatic transmission of documents at a specified time (for example, at night when telephone rates are lower), the inclusion of multiple documents in a single transmission, and the transmission of different combinations of documents to different remote sites.

By the time you read this article, the Smartfax board will be available from American Data Technology at a price between \$1000 and \$1500. This board operates at 2400, 4800, 7200, or 9600 bps. The software package that comes with it includes a built-in graphics editor that lets you compose new images, enlarge or reduce existing images, rotate all or part of an image, and perform cutand-paste operations.

The telecommunications routines let you send or receive fax images as a background task while you're running some other application. In addition, they include facilities for automatic dialing, for scheduling drawing-file transfers at specific times, for usage logging, and for looking up the current time associated with area codes throughout the world.

The Panasonic FX-BM88 expansion board (\$1000) is intended for use in Panasonic's own IBM-compatible Personal Partner PC, but it also operates in IBM PCs and other compatibles. The board provides group 3 fax transmission of images originating either from an associated flat-bed image scanner or from the PC's disk storage.


Transmission speed may be 9600, 7200, 4800, or 2400 bps, and the hardware provides adaptive equalization, error detection, and automatic retransmission of an erro-

neous block. The hardware always attempts to operate at 9600 bps, but automatically falls back to the highest speed at which the line (and remote equipment) can maintain error-free communication.

The resident software lets you send or receive fax messages as a background task while you're running another application. You can create, store, and update a fax-machine telephone directory, and the software can use this directory to send one or more fax files to selected destinations at specified times. The software also keeps a history log of all outgoing and incoming fax transmissions, and you can display or print the log at any time.

Board provides disk storage

The Kofax KF-8000 board differs from these other three boards in that it is strictly an image-compression/expansion coprocessor used primarily for efficient storage of images. You can generally store a 1M-byte image in 64k bytes of memory or disk storage. Typical applications include CAE drawing-storage and-retrieval systems, machine-vision



The KF-8000 board from Kofax compresses and expands bit-mapped images and uses the Am7971 CEP.

systems, and medical imaging systems.

You can create a fax system by using the board's group 3 compression techniques and a separate modem that communicates with any standard fax machine. For maximum resolution, and for PC-to-PC drawing transfers, however, you need to use its more efficient group 4 compression techniques.

The \$995 board comes with an easy-to-use MS-DOS device driver. (According to the vendor, it often takes less than one day of programming to interface an application program to the KF-8000.) The board also has a demonstration program that lets you perform disk-file-to-disk-file expansion or compression.

In the very near future, Kofax will be offering its KF-8200 image

Fax boards may raise legal issues

In most states, a document sent by one dedicated fax machine and received by another similar machine is accepted as a legal copy of the original: Dedicated fax machines don't provide any facilities for changing the document. The advent of PC fax expansion boards, however, may cast doubts on the legal acceptability of a faxed document. If you send a document to a PC that emulates a fax machine, the recipient of the document can change its contents by means of the PC's graphics editor.

For this reason, the Portable Office from Medbar Enterprises (Woodside, NY) includes a portable, dedicated facsimile machine. The Portafax weighs only 7½ lbs and attaches to any telephone system by means of an acoustic coupler. The Portafax can communicate with group-2 (analog) or group 3 (digital) facsimile machines.

The other components of the Portable Office are a Data General Model II lap computer with internal or external modem, and an ink-jet printer. The price of the complete system varies from \$3939 to \$5500, depending on the computer options installed. The facsimile machine is also available separately for \$1475.

AMERICA'S BEST PROGRAMMERS



Z-1000B UNIVERSAL PROGRAMMER

- Over 600 PLDs, EPROMs, EEPROMs, Bipolar PROMs and INTEL MCUs.
- · Separate D/A channels for each pin.
- Upgradeable PROM based software.
- Stand alone or PC/XT/AT operation.
- Two independent RS-232 ports.
- 64K or 256K bytes of DATA RAM.
- EXATRON handler interface is standard.



Z-3000 HIGH VOLUME GANG/SET PROGRAMMER

- 14,000 27256s programmed per day.
- 32 EPROMs simultaneously with 1 to 8 DATA BLOCKS.
- 16 Intel or Motorola MCUs at a time.
- 64K to 256K bytes of DATA RAM.

Z-1200B TWELVE SOCKET GANG/SET PROGRAMMER

- 2716 27512, 1 to 4 DATA BLOCKS.
- 64K to 256K bytes of DATA RAM.
- Software personality. No plug-ins.

Z-2500B IN-CIRCUIT MEMORY CARD PROGRAMMER

- Programs up to 32 memory cards with EPROMs or microcomputers at a time.
- Two 1.2 Mbyte DSDD floppy disk drives. Optional 20 Mbyte hard disk.
- Turnkey systems include programmer, terminal, custom interface hardware and software.
- · Simple menu driven operation.

ZAP SERIES engineering and field service programmers for EPROMs to 27C1024, Intel and Motorola microcomputers.

Z-400 economical bipolar PROM and EPROM programmer.



SUNRISE ELECTRONICS, INC.

524 South Vermont Avenue Glendora, California 91740 (818) 914-1926

CIRCLE NO 11

TECHNOLOGY UPDATE

For more information . . .

For more information on the expansion boards described in this article, contact the following manufacturers directly or circle the appropriate numbers on the Information Retrieval Service card.

American Data Technology Inc

Box 3453 Sunnyvale, CA 94088 (408) 732-2400 Circle No 709

Gammalink

2452 Embarcadero Way Palo Alto, CA 94303 (415) 856-7421 Circle No 710 **Kofax Image Products Inc**

2691 Richter Ave, #108 Irvine, CA 92714 (714) 474-1933 Circle No 711

Panasonic Industrial Co

1 Panasonic Way Secaucus, NJ 07094 (201) 348-7000 Circle No 712

compandor (for approximately \$2000). This expansion board is similar to the KF-8000 but includes 2M bytes of onboard RAM, a piggyback personality board that matches it to various scanners and laser printers, and a hardware scaling feature that lets you match the drawing size to your video display or printer. As with the KF-8000, the vendor supplies an MS-DOS driver, but you have to write your own interfaces to your application programs.

An on-line alternative exists

One of the principal uses for fax expansion boards is to communicate updated drawings between concerned parties (such as engineers and their customers), but the boards don't permit *interactive* online modification of drawings at both ends of a link. To this purpose, American Video Teleconferencing Corp (Farmingdale, NY) offers a RAM-resident software package that permits the operators of two IBM PCs (or compatibles) to call up a drawing or file at both ends and modify it interactively.

Called In-Synch and priced at \$149.95, the package's only requirement is that both PCs run the same applications program. Once one party has established a modem link (and preferably a voice link as well), either party can initiate operations that appear simultaneously on both screens. Thus, you can create a new spreadsheet or schematic drawing (or change an existing one), make suggestions about technique or lay-

out, and end up with an identical file at each end—without any difference of opinion between you and your colleague.

You don't incur high connect-time charges for transmitting large files in DIF (data interchange format) or ASCII format because only the concise commands to the application program go over the line; each PC builds or modifies its local file as the result of those commands. Even more important, you can discuss the contents of the file, suggest modifications, and immediately act on them in real time via the modem link. Clearly, this program isn't a complete replacement for all facsimile applications, but just as clearly, it can supplement your PC's fax capability.

References

1. Fuchs, Peter M, "Compressing data conserves memory in bit-mapped displays," *EDN*, October 30, 1986, pg 173

Article Interest Quotient (Circle One) High 500 Medium 501 Low 502

So, Is There a Real ASIC Second Source Setup in the Picture?



(Hint: Raytheon's RL7000 and LSI Logic's LL7000 are like . . .)

There's been a lot of wishful thinking about an active, genuine, semi-custom logic array second source. For very good reasons, but without a very good solution. Now, the right people, technology, and systems have been brought together. Raytheon and LSI Logic. It's happening.

□ Complete and identical: Long term maintenance and bilateral updates of well-known LDS™ front and back end software. The same methodology. The same libraries, logic design, physical design, testing. Identical.

LL7000 and LDS are trademarks of LSI Logic Corp.

☐ The Right Product: According to the marketplace, 7000 Series is the leading choice in 2-micron HCMOS logic. Now, with a full-on second source, 7000 Series is the ASIC standard.

☐ It's Happening: Raytheon has over ten years of logic array experience. LSI Logic has over five. Real time, in the market, with real products.

☐ Now: You ought to can the apples and oranges routine. Call Raytheon for a real ASIC matchup.

Raytheon Company Semiconductor Division 350 Ellis Street Mountain View, CA 94039-7016 (415) 966-7716

Access to the right technology

Raytheon









CY7C162

64K

CY7C185
8Kx8 35ns 100/20mA 300 mil
CY7C186
8Kx8 35ns 100/20mA
CY7C161
16Kx4 25ns 70/20mA
CY7C162
16Kx4 25ns 70/20mA
CY7C164
16Kx4 25ns 70/20mA
CY7C166
16Kx4 25ns 70/20mA
CY7C167
16Kx4 25ns 70/20mA
CY7C187
64Kx1 25ns 70/20mA

CMOS SRAM

If your job is building faster systems, here are a few compelling reasons to think Cypress Semiconductor when you think fast SRAM.

As the specs on the left indicate, we have the speed you need. In cool, low power CMOS.

And it's all available in the packaging you need.
From CERDIP to plastic to surface mount to flat packs.
Military versions? Yes *sir*.

A word on speed. And on choice.

We offer each of our SRAMs in a variety of configurations. So you only pay for the speed, size, or organization you need.

And if you need the high

New SRAM Highlights:

64K SRAM: A variety of con-

• 1K SRAM: Scheduled for Q2

compatible SRAM.

And if you need the highest speeds available, our customers tell us we are leading the way in delivering production quantities of the fastest, 25ns parts.

That benefit is a direct result of our success in pro-

ducing the most advanced VLSI technology available.

As a result, when you design in our highest performance SRAM specs, you are designing in deliverable parts.

When you're in production, the ability to choose the speed you need and the ability to rely on production quantities become extremely important. Narrow-line SRAM suppliers don't always offer you these key benefits.

How to simplify your SRAM selection:

Beyond performance specs, look for a supplier in control of the fab process, for dependable delivery of the most demanding, high performance parts.

Look for a full line SRAM supplier, so you spend less time qualifying, and more time engineering.

That is our fast SRAM story.

We have an equally beneficial story to tell you when it comes to our other three product families:

High performance PLD. High performance PROM. High performance LOGIC.

It's all in our new 1987 databook and our databook is yours for a phone call.

DATABOOK HOTLINE
1-800-952-6300, Ask for Dept C29
1-800-423-4440 (In CA), Ask for Dept C29
(32) 2-672-2220 (Europe)
(416) 475-3922 (In Canada)






ANALOG IS ALIVE AND WELL IN: A Designer's Guide to Innovative Linear Circuits

As exciting as digital technology is, you still need analog circuitry to operate on signals from real-world sources. Now, EDN is offering a wealth of analog design information in A Designer's Guide to Innovative Linear Circuits.

This 186-page collection of articles was developed by Jim Williams, one of America's foremost linear-circuit designers. It includes practical and efficient ways to use op amps, comparators, data converters, and other analog ICs, and discusses the theories behind all the design techniques presented.



Mail coupon to:				
Linear Circuits Reprints				
EDN Magazine	NAME			
Cahners Building	17/17/11			
275 Washington Street				
Newton, MA 02158-1630				
Please send copies of A De-	TITLE			
signer's Guide to Innovative Linear				
Circuits				
□\$14.95 UPS □\$17.95 non USA	COMPANY			
(BANK DRAFT ONLY)				
Check or money order made out to				
EDN REPRINTS must accompany	ADDRESS			
each order. No COD. Mass. residents	ADDRESS			
add 5% sales tax.				
Please print clearly. This is your	CITY	STATE	ZIP	
mailing label.		SIME		FDN 3487
				35

Nothing makes more contacts

than SIEDECON

Siemens offers a highly extensive range of tried and tested electromechanical components, plus all the experience of a manufacturer who has consistently invested a wealth of know-how in developing and perfecting electromechanical components geared to market requirements.

A typical example is the new SIEDECON. The first connector for double Eurocard format conforming to DIN 41612.

Based on the indirect connection principle, it solves every connection and tolerance problem.

This design provides enormous performance potential:

- Max. 256 LF contacts
- Max. 8 pre-mating LF contacts as standard
- Max. 6 special contacts
- More than 900 polarizing options
- Packing density of 15.24 mm
- Can be fully integrated into racking standard 41494

This makes SIEDECON the ideal connector for all applications requiring a large number of contacts, compatibility and flexibility.

All the other features of SIEDECON are detailed in a special publication. If you would like one, please use this journal's reader service or send us the coupon.

Contacts you can rely on. Electromechanical components from Siemens.

CIRCLE NO 47

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Edward

Coupon: To siemens AG, Intoservice 14312 Ago, Postact 2348, D. 8510 Ago, Post

NOW YOUR TWO FAVORITE TABLOIDS COME TOGETHER



IN ONE HOT NEWSPAPER... EDN NEWS



In January, EDN Product News and EDN Career News, EDN's two tabloid editions, merge to form EDN News...

bringing you all the hottest news of products, technology, and careers.

HOT NEWS OF PRODUCTS

The focus of EDN News is on hot products that will have the most powerful impact on the way you do your job. EDN News will cover the best products on the market, how they evolved, and why. Plus, it will now cover industry events (news of business, finance, economics) that drive product technology and hence product introductions.


HOT NEWS OF CAREERS

In a separate section, EDN News will keep you abreast of professional developments and job openings in the electronics field. It will carry editorial aimed at your career and professional growth. Editorial that will help you find a job and keep it.

Watch for your copy of EDN News arriving in the mail soon!

EDN News. Hot News of Products, Technology, and Careers

EDN NEWS



MEET THE INDUSTRY'S MOST WELL-CONNECTED PC. THE PERSONAL LOGICIAN.

The IBM PC-AT and Daisy's proven CAE tools.

Daisy's Personal Logician starts with the IBM® PC-AT[™] platform, plus:

- High resolution, high performance workstation graphics.
- Multi-window, multi-tasking UNIX [™]-based DAISY-DNIX operating environment.
- Expanded memory—up to 6.5 Mb RAM, 140 Mb disk—enough capacity for large designs.
- Optional Physical Modeling, to plug actual chips into system simulations.
- The broadest range of CAE/CAD software available, including: Design Entry; Digital *and* Analog Simulation; Verification; Test.
- Plus these *new* additions: Personal Boardmaster for PCB design; Personal Gatemaster for Gate Array Design; Personal Chipmaster for Custom IC Editing.

The result: A *professional* CAE/CAD workstation, at prices you can afford. For system design. For ASIC design. For custom IC editing.


Sit here. Run it there.

Beyond transparent *access* to files on the network, only the Personal Logician gives you transparent *control* of network resources, right from your desktop.

Just open a window, and control operations on other network resources—even hardware accelerators. That window displays—interactively—the remote process as it executes on another network resource or node.

Access and control accelerators for simulation. File server nodes for design data bases. Application nodes for layout verification. All *transparently*. The power of the Personal Logician gives you true CAE. A *networked* Personal Logician gives you the full power of CAE resources in a desktop system. By itself, a tool to accelerate the engineer. Networked, a tool to accelerate engineering *teams*, large or small.

Trademarks: DAISY-DNIX, Personal Boardmaster, Personal Gatemaster, Personal Chipmaster — Daisy Systems Corp.; AT — International Business Machines; UNIX — Bell Laboratories, Inc.; VAX — Digital Equipment Corp. Registered Trademarks: IBM — International Business Machines Corp.; Daisy, Personal Logician — Daisy Systems Corp.





demonstration video*: 1-800-556-6661, ask for Dept. **D86** 1-800-824-2385, (In CA) ask for Dept. D86

*We reserve the right to qualify recipients. @1986, Daisy Systems Corporation.

Psst! Valid's 78 ASIC design kits are But the good word is getting around. All the leading ASIC vendors support our design the best-kept secret in CAE.

All the leading ASIC vendors support our design validation software. Now Valid users can design a gate array or standard cell as easily as a TTL board.

Choose your ASICs from AMCC, AMD, Fairchild, Ferranti, Fujitsu, Harris, Hitachi, Hughes, LSI Logic, Motorola, National, NCR, NEC, OKI, Phillips, RCA, Ricoh, TI and Toshiba. To name a few. And we're adding more all the time.

Our design validation software features ValidGED, a graphics editor, and ValidSIM, a logic simulator that distinguishes between an ASIC and a PC board. To boost its performance, each ASIC vendor's design kit includes a library, netlist generator and utility programs.

Moreover, the design validation software runs on the IBM PC AT,™VAXstation II,™or on Valid's own SCALDsystem.

Now that the word is out, read all about it. Call for our brochure on Valid's ASIC design kits today.





Industry standard solutions

For a brochure, call us at 1-800-821-9441. In California, call 408/945-9400.

Trademarks: SCALDsystem, ValidGED, ValidSIM—Valid Logic Systems Incorporated; IBM PC AT—International Business Machines Corporation; VAX station II—Digital Equipment Corporation.

Scan-path tools speed the conversion of your design into a testable chip

Chris Everett, Regional Editor


Large chips—those with more than 10,000 to 20,000 gates—are difficult if not impossible to test. It's just not the sheer number of gates that is complicating the testing problem, but also the inclusion of memory devices such as flip-flops and latches.

You could employ a scan-path design methodology to make your chip more testable. But manually designing the additional test logic takes time. Moreover, the additional test logic increases die size and introduces timing delays, which hamper system performance. Automated scan-path design tools, however, can speed the design process while minimizing die size increases and system performance losses.

The idea of using a scan-path design methodology to make designs testable isn't new. The first published description appeared in 1973. Designers at some companies, including AT&T and NCR, have embraced the concept, expanded it, and incorporated it into their chipdesign processes.

Many other designers also tried to use scan-path design technology as well—but they gave up. They found that there were no commercially available tools to help implement scan-path testing. Similarly, the multiplexed flip-flops that the scan-path technique requires were not available as standard parts.

In addition, the available ATE systems did not support scan-path testing. Scan-path testing requires that flip-flops be chained together into a shift register so that test data can be serially shifted into and out of the circuit under test. Hence,



Large semicustom ICs are proving to be difficult if not impossible to test unless you design-in testability. Test-design tools such as Tangent Systems' Tantest suite of tools are integrated with other design-verification tools in a CAE workstation. After design entry, you can check your design for its testability, add needed test logic, verify the design's operation, and automatically generate test vectors.

each test cycle required application of a test vector one bit wide but tens of bits deep. Testers provided neither the memory depth nor the control needed to shift long strings of test data into the device.

But even had designers gotten over these hurdles, they would have been faced with the penalties of using scan-path design. First, adding multiplexers, mode-select lines, clocking logic, and other test-logic overhead would have made designs larger, which meant larger die sizes and lower manufacturing yields. On scan-path designs that were implemented, die size increases of 10 to 30% were common, with some designs incurring a 50% penalty. Moreover, adding multiplexers also adds time delays, thereby slowing down system speeds.

Thus, many engineers gave up on scan-path techniques and hoped that the test engineering department would find a way to test their designs. But now, you'll find that with chips containing 20,000 or more gates, the test engineering department won't necessarily be able to bail you out. Given enough computer size and time, automatic test-pattern generators and their associated fault simulators can generate tests for combinational logic designs, but there is a theoretical limit on the size of testable sequential-logic designs.

Therefore, to keep test development costs down or even to make testing of your sequential device possible, you must turn to some alternative like scan-path design techniques for test development and

TECHNOLOGY UPDATE

accept the penalties.

The hurdles that designers have encountered when they tried to use scan-path design techniques are now disappearing. ATE vendors are supporting scan-path designs with deep memories and scan-path test options on their ATE systems. For example, Tektronix offers a scanpath design testing option for its S-3295 tester, and Teradyne offers options for its J-967 and J-983 testers.

Semicustom vendors, such as LSI

Logic, are now offering scannable flip-flops and latches in their device libraries. Hitachi, for example, includes scan-path design testing logic in several of its CMOS and bi-CMOS gate arrays.

Automated tools available

Three companies provide tools to help you implement scan-path design: Aida, Gateway Design Automation, and Tangent Systems.

Aida's test development tools are an integral part of its Design System, which resides on the 32-bit Apollo workstation. To help you design a testable chip, Aida includes a monitor to check that you are adhering to logic-design rules so that the scan-path design circuitry can be easily added to your circuit.

The monitor is called the Logic Design Rules Checker (LDRC), an AI-based system. You can add to it your own design methodology conventions, electrical rules, technology constraints, and parts preferences.

Scan design solves sequential-logic test problems

Circuits with memory devices like flip-flops and latches are difficult or impossible to test. For instance, when attempting to initialize your circuit, you may not be able to find a test vector or a set of test vectors that can toggle your circuit's flip-flops to known states. Also, you must contend with parametric faults. Not only must memory devices be updated with correct values, but the control signals must also arrive in the correct order at the correct time. Although tools are available to develop tests for sequential logic, they have not been totally satisfactory.

Obviously, you can't be asked not to use memory elements in your design. But if the memory elements could be eliminated or masked during test, the test would be reduced to a straightforward one of testing combinational logic. Scan-path testing techniques provide just that capability.

By adding a 2-to-1 multiplexer in front of each flip-flop in your design, you set the stage for scanpath testing (Fig A). One input of each multiplexer connects to your circuit where each flip-flop's input would have been connected, and each flip-flop's input connects to its multiplexer's output. The multiplexers' second inputs are used to serially chain all the flip-flops together. That is, the output of the first flip-flop connects to the second input of the second flip-flop's multiplexer, the second flip-flop's output connects to the second input of the third flip-flop's multiplexer, and so on. The output of the last flip-flop connects to an output pin on your device. The second input of the first flip-flop's multiplexer connects to an input pin, and another input pin serves as the mode-select line, which controls whether the flip-flops operate in the normal mode or in the serial-shift mode.

In the normal operating mode, the flip-flops




Fig A—A multiplexer in front of each flip-flop sets the stage for scan-path testing.

function as usual (except for some time delay inserted by the inclusion of the multiplexer). In the serial-shift mode, the flip-flops function as a shift register. You can serially shift data into the flip-flops and set them to known states. In effect, you

TECHNOLOGY UPDATE

Initially, you load your design onto the Apollo workstation using either Aida's design-entry tools or translators, which can load net lists from Mentor Graphics workstations or workstations that can provide a Tegas-like net list. You then run the LDRC to spot any design considerations, such as feedback loops, that would prohibit you from implementing the scan-path design.

Before using the Scan-ring Generator, you select the number of scan-path chains to be added to your

design and determine the order in which the flip-flops are to be connected in each chain.

You can specify the connection of the scan-path logic chains before or after physical layout. Aida suggests that you do so before, because semicustom houses don't usually want to get involved with specifying the scan-path logic after the design has been laid out and simulated. Also if the scan-path logic chains are defined before physical layout, there tends to be less work involved if a layout change is needed. But there is a tradeoff. You may find your design requires a larger die size if the test logic is specified before instead of after the physical layout.

The Scan-ring Generator automatically converts the flip-flops to scannable flip-flops, routes and connects the scan chains, and adds the needed scan-control logic. The Automatic Test-Pattern Generator (\$45,000) then develops the patterns for both the normal I/O pins and the scan-path pins. The Fault Simulator

convert the memory elements in your design to pseudo-inputs and pseudo-outputs that can supply vectors to the combinational logic surrounding them. In essence, you increase the visibility into your design by the number of pseudo-inputs and -outputs the scan-path adds to your design. The tester doesn't care whether test vectors are applied at the device's input pins or through the pseudo-inputs created by the scan path, nor does it care where the results are gathered. The only difference between the device's I/O pins and the pseudo-I/O pins is how the tester applies and recovers the test data.

To test a device, the tester first switches the mode-select line to the serial-shift mode. The tester then clocks test data onto the flip-flops via the scan path. After the mode-select line is switched back to the normal operating mode, the tester applies test vectors to the device's input pins. The test clock is exercised, and the tester then collects and evaluates the data at the device's output pins. The tester then again switches the mode-select line to the serial-shift mode and serially shifts out the updated contents of the flip-flops and evaluates the data. While the updated contents of the flip-flops are being shifted out, new test data can be shifted in for the next test cycle.

The use of a multiplexer in front of flip-flops is the first published description of a scan-path test technology, but it has been followed by several other approaches. Currently, four other techniques are receiving attention.

NEC uses a 2-port flip-flop in its designs to implement its scan-path technique. The 2-port flip-flop uses two clock inputs instead of the single clock input and mode-select line used in the traditional multiplexer/flip-flop combination.

Instead of flip-flops, IBM uses latches in its level-sensitive scan-design technique. With this approach, you would design your chip with single-port latches instead of flip-flops and then replace each latch with a 2-port latch. However, the latches cannot be directly chained together to construct the shift register. You would have to add a second single-port latch to each 2-port latch to build the shift register.

The advantage of latches over flip-flops is that latches are hazard free; that is, they are not dependent on the clock's rise and fall times for correct operation. As long as the clock is active, the output of a latch will follow level changes on the input—hence the name "level-sensitive scan design."

To avoid the problem of having to add latches when chaining the system latches, Unisys uses a separate test-data shift register to clock data into and out of the system latches. Although you need more hardware to implement Unisys's scan-set technique, you gain two advantages over the IBM technique. You can clock the contents of the system latches into the test-data shift register during normal system operation, allowing you to take a status check any time you want. Also, data from nodes other than the latch nodes can be clocked into the test-data shift register, thereby increasing the visibility into the design.

Instead of a shift register, Fujitsu/Amdahl uses a multiplexer and a demultiplexer to implement its random-access scan-design technique. You use the multiplexer to clock data out of the system latches and other circuit nodes you want to observe. You use the demultiplexer to set the latches to known states prior to test. Like Unisys's scan-set technique, you can scan the latches during normal operation of your system.

TECHNOLOGY UPDATE

(\$15,000) grades the resulting patterns using both the Logic Simulator (\$50,000) and the Cosimulator Processor (\$40,000). The coprocessor is a special-purpose RISC machine that plugs directly into the Apollo workstation. Aida claims a

2.5 to 6.8 times improvement in time to prepare and run a simulation on a 102k-gate design using its coprocessor and simulator versus competitive systems.

The compiled fault simulator uses a variation of the D-algorithm.

After propagating and justifying the fault path, the simulator runs the resulting test vector against all the faults remaining in the undetected fault list. Any additional faults detected are then removed from the list.

How much fault coverage is enough?

The ultimate goal of testing is to limit the number of defective parts shipped to customers to an acceptable level. However, the defect level after testing is dependent on not only the number of faults your test vectors will uncover during test (its fault coverage), but also on the yield of your manufacturing process. The equation

Defect Level=1-Manufacturing Yield(1-Fault Coverage)

has proven to be an adequate model for many different manufacturing processes. You can use the graph in Fig A to visualize the effect that both fault coverage and manufacturing yield have on the percentage of parts shipped that have defects.

If you are manufacturing pc boards with a manufacturing yield of about 95% and have generated a set of test vectors that will uncover 70% of all the potential faults in your boards, then you can expect that about 1% of all the tested boards shipped will have defects. On the other hand, if you use a set of

test vectors with 70% fault coverage to test your IC design, then you can expect about 90% of your tested parts to be shipped with defects. Even if your test vector set is expanded or improved to provide 97% fault coverage, you can still expect to ship 10% of your parts with defects.

The higher defect level in ICs shipped results because of the much lower manufacturing yields found in IC manufacturing processes than found in pc-board manufacturing. IC yields of 1 to 10% will force you to use vector sets with greater than 99.90% fault coverage to ensure that you will have less than 0.1% of your tested parts with defects.

How much fault coverage is enough? It depends on your manufacturing yields and what percent of parts shipped that you can afford to be defective. If, however, you find that you do need better than 70% fault coverage, you will probably have to turn to automatic test-pattern generators and their associated fault simulators to generate the required test vectors.





Fig A—Defect level is dependent on both the manufacturing yield of its fabrication process and the percentage of potential faults in the products that are tested. Low manufacturing yields, such as found in IC manufacturing, force you to increase test fault coverages to better than 99% in order to keep the percentage of defective devices below 1%.



Engineering calculation raised to a new power.

The only software program to combine the flexibility of a blackboard, the simplicity of a calculator, and the power of a personal computer.



Now you can write calculations on your PC in standard math notation—mixing text, formulas and graphics with the

same free-form ease you have on a blackboard or scratchpad.

No new languages to learn. Simply type equations anywhere on the screen and MathCAD automatically calculates and displays your results as numbers or graphs—exactly as you want to see them. Change anything, and MathCAD instantly recalculates the results. Add text at any point to support your work. Then print and save your entire calculation as an integrated document.

Powerful built-in functions.
MathCAD handles both real and complex numbers and does automatic unit conversion and dimensional analysis. It has a full range of built-in functions including integration, differentiation, fft's and cubic splines. Or you can define your own. No wonder thousands of engineers use MathCAD every day, for everything from robotics

to signal processing and thermodynamics to fluid mechanics.

Call us today.

We're convinced that MathCAD belongs on every engineer's desk. At \$249, with our no-risk, 30-day money-back guarantee, you really can't afford not to try it. To place your order or to request further information, call us now at:

1-800-MathCAD

(in Massachusetts: 617-577-1017)

MathCAD. Once you've tried it, you'll wonder what you ever did without it. Order today.

Requires IBM PC $^{\mathfrak{G}}$ or compatible, 512KB RAM, graphics card. IBM PC is a registered trademark of International Business Machines Corporation. MathCAD $^{\mathfrak{m}}$ MathSoft, Inc.

Math CAD

TECHNOLOGY UPDATE

Gateway Design Automation's fault simulator in its Testscan (\$75,000) test-development tool operates in a different manner. Test-scan's automatic test-pattern generator (ATPG) first examines your circuit, then generates an initial set of test vectors. The vectors are then run against all the faults in your design and graded according to the number of faults found. Then the ATPG generates a new set and repeats the process until the maximum possible fault coverage is achieved.

Testscan also detects and reports all fault locations in redundant logic that are untestable. At the end of the generation step, Testscan gives you a list of those faults plus a listing of the detected faults arranged by the test vector that detected them.

To begin the generation process, you load your circuit description onto the workstation using Gateway's design-entry tools or translators to move your design from a Mentor Graphics system or any system which can provide you with a Tegas-formatted net list.

You can implement any of the four most popular scan-path techniques: IBM's LSSD, NEC's Scan Path, Fujitsu/Amdahl's Random Access Scan, or the Scan Set design technique developed by Unisys (see box, "Scan design solves sequential-logic test problems"). Also, if portions of your design are not to be tested using the scan-path techniques (such as embedded memories), you can have Testscan ignore those portions of your design.

After your design is loaded, Testscan audits the design to check that it conforms to the scan-path design rules. Any errors are listed along with diagnostic messages that tell you where they occur. Then the ATPG automatically completes the process. Typically, Testscan can audit, generate, and grade test vectors for a 2000-gate circuit in less than two minutes.

Testscan operates on a Sun or

Apollo workstation, a DEC VAX system, or an IBM mainframe. You can use Testscan to add scan-path design logic and generate test patterns for either chip designs or digital-circuit designs.

Tool waits to minimize silicon

Tangent Systems' Tantest (\$55,000) is optimized for standard-cell designs. It's an option on Tangent's Tancell system—a fully automated layout system for cell-based semicustom integrated circuits

After you enter your net list and cell library onto the workstation, you ask Tantest to run an audit. Tantest checks your design for feedback loops, inaccessible set or reset signals, and untestable faults due to redundant logic. Tantest will also check your cell library to make sure that the components needed to design the scan-path test circuitry are available. After you have sorted out any design problems, you proceed to the testability-synthesis step.

During testability synthesis, Tantest substitutes scannable flip-flops for the standard flip-flops in your design, adds test-clock circuitry, and assigns the scan-path input and output pads. It substitutes edge-triggered flip-flops in your design to support the standard scan-path design technique.

Tantest also locates each clocking network in your design and adds multiplexers so that the networks can all be connected to a single clock source for testing.

Tantest waits until after the celllayout step before determining the order in which the flip-flops are to be chained together. The flip-flops can later be chained together in any seemingly illogical order and not affect the testability of the design. The ATPG keeps track of their location within your design. By waiting, Tantest therefore does not limit the layout tool's options. Constrained layout options lead to increased die sizes. Also, because the timing within the scan-path circuitry is not critical during test, the scan-path control components can be laid out anywhere on the die to minimize die size.

However, the inclusion of the multiplexers in front of your flip-flops does impact your design's timing performance during normal operation. To minimize performance losses, Tancell uses its timing analyzer to drive the layout tool. The timing analyzer calculates the timing margins for every circuit path, including the additional scan-path test logic. The results are used to force the layout tool to move cells and interconnect routings to compensate for the additional circuit delays caused by the scan-path test logic.

After the cells are laid out, Tantest determines the order in which the flip-flops are connected based on ease of routing and reduced die size


For more information . . .

For more information on the design-for-testability tools described in this article, circle the appropriate numbers on the Information Retrieval Service card or contact the following manufacturers directly.

Aida Corp 3375 Scott Blvd, Suite 340 Santa Clara, CA 95054 (408) 748-8571 Circle No 706

Gateway Design Automation Corp Box 1545 Littleton, MA 01460 (617) 486-9701 Circle No 707 Tangent Systems Corp 2840 San Tomas Expressway Santa Clara, CA 95051 (408) 980-0600 Circle No 708

SURVIVABILITY.



4SX-3159R1

SPRAGUE As you might expect, Sprague was first to offer Option H 'High Random Vibration and High Shock' Mil Style CLR79 Tantalum-cased Tantalum Capacitors. They're made to MIL-C-39006/22 in all four case sizes (T1 thru T4) and in all voltages (6 thru 125 VDC). The 51g random vibration capability of Type 135D/Mil Style CLR79 capacitors is provided by unique cathode construction at no extra cost to users.

Performance characteristics are backed with over 50 million hours of documented testing. Sprague Electric Company, *a Penn Central unit*, Lexington, MA. For Engineering Bulletin 3760B, write to Technical Literature Service, Sprague Electric Company, P.O. Box 9102, Mansfield, MA 02048-9102.





New CMOS 1K serial EEPROM's use 3 mA active, 10 μ A standby.

Samples of Catalyst Semiconductor's two new EEPROMs are available for immediate delivery from stock. Quantity deliveries are available 30 days ARO.

The CAT93C46 unit is pin-for-pin compatible with National Semiconductor's NMOS part #NMC 9346, and the CAT59C11 with General Instrument's part #ER5911. Pricing is very competitive.

Both Feature:

 \square Reliable CMOS floating gate technology with a power drain of 3 mA active and 10 uA standby. \square Single 5-volt supply. \square Eight pin DIP and Small Outline Packages. \square 64×16 or 128×8 user selectable serial memory. \square Word and chip erasability. \square Self timed programming cycle.

They each operate over a temperature range of 0°C to 70°C, offer 10,000 erase/write cycles, ten year data retention, and power-on data protection.

Both provide a 10 ms programming cycle.

Write or Call for our Serious, No Fooling Data Pack.

Please address Catalyst Semiconductor, 4051 Burton Drive, Santa Clara, CA 95054. Phone (408) 980-9144. FAX (408) 980-8209. TWX 510-601-7631.

In Europe, contact Catalyst (U.K.): 14 Lackswood Rise, St. Albans, Herts, England ALA 9JU. Phone (44) 0727-38183. FAX (44) 0727-93365.



UPDATE

considerations.

At the completion of the testability synthesis step, the test generation process begins. Tantest uses a deductive fault-simulation process. The ATPG generates an initial test vector sequence to sensitize the signal paths in your design. The simulator then starts at the inputs and deduces what faults were detected and lists them. More vectors are generated and the process is repeated until the fault coverage goal is reached. Tangent Systems' tools are used on DEC Vax systems as well as on Intergraph's Interpro 32 workstation.

It has been said that the primary barrier to the use of scan-path design has been the lack of tools. Robert Blauth, vice president of marketing at Gateway, doesn't agree. "I'm not really sure that it's a lack of tools that is slowing [the use of scan-path testing techniques] down. I really think that the designer is not yet convinced [that he needs a scan-path design]. He feels he has got to design the highest performance or the smallest system, and he's heard horror stories as to overhead taking 20 to 50% of silicon and slowing his machine down 50%. And he's very concerned about those issues." But Blauth adds, "The world is starting to become aware of testability issues and sees the real testability problem facing-especially-ASIC design."

References

1. McCluskey, E J, "A Survey of Design for Testability Scan Techniques," Semicustom Design Guide, CMP Publications, Summer 1986, pgs 110-119.

2. Miczo, A, Digital Logic Testing and Simulation, Harper & Row, New York, 1996, pp. 277, 285

York, 1986, pgs 273-285.

3. Williams, T W, and N C Brown, "Defect Level as a Function of Fault Coverage," *IEEE Transactions on Computing*, Vol C-30, No 12, December 1981.

Article Interest Quotient (Circle One) High 509 Medium 510 Low 511

0.7µ CM05 64K 5RAM5

This blazing 64K SRAM, with 12ns address access time, is twice as fast as any non-Performance 64K. It joins our family of 64K architectures—all with 6 transistor storage cells to optimize for performance, margins, temperature range, and supply tolerances.

		Com'l	Mil
P4C187	64K x 1	12ns	15ns
P4C188	16K x 4*	17ns	25ns
P4C164	8K x 8	20ns	25ns
*Also availab	ole: Common I/e	O with outp	ut enable

For optimal packing density, our standard 64K SRAMs are delivered in the popular 0.3" package widths, in either hermetic or plastic.

But that's not all. While others are still trying to catch up to the pace set by our 0.8 micron channel lengths and 2.75 micron metal pitch, we have pushed the frontiers of technology out even further. Now Performance's PACE Technology™ features 0.7 micron effective channel lengths, and 2.25 micron metal pitch. (As we've said before, metal pitch is the design rule that separates the men from the boys in VLSI technology.)

All of our chips are made here in our Sunnyvale facility for six-inch wafers, which has now attained Class 1 status.

Memory technology with the highest speed and greatest density gives you faster systems at a lower cost. So don't be left behind. Call the company that is ready to deliver the performance your system needs.

> Performance Semiconductor 610 E. Weddell Drive Sunnyvale, CA 94089 Telephone: 408-734-9000 Telex: 6502715784 FAX: 408-734-0258

© 1987 Performance Semiconductor Corporation. PACE Technology is a trademark of Performance Semiconductor Corporation.

PERFORMANCE SEMICONDUCTOR SHATTERS THE SPEED BARRIER with a new CMOS 64K x 1 SRAM



"It is with enormous pride in the achievements of the employees of our young company that we are able to announce that our technological pace is accelerating. Our engineers and scientists are smart, dedicated, and focused. New levels of technical productivity are being established every month. We are at the tip of the tablished every month and technology vector into the future and we intend to stay there."

President



I want a faster system! Please send me detailed information on your SRAMs		
NAME	•	
TITLE		
COMPANY		
ADDRESS		
CITY/ST/ZIP		
PHONE		
	EDN 2407	





MC68020 vs. 80386.

How to run apples-to-apples vs. apples-to-oranges benchmarks on these archrival 32-bit MPUs.

Choosing the world's highest-performance 32-bit microprocessor should be as easy as making an apples-to-apples comparison with such industry-standard benchmarks as Whetstone and Dhrystone performance.

How to tell apples from oranges.

When pulling an apples-to-apples comparison, anyone, anywhere, should be able to easily duplicate the comparison factors and results.

Repeatably.

Attempt no. 1.

So, when comparing the MC68020 and 80386, the first task is to find one of each.

Motorola shipped over a quarter of a million MC68020s last year, so finding one is easy. Get the fastest available—a 25 MHz—and a 20 MHz Motorola floating-point coprocessor, the MC68881.

Next (things get harder), try to get your hands on a fully functional, bug free 80386 MPU and 80387 floating point.

And now you know why it's so hard to make an apples-to-apples comparison: you can get the Motorola devices, but "comparable" '386 and '387s? No way. You have to settle for the slower '386 and the promise of silicon yet to come on the '387.

Attempt no. 2.

All right, if you cannot find the chips, reach for readily-available 32-bit systems and compare real, live, '020- and '386-based systems from the open, commercial market.

Exasperating, isn't it? There are hundreds of choices of commercially-available, '020-based systems. But, finding comparable '386-based systems...?

Attempt no. 3.

Running real benchmarks on real products is the best comparison. There have been two attempts at questionable comparisons. Now it's time to try some industry-standard approaches, such as Whetstone and Dhrystone benchmarking. That should allow an apples-to-apples comparison, shouldn't it? If not, at least an apples-to-apples "paper" comparison should be used.

Shown here are currently-available Whetstone and Dhrystone procedures for the MC68020 and the 80386 32-bit processors. Should you wish to use industry-standard methods of comparison, you'll have to—must—rerun the Whetstones and Dhrystones for the '386 along the

WHETSTONE PERFORMANCE

The Whetstone is a standard double-precision, floating-point benchmark written in FORTRAN.

MC68020/68881

- Execution of standard Whetstone benchmark written in FORTRAN: recognized and run by all leading systems manufacturers (Cray, DEC, IBM, etc.).
- Double-precision floating point: specified by standard Whetstone for high accuracy.
- Complete, 10-loop-count execution: 1 million Whetstone instructions.
- Unary instructions executed: specified by standard Whetstone; single-operand operations.



 Entire Whetstone benchmark procedure was not modified from the original standard: no tricks or tweaks to hype performance.
 Result: 1.24 million Whetstones/

Result: 1.24 million Whetstones/ second with commerciallyavailable silicon (68020, 68881).

80386/80387

- Execution of vendor-modified Whetstone benchmark written in C: nobody else in the industry uses this particular procedure.
- Single-precision floating point: non-standard Whetstone sacrifices accuracy for "performance."
- Incomplete, 2-loop-count execution: only 200,000 Whetstone instructions.
- No unary instructions executed: intentional '386vendor modifications to Whetstone spec avoids single-operand operations.
- Altered Whetstone benchmark procedure allowed '386 vendor more favorable results: avoided branch control overhead.

Result: Claims that provide no ability for apples-to-apples comparison.



DHRYSTONE PERFORMANCE

The Dhrystone Benchmark measures CPU performance on a typical mix of high-level language statements.

MC68020

- Dhrystone results measured on commerciallyavailable system: Sun Microsystems 3/200 workstation.
- Commercially-available operating system (UNIX®).
- Commercially-available UNIX® C compiler (cc).



 Real-world memory architecture: Dhrystone WRITE operations must pass through to mainmemory DRAM.

Result: 6362 Dhrystones with commercially-available, real-world systems.

80386

- Dhrystone results measured on specially-modified "hot box" built by '386 vendor: '386 "starter kit" version not commercially available.
- No operating system used: '386 vendor used own modified debug monitor.
- '386 Vendor used own internal "beta" version of C compiler: not commercially available.
- Utopian memory architecture: zero-wait-state WRITE operations to unlimited cache SRAM —no write through to main memory.

Result: Claims that provide no ability for apples-to-apples comparison.



UNIX is a registered trademark of AT&T

same universally-accepted lines as for the '020.

And discover which processors have the greater potential for being keystones and which for being millstones in your new designs. The MC68020 is *still* the highest-performance microprocessor no matter how you slice it! For more information on the world's highest-performance 32-bit microprocessor, the MC68020, fill out the coupon and mail it to Motorola.

We're on your design-in team.

HEADQUARTERS:

Geneva, Switzerland 16 Chemin de la Voie-Creuse P.O. Box 8 1211 Geneve 20, Switzerland

SALES OFFICES:

Eastern Europe/

Vienna Denmark Finland Helsinki Paris, Grenoble, France Rennes, Toulouse Munich, Hannover, Nuremberg, Wiesbaden Germany Italy Netherlands Milan, Rome Utrecht Norway Madrid Stockholm Sweden Switzerland Zurich Aylesbury East Kilbride (Scotland) United Kingdom .

1	1	
/ ▲	A \	
	\sim	
\ /	1/	

MOTOROLA INC.

European Semiconductor Division

Write To	: Motorola Ltd., Europea Drive, Blakelands, Milto United Kingdom.	an Literature Centre, 88 Tanner on Keynes MK14-5BP,
Please		0 vs. 80386 information.
Name		
Title		
Compa		
Addres	s	
Call Me	. Phone:	289EDN03048



American Automation has designed more emulators than Intel or Motorola, more than Hewlett Packard or Tektronix, more than anyone. Count on American Automation's emulator experience.

For each EZ-PRO emulator, American Automation provides complete software support: macro cross-assembler, linker, symbolic debugger. C Language for selected processors. Count on American Automation software.

Count on EZ-PRO from American Automation for the features you need for your projects, including Deep Trace, 4,096 real-time events, 256 break-points with zoning, complex triggering, on-line assembly/disassembly.

EZ-PRO 2.1* SUPPORTS:

Intel: 8031	Motorola:	Hitachi:	Rockwell:
8032 8035 8039 8044	6800/B00 6801 6802/B02	6301 6303 6309E 64180	6502 6503 6504 6505
8048 8049 8050 8051 8052 8085A/A-2	6803 6808 6808 68808 6809/09E 68809/809E	RCA: 1802 1805 1806 CDP6805C4	6506 6507 6512 6513 6514 6515
8086 8088 80186 80188	68000 68008 68010	CDP6805D2 CDP6805E3 Zilog: Z80A	Signetics: 8X300 8X305
80286 Harris: 80C86 80C88	V20 V30	Z80B Z80H Z8001 Z8002	National: NSC800

...AND MORE.

*Connected to PC with MSDOS 3.1

american automation

2651 Dow Avenue, Tustin, California 92680 **(714) 731-1661**Telex II: 910-595-2670 AMAUTO TSTN

IBM is a trademark of International Business Machines, Inc.

Magnetic materials provide the final piece to the high-frequency switching-supply puzzle

Charles H Small, Associate Editor

Driven by the need for physically smaller supplies, power-supply designers are beginning to push beyond the 100-kHz switching speeds of today's switch-mode supplies to frequencies of 1 MHz and higher. The magnetic materials—principally ferrites—used to construct a supply's transformer core are the limiting factor of high-frequency designs, because all the other required components-high-speed power transistors, control chips, and nonmagnetic passive components-can easily handle high frequencies.

Some engineers might wonder why magnetic materials for highfrequency switch-mode power supplies pose problems. After all, the magnetic-materials industry has been supplying ferrite-core transformers of much higher frequencies for applications like local-area networks (LANs). The high-frequency signal-transformer materials have not proved suitable for power applications, however. The problem is simply that these high-frequency ferrites exhibit negative temperature coefficients. Therefore, the signal-transformer materials' inductance values decrease to unusable levels in the 100°C-plus environment of power supplies.


Only the most recent introductions from magnetic-materials makers provide acceptably low losses at moderately high frequencies. Right now, most high-frequency switch-mode power-supply projects are military designs. The smaller size and potentially lower cost of these high-frequency supplies will inevitably—and soon—force commercial engi-

neers to adopt such designs.

For example, AIE Magnetics has introduced a complete transformer assembly for 50W, high-frequency switch-mode power supplies that operate at frequencies to 1.5 MHz. The company designed the transformer to operate with the Unitrode PWM UC 3825 current-mode IC. The company claims that the transformer is 98% efficient at full load. The unit measures 1.25×1.06×0.70 in.

The transformer requires only a 700-nH, air-core output-filter inductor whose coil measures 0.5×0.5 in. The inductor is both cheaper and lighter than ferrite- or iron-core chokes. The transformer costs \$13.50, and the choke costs \$2.25 (1000).

For engineers who must design their own transformers, selecting a transformer core material for high-






Fig 1—Small differences in ferrite processing can have a major effect on the material's losses at high frequencies. These microscope photographs (magnified 400×) show two ferrites with exactly the same mix of raw materials. The material with the more uniform grain size (a) exhibits one-half the losses at high frequencies that the nonuniform material (b) exhibits.

Your very own system specialist PEA

The process controller for interference-free automatic measurements



Choose your favourite model from this family of process controllers: PCA 2/5 with 80186 CPU or PCA 12/15 with 80286 CPU plus co-processors 80287 and 80186, all rackable 19" units. External interference and RF leakage are extremely low complying with VDE 0871/0875, limit class B. And the storage space? 1-Mbyte RAM, 1.2 Mbyte on 5 ½" floppy disk drive (two drives, if required) as well as formatted 21.3 Mbyte on Winchester disk drive (option) are there to be used.

Interfaces

IEC/IEEE bus, RS-232-C, Centronics, TTL I/O (56), 14 bit D/A, Multibus I (PCA 12/15 only).



Software

MS-DOS 3.1, extended Basic incl. interfaces, extended Pascal incl. interfaces, UDI, XRUN, Kermit, dBase II, Wordstar, Knowledgeman, Multiplan, Pictures graphics software (PCA 12/15 only).

Test software

RT tests, impedance measurements, useful and interference signal measurements, audio analysis, intermodulation measurements.

And of course: custom test software developed by our system specialists.

Ask for details on Process Controllers PCA.

Rohde & Schwarz Postfach 80 14 69 D-8000 Muenchen 80 Federal Republic of Germany Telex 523 703 (rus d) Tel. internat. + (49 89) 41 29-0

There are R&S agencies in 80 countries. We plan and supply stationary and mobile systems, also on a turn-key basis. R&S services comprise installation, maintenance, calibration, training and documentation.



TECHNOLOGY UPDATE

frequency switch-mode power supplies is not easy. Manganese zinc (MnZn) and nickel zinc (NiZn) are the two leading candidates for high-frequency switch-mode power supplies, but your choice of either involves your accepting some tradeoffs.

NiZn offers much higher bulk—or volume—resistivity than MnZn. Higher bulk resistivity results in lower eddy-current losses, and eddy-current losses are proportional to the square of the supply's operating frequency. If high-frequency switch-mode power supplies eventually go higher than the 1-MHz operating-frequency region—to speeds of 20 MHz or greater—then NiZn materials will clearly be the best choice.

But MnZn ferrites offer higher initial permeability and will support higher flux densities without saturating than will NiZn. Also, MnZn materials will work over the entire military temperature range, while NiZn materials will not.

The process is the key

Making cores for high-frequency switch-mode power-supply transformers calls for new formulations and exacting process controls on the part of the ferrite manufacturer. Very subtle differences in manufacturing processes can make large differences in core performance at high frequencies, according to Ceramic Magnetics, a manufacturer of custom cores.

Fig 1 shows microscope photographs taken at 400× magnification of the company's standard MN80 ferrite after different processing runs. Fig 1a shows small, uniform grains in the material; Fig 1b's ferrite has exactly the same mix of raw materials as that shown in 1a, but it exhibits twice the loss at high frequencies because of its nonuniform grain. Despite this large difference in performance of the two materials in a circuit, they exhibit the same properties when subjected to standard bulk-resistivity tests.

Decreasing the grain size and obtaining thinner grain boundaries are not the only means of increasing bulk resistivity. This summer, TDK will introduce a 1-MHz MnZn ferrite material that features both lower eddy-current and hysteresis losses. Controlled amounts of impurities and low-temperature sintering help the material achieve twice the bulk resistivity of the company's 500-kHz H7C4 material.

No adequate tests

One curious lag between design principles and actual practice is the lack of instrumentation for testing high-frequency magnetic materials. The industry-standard square-wave tests currently employed for lower-frequency magnetic materials will not work at high frequencies. At high frequencies, magnetic-material users must employ sine-wave stimuli.

In addition, the instrumentation needed to take accurate core-loss measurements at high frequencies currently involves fairly strenuous techniques. Accurate results demand that the engineer dunk the core under test in a Dewar flask filled with nonconductive fluid (that is, in a calorimeter) and measure the core's temperature under load. You

can also make less strenuous, but also less accurate, core-loss measurements with an inexpensive RF power meter ("inexpensive" means approximately \$3500).

If you have neither a Dewar flask nor an RF power meter, you will have to rely on the manufacturers' published data. Unfortunately, not all magnetic-materials makers specify products in the same fashion.

For example, Ferroxcube conservatively specs its new 3F3 MnZn ferrite material for frequencies to 500 kHz. According to the company, however, the 3F3 material is equal to materials that are specified for 1-MHz operation by other companies. Ferroxcube performs production tests of the 3F3 material at 100 and 400 kHz.

Surprisingly, makers of iron transformer cores are not far behind the ferrite-core makers. For example, the Magnetics Division of Spang and Company (formerly Mag Inc) uses a new cobalt-alloy, amorphous-steel (Metglas) material to make tape-wound cores for magnetic amplifiers (also known as saturable reactors). These mag-amp cores can operate efficiently at switching speeds to 250 kHz, as robust post-regulators for multiple-output

For more information . . .

For more information on the magnetic materials described in this article, circle the appropriate numbers on the Information Retrieval Service card or contact the following manufacturers directly.


AIE Magnetics 701 Murfreesboro Rd Nashville, TN 37201 (615) 244-9024 Circle No 701

Ceramic Magnetics Inc 87 Fairfield Rd Fairfield, NJ 07006 (201) 227-4222 Circle No 702

Ferroxcube Div of Amperex Electronic Corp 5083 Kings Hwy Saugerties, NY 12477 (914) 246-2811 Circle No 703 Spang and Company Magnetics Div Box 391 Butler, PA 16003 (412) 282-8282 Circle No 704

TDK USA Corp 3102 Kashiwa St Torrance, CA 90505 (213) 530-9397 Circle No 705

Call 4C Electronics today . . .




To match your new IC to your old PC!!!

4C's Dip-Adaptor™ socket is the quick solution. Programmed to your specifications to match the new IC to your old PC, obsolete IC's are now an obsolete problem!!!

To reduce PC layers and expense!!!

Unscramble your PC traces while stripping away excess PC layers and cost with one small dip package. 4C's Circuit-Bridge™ dip plug is programmed to your specifications in just days.





To get the lowest profile available today in RS-232 Gender-Changers and Null-Modems.

4C offers a complete line of Gender-Changers and Null-Modems featuring a mere .915" flange to flange with zinc diecast bodies and shells for total shielding.

WE'RE THE PROBLEM SOLVERS WITH:

QUALITY • QUICK TURNAROUND • COST EFFECTIVENESS VERSATILITY • PROFESSIONALISM

(216) 354-6800

ALL PRODUCTS AVAILABLE IN STANDARD SIZES AND CONFIGURATIONS.



9330 PROGRESS PARKWAY, P.O. BOX 868, MENTOR, OH 44060 (216) 354-6800 TELEX-361717 CIRCLE NO 13

DID YOU KNOW?

EDN serves
electronic engineers and
engineering managers in more than
100 countries worldwide.

EDN

UPDATE



When fired in a newly designed elevator kiln instead of an older elevator kiln, Ferrox-cube's high-frequency ferrite materials exhibit more uniform specs from batch to batch.

switchers. The cores cost between \$1.34 and \$3.70 (100), depending on the size. For designers unfamiliar with mag-amp regulator design, the company can supply several application notes detailing the process.

Of course, obtaining a suitable transformer core isn't the end of the power-supply designer's problems. To a certain extent, the designer is no longer a power engineer so much as an RF engineer. High-frequency switch-mode power supplies change many of a designer's priorities.

Because high-frequency switchmode power supplies operate at lower flux densities, you need to minimize eddy-current losses rather than reduce hysteresis losses. Also, because the number of turns in the power supply's transformer is small, losses traced to the copper wire become less important at high frequencies. The mechanical layout of the cores and windings are very important, because even very small parasitic capacitances can lead to a significant loss of efficiency at high frequencies. Consequently, engineers are also developing entirely new mechanical configurations for transformers. In short, improved magnetic materials may provide the last piece to the component-choice puzzle, but the design puzzle is just beginning to take shape.

Article Interest Quotient (Circle One) High 503 Medium 504 Low 505

THE BIRTH OF A NEW ERA IN DIGITIZING AND ANALOG OSCILLOSCOPES.

Tektronix COMMITTED TO EXCELLENCE

TOUCH

The Tek 11000 Series is nothing less than a new generation of oscilloscopes. What you can do with it, and the way you work with it, will fundamentally alter your expectations of a scope.

These fully programmable scopes display more traces (up to 8) at higher bandwidths (up to 1 GHz), with greater accuracy (1% vertical) and include more new functions for expediting the capture and processing of data than can ever be listed here.

Two digitizing scopes exert the power of

three 16-bit processors towards longer records, more powerful triggering and higher throughput than ever before. Two analog scopes virtually eliminate manual computation, even for the most complex measurements.

Most startling is the simplification and automation of the whole measurement and analysis process. Large displays, touch-screen control, pop-up menus and built-in intelligence unclutter the front panel and keep eyes focused on the display. For the first time, you need know nothing about a scope's technology to get the most out of it.

The 11000 Series continues the plug-in versatility of the Tek 7000 Series. Five new plug-ins and three new probes tailor 11000 Series scopes to a full range of applications, from design and debug to production test.

Demonstrations are now in progress throughout North America.

To get in touch with the future of measurement. contact your local Tek sales engineer or call Tektronix at 1-800-547-1512.

DIGITIZING	11401	11402	ANALOG	11301	11302
Bandwidth	500 MHz	1 GHz	Bandwidth	400 MHz	500 MHz
Risetime	700 ps	350 ps	Risetime	875 ps	700 ps
No. Channels ¹	1-12	1-12	No. Channels ¹	1-8	1-8
Vert. Sensitivity ⁴	1 mV/div	1mV/div	Vert. Sensitivity ⁴	1 mV/div	1 mV/div
Vert. Resolution	10-14 bits ³	10-14 bits ³	Jan. 18		
Automatic Measure- ments	Min, Max, Mid, Mean, RMS, Peak- Peak, Rise, Fall, Width, Delay1, Cross, Period, Fre- quency, Main→ Window Trigger, YT Area, YT Energy, Cursors		Automatic Measure- ments	Peak-Peak Mid, Frequ Period, Wi Cycle	
Timebase Accuracy	100 ps + .002% of the measured interval		Built-in counter/ timer	500 MHz 6 Function 10 digits	500 MHz 6 Function 10 digits

²Absolute DC accuracy with full scale offset or Vc ³14-bit resolution obtained using signal averaging ⁴Except with 11A71 which has 10mV/div

11401/11402 Digitizing Oscilloscopes

One example of innumerable waveform processing capabilities: square a voltage waveform and divide by a load resistance — (L3*L3)/10 — to make a power measurement.

Customize automatic measurements to meet your needs. Touching any measurement result, for example, causes annotation to appear showing exactly where the measurement is being taken. Point Accumulate Mode keeps all digitized points in display memory to help you handle complex displays such as eye diagrams, measure worst case jitter, or catch low rep-rate glitches.

How the new technology will simplify your life.


The 11000 Series, makes it unnecessary to learn oscilloscope theory. You get more out of your scope with less effort than ever before.


Mechanical frontpanel controls have all but vanished in favor of a touchscreen interface that presents only valid selections in logical groups. Select a trace, a trigger, a measurement or other function just by touching the appropriate area of the screen or by selecting from pop-up menus that fold down out of the way once selections are made.

Or, push a button on the new probes to initiate an autorange or a sequence of stored test setups—your hands and eyes never leave the job.














11301/11302 Analog Oscilloscopes

Call up cursors to help you make high-accuracy measurements, displayed in decibels, percent, degrees, volts or seconds. Dual delayed sweeps allow expansion of the main sweep for close examination and accurate measurement of waveform parameters such as risetime and falltime Integrated 500 MHz universal counter/timer includes a unique counter-view feature that lets you see exactly what the counter/timer is triggering on.



5 AUTOSET FROM PROBE TIP. Push a button on the front panel or on the probe to set up a scaled and triggered waveform display, or to sequence automatically through a series of tests.

6 1 mV/DIV VERTICAL SENSITIVITY. Applies across the full bandwidth, right at the probe tip. Achievable on three new plug-ins.

7 MICROCHANNEL
PLATE. Enables a single
shot trace brightness in the
11302 almost 1000 times
brighter than on conventional
scopes—making even the
fastest transients clearly visible
to the eye.

ANALOG

8 500 MHz SIX FUNC-TION COUNTER/ TIMER. With 2 ns single shot resolution — 10 ps with averaging. Use with dual delayed sweeps for precise timing measurements between selected points. Counter/timer view trace ends guesswork.





1 GHz. The 11402 Digitizing Oscilloscope feares a full 1 GHz bandwidth that at the probe tip—with no acrifice in vertical resolution to help you make the most umanding voltage and timing leasurements.

2 UP TO 8 TRACES.
High-resolution screen
lets you display up to eight
waveforms simultaneously, with
an update nearly as fast as an
analog scope. No scopes ever
let you see so much at once.

3 10 ps HORIZONTAL RESOLUTION. 10-bit vertical resolution is averageable to 14 bits. Self-calibration decreases error to less than 1% DC.

4 TOUCH SCREEN OPERATION.
Procedures are fast, intuitive—the closest link ever between engineer and scope.

ALABAMA

Huntsville 35805 4900 Corporate Drive Suite H

Phone: (205) 830-9212

ARIZONA

(Phoenix)

3015 S. 48th Street, Suite 100 Tempe 85282

Phone: (602) 438-1011

Tucson Area: (602) 790-3099
Mailing Address:

P.O. Box 29540

Phoenix 85038

CALIFORNIA

(Concord) 3451 Vincent Road

Pleasant Hill 94523

Phone: (415) 932-4949 From Oakland/San Francisco: (415) 254-5353 From Sacramento: (916) 447-5072

From Fremont/Milpitas: (415) 490-7067 From Livermore: (415) 449-5176

Mailing Address:

P.O. Box 4040

Concord 94524-2040

17052 Jamboree Blvd

Mailing Address: P.O. Box 19523

Irvine 92713

Phone: (714) 660-8080

TELEFAX: (GP1)(714) 660-8080 X311

(Los Angeles)

21300 Erwin Street Service Center

20920 Victory Blvd

Woodland Hills 91367

Phone: (818) 999-1711

Mailing Address:

21300 Erwin St

P.O. Box 8500

Woodland Hills 91365

San Diego 92123

Phone: (619) 292-7330

Santa Clara 95054-1196 3003 Bunker Hill Lane

Phone: (408) 496-0800

TELEFAX: (GP 1) (408) 496-0800

COLORADO

(Denver)

393 Inverness Drive South

Englewood 80112 Phone: (303) 799-1000

Telex: (Infocom) 45-4455

From Colorado Springs: (303) 634-3933

CONNECTICUT

Milford 06460

40 Commerce Park Road Phone: (203) 877-1494

FLORIDA

Fort Lauderdale 33309

2003 N.W. 62nd Street, Suite 102 (known as) Cypress Creek Road Phone: (305) 771–9700 From Miami: (305) 947–6053

Also serves Puerto Rico and U.S. Virgin Islands

Orlando 32803

3657 Maguire Blvd., Suite 100

Phone: (305) 894-3911

From the Cape Kennedy Area

(305) 636-0343

Pensacola 32503

4700 Bayou Blvd., Bldg. 1

Phone (904) 476-1897

GEORGIA

(Atlanta)

Technology Park/Atlanta

650 Engineering Drive

Norcross 30092

Phone: (404) 449-4770

Mailing Address: P.O. Box 6500

Norcross 30091

HAWAII

Honolulu Service Center 96819 **EMC** Corporation 550 Paiea Street Suite 103

Phone: (808) 836-1138 (Service) (800) 538-8125/6 (Sales)

ILLINOIS

(Chicago)

5350 Keystone Court Rolling Meadows 60008

Phone: (312) 259-7580 TELEFAX: (GP 1) (312) 259-7580

INDIANA

Indianapolis 46268

8751 Wesleyan Road Phone: (317) 872-3708

KANSAS

(Kansas City)

10513 West 84th Terrace

Lenexa 66214

Phone: (913) 541-0322 Omaha, Lincoln, Wichita

ENterprise 6537

LOUISIANA

(New Orleans)

1940 I-10 Service Rd

Concourse Place

Kenner 70065 Phone: (504) 466-4445

MARYLAND

(Baltimore)

102 Lakefront Dr

Cockeysville 21030 Phone: (301) 771-6400

700 Professional Drive P.O Box 6026

Gaithersburg 20877

Phone: (301) 948-7151 TELEFAX (GP 1) (301) 948-7151 X321

MASSACHUSETTS

(Boston) 482 Bedford Street

Lexington 02173

Phone: (617) 861-6800

MICHIGAN

(Detroit) 24155 Drake Boad

Farmington 48024

Phone: (313) 478-5200

MINNESOTA

St. Paul 55126

4660 Churchill Street Phone: (612) 484-8571

MISSOURI

(St. Louis)

2318 Millpark Drive

Maryland Heights 63043 Phone: (314) 429-7707

NEW JERSEY

Woodbridge 07095

40 Gill Lane

Phone: (201) 636-8616 TELEFAX (GP 1) (201) 636-8616 X266

NEW MEXICO

Albuquerque 87108

1258 Ortiz Drive, S.E.

Phone: (505) 265-5541 Southern N.M. Area: ENterprise 678

Southern Nevada Area: ENterprise 678

El Paso, TX ENterprise 678

TELEFAX: (GP 1) (408) 358-3421

NEW YORK

Albany 12205

26 Computer Drive West Phone: (518) 458-7291

(Long Island)

1895 Walt Whitman Road Melville, N.Y. 11747

Phone: (516) 756-9690 NYC Customers (718) 895-8010

Poughkeepsie 12601

Beechwood Office Park 385 South Road

Phone: (914) 454-7540 Rochester 14623

1210 Jefferson Road Phone: (716) 424-5800

(Syracuse)

Northern Concourse

North Syracuse 13212 Phone: (315) 455-6661

NORTH CAROLINA

Raleigh 27612 3725 National Drive, Suite 104 Phone: (919) 782-5624

OHIO

(Cleveland)

7830 Freeway Circle

Middleburg Heights 44130 Phone: (216) 243-8500 (Sales)

(216) 243-8505 (Service)

Dayton 45449-2396 501 Progress Rd. Phone: (513) 859-3681

OKLAHOMA

Oklahoma City 73108

4400 Will Rogers Parkway

Suite 220

Phone: (405) 943-8127 Oklahoma Wats Only

Phone: (800) 522-8196

OREGON

10220 S.W. Nimbus Drive Suite K-4

Portland 97223

Phone: (503) 620-9100

Factory Service Center

Tektronix Industrial Park

Beaverton 97077 Phone: (503) 642-8600 TWX: (910) 467-8708

TI X: 15-1754

PENNSYLVANIA

(Philadelphia) 450 Sentry Parkway

Phone: (215) 825-6400 Pittsburgh 15221 1051 Brinton Road, Suite 300

Phone: (412) 244-9800

TENNESSEE

Knoxville 37923 9041 Executive Park Drive

Phone: (615) 690-6422 From Oak Ridge (615) 482-7349

TEXAS

(Dallas)

1551 Corporate Drive Irving 75038

Mailing Address:

P.O. Box 165027

Irving 75016 Phone: (214) 550-0525

Metro: (214) 751-0470

TELEFAX: (GP 1) (214) 258-0525 X256 Houston 77099

10887 S. Wilcrest Drive Phone: (713) 933-3000

Mailing Address:

P.O. Box 4309 Houston 77210

San Antonio 78232

14800 San Pedro Avenue

Suite 112 Phone: (512) 496-1161

Kelly 78226

Billy Mitchell Center 227 Billy Mitchell Road

Phone: (512) 432-1341 UTAH

Salt Lake City 84115

Timesquare Park 300 Mercer Way Phone: (801) 486-1091

VIRGINIA

(Crystal City) Rosslyn Center

1700 N Moore Street

Suite 1620 Arlington, VA 22209

Phone: (703) 522-4500 Newport News 23602

606 Denbigh Blvd., Suite 703 Phone: (804) 874-0099

WASHINGTON (Seattle)

3709 157th Avenue NE P.O. Box 97021 Redmond, WA 98073-9721

Phone: (206) 885-0900

CORPORATE OFFICE Tektronix, Inc

P.O. Box 500 Beaverton, Oregon 97077

Telephone (503) 627-7111

PRINCIPAL PLANT Tektronix Industrial Parl

Beaverton, Oregon 97077 **DIRECT ORDER:**

For Continental United States, Alaska Hawaii, Virgin Islands and Puerto Rico. Contact our National Marketing Center

Phone: (800) 426-2200 For State of Oregon, call collect (503) 627-9000

ADDITIONAL

LITERATURE or Tektronix Sales Office

serving you: P.O. Box 1700

Beaverton, Oregon 97075 Phone: (800) 547-1512

Oregon only: (800) 452-1877 TLX: 151754, TWX: (910) 467-8708 TEKTRONIX BEAV

Copyright @ 1986, Tektronix, Inc. All rights reserved. Printed in U.S.A. Tektronix products are covered by U.S. and foreign patents, issued and pending Information in this publication supersedes that in all previously published material. Specification and price change privileges reserved. TEKTRONIX, TEK PLOT 10, TEKTEST, SCOPE-MOBILE, and 🗃 are registered trademarks. For further information, contact: Tektronix, Inc., Corporate Offices, P.O. Box 500 Beaverton, OR 97077. Phone: (503) 627-7111; TLX: 151754; TWX: (910) 467-8708. Subsidiaries and distributors worldwide.



ADEE West '87 will keep you up to date on chip and system design with CAD/CAE

Joan Morrow, Assistant Managing Editor

If you need to catch up on developments in computer-aided engineering and design, you won't want to miss the Automated Design and Engineering for Electronics conference. ADEE West '87 takes place from March 31 to April 2 at the

Anaheim Convention Center in Anaheim, CA. You can choose among 15 sessions, four short courses, two workshops, and four panel discussions. But leave room on your agen-

ADEE West '87 registration and schedule

The Automated Design and Engineering for Electronics conference—ADEE West '87—will be held on March 31 to April 2 at the Anaheim Convention Center in Anaheim, CA. The conference will include 15 sessions, four short courses, and two workshops. If you plan to attend the courses and


workshops, you'll need a separate registration. For more information, you can contact the Show Manager, ADEE West '87, Cahners Exposition Group, 1350 E Touhy Ave, Des Plaines, IL; phone (312) 299-9311. For a preview of the conference sessions, consult the schedule below.

TIME	MONDAY, MARCH 30	TUESDA	AY, MARCH 31	WEDNE	SDAY, APRIL 1	THURS	DAY, APRIL 2
9:30 AM	SHORT COURSE 1 CAE/CAD SYSTEMS:	SESSION 1	SYSTEM DESIGN AUTOMATION: SIMULATION AND VALIDATION	SESSION 7	EVALUATING THE PAYBACK OF CAE TOOLS	SESSION 13	INTEGRATING DOCUMENTATION INTO THE CAD/CAE ENVIRONMENT
	SELECTION, JUSTI- FICATION AND IMPLEMENTATION PART ONE	SESSION 2	PRINTED CIRCUIT DESIGN METHO- DOLOGIES	SESSION 8	INTERFACING PRINTED CIRCUIT DESIGN WITH MANUFACTURING	SESSION 14	USING FAULT SIMULATION: AN EXAMINATION OF PRACTICAL APPROACHES
	SHORT COURSE 2 AN OVERVIEW OF	SESSION 3	AUTOMATION OF THE ASIC DESIGN PROCESS	SESSION 9	LOGIC SIMULATION	SESSION 15	SILICON COMPILA- TION USERS' VIEWS
	VLSI ASIC DESIGN AND TECHNOLOGIES PART ONE	SHORT COURSE 3	VLSI ASIC DESIGN WORKSHOP PART ONE	SHORT COURSE 4	DESIGNING FOR TESTABILITY: THEORY AND PRACTICE PART ONE	WORKSHOP 2	COMPUTERIZED METHODOLOGIES FOR PCB CAD
1:00 PM	1:00 PM SHORT COURSE 1 CAE/CAD SYSTEMS: SELECTION, JUSTI- FICATION AND IMPLEMENTATION PART TWO SHORT COURSE 2 AN OVERVIEW OF	SESSION 4	CAD SYSTEM INTE- GRATION AND DATA STANDARDS	SESSION 10	CAE FOR SEMI- CUSTOM IC DESIGN		
		SESSION 5	USER STRATEGIES FOR PLACE AND ROUTE IN PRINTED CIRCUIT LAYOUT	SESSION 11	TO CAD OR NOT TO CAD: USERS' EXPERIENCES WITH AUTOMATED ELECTRONIC DESIGN TOOLS		
		SESSION 6	SOFTWARE TOOLS FOR ANALOG DESIGN	SESSION 12	ASIC PHYSI- CAL DESIGN		
	VLSI ASIC DESIGN AND TECHNOLOGIES PART TWO	SHORT COURSE 3	VLSI ASIC DESIGN WORKSHOP PART TWO	SHORT COURSE 4	DESIGNING FOR TESTABILITY: THEORY AND PRACTICE PART TWO		
				WORKSHOP 1	SMT DESIGN AND LAYOUT		
3:30 PM		PANEL DISCUSSION 1	BOARD LEVEL SIMULATION: IMPACT AND TRENDS	PANEL DISCUSSION 3	LIBRARY SYMBOL AND MODEL STANDARDIZATION		
		PANEL DISCUSSION 2	THE VIABILITY OF DESKTOP ENGINEERING	PANEL DISCUSSION 4	THE ROLE OF CASE IN ELEC- TRONIC SYSTEM DEVELOPMENT		

EDN March 4, 1987

SPULLICILIE #15

NEW SERVO CHIP SET FOR HIGH PERFORMANCE HARD DISK DRIVES



FEATURES:

SSI 567 SERVO DEMODULATOR

- Servo demodulation for dedicated surface servo systems
- Di-bit quadrature servo pattern
- PLL synchronization

SSI 568 SERVO CONTROLLER

- Servo control for dedicated surface servo systems
- Quadrature servo pattern
- Linear velocity control loop
- Programmable offset and gain control
- Microprocessor bus compatible interface

SSI 569 SERVO MOTOR DRIVER

- · Voice coil servo motor predriver
- Compatible with complementary power FETS
- Bridge output driver configuration
 Automatic head retract and spind
- Automatic head retract and spindle motor brake command in the event of power supply failure

Now, with Silicon Systems new Servo Chip Set, HDD designers have the means to provide fast, precise, head positioning in their high performance hard disk drives.

The new chip set provides superior performance and features lower power dissipation, reduced board space, and lower cost than alternative design approaches. With its high level of integration, the set includes all the functional building blocks needed in the servo channel, and it is easily controlled via the microprocessor interface.

For more information, contact: **Silicon Systems**, 14351 Myford Road, Tustin, CA 92680. Phone: **(714) 731-7110, Ext. 575.**



TECHNOLOGY UPDATE

da for evaluating new products numerous companies will be exhibiting their latest innovations.

New on the docket this year is an exhibit called Circuitpath, which will demonstrate how to ease the integration of CAD/CAE hardware and software from various manufacturers. The exhibit links equipment from such manufacturers as Harris CAD, Gerber Scientific, FutureNet, Digital Equipment Corp, and Valid Logic Systems via a common localarea network using the TCP/IP communications protocol. During the conference. Circuitpath will design a multilayer pc board and a standard-cell IC. At different stations in this exhibit, you'll be able to see everything from circuit design and layout to documentation and plotting.

The conference sessions will mirror what Circuitpath demonstrates. For example, session 3 will focus on the automation of application-specific IC designs. Speakers from VTC Inc, NCR, Micronix Integrated Systems, and Harris Semiconductor will detail how to combine analog functions, μ Ps, memory, and other high-level functions on one ASIC. And in session 12, speakers will present papers on gate-array layout, cell-based layout, "sea of gates" layout techniques, and management issues.

"CAE for semicustom-IC design" is the topic of session 10. During this session, speakers will present papers entitled, "Analog/digital simulation," "ASIC vendor CAE limitations," "CAE for semicustom ECL design," and "AI applications in CAE."

The discussions in session 2—
"Printed-circuit design methodologies"—will attempt to cover many of the aspects of designing complex boards. Speakers will present five papers: "Bridging the gap (product-design groups vs printed-wiring design)," "Unravelling the routers: finding your way through the maze of placement and routing algorithms," "Gridless and gridded PCB

routing," "Rules-based router meets completion/design rule requirements," and "Advanced routing technologies."

Users' viewpoints

At least two of the conference sessions will be devoted to the experience of users. In session 11, panelists will describe their experiences using automated-design tools for ICs, pc boards, and board-level systems. In session 18, four speakers will describe their trials and tribulations with silicon compliers.


In addition to the 15 sessions, the conference program includes four full-day courses. "CAE/CAD systems: selection, justification, and implementation" and "An overview of VLSI ASIC design and technologies" will be conducted on March 30. The first course, which targets those in charge of selecting a CAD/ CAM/CAE system, will cover system requirements, and then show you how to find vendors, screen systems, develop operations, and track productivity. The second course will describe gate arrays and compare them with other technologies and provide an overview of gate-array design.

Short course 3, "VLSI ASIC design workshop," which begins on Tuesday morning, will teach attendees how to anticipate the problems that can occur in each phase of ASIC design. Short course 4, "Design for testability: theory and practice," scheduled for Wednesday morning and afternoon, will cover a variety of design-for-testability methods and show how you can modify a testability technique for your circuits.

Two workshops—one on surfacemount design and layout and the other on methodologies for pc-board CAD—and four panel discussions round out the agenda.

Article Interest Quotient (Circle One) High 512 Medium 513 Low 514

NEW FROM SILICON SYSTEMS— A SERVO CHIP SET FOR HIGH PERFORMANCE HDD's!



Silicon Systems now introduces the SSI Servo Chip Set. It is a 3-chip servo set for precise head positioning in the new high-performance hard disk drives. This is just the latest development in the company's program for the full integration of disk drive electronics.

The new set consists of the SSI 567 Servo Demodulator, which provides servo demodulation for dedicatedsurface servo systems; the SSI 568 Servo Controller, which provides servo control; and the SSI 569 Servo Motor Driver, which is a voice coil servo motor predriver that is compatible with complementary power FETS. The chip set includes all the functional building blocks required in the servo channel, and is easily controlled via the microprocessor interface.

This chip set will break down major barriers to entry into the development of high performance hard disk drives. With its high level of integration, it provides superior performance and features for lower power, reduced board

space, and lower cost.

For more information on the new SSI Servo Chip Set and the other exciting product families in the complete ESDI and SCSI Chip Sets for HDD and FDD disk drive electronics, contact Silicon Systems today.

Silicon Systems, 14351 Myford Road, Tustin, CA 92680. Phone: (714) 731-7110, Ext. 575.



We've taken our to its next logical

Introducing the VME Delta
Series Computer System:
The ultimate in system-level
flexibility. For years, Motorola
has supplied OEMs and system
integrators with the widest
selection of VME boards
on the market—all based

on the most advanced VMEbus technology available.

We have now taken this experience a major step forward.

First, we formed an entirely new division to better serve our OEMs and focus on their needs as VME boards and system customers. And then, our new Microcomputer Division designed the next level of systems integration—and *your* next logical system conclusion.

The VME Delta Series Computer System. The VME Delta Series redefines the concept of configurability in VME systems. For starters, take its compact enclosure. It contains 12 VME slots—plus room for up to four disk drives and a streaming tape.

Major memory configurations.

Main memory includes both parity and ECC. Up to 1.3 Gigabytes of mass storage is satisfied by a family of ST-506, ESDI and SMD disks. Quarter-inch streaming tape backup and half-inch, 9-track tape drives are available.

Unsurpassed communications with other worlds. Through intelligent communication controllers, the VME Delta Series can handle data from local or remote asynchronous devices. Industry standard communications networks and host computers can be connected using protocols such as SNA, Bisynch and more. For high-speed, local area networking, Ethernet® and TCP/IP controllers are available.

From MC68020 to the next generation—just plug in the board. By adhering to industry-wide standards, the open architecture of the VME Delta Series assures the future viability of your product. Its system

CPU uses the popular MC68020 microprocessor. You can continue to upgrade to new generations and even faster versions as they become available.

We can get you up and running in record time. The VME Delta Series is available with all the OEM tools needed to bring your applications up to speed and up to date—fast! The UNIX® System V/68™ Release 3 operating system offers a rich

environment for developing multi-user and networking applications. Other enhancements include Remote File Sharing—allowing users to share files among different computers transparently.

Also available are development tools and high-level languages such as C, FORTRAN, Pascal, and COBOL.

Powerful data management software includes UNIFY,® Oracle,® Informix,® color graphics, word processor, spreadsheet and project manager.

The team behind your team: Our Micro-computer Division team can help your OEM team with application and technical support through 100 field offices located world-wide.

We also provide comprehensive support in a wide variety of other areas—software and application update newsletters and a toll-free hotline—such as the one below.

Use it now—to find out more about our new Microcomputer Division in general and more about the VME Delta Series in particular.

1-800-521-6274



VIVIE experience conclusion.

Powerful Processors

Uses 32-bit MC68020 MPU and MC68881 Floating Point co-processor; easy upgrade to next generations.

> UNIX-V.3/Remote File Sharing (RFS) Uses SYSTEM V/68-

compliant with AT&T's UNIX System V Release 3 with RFS for easy system networking. Real-time executives are available.

Large Main Memory Up to 16 Megabytes, with both ECC and parity.

Flexible Mass Storage, up to 1.3 Gigabytes Internally, up to 4-51/4" mass

storage drives including floppy and Winchester drives, 1/4" streaming tape. SMD disk and 9-track tape interfaces for additional external mass storage.

Open/Expandable Architecture

Twelve I/O connector/transition slots; 12-slot VMEbus card cage (A32/D32); whopping 450 watt power supply covers any expansion need.

Local and Remote **Diagnostics**

Provides for cost effective remote testing via modem and comprehensive local testing.

Complete Development Support

Supports C, Pascal, FORTRAN, COBOL and other high-level languages; varied development tools available.

Attractive/Sturdy Enclosure

Floormount enclosure meets UL, CSA, VDE, IEC, FCC requirements; shock mountings for disk drive protection.

VME DELTA SERIES, System V/68 are trademarks of Motorola, Inc. UNIX is a registered trademark of AT&T Ethernet is a registered trademark of Xerox Corporation. INFORMIX is a registered trademark of Informix Software. ORACLE is a registered trademark of Oracle Corporation. UNIFY is a trademark of UNIFY Corporation.

Allows Manufacturing Automation Protocol (MAP) technology to be incorporated into products.

Data Management Software Supports UNIFY, Oracle, Informix relational database systems.

Office Automation Software

Color graphics, word processor, spreadsheet, project manager and many more packages



MOTOROLA Microcomputer Division

Approaching our technology from your point of view. CIRCLE NO 97


Fiber Optic Devices

The Strongest Link.



Put your local network on a firm footing

with NEOLINK optical data links from NEC. These high-speed devices operate at a wavelength of 1300 nm making them the ideal choice for all high-capacity digital communication applications up to 200 Mbit/s.



NEC's ECLcompatible system solu-

tion links a computer to peripheral components up to 3 km away. The 2012T transmitter uses an InGaAsP LED, while the 2012R or 1311R receiver features an InGaAs PIN photodiode and automatic gain control.

State-of-the-art LSI technology sinks costs and boosts performance. Small size, a low parts count, high reliability and simple snap-on installation combine to make NEOLINK the strongest link in your communications network.

West Germany: Düsseldorf 0211/650301, Telex 858996-0 The Netherlands: Eindhoven 040/445845, Telex 51923 France: Paris 01/39469617, Télex 699499 Italy: Milano 02/6709108, Telex 315355 Sweden: Täby 08/7328200, Telex 13839 UK: Milton Keynes 0908/691133, Telex 777565




Floating-point chip set executes 60M flops, comes in ECL- and TTL-compatible versions

The B3110/B3120 floating-point chip set executes 60M nonpipelined, 64-bit floating-point operations per second. The set comprises a multi-

plier and an arithmetic logic unit (ALU), and it supports both the IEEE-754 and the DEC F and G floating-point formats.

The multiplier performs singleprecision (32-bit) or double-precision (64-bit) floating-point multiplication, division, square-root



Comprising a multiplier and an ALU, the 10 KH ECL-compatible B3110/B3120 floating-point chip set uses a flow-through architecture that skirts the problems of pipelining by completing every operation in only one cycle.

EDN March 4, 1987

Does your analog simulator analyze:

- production yield?
- sensitivity?
- worst case?

Good circuit simulators, will analyze your "best case" design . . . but what about the real world?

Use MicroSim's **PSpice.** We offer a fully integrated, **Monte Carlo Analysis** package which will analyze both discrete (printed circuit) and IC designs using statistical techniques.

Predict yield by simulating the effect of component tolerances, and the combined effect of variations. Identify performance sensitivity to individual components, and the "worst case" combinations. The Monte Carlo Analysis is fully integrated for error-free setup and use, faster simulation, and collated results.



Our **Probe** graphics option shows the performance variations of your design, quickly and accurately. Also, PSpice gives you more than just voltages (for example, *group delay* for filter design is included).

Monte Carlo Analysis is just one of the options available for PSpice, the world's most widely used analog circuit simulator.

MicroSim's PSpice software runs on IBM-PC™ compatible and DEC VAX™ computers.



MicroSim Corporation

23175 La Cadena Drive Laguna Hills, CA 92653 (714) 770-3022 • (800) 826-8603

Call today for further information and a free evaluation copy of our software.

IBM-PC is a trademark of International Business Machines Corp. VAX is a trademark of Digital Equipment Corporation.

CIRCLE NO 16

UPDATE

calculation, or 32×32-bit integer multiplication in a single cycle. Its division and square-root instructions don't require external seed or look-up-table storage. The chip accomplishes single-precision multiplication in 35 nsec and double-precision multiplication in 45 nsec. It calculates square roots in as little as 170 nsec (single precision) or 325 nsec (double precision). Its worst-case division times are 105 nsec and 180 nsec for single and double precision, respectively.

The ALU's instruction repertoire includes add, subtract, integer shift, rotate, and arithmetic or Boolean operations on 32- or 64-bit integers in a single cycle. It executes integer operations in 10 nsec and floating-point operations in 25 nsec. The multiplier and the ALU incorporate 63,000 and 65,000 transistors, respectively.


The chip set uses a flow-through architecture instead of a pipelined approach. One disadvantage of pipelining is that it requires multiple cycles in order to generate results. Another problem is that the controlling software must manage the pipeline stages. The flow-through architecture skirts these problems by completing every operation in only one cycle.

The chip set incorporates errorchecking features, which include parity generation and checking on all data ports. Scan paths are also provided on all registers.

The B3110 floating-point multiplier and B3120 ALU are compatible with 10KH ECL parts; they cost \$640. The B2110 and B2120, TTL versions of the multiplier and ALU, sell for \$490.—Jim Wiegand

Bipolar Integrated Technology, 1050 NW Compton Dr, Beaverton, OR 97006. Phone (503) 629-5490.

Circle No 725





Lucas NSF Pushbuttons

New RF 1519 flat panel switches with superior audible click and feel operate millions of times. PC mounted, low profile switches, upgrade any switch panel with improved durability. Wide array of options (lighted or unlighted). Two sizes: 15mm and 19mm.

Unique, Series 75 pushbutton switch for front mounting allows socket to be flow soldered to PC board, eliminating wicking. Full range of SL (solder lug) or PC mountable switches.


Lucas NSF Keylite® keyboard switches are noted for low cost, dependability, 5 million cycle life, and versatility.

All switches stocked. Request switch catalogs.

Ledex Inc. P.O. Box 427 Vandalia, Ohio 45377-0427 U.S.A. Phone: 513-898-3621



helpful switch technology
CIRCLE NO 17



AN OPEN AND SHUT CASE FOR VME.

DIN connectors are terrific for long life and resistance to corrosion, but they also resist being plugged in and out.

Your average VME card with 192 pins, for example, may take about 24 pounds to get out of your card cage. That's a lot of force to apply with a couple of fingers.

Scanbe has two fixes for the problem. Pick one or the other, or both, depending upon your packaging situation:

E-Z-JECT is a replacement for a standard VME front panel. It has a hinged handle that lets you pop out a VME card from its backplane without the yanking and struggling you're used to. It works in any standard VME card rack. It's the way the VME front panel should have been designed in the first place.

S-217 is an injector/ejector system that gives you a lot of leverage—about 3.5 to 1—for the easiest

insertion and ejection of cards without front panels. It's a great help for 6U cards and it's the ultimate answer if you're using 9U cards. (If you're using Eurocards, you should be talking to us about our versatile standard and mixed-height Eurocard cages.)

Or you can use both. Our newest VME card cages let you intermix S-217 and E-Z-JECT.


So there's no mystery at all to getting VME cards in and out of your system. Just call Scanbe today for the solution:

800-227-0557 (in California 818-579-2300)



LEADERS IN PACKAGING TECHNOLOGY

3445 Fletcher Ave., El Monte, CA 91731-3001 TWX 910 587 3437



Update 3... complete 10-bit ADC.

Ferranti is extending its range of standard product ICs adding new voltage references, data converters, timers, motor speed controllers, telecom and SCSI

devices among others.

Our philosophy is to provide system solutions at an economic cost. To achieve this, many of the products are designed to require little or no external circuitry.

However, sometimes the need for flexibility in system design requires a less dedicated approach. Ferranti also offers many of the sub-functions in monolithic form.

Ferranti is also very aware of the increasing demand for surface mounted packages, so most products are available

in SO and LCCs. But perhaps the best reason for buying from this product range is that Ferranti is committed to it.

To implement this commitment we have teams of design, application and marketing engineers whom you are welcome to consult and a wealth of data and application reports to make the design-in function that little bit easier.

Watch this space for the latest update.

IC Marketing Ferranti Electronics Limited Fields New Road Chadderton Oldham OL9 8NP Tel: 061-624 0515 Telex: 668038 Fax: 061-626 4946



FERRANTI Semiconductors



International Addresses:

☐ Ferranti GmbH, West Germany, Munich, Tel: (089)-3609-06-0 ☐ Ferranti Electronics Benelux, Antwerp, Tel: (0)-3/542.62.73 ☐ Ferranti Electronics Sweden, Stockholm, Tel: (08)-52 07 20☐ Ferranti Computer Systems (Australia) Pty Limited, Revesby, Tel: (02)-708 6655 ☐ Ferranti Wheelock Microelectronics, Aberdeen, Hong Kong, Tel: (5)-538298-9 ☐ Ferranti Electric Inc., USA, New York, Tel: (516)-543-0200.

Low-cost, digital pattern generator specs 35-MHz, 64k-bit performance

For \$6995 you can buy a 35-MHz digital pattern generator, recorder, and analyzer that handles 16 to 72 64k-bit data channels. The Data-Source-8600 is a hardware/software package that plugs into your IBM PC or into a compatible computer to perform real-time data recording, data-stream comparison, and error detection at frequencies ranging from 0.3 Hz to 35 MHz with 0.01% accuracy.

The product's hardware includes a benchtop or rack-mountable chassis that comes with two 8-channel cards and TTL or CMOS probes. You expand the system to the 72-channel limit by adding more cards and probes. Each card provides 64k bits of pattern memory per channel. A half-length expansion card connects the chassis to any IBM PC or compatible computer; you insert it

into the PC, and it provides its own bus to handle high-speed data reception. You are therefore not restricted by the slow performance associated with RS-232C and IEEE interfaces, which use the PC bus. You can designate each channel as an input or an output, and you can obtain a printout of generated data patterns.

It's the WaveEdit software, however, that distinguishes this product. Referred to by its developers as "a wordprocessor for waveforms," the program uses pop-up help windows, menus, and interactive color graphics to guide you through waveform-design commands such as counter and clock creation, channel concatenation based on Boolean logic, and waveform inversion.

WaveEdit also lets you copy and move sections of waveforms, much in the way a wordprocessor lets you copy and move sections of text. The display window shows as many as 16 channels; horizontal and vertical scrolling and paging let you scan additional patterns. The software highlights comparison errors between waveforms. You can also name and annotate channels, elect binary or hexadecimal data display, and select horizontal scales ranging from 32 bits to 64k bits.

If speed isn't a critical factor in your waveform analysis, however, you may want to order µSource instead. Priced at \$395, this software-driven pattern generator and analyzer offers the same functions as the DataSource-8600, but at frequencies reaching only 50 kHz when used with a 6-MHz 80286-based computer (a standard 8086-based PC performs at approximately 20 kHz). Besides the software (which is 95% compatible with the Data-Source version), you receive an interface card and a 16-channel TTL/ CMOS probe.

Additional 8-channel card/probe sets for the DataSource-8600 cost \$1295 (5). Extra 16-channel µSource probes cost \$195. The manufacturer also offers a free demonstration disk that reviews the WaveEdit functions and lets you compose waveforms.—J D Mosley

Analytic Instruments Corp, Box 20340, Dallas, TX 75220. Phone (214) 357-3882.

Circle No 726



Boasting a 35-MHz clock rate and the capacity for 72 channels, the DataSource-8600 turns your computer into a low-cost, high-performance digital pattern generator, recorder, and analyzer.

Compact magnetic rotary encoder operates in harsh environments

The Model RE10 magnetic rotary encoder bridges the gap between industrial encoders and open-frame kits, offering a useful alternative that combines the best features of both. Instead of relying on electromechanical wiper contacts or optical components, which require a good deal of volume to accommodate alignment and focusing, the RE-10 employs high-density magnetic materials to achieve its compact size—14.3 mm in thickness by 38.5 mm in diameter.


Model RE10 offers a selection of seven angular resolutions ranging to 2048 counts per revolution; the maximum rotational speed is 5000 rpm. The lightweight unit (40 grams) comes in a protective, shielded case; you can design it into tight spaces with little concern for accumulation of dirt, splashes of oil, and other hazards that would degrade the reliability of optical encoders.

Whether the RE10 is operating as a tachometer or as a shaft-position encoder, it connects to the host equipment via an optional universal coupler and rotor shaft. The encoder accommodates radial and axial shaft loads of 1 and 0.5 kg, respectively.

Inside, the 4-mm rotor shaft terminates in a nonferrous aluminum wheel (¾ in. in diameter and ¼ in. thick). A plastic toroid-shaped magnet, integrated onto the circumference of the wheel, is made up of a rare-earth samarium cobalt magnetic material suspended in a polymer base.

A look inside

The manufacturer records magnetic domains in the circular plastic magnet, at selected pitches that define the encoder's angular resolu-



A compact, lightweight unit, the RE-10 magnetic rotary encoder works well in tight spaces, and it's impervious to accumulations of dirt, splashes of oil, and other hazards that would degrade the reliability of an optical encoder.

tion. A magneto-resistive read head is positioned tangentially to the wheel's circumference and separated by an air gap of about 0.02 in. The read head is fabricated on a ceramic substrate and comprises a thick-film resistive element that effectively changes its resistance under the influence of an external magnetic field.

A bias current flows in the read head. As encoded domains sweep by the read head, they alternately oppose and aid the bias current's own inherent flux fields, modulating the bias current. Subsequent modulations are directly analogous to the speed and polarity of the magnetic domains as they pass by the read head.

Because of the large air gap separating the wheel from the read head, and because the read head is located at the edge of the wheel rather than at its face, no alignment in the assembly has to be precise. Even under extreme ambient conditions and heavy shaft loading, the encoder operates reliably because there are no critical part tolerances or alignments as in optical encoders.

CMOS hybrid processes outputs

As magnetic domains sweep past the sine and cosine sense elements, they produce two sinusoidal signals (A and B) in quadrature phase. These signals are amplified, squared, processed, and buffered in a 5V CMOS hybrid circuit. Two open-collector npn transistors, each of which can sink 30 mA, send the electrical output to the host circuitry. The CMOS hybrid circuit's metal housing shields against ambient magnetic fields and RFI.


You order the device according to the way the wheel is encoded at the factory. For a resolution of 2048 counts per revolution, you would order the encoder with a -512 suffix. Currently, there are seven suffix numbers available: -512, -500, -400, -360, -256, -200, and -100. The RE10-100 features a resolution of 400 counts per revolution. The maximum output frequency of any of the seven models is 100 kHz.

The units operate from a 5V supply and consume 150 mW max. The operating range spans -10 to +60°C, and the maximum operating humidity equals 95%. The required starting torque is 10 g-cm max; the shaft, wheel, and bearings produce a 2.5 g-cm² max moment of inertia. Encoder, \$111; coupler, \$9.

-Tom Ormond

National Machine Systems Inc, 137 Bristol Lane, Orange, CA 92665. Phone (714) 921-0630.

Circle No 728



ASIC answers close to home.

Design Support Centers give complete service, from questions answered to turn-key designs in your choice of technologies.

The quality and convenience of a supplier's support and service must rank high among key determinants in your selection of an ASIC source.

You'll want design centers close at hand, not just at a distant headquarters. You'll expect application engineers in the field who know their way around semicustom technologies, who can provide the guidance to assure you of fast-cycle silicon that works right the first time.

That's Motorola ASIC support and service. You get exactly the help you need, from first contact to final silicon. It's customer-specific ASIC support.

There to help with whatever it takes.

We've got Bipolar, CMOS and BiMOS technologies. We've got Macrocell arrays and Standard Cells. If your choice is already made, great. If not, our Design Support Centers have the people to help identify the optimum approach for you.

Got a software question? Need a turnkey design? Looking for expert help in our shop or yours, or questions answered over the phone? A handy Design Support Center has your solution. Use Motorola resources to decide if and how semicustom can help, and to optimize design trade-offs for reduced costs. Use our workstations if need be. It's customerspecific support.

Service and support where you want it.

Our first class factory team is always on call, but we're determined to serve you as close to home as possible. Motorola Design Support Centers worldwide are staffed by our own ASIC specialists and provide full service.

The Motorola authorized distributor Design Centers of Hall-Mark, Hamilton/Avnet and Schweber offer full design support as well as convenient stocking. Five separate U.S. independent Design

Centers extend broad support ranging from system definition to technology selection and total turn-key capability.

Finally, Motorola's Technical Training group offers acclaimed ASIC training.

Motorola should be your ASIC supplier. To learn more about our ASIC training courses or find the location of the closest Motorola Design Support Center, contact

your Motorola sales office. For published Motorola ASICs information, please write or send the completed coupon to Motorola.

We're on your design-in team.




MOTOROLA INC.

European Semiconductor Group

	Write To: Motorola Ltd., European Literature Centre, 88 Tanners Drive Blakelands, Milton Keynes MK14-5BP, United Kingdom
Agent	Please send me more information on Motorola ASICs.
Reporter the	Name
	Title
GNICTO FAMOUR.	Company
	Address
to second	City
	Country

IDEAS THAT POWER TECHNOLOGY



THE VF SERIES
GIVES YOU
AN
AFFORDABLE
AND
UNIQUE
ALTERNATIVE
TO A
UPS

ur new failsafe VF power supply series is a good idea that's now a quality product.

When loss of AC power is experienced, the VF series switching power supplies allow instant transition from AC to DC battery power input. The DC battery takes over WITHOUT INTERRUPTION. That's right, not one single glitch. That means no data loss and no unorderly shut down.

Our unique VF circuitry features a common transformer between the AC and DC input circuitry. You're guaranteed failsafe power. Plus, it fits easily inside your operating system.

Like all Converter Concepts' power supplies, the VF series CIRCLE NO 18 operates on any voltage in the world WITHOUT SWITCHES, JUMPERS, TAPS OR OTHER MODIFICATIONS. And they're designed to meet international safety standards.

Too good to believe? Well, believe it. The VF series is but one of our many powerful ideas that work.

To find out more, contact the Converter Concepts' representative nearest you. Or call us directly. That's the best idea yet.



Industrial Parkway • Pardeeville, WI 53954 (608) 429-2144 • TWX: 910-280-2630 Toll-Free 800/253-5227

CALL YOUR NEAREST CONVERTER CONCEPTS REPRESENTATIVE:

ALABAMA Futron Inc. (205) 895-9160 ARIZONA Cantec Sales Inc. (602) 829-0191 ARKANSAS

Tesco (214) 681-1376 CALIFORNIA (Northern and Central) Pacific Marketing Inc. (415) 887-1620 (Southern)

(Southern)
Converter Concepts Inc.
(800) 253-5227
COLORADO

Dynatech Inc. (303) 773-2830 CONNECTICUT Wayland Engineering (617) 655-6080 DELAWARE

Koebert Associates
(215) 887-2310

DISTRICT OF
COLUMBIA
Converter Concepts Inc.

COLUMBIA Converter Concepts Inc. (800) 253-5227

FLORIDA (Central) Perrott Associates Inc. (305) 298-7748 (Western) Perrott Branch Office (813) 443-5214 (Southern) Perrott Branch Office (305) 792-2211 GEORGIA

Futron Inc. (404) 263-9688 **IDAHO** Dynatech Branch Office (801) 546-4837

(801) 546-4837 ILLINOIS KMA Sales Company (312) 398-5300

INDIANA (Central, Southern) Jim Finnegan Branch (513) 890-8322 (Eastern) Jim Finnegan Branch (616) 846-4980

10WA Microelectronic Sales (612) 829-0948

KANSAS Converter Concepts Inc. (800) 253-5227 KENTUCKY

KENTUCKY Jim Finnegan Branch (513) 890-8322 LOUISIANA Tesco (214) 681-1376

MAINE Wayland Engineering (617) 655-6080

MARYLAND Koebert Associates Branch (304) 229-8401 MASSACHUSETTS

Wayland Engineering (617) 655-6080 MICHIGAN Jim Finnegan Branch (616) 846-4980 MINNESOTA

MINNESOTA Microelectronic Sales (612) 829-0948 MISSISSIPPI

Futron Inc. (205) 895-9160 MISSOURI

Converter Concepts Inc. (800) 253-5227 MONTANA Converter Concepts Inc. (800) 253-5227 NERRASKA

NEBRASKA Converter Concepts Inc. (800) 253-5227

NEVADA (Northern) Pacific Marketing (415) 887-1620

NEW HAMPSHIRE Wayland Engineering (617) 655-6080

NEW JERSEY Koebert Associates (215) 887-2310 NEW MEXICO

Cantec Sales Inc. (602) 829-0191 NEW YORK (New York City, Long Island)

Long Island) Koebert Associates (215) 887-2310 (Upstate New York) Pl'Tronics Inc. (315) 455-7346

NORTH CAROLINA Futron Inc. (919) 833-8755

NORTH DAKOTA Microelectronic Sales (612) 829-0948

Jim Finnegan & Co., Inc. (216) 398-6300 (513) 890-8322

OKLAHOMA Tesco (214) 681-1376 OREGON

OREGON Converter Concepts Inc. (800) 253-5227 PENNSYLVANIA

(Western) Jim Finnegan Branch (412) 823-5400 (Eastern) Koebert Associates (215) 887-2310

RHODE ISLAND Wayland Engineering (617) 655-6080

SOUTH CAROLINA Futron Inc. (919) 833-8755

SOUTH DAKOTA Microelectronic Sales (612) 829-0948

TENNESSEE Futron Inc. (404) 263-9688 TEXAS

Tesco (214) 681-1376 UTAH

Dynatech Branch Office (801) 546-4837 VERMONT Wayland Engineering

Wayland Engineering (617) 655-6080 VIRGINIA Koebert Associates Branch (304) 229-5797

WASHINGTON Converter Concepts Inc. (800) 253-5227

WEST VIRGINIA Jim Finnegan Branch (412) 823-5400 WISCONSIN

WISCONSIN KMA Branch Office (414) 259-1771 WYOMING

WYOMINGDynatech
(303) 773-2830

INTERNATIONAL

ENGLAND Computer & Aerospace Components Ltd. Tel: 01 397 5311 ISRAEL 52523 Milchan Bros. Ltd.

Tel: 9723 728158

ITALY
Elcam S.R.L.
Tel: 02 2366 641

NETHERLANDS


NORWAY
Powerbox Norway A/S
Tel: 472 535837
SWEDEN
Powerbox AB
Tel: 11502

WEST GERMANY Powerbox BRD Tel: (0711) 2261150

CIRCLE NO 19

PRODUCT UPDATE

20-nsec cache RAM features on-chip comparator



Boasting a 30% improvement in speed over that of similar RAMs that use external, discrete comparator circuits, the MK41H80 Tagram static RAM also provides a Flash Clear function and full-speed read access.

Eliminating any need for an external comparator circuit, the MK41H80 Tagram, a 4k×4-bit static RAM, is suitable for use in cachetag applications. The chip contains a 4-bit comparator that compares RAM contents to current input data in as little as 12 nsec.

The MK41H80 compares the contents of addressed RAM locations to current data inputs. An output of logical one on the chip's Match pin indicates that the input data and the RAM contents match. You can connect the Match pins of several Tagrams to provide Enable or Acknowledge signals to a data cache or μP .

The part's Flash Clear feature lets you clear all RAM bits to logical zero in 40 nsec or less. The Tagram also gives you full-speed read access to the RAM's contents, thus reducing the possibility that the Tagram will induce delays in circuits controlled by high-speed μPs .

You can order the Tagram with an address- and match-access time as low as 20 nsec. Other versions spec 25- and 35-nsec access times. The Tagram operates from a single 5V power supply. Its inputs and outputs are TTL compatible and are protected against static discharge. Available in a 22-pin, 300-mil plastic or ceramic DIP, the Tagram ranges in price from \$10.19 to \$22.50 (100).—J D Mosley


Thomson Components-Mostek Corp, 1310 Electronics Dr, Carrollton, TX 75006. Phone (214) 466-6000. TLX 730643.

Circle No 727

Modelec BV Tel: 08380 86262

DADISP.

the First Spreadsheet designed exclusively for Scientists and Engineers.



Make Waves ...



make Sense.




(617) 577-1133

Order our \$20 Interactive Demo Disk. Ask about DADiSP for IBM-PC/XT/AT, DEC MicroVAX, HP9000, Masscomp 5000, and Sun Workstations. For further information write DSP Development Corporation, One Kendall Square, Cambridge, MA 02139, (617) 577-1133



PRODUCT UPDATE

Voice-compression chip doubles T1-line capacity



By compressing the speech bit rate for telephone voice transmissions from 64k to 32k bps, Dallas Semiconductor's DS2167 ADPCM processor lets you double the capacity of T1 networks.

The DS2167 combines a digital signal processor (DSP) with an algorithm known as Adaptive Differential Pulse Code Modulation (ADPCM) on a single chip. The result is a voice-transmission rate of 32k bps, which effectively doubles the capacity of 64k-bps full-duplex telephone links.

The ADPCM algorithm allows the DS2167 to conform to the latest CCITT standards while dividing the bit rate for standard speech transmission. The algorithm was developed by CCITT and enhanced by T1Y1 (a North American standards body) to facilitate full-duplex compression and expansion of a voice channel.

In T1 networks, the DS2167 doubles the transmission capability of existing equipment without any need for extensive modification. Thus, you can expand your 24-voice-channel T1 line to accommodate 48

channels by splicing one DS2167 chip per voice channel into each end of the T1 line.

You can also use this chip to integrate voice and data services. The DS2167 offers transmission capabilities that are similar to the Integrated Services Digital Network (ISDN), because the reduced voicetransmission bandwidth lets you combine voice and data transmission on a single line. Such a voice-compression function previously required an entire pc board of electronics. The 24-pin CMOS IC consumes less than 150 mW and costs \$39 (1000).—J D Mosley

Dallas Semiconductor Inc, 4350 Beltwood Parkway, Dallas, TX 75234. Phone (214) 450-0446.

Circle No 729

For more confidence in your scope measurements...



Explore HP Digitizing Oscilloscopes.

Digitizing technology provides a highly accurate display of your signal.

Unlike their conventional analog counterparts, digitizing oscilloscopes are quantitative measurement instruments that capture and quantize input signal information. This gives a more accurate picture of a signal than an analog scope's trace. While analog scopes provide a good qualitative look at signal behavior, digitizing scopes do more...letting you pinpoint causes of the behavior and more precisely measure and analyze captured information.

Display accuracy comes of age.

HP designed the HP 54000 series digitizing oscilloscopes for greatest possible accuracy of displayed information. So you can use them with confidence, even in measurement reference applications. That's because nonlinearity, distortion, drift, and jitter common to analog scopes aren't a problem with our digitizing scopes. Neither is blooming or fading of traces. What you see on the display is the clearest, most accurate representation of your signal.

Elusive glitches easy to find.

Finding infrequent, fast glitches in digital circuits is tough enough. When the glitch is superimposed on

normal data with a high duty cycle, it's nearly impossible. HP's new digitizing scopes solve this problem by letting you retain glitches, worst-case conditions, or metastable states on the screen indefinitely and view them right along with normal



Events that would be hard or impossible to find with an analog scope can be isolated and retained



HP-IB: Not just IEEE-488, but the hardware, documentation and support that delivers the shortest path to a measurement system.

while you're away from your digitizing scope; precisely quantified; saved in memory for later analysis; or recorded on a printer or plotter.

Capture pre-trigger events.

With digitizing scopes, you can see events before as well as after the trigger. This is highly useful in finding the cause of undesired or unusual events in various types of circuits—and absolutely critical when measuring setup time on logic ICs.

Find signals buried in noise.

Digitizing scopes let you take signals from uncorrelated noise and measure them accurately. Analog scopes can sometimes reduce noise, but not without removing high-frequency information and adding phase shift. The averaging function in HP digitizing scopes won't distort the signal, or remove or add any information.

Color enhances confidence.

The multiple-color capability found in the HP 54110D and the HP 54111D digitizing oscilloscopes makes using your displayed information easier. For instance, you can clearly distinguish channel one information from that of channel two, even when your signals overlap and both have multiple levels, jitter, and noise.

Call today for our free display confidence videotape and mini-brochure.

Explore HP digitizing oscilloscopes. Get a free VHS videotape and mini-brochure by calling 1-800-558-3077.




*Offer expires May 1, 1987











View Your Future Through Triplett Technology Precision LCD, Digital and Analog Panel Instrumentation

No matter what kind of panel instrumentation you're looking for, look to Triplett. We have the most complete and the most up-to-date technology in the industry. Our prices are very competitive, and our quality is backed by Triplett's reliable warranty.

But, at Triplett, we're not resting on our reputation. We're constantly developing technology that will set the standards for the next generation of panel instrumentation. Our eyes are on the future.

LED/LCD Bar Graphs. We've made a breakthrough in display technology with bar graphs that give you all the digital advantages with analog-style displays.

Our programmable 555 LED Bar Graphs are designed for process control, as well as industrial environments. The units accept standard analog inputs as well as 4-20~mA or 1-5V loop signals.

Our new LCD Bar Graphs give you high-speed displays, individual multicolor capabilities to meet your application, and are designed as direct replacements or new equipment design or development.

Digital Panel Meters. With more than 1,000 different panel instruments offered, we're the industry leader. Our standard models are designed as alternatives for our reliable analog instruments. In addition, we have five digital indicator comparators, an LCD two-wire process meter and a selectable range LCD digital panel meter.

Depending on your specific application or reference, you can choose from four different displays: LED, LCD, Gas Discharge or Vacuum Fluorescent.

Our $3\frac{1}{2}$, 4, $4\frac{1}{2}$ Digit Display Series is extremely popular because of its wide range of features, and our miniature and sub-miniature series is an excellent choice where space is at a premium.

Analog Panel Instruments. We manufacture more than 6,000 types of analog instruments ranging from $1\frac{1}{2}$ " to $8\frac{1}{2}$ " as well as custom-designed instrumentation to meet highly specialized applications.

In addition to standard meters, we offer an edgewise series, a pyrometer series, and a ruggedized series, as well as watt, VU, dB and motor load meters.

Unequalled selection. Highest quality. Best cost-value. Fully backed warranties. For the best in panel instrumentation, look to the future. Look to Triplett.


For more information, call 1 800-TRI-PLET, ext. 53.



107

READERS' CHOICE

Of all the new products covered in EDN's **December 25**, 1986, issue, the ones reprinted here generated the most reader requests for additional information. If you missed them the first time, find out what makes them special: Just circle the appropriate numbers on the Information Retrieval Service card, or refer to the indicated pages in our **December 25**, 1986, issue.



▲ ANTIALIASING FILTERS

The 650 and 670 Series antialiasing filters offer close unit-to-unit gain and phase matching; they're designed for use as input filters for 8-, 10-, 12-, and 14-bit A/D converters (pg 133).


Frequency Devices Inc. Circle No 605



▲ WAVEFORM DIGITIZER

Model 640, a plug-in for the company's Data 6000 mainframe, can capture repetitive signals at frequencies as high as 1 GHz at a resolution of 16 bits (pg 110).

Data Precision. Circle No 604



▲VIDEO D/A CONVERTER

The Bt109 triple video D/A converter is an ECL device that suits application in high-resolution (to 2048×1536-pixel) color graphics systems (pg 38).

Brooktree Corp. Circle No 601

SOLID-STATE EL DISPLAY

Model MD640.200 thin-film electroluminescent display accommodates 25-line, 80-character text and 640×200-pixel graphics for MS-DOS applications (pg 134). Finlux Inc. Circle No 606

CAD FOR PC

DiaCAD is a CAD software package that runs on the IBM PC and compatible computers having only 256k bytes of memory and one floppy-disk drive (pg 92). Diacad Associates. Circle No 603



▼ FIBER-OPTIC MODEM

The LDM85 fiber-optic modem offers multidrop capability: You can connect several stations of the associated data terminal equipment along a single line (pg 61).

Burr-Brown Corp. Circle No 602

We Have A Fit Over The Competition.




Viking compliant pin connectors will give you a better fit than anyone else's. Our proprietary finishing process produces round, slipperysmooth surfaces on the flexible twin beams of our "eye of the needle" design – on both card-edge and D-subminiature connectors.

This superior process gives you equal insertion and retention forces. And a solid mechanical and electrical fit. It virtually eliminates radial and axial damage to plated thru-holes. In all your printed circuit boards – .062," .093" or .125" thick.

Viking compliant pin connectors help you cut production time and expense and help you produce a higher quality product.

Get complete details on cardedge and D-subminiature compliant pin connectors. Your best contact is Viking Connectors Co., 21001 Nordhoff Street, Chatsworth, CA 91311. Phone (818) 341-4330.



Compliant Pin Connectors

Viking

CIRCLE NO 143

LEADTIME INDEX

Percentage of respondents

	N	V		V	V	8	Merage 110	
- 10			Ν	A	Q.		Mon	
9	ine shell	5 Weeks	12	21.30 Meeks	Lex 3		30	
N N	16.5%	We !	200	Ye.	40	We We	Med Se	Ve Ta
ITEM	ION.	C.K.	* S	CKS .	S. S.	eks	15 G	6
TRANSFORMERS								
Toroidal	0	9	45	46	0	0	11.0	8.8
Pot-Core	0	13	50	37	0	0	10.2	10.5
Laminate (power)	7	13	47	33	0	0	9.3	8.0
CONNECTORS	Monte of Section		55545 - 10.5A	4				
Military panel	0	25	25	25	12	13	13.7	8.8
Flat/Çable	21	47	16	16	0	0	5.1	5.9
Multipin circular	0	27	33	13	13	14	13.1	9.6
PC	0	64	18	18	0	0	6.2	5.7
RF/Coaxial	21	29	36	7	7	0	6.6 5.4	5.4 4.4
Socket	20	40	27	13	0	0	5.9	5.6
Terminal blocks Edge card	12	41 33	35 40	14	0	0	6.3	7.0
Subminiature	20	30	40	10	0	0	5.7	6.4
Rack & panel	0	29	57	14	0	0	7.6	6.2
Power	15	31	39	8	0	7	7.6	7.4
PRINTED CIRCUIT BO								
Single-sided	AHDS 0	55	40	5	0	0	5.6	4.8
Double-sided	0	38	58	4	0	0	6.4	6.5
Multilayer	0	23	62	15	0	0	8.0	8.9
Prototype	0	79	11	10	0	0	4.8	4.4
RESISTORS	-							
Carbon film	50	29	21	0	0	0	2.5	4.2
Carbon composition	43	29	10	19	0	0	4.9	3.9
Metal film	44	16	36	4	0	0	4.0	4.5
Metal oxide	30	39	31	0	0	0	3.6	4.3
Wirewound	16	28	56	0	0	0	5.3	2.4
Potentiometers	17	33	38	12	0	0	5.9	5.9
Networks	7	47	33	13	0	0	6.1	6.1
FUSES					_			
	29	29	35	7	0	0	4.8	2.4
SWITCHES			88					8
Pushbutton	6	19	63	12	0	-0	7.5	4.7
Rotary	5	18	65	12	0	0	7.5	5.7
Rocker	20	13	47	20	0	0	7.2	4.6
Thumbwheel	0	22	45	22	11	0	10.5	5.4 3.5
Snap action	20	20	30	20	10	0	8.7	
Momentary Dual in line	10	33	50 17	17	10	0	9.2	4.4
Dual in-line	E V	33	17	17	10	U	3.2	4.2
WIRE AND CABLE	40	00	20	^		0	3.1	1.8
Coaxial Flat ribbon	43	28	29 33	0	0	0	3.3	1.7
Multiconductor	42	17	42	0	0	0	3.8	2.9
Hookup	61	30	9	0	0	0	1.6	1.5
Wire wrap	58	25	17	0	0	0	2.1	1.0
Power cords	36	23	36	5	0	0	4.3	4.3
Other	33	33	17	17	0	0	4.9	5.8
	- A					-		
POWER SUPPLIES Switching	0	18	46	36	0	0	9.8	6.5
Linear	20	20	50	10	0	0	6.2	4.8
CIRCUIT BREAKERS	20	20	33	27	0	0	7.4	5.7
HEAT CINIVO								
HEAT SINKS	27	20	47	6	0	0	5.4	3.9
	- 21	20	**	U	U	U	3.4	0.0

9	the shell	1.5 Weeks	11.20 Weeks	21-30 Weeks	Weeks Weeks	Weeks	THE	Saverage KS)
No.	78	5 6	4	4	4	Weeks	th (weeks)	SZ.
	Shel	Cex	eeks	eek	COX.	eek c	6.3	100
ITEM	-	· · · ·		w	•	AD.	7 -0	- 0
RELAYS	6 1						ul	
General purpose	28	22	39	11	0	0	5.5	5.2
PC board	0	25	58	17	0	0	8.0	8.1
Dry reed	25	25	37	13	0	0	5.7	6.9
Mercury	0	22	67	11	0	0	7.7	7.6
Solid state	21	36	29	14	0	0	5.6	8.9
DISCRETE SEMICOND								
Diode	38	23	31	8	0	0	4.3	4.8
Zener	25	25	30	20	0	0	6.3	5.7
Thyristor	23	39	23	15	0	0	5.4	6.5
Small signal transistor	19	31	31	13	6	0	7.0	5.3
FET, MOS	24	23	18	35	0	0	7.6	7.6
Power, bipolar	25	8	33	34	0	0	8.1	4.8
INTEGRATED CIRCUIT	rs, di	GITAI			Phro Janeiro		Silings to he	
CMOS	10	26	32	32	0	0	8.2	6.4
TTL	31	19	38	12	0	0	5.5	6.5
LS	8	42	42	8	0	0	5.9	5.7
INTEGRATED CIRCUIT	S, LI	NEAF	1					
Communication/circuit	0	14	57	29	0	0	9.4	6.3
OP amplifier	10	20	40	30	0	0	8.5	6.5
Voltage regulator	11	33	39	17	0	0	6.7	6.6
MEMORY CIRCUITS							A1	
RAM 16	37	18	27	18	0	0	5.5	4.0
RAM 64	20	40	30	10	0	0	5.2	4.2
RAM 256	20	20	40	20	0	0	6.9	5.0
ROM/PROM	22	22	45	11	0	0	5.9	5.3
EPROM	- 14	29	36	21	0	0	7.0	6.9
EEPROM	22	11	45	22	0	0	7.3	8.2
DISPLAYS								
Panel meters	11	45	33	11	0	0	5.7	6.4
Fluorescent	20	20	20	40	0	0	8.4	10.1
Incandescent	0	50	25	25	0	0	7.4	4.3
LED	17	33	33	17	0	0	6.3	5.6
Liquid crystal	0	31	46	23	0	0	8.2	7.2
MICROPROCESSOR IC	Cs							
8-bit	27	9	37	27	0	0	7.4	4.2
16-bit .	20	10	50	20	0	0	7.4	2.9
FUNCTION PACKAGE	S							
Amplifier	25	0	50	12	13	0	9.1	4.9
Converter, analog to digital	0	30	50	20	0	0	8.0	8.6
Converter, digital to analog	0	22	56	22	0	0	8.6	8.5
LINE FILTERS								
	11	33	34	22	0.	0	7.1	6.4
CAPACITORS	***************************************							
Ceramic	13	39	35	9	4	0	6.4	5.2
Ceramic monolithic	19	19	37	19	6	0	8.1	5.5
Ceramic disc					1			5.5
Film	14	33	29	19	5	0	7.5	5.9
	10	30	35	20	5	0	6.6	6.6
Electrolytic Tantalum	13	25	52	13	0	0	6.8	6.6
	13	a	JZ	13		U	0.0	0.0
INDUCTORS	MAR	46	64	40			0.5	
	0	18	64	18	0	0	8.5	5.5

Source: Electronics Purchasing magazine's survey of buyers



Adaptable cell-based semicustom.

Find solutions in standard cells with high density, unique functions, great tools and top performance.

Motorola has your design solutions, with both 3- and 2-micron standard cell process technologies, gate densities up to 20,000 gates and a functionally comprehensive library.

Unique complex functions such as a deep selection of analog cells, a '68HC05 core, CRT Controller, I/O, memory and timers reside in the library. And, all product is built on a Motorola line qualified to meet the stringent reliability requirements of the automotive industry.

The broad functionality of Motorola cell-based semicustom can be your entry to new applications in more markets—fast growth markets like MAP and ISDN.

Works right the first time.

The same unexcelled development support that's building Motorola's reputation as the easiest source anywhere to work with is also basic to product that works right the first time, every time.

Our '68HC05 support environment includes behavioral simulation, evaluation boards, 4 MHz evaluation modules and time-proven emulator software.

Motorola silicon generators and compilers tailor high-level functions to meet specific design requirements, and comprehensive workstation support makes a snap of design jobs from simple digital to complex core-based systems.

That's great interface. No wonder the product works right the first time.

Alliance leads to merged 2-micron library.

A mid-1985 alliance between Motorola and NCR for the co-development of standard-cell software libraries now has resulted in our Version 2.0 Merged 2-Micron Library, for the best in performance and density. Inherent mappability permits straightforward conversion from 3-micron to 2-micron designs.

Evaluate the variables.

Sort through the variables among sources for cell-based semicustom: process technologies, libraries, interface and support, workstation support, functionality, price/performance, technical support, factory accountability, reliability.

Choose Motorola.

When you're ready, contact the Motorola sales office to begin your cell-based design.

For information on our Standard Cell families, send the completed coupon or write to Motorola. We're on your design-in team.



MOTOROLA INC.

European Semiconductor Group

	Write To: Motorola Ltd., European Literature Centre, 88 Tanners Drive Blakelands, Milton Keynes MK14-5BP, United Kingdom
Your Complete 2-Microsi	Please send me information on Motorola Standard Cell families.
Standard Čeli Design Solution	Name
	Title
nninnanga aga	Company
	Address
i	City
	Country


Graphics engines


By offloading pixel-manipulation chores from a host CPU, graphics engines can provide higher resolution, more colors, and faster response in your graphics applications. Graphics engines also handle display-memory access and generate CRT control signals.


Margery Conner, Regional Editor

A graphics engine can free your host CPU, whether it's an 8088 or a VAX 11/70, from such time-intensive graphics-manipulation tasks as object rendering and window management, allowing your application programs to run much faster. Because graphics applications come in such a wide variety-stand-alone workstations, add-in PC graphics boards, instrumentation, and laser printers, for example—no one graphics chip can be optimized for all applications. To find the chip that's right for your application, you need to examine the tradeoffs between two basic factors: the chips' speed and their flexibility.

Graphics engines differ from







To produce this issue's cover, artist David Hamby digitized his free-hand sketches of the cover figure's component parts. Then, the Superset Model PGM-2 graphics-processor system, running the artist's proprietary software, performed a B-splined interpolation on the 2400 digitized points to generate the 26,000 nodes necessary to represent the figure in three dimensions. The wire-frame figure results from the high-resolution vector output of the Superset geometry file.

would make programming easier and more transportable but would make the display's response perceptibly slower. Graphics engines remove at least some of the graphics-manipulation chores from the host while still handling display-memory access and generating CRT control signals.


Speed vs flexibility

The speed and flexibility of a graphics engine are determined basically by its degree of programmability. In general, a graphics engine that's highly programmable is flexible—that is, it lets you easily draw any image you wish. A graphics engine that's not programmable can draw any of its standard shapes rapidly, but it's much slower at drawing nonstandard shapes.

A highly programmable graphics engine, such as Texas Instru-

ments' TMS34010 or National Semiconductor's Advanced Graphics Chip Set (AGCS), has a minimal instruction set of hardwired graphics primitives. A nonprogrammable graphics engine, such as AMD's QPDM, Hitachi's ACRTC, Intel's 82786, or NCR's 7300CGC/7301MIC has a large set of hardwired primitives.

Graphics primitives are basic commands that specify the lines, shapes, and characters that make up a picture. These primitive commands are either hardwired into the processor or built into software from assembly-language instructions. The line-drawing primitive for a programmable chip is far more complex than that for a hardwired chip: A software primitive for drawing a standard circle, for instance, would comprise 101 lines of code; the hardwired primitive would have two.



Graphics primitives specify the lines, shapes, and characters in a picture; they can be hardwired into the processor or built into software.

Other common primitives let you draw dots, polygons, and 1-pixel lines.

In general, primitives implemented in hardware run faster than do their software equivalents. However, because primitives have set capabilities, obtaining any function besides the standard ones requires intervention from the host processor. The \$21.60 (1000) Hitachi ACRTC graphics engine can rotate a drawing in units of 90° via the Graphics Copy command, or in units of 45° via the Pattern command, but rotating by just one degree requires assistance from the host processor.

Similarly, if you need to draw a picture that you can't define with such primitives as circles, lines, and boxes, the host processor must either draw the figure using the Dot command or else draw it in system memory and then transfer the drawing to the frame-buffer memory. As a rule, when it's executing a standard primitive, a hardwired chip performs the function faster than a programmable chip does, but when the hardwired chip requires intervention from the host CPU, the programmable chip is faster.

Further, keep in mind that the hardwired chips' speed advantage will eventually disappear as graphics technology becomes more sophisticated. As higher-resolution displays become available, the hardwired primitives will be less useful. The hardwired line-drawing primitive of the Intel 82786, for example, draws a line one pixel wide. A 1-pixel-wide line is easy to see on a display like the one provided by IBM's CGA, which has a 640×200-pixel resolution, but it's more difficult to see in a 1024×1024-pixel display. On such high-resolution displays, therefore, you'd want to draw a wider line, which would require intervention from the host processor.

TI's TMS34010, which sells for \$50 (25,000), is actually a general-purpose processor that's optimized for graphics functions. You can write your own primitives and subroutines in the graphics processor's assembly or C language, or you can purchase a graphics subroutine library and source code for \$10,000. You can use the functions as they are or modify them to suit your application.

Unfortunately, no widely accepted benchmarks exist yet for graphics engines. In any case, broad speed figures such as vectors per second or character-transfer rate may not be an accurate measure of the chips' relative processing power. What's important is how well a particular chip's drawing capabilities fit your application. To judge whether a chip is suitable for your application, you must weigh your need for nonstandard




Fig 1—A sequence of instructions resides in memory in the Intel 82786; it runs only when the application program needs to change bit-map contents or support a special function, such as when you're making menu selections with a mouse. The 82786 tests the GECL (Graphics End of Command List) bit and switches to Poll mode whenever the GECL is 1. Poll mode halts the 82786 until a Link command and address are loaded into the control register. The 82786 begins executing a new linked list of instructions when the GECL bit is reset to 0.

primitives against your need for fast execution.

As you might expect, the different graphics engines require varying levels of processing support from the host. The host processor communicates with the Hitachi ACRTC by loading calls to primitives into the

GRAPHICS ENGINES

MANUFACTURER	CHIP	DISPLAY- MEMORY ARCHITECTURE	MAXIMUM SIZE OF DISPLAY MEMORY	BITS PER PIXEL	HARDWARE WINDOWS*	CHIP PACKAGE	PRICE	PROGRAM- MABILITY
AMD	Am95C60 (QPDM)	PLANAR	4096×4096×4 BITS PER QPDM	4 BITS PER QPDM TO 256 BITS MAX	1 WINDOW WHEN USED WITH THE 8171 CHIP	144-PIN PGA (CMOS)	\$250 (100)	HARDWIRED
HITACHI	HD63484 (ACRTC)	PACKED- PIXEL	2M BYTES	1, 2, 4, 8, OR 16	1 WINDOW, 3 HORIZONTALLY SPLIT SCREENS	68-PIN PLCC OR 64-PIN DIP (CMOS)	\$21.60 (1000)	HARDWIRED
INTEL	82786	PACKED- PIXEL	4M BYTES	1, 2, 4, OR 8	16 HORIZONTAL, UNLIMITED VERTICALLY	88-PIN PGA OR LCC (CHMOS)	\$80 (10,000)	HARDWIRED
NATIONAL SEMICONDUCTOR	AGCS (2 CHIPS: RGP** AND BPU)	PLANAR	16,384×16,384× UNLIMITED PIXEL DEPTH	UNLIMITED	NONE	RGP, 68-PIN PLCC; BPU, 44-PIN PLCC	\$140 (100)	PROGRAM- MABLE
NCR	7300CGC AND 7301MIC	PLANAR	1M BYTE	2 BITS PER MIC TO 8 BITS MAX	NONE	7300CGC, 68-PIN PLCC; 7301MIC, 28-PIN PLCC OR DIP	7300CGC, \$48 (1000) 7301MIC, \$6 (1000)	HARDWIRED
TEXAS INSTRUMENTS	TMS34010	PACKED- PIXEL	128M BYTES	1, 2, 4, 8, OR 16	NONE	68-PIN PLCC	\$50 (25,000)	PROGRAM- MABLE

*ALL THE ENGINES SUPPORT SOFTWARE WINDOWS
**RGP WILL BE INTRODUCED IN THE 2ND OTR OF 1987

ACRTC's FIFO instruction port. The other engines can communicate with the host through a display list, allowing the CPU and the graphics engine to be fairly independent of each other.

The \$80 (10,000) Intel 82786, for example, fetches graphics calls to primitives from a linked list in memory that the host processor creates and updates. The host loads the list's initial address into a dedicated register in the 82786; each instruction contains the address of the subsequent instruction. The first bit in each instruction, if set, indicates to the 82786 that it should stop and wait for new instructions (Fig 1). The host processor can update the display list in the graphics memory through the 82786's dynamic-RAM controller.


In a low-end system, the host and the 82786 can share a single memory, which the dynamic RAM controller section of the 82786 manages. For higher performance, the system can have both graphics memory and system memory: The host can store character fonts or graphics objects in system memory, which the 82786 can access by using a virtual-mode 80286 or 80386 configuration.

Because the 34010 is based on a stand-alone generalpurpose microprocessor core (see EDN's Thirteenth Annual $\mu P/\mu C$ Chip Directory, November 27, 1986, pg 102), it can act as a slave to a host processor or operate as a stand-alone system processor. For systems with a host CPU, the 34010 provides access to four programmable 16-bit registers that can be mapped into the host processor's memory or I/O address space, allowing command, status, and data transfer between the 34010 and the host processor. The host doesn't have direct access to the 34010's graphics memory; indirectly, it can perform block moves to the memory through an autoincrementing address register and data port. To eliminate contention with the 34010 for the graphics memory, the host can suspend the 34010's program execution, although the 34010 continues dynamic-RAM- and screen-refresh cycles.

Display-memory architectures

Another basic difference in the architectures of graphics engines lies in the way pixels are stored and accessed in display memory. In a 2-dimensional display memory, each pixel consists of one bit, which can be either on or off, indicating the presence or absence of a dot. Such a display memory supports a monochrome, single-intensity display. In a color display, additional bits at each pixel add color and control the intensity. A

Primitives implemented in hardware generally run faster than do their software equivalents; however, they let you draw only a standard set of lines and shapes.



Data and instructions reside in the same memory space in the TMS34010 memory architecture, so the chip can theoretically support a maximum display size of 65,536×65,536 pixels.

4-bit pixel, for instance, can control the CRT's red, green, and blue color guns as well as the pixel's intensity. Each bit within the pixel corresponds to a plane.

Planes can provide information other than color. For example, one plane can show a static picture while another displays an icon that the user can drag around the screen with a mouse. To make objects appear to move, you display their changing position on separate planes. Alternatively, you can use a 1-bit plane to mask certain regions of another plane.

Planar vs packed-pixel display memory

Graphics engines have two basic display-memory architectures: the planar architecture (used by AMD, National Semiconductor, and NCR), and the packed-pixel architecture (used by Hitachi, Intel, and Texas

Instruments). A chip's display-memory architecture, like its degree of programmability, affects its speed. In general, the packed-pixel architecture is faster for applications that require the ability to access individual pixels; the planar architecture is faster for applications that require access to large sections of data related to one plane.

In a planar architecture, display memory is divided so that all the bits associated with one plane are stored in the same area of memory (see Fig 2a). Each word, therefore, comprises bits associated with only one plane. The display-memory data is accessed a word at a time (a word is usually 16 to 32 bits), so to manipulate one bit within a pixel, the chip accesses at least 15 unnecessary bits.

The planar architecture-based AGCS from National Semiconductor comprises four chips: the raster graphics processor (RGP), the BitBlt processing unit (BPU), a video clock generator, and a video shift register. This modularized approach gives you flexibility in designing or expanding a high-resolution pixel system. In chips based on the packed-pixel architecture, the maximum number of bits per pixel is 16. However, it's common for image-processing applications to require as many as 24 bits.

Because it can support virtually an unlimited number of planes, the AGCS is optimized for use in high-end graphics workstations. Its high price—\$140 (100) for one RGP and one BPU—and large chip area make the 4-chip set an unlikely candidate for use on a personal-computer graphics board. To use this chip set, you need one RGP, one video clock generator, and as many BPUs as you have planes (Fig 3).

One disadvantage of planar architecture is that it causes difficulty in manipulating individual pixels. Drawing a line, for instance, is a function that planar architecture is not especially suited for. However, the National chip set provides a line-drawing mode that circumvents the problem. In this mode, the BPU can select the individual bits corresponding to a pixel by masking all the other bits. A hardwired algorithm generates the addresses of the line's pixels. The chip operates more slowly in this mode, because each BPU accesses only one bit of a pixel, instead of a 16-bit plane word as it does in its normal mode.

The AMD QPDM also has a planar architecture; like the National chip set, the QPDM lets you add planes (to a maximum of 256) by adding more of the chips; however, unlike National's BPU chip, which supports one plane, each QPDM supports four planes instead of




Fig 2—A graphics engine with a packed-pixel memory organization (a) accesses complete pixels. This architecture optimizes the memory for pixel manipulations such as antialiased line drawing. A graphics engine with a planar organization (b) divides display memory so that all the bits associated with one plane are stored in the same area of memory. This architecture is optimum for manipulating planar information, such as performing a masking operation.

one. The QPDM costs \$250 (100).

In a packed-pixel architecture, memory storage is organized so that all the bits in a pixel are contained in the same memory word (Fig 2b). When pixel depth is shorter than word length, multiple pixels can be packed into each word. When the graphics engine accesses a word of display memory, all of a pixel's bits are available simultaneously.

One of the major functions of a graphics chip is to provide software windows; they do so by means of a powerful primitive: the bit-block transfer, or BitBlt (pronounced "bit-blit"). The BitBlt performs a Boolean operation on a source and destination array in one plane of display memory. The graphics engines all implement the BitBlt in hardware. The Intel, AMD, TI, and National chips perform the full set of 16 logical operations; the Hitachi chip performs a subset of the 16 operations.

The TI TMS34010 supports both BitBlts and pixel block transfers, or PixBlts. PixBlts operate on multiple-bit pixels; in color systems, they have a speed advantage over BitBlts because they perform the operation on all planes at once. They can perform logical and arithmetic operation, transparency detection, plane

To judge whether a chip is suitable for your application, you must weigh your need for nonstandard primitives against your need for fast execution.





Fig 3—To allow an almost infinite number of color planes, the AGCS from National Semiconductor uses a building-block approach. A system needs only one raster graphics processor (to be introduced in the second quarter of 1987); you add one BPU per memory plane.

masking, and color expansion. Because PixBlts perform arithmetic operations that require the processor to have the ability to handle carries between bits, only a chip with a packed-pixel architecture can perform PixBlts. PixBlts are useful for performing the Bresenham antialiasing algorithm for line-drawing primitives.

BitBlts are useful for creating software windows. For example, you can use the Replace BitBlt command to create a window of text on the screen by specifying the text array as the source array and the windowed area as the destination array. Note that the rectangle of text, although it's in the display memory, is not normal-

ly visible on the screen. Because the display memory can be much larger than the actual viewing area, renderings can be stored in areas of the memory outside the viewing area and bit-block-transferred to the screen for rapid display. You don't need to regenerate a drawing each time you need it.

The TMS34010 lets you specify the window's location by loading a register with the XY coordinates of the pixels in two of the window's corners (two corners diagonally across from each other). By specifying the window location in registers, instead of in the primitive, you can keep the basic software extremely flexible;



Finally a graphics controller card in sync with your 286/386-based application

Vectrix matches your high-speed microprocessor with high-speed graphics. The PEPE graphics controller card utilizes a proprietary Digital Differential Analyzer (DDA), a custom bit-slice processor, and a unique organization of high speed video shifter RAMS. The result - line drawing speeds in excess of 10 million pixels per second.

4 YEARS OF GRAPHICS EXPERIENCE

Sophisticated technology like this doesn't just happen. Vectrix has been a

leader in the complicated and competitive field of graphics for over four years. During that time, we have assembled an experienced, innovative engineering staff ready to focus their expertise on your system needs.

OEM-ORIENTED DEVELOPMENT TOOLS

Because they understand your requirements, our engineers provide a variety of tools to simplify applications development. Onboard high level graphics commands are accessible directly or through standard programming language libraries provided on disk. Customized firmware can be provided using a plug-in, downloadable RAM card in place of the ROM control memory.

An onboard character generator addresses a separate text overlay plane. Graphics planes can be zoomed and panned independently of the text overlay plane. Bitblts, raster ops and DMA further enhance PEPE's speed.

Thus PEPE is ready to provide the graphics for your next system. And Vectrix stands ready to serve you with state-of-the-art technology, proven product reliability, and an engineering staff capable of translating your system needs into product functionality.

Resolution - 1024 x 1024 or 1024 x 768

Available in Five Configurations:

16 colors

16 colors, double buffered

16 colors from a palette of 4096

256 colors from a palette of 16.8 million 4096 colors Speed - 10,000,000 pixels per second

DMA speed: matches host bus speed

Interface - 8-bit or 16-bit PC family

40,000 short vectors per second

Video - 60 Hz non-interlaced

SOFTWARE DEVELOPMENT TOOLS

Computer Innovations C Library IBM Macro-assembler Library



Vectrix Corporation, 2606 Branchwood Drive, Greensboro, NC 27408 (919) 288-0520

EDN March 4, 1987

CIRCLE NO 142

Broad speed figures such as vectors per second or character-transfer rate may not accurately represent a graphics engine's processing power.

changing the window locations is a matter of changing the register contents once, rather than changing each occurrence of the location in the primitive.

Clipping, including postclipping and preclipping, is a graphics function that permits windowing: It prunes the BitBlt array to fit inside a display window. When a graphics engine performs postclipping, it calculates the positions of all the pixels in a drawing and then discards those pixels that fall outside the window, or "clipping rectangle" (Fig 4a). Postclipping generates an accurate line, but the engine wastes time calculating pixels that it never displays.

When a graphics engine performs preclipping, it determines only the portion of the drawing that will fit inside the window; it avoids calculating any part of the picture that falls outside the window (Fig 4b), thus saving processing time. When the engine uses an antialiasing algorithm, however, preclipping can produce a less-accurate line (a greater staircase effect) than does postclipping, because the endpoints of a preclipped line lie on the boundary of the window. In other words, a graphics engine calculates an antialiased preclipped line without taking the history of the ideal line into account. Conversely, a chip that uses an antialiasing algorithm to perform postclipping displays the smoothest possible line in the window, because it calculates the position of all the pixels in the ideal line.

The programmable TMS34010, which uses antialiasing algorithms, can perform both postclipping and preclipping. To obtain a smooth preclipped line, you can program the chip to include error-term initialization in its antialiasing algorithm (Fig 4c). "Error term" refers to the distance between the calculated pixel and the ideal line. The result is a preclipped line that's as smooth as a postclipped one (Fig 4d).

AMD's QPDM, a hardwired chip, can also draw antialiased lines. In color systems, however, the chip works best when you dedicate one QPDM to each color plane, the manufacturer claims.

The clipping rectangle provided by a graphics engine can also support the use of a mouse for making menu selections. In pick mode, when the user points to an icon (which is surrounded by the invisible clipping rectangle) and clicks the mouse, the graphics engine locates the graphics commands that drew the icon's bit map. These commands act as a pointer to the function that the icon represents.

The Intel 82786 offers window control in hardware as well as in software. When it performs hardware windowing, the chip constructs the display image from




Fig 4—When a graphics engine performs postclipping, it calculates all the pixels in a line and discards pixels that fall outside the "clipping rectangle," or display window (a). When a chip uses an antialiasing algorithm to perform preclipping, it calculates only pixels that lie inside the clipping rectangle, without taking into account the history of the ideal line (b). To minimize the staircase effect in such a preclipped line, the programmable TMS34010 can include initialization of the error term in the line-drawing algorithm (c). The result is a preclipped line that exactly matches the postclipped line (d).

"This is <u>absolutely</u> the disk drive you need for real-time imaging applications."

Norman B. Petersen
President, Storage and Peripheral Products
Fujitsu America, Inc.

No other disk drive available today offers real-time data capture this fast, storage capacity this large, a footprint this small and a price/performance ratio this good.

With Fujitsu's new 474-megabyte M2350A Parallel Transfer Disk Drive (PTD), you could create significant breakthroughs in real-time imaging and simulation applications requiring

fast data transfer rates.

The PTD's data-throughput rate is capable of displaying 512 x 512 x 8 bit images at 30 frames per second. That's fast enough for exciting new applications in fields like image processing, medical imaging, flight simulation, digital film animation and seismic recording.

No other disk drive compares to the PTD.

In addition, third-party controllers are available today, saving you months of development time and thousands of research dollars.



The PTD's design is based on existing, reliable technologies shared with Fujitsu's M2351 "Eagle" disk drive. And it's ready to go—today. You'll avoid design delays now and production delays later.

Take a minute to look at the specs on the PTD. If you're seriously involved in developing systems for real-time imaging or simulation, you'll want more information.

Write Fujitsu America today at 3055 Orchard Drive, San Jose, CA 95134. Or—better yet—give us a call at (408) 946-8777.

Fujitsu Storage Products. Maximum Performance. Maximum Quality.

FUJITSU AMERICA INC.

FUJITSU

Implementing windows in hardware is very fast but requires support from your application software.

independent bit maps for each video frame; a pointer keeps track of the section of the bit map being displayed in the window. Software windowing uses BitBlts to copy text or drawings from source arrays into the visible portion of the display memory. The display memory contains the picture in the final form and order in which it will appear on the screen.

The advantage of hardware windowing is speed—it's fast enough, for example, to let you rearrange the screen on every video-frame retrace. Further, once you create the images for a window, you don't need to perform a BitBlt to display memory in order to call the image up on the screen. Instead, you use a pointer to locate the image you want to display; to display a different image, you simply change the contents of the pointer.

When used with dynamic RAMs, the Intel 82786 is limited to 2M bytes of display memory (for example, a 640×480×8- or 1024×1024×2-pixel display). When used with video RAM, its display memory can be as large as 8M bytes (1024×1024×8 pixels). Note, however, that when its display memory is video RAM, the 82786 can't perform hardware windowing, because the chip performs that function by making use of the fast-access modes of dynamic RAM.

Hardware windowing has its drawbacks: For instance, it limits the number of windows you can display. The Intel chip can display a maximum of 16 windows horizontally, the Hitachi ACRTC can display four, and the AMD QPDM (when used with the 8171 video-data-

Manufacturers of graphics engines

For more information on graphics engines, contact the following manufacturers directly or circle the appropriate numbers on the Information Retrieval Service card.

Advanced Micro Devices 901 Thompson Pl Sunnyvale, CA 94088 (408) 732-2400 Circle No 650

Hitachi America Ltd 2210 O'Toole Ave San Jose, CA 95131 (408) 435-8300 Circle No 651

Intel Corp 3065 Bowers Ave Santa Clara, CA 95051 (408) 987-8080 Circle No 652 National Semiconductor Corp 2900 Semiconductor Dr Santa Clara, CA 95052 (408) 721-5000 Circle No 653

NCR Microelectronics Div 1635 Aeroplaza Dr Colorado Springs, CO 80916 (303) 596-5612 Circle No 654

Texas Instruments Inc Box 1443 Houston, TX 77001 (713) 490-2000 Circle No 655 assembly FIFO chip) can display one. To avoid exceeding the limit, you must keep track of the number of windows you have open at a time. What's more, little application software and no software-interface standards (such as MS-Windows) support hardware windowing; in fact, software-interface standards exist to relieve the dependence of application software on graphics hardware.

Some of the graphics-engine manufacturers boast that their chips can work with dynamic RAMs as well as video RAMs, thus saving you money. In the past year, however, the trade restrictions against imported dynamic RAMs have driven their prices up, so they're no longer much less expensive than video RAMs. The 20% premium that you may still have to pay for a video RAM is offset by the ease of interfacing the video RAMs to your graphics hardware; the video RAMs perform parallel-to-serial conversion internally. One possible compromise would be to use video RAMs for onscreen memory and dynamic RAMs for off-screen memory and bit maps.

Support circuitry

Finally, graphics engines require some amount of external circuitry to control the video and memory. Hitachi offers two companion chips for the ACRTC: the HDC63485 Graphics Memory Interface Controller (\$10.50) and the HDC63486 Video Attribute Controller (\$11.60). The chips implement all the hardware needed for a graphics subsytem (except for RAM and video D/A converters) in less space and at a lower price than any other manufacturer's chips do. With one 63486, the display is limited to a 640×480-pixel resolution and 16 colors; by adding four 63486 chips, you can increase the resolution to 1280×1024 pixels or increase the number of colors to 64k. The three chips are each available in 68-pin PLCCs and 64-pin shrink DIPs.


Article Interest Quotient (Circle One) High 470 Medium 471 Low 472


IFYOU CAN'T AFFORD TO SPEND NINE MONTHS DEVELOPING HIGH-PERFORMANCE GRAPHICS, WE HAVE **IMPORTANT** NEWS.

YOUR PICTURES ARE READY.









Until now, there was only one way to make a desktop system produce a decent image. You had to tie up your development team for at least 9 months writing software.

But now, with our new 82786 graphics copro-

cessor, which has the key software drivers already written, you can get a highperformance graphics system to market in weeks.

To begin with, all the speed-critical functions of CGI, DGIS, GDI and VDI are already built into the 82786.

AutoCAD is a trademark of Autodesk, Inc. Windows is a registered trademark of Microsoft Corporation.

So you can draw lines, characters, polygons, circles, arcs and fill primitives at blazing speed. And Bit BLTs are almost instantaneous. Better yet, since the 82786 has these functions built in, you won't have to go back to school to learn how to program an additional microprocessor. And with AutoCAD, DGIS, Gem and Windows, you get all this without writing one line of code.

In addition to time savings, you don't have to buy expensive development tools such as emulators, compilers and debuggers. As a result, you can give your next system the graphics capability of a high-end workstation. Without the aggravation of debugging a multiple processor system.

And when we say high performance, we mean high. With the 82786, you can look for speed and resolution gains on the order of 10x to 100x. Even using standard, low-cost DRAMs. You can manipulate

Key Specifications				
Supported output devices:	CRT, LCD, Laser Printer			
Maximum resolution:	33.5 Megabits (1-8 bits/pixel, any aspect ratio)			
Maximum line drawing rate:	2.5M pixels/sec			
Number of colors:	Monochrome to 256 colors (1-8 bits/pixel)			
Maximum Clock Frequency:	20 MHz Bus Clock 25 MHz Video Clock			

hardware windows 100 times faster than a typical software approach. And by using video RAMs, you can get virtually unlimited resolution in non-hardware windowed environments.


So if you'd rather make great-looking pictures than write endless lines of code, we're ready to help.

Just call Intel at (800) 548-4725, toll-free, and ask for Literature Department W352.

And see what develops.



125



The new TI-60 is better than the best-selling advanced scientific ever.

We know, because we made that one too.

No one knows the advanced scientific calculator market better than Texas Instruments. Because no one has sold more advanced scientific calculators than we have.

The new TI-60 has 124 of the most commonly used functions to help you get your work done faster and more reliably.

Functions such as: hexadecimal/ octal conversions, integration using Simpson's rule, statistics including linear regression, trend line analysis and metric to English calculations.

In other words, lots of built-in power to provide you with quick, reliable solutions to a wide variety of engineering problems.

The TI-60 is also programmable up to 84 keystrokes. Which allows you to solve repetitive calculations in the shortest amount of time.

CIRCLE NO 139

And there's 12 constant memory locations that store data for future use and an "easy-touch" keyboard to help get your work done even faster.

The new TI-60 Advanced Scientific Calculator. It's better than the best-selling advanced scientific ever. And we should know. After all, we made that one too.



CLASSIC QUALITY

Nothing else in the world performs like a Stradivarius. A unique symbol of excellence created by Antonio Stradivari, a master craftsman in fine woods, it stands by itself. Fashioned with select components, this prestigious violin has continued to be a hallmark of quality through the centuries.

In much the same way, the proper components are vital to that singular new instrument you're designing. If it measures, processes or controls, your new product should operate as a Stradivarius does—with a precision and sensitivity all its own to your exacting design requirements. Because the components you choose make that happen, your logical choice is Switchcraft.

For more than forty years, we've been committed to excellence. Although we manufacture over 6,000 standard, miniature and subminiature products and components, we never skimp on quality.



In fact, we constantly maintain precise quality with Statistical Process Control and 100% electrical/mechanical verification.

We further augment your experience with our team of knowledgeable support engineers to develop a new product and/or customize an existing one to meet your unique design demands.

For a recital of our classic components, simply send for our

General Line Catalog. You'll discover even more specifically that we—like you and the world's most vaunted violin—are very performance oriented.

Send me informa	tion on your quality	components:				
Please have a representative contact me.						
Please send me your General Line Catalog covering the complete Switchcraft line.						
My area(s) of interest is:						
Switches Connectors Power Cords						
☐ EAC Receptacles ☐ Jacks/Plugs						
-	Assemblies	•				
☐ Future ☐ (da	ite)					
	,					
Name						
Company	Title					
Address						
City	State	Zip				
Telephone ()					
Mail To: Marketing	Communications Dep	t.,				
Switchcraft, Inc., 5	555 N. Elston Ave.,					
Chicago, IL 60630		ED3-8				

Switchcraft

A Raytheon Company

5555 N. Elston Ave. Chicago, IL 60630 (312) 792-2700

Some MUX makers try to disguise a basic fact: they don't have our selection.

Harris gives you more MUX choices.

Let's face it...designing a better data acquisition system is no time to clown around. You want straight answers about the best parts. Like Harris MUXes.

For peak protection against faults and spikes, design-in our HI-546/549 series MUXes. Their built-in active overvoltage protection enables them to perform to the max despite ESD, input spikes and power supply transients


that fry lesser MUXes.
Typically, HI-546/549 MUXes withstand more than 4,000 volts ESD on analog inputs—twice the military's ESD standard.

Our OV-protected

series offers guaranteed ON-resistance channel matching. Harris Dielectric Isolation eliminates latchup and dramatically reduces power drain. Add to that 70-volt peak-to-peak input OV protection, and you have MUXes that'll shine in the toughest environments.

And you can get them fast, in MIL-STD-883, commercial and industrial grades; in DIPs and surface-mount packages.

Make no mistake — Harris parts and your smarts are a great combination. To find out more, contact: Harris Semiconductor Sales Ltd., Eskdale Road, Winnersh, Wokingham, Berks, RG11 5TR, England.



Harris Semiconductor: Analog - CMOS Digital
Gallium Arsenide - Semicustom - Custom

"Try to look like
a first-class MUX family!"

"Say 'Harris'!"

©1987, Harris Corporation

Some MUX makers try to disguise a basic fact: they don't have our selection.

Harris gives you more MUX choices.

Let's face it...designing a better data acquisition system is no time to clown around. You want straight answers about the best parts. Like Harris MUXes.


For high performance, specify our industrystandard HI-506/509 series MUXes. Their Dielectric Isolation processing prevents latchup and dramatically reduces power consumption.


But there's more. You also get low ON resistance (180 ohms), fast access time (250 ns) and fast settling (600 ns to 0.01%).

And our industrystandard MUXes typically withstand static discharges beyond 3,000 volts on analog inputs. Harris HI-506/509 series MUXes: more flatout speed and immunity from latchup than you can find anywhere else. Anytime. In DIPs and surface-mount packages; in MIL-STD-883, commercial and industrial grades.

By now, you've discovered that there's a tremendous difference in MUXes (and in MUX ad copy). And thanks for learning about ours.

Harris parts and your smarts belong together. To find out more, contact: Harris Semiconductor Sales Ltd., Eskdale Road, Winnersh, Wokingham, Berks, RG11 5TR, England.







©1987, Harris Corporation

3 [3

set free an idea!

At **EIE** we respect human creativity. So we provide specialist tools that leave you free to conceive and implement valuable ideas.

Our new CAD/CAM tools for IBM PC/AT's and photoplotters for PCB and hybrid circuit development are only announced when they have satisfied these three criteria:

- So easy to use that they're immediately operational.
- Reliability and precision being Swiss helps!
- Unbeatable price/performance.

EIE's technology is supported worldwide. Our complete solutions have been setting free ideas since the dawn of the CAD age.

For product information, contact:

EIE-Electronic Industrial Equipment SA

15, rue Marziano CH-1227 Geneva-Switzerland Telephone: (022) 42 32 60 Telex: 429 484 eie ch Telefax: (022) 42 81 72



A new dimension in electronic design.

CMOS ADC achieves reliable 12-bit resolution

It's not easy to achieve maximum performance from a 12-bit ADC. Conversion results can be quite misleading if you fail to adjust the converter's endpoints prior to operation. Such adjustments usually require that you calculate the overall converter error budget by combining offset, gain, and linearity errors into a total error spec.

John Reidy and John Wynne, Analog Devices

An increasing number of applications require A/D converters with 12 bits of resolution or more. In the past, many designers found that it wasn't easy to work with such converters; achieving true 12-bit performance requires a good deal of bench time (and patience) to trim out offset and gain errors. Luckily, a recently introduced CMOS ADC satisfies a number of high-performance applications while keeping time-consuming design calculations to a minimum.

The AD7578 single-channel device guarantees a total unadjusted error spec of ± 1 LSB over its operating range. It converts in 100 μ sec and uses an autozeroing

technique to reduce offset drifts to less than 100 $\mu V.$ If your application requires more than one channel, you can use the AD7582, which is identical to the AD7578 except that it accepts four channels.

Converter-to-µP interface is novel

One application in which this converter saves on design time involves interfacing to a microprocessor. When you need to interface an A/D converter to a μP , you'll often find it difficult to ensure that the conversion process is complete before you try to perform a dataread operation. If the conversion hasn't finished by that time, then the converter will reset, or, at the very least, the conversion data will be affected.

To aid in ascertaining when to initiate a read operation, most modern converters have a conversion-inprogress or \overline{BUSY} output flag, which you can use as an interrupt input for the $\mu P.$ Using this approach, you command the A/D to start a conversion as the system software continues to run. When the conversion is complete, the \overline{BUSY} flag forces the μP into a data-read interrupt routine to fetch the data.

Another way to ensure that valid data is available also exists. You simply insert a software delay in the program (longer than the A/D-conversion time) between the conversion-start instruction and the read instruction.

The interface scheme in Fig 1a contains elements of

EDN March 4, 1987




Fig 1—For this μ P-interface application, you can use a valid read request to gate the converter's BUSY flag (a). When the μ P executes a read instruction, it has access to the data immediately (b) if BUSY is high. A low BUSY (c) puts the μ P into a wait mode. When the conversion ends, the read cycle continues until completion.

both techniques. Here, a valid (low) read request via IC_1 gates the \overline{BUSY} flag (which is low during a conversion) at the input of OR gate IC_2 . IC_2 's output connects to the Ready or Wait input on the μP . When this input goes low, the μP goes into a wait mode and stays there until the Wait input goes high again. Because the start-conversion command uses a write instruction, IC_2 's output remains high after a start-conversion command, and the μP continues to run.

If, at some later time, the μP needs to use the new conversion data for computations, it simply executes a read instruction to the converter to fetch this data. If \overline{BUSY} is high, the conversion is complete and the data is available immediately (Fig 1b). If \overline{BUSY} is low, the conversion is still in progress. The Z80A's Wait input immediately goes low and places the μP in the wait mode, where it stays until the conversion is complete. When the conversion ends, the read cycle continues until it's complete (Fig 1c). Processor wait time can vary from nonexistent (conversion finished when dataread request arrives) to approximately the full conversion time (conversion just started when data-read request arrives). To keep things simple, neither of these timing diagrams includes the BYSL input.

Although Fig 1a uses a Z80A, you can use this approach with any μP that allows you to extend its read cycle to 100 μ sec max. Of course, you have to modify the circuit slightly to accommodate different processors. With the 8085A, for example, the \overline{RD} signal may occur too late in the read cycle to affect the Ready input and thereby extend the read cycle. To avoid this problem, you should use the 8085A's SO status output as an advanced read signal and connect it to IC₁ in place of \overline{RD} .

Simple loop detector works well

Another application for this 12-bit A/D converter is the detection of 4- to 20-mA signals. A popular method involves terminating the loop with a 250Ω resistor and then monitoring the voltage drop across the resistor. Over the full-scale current range, this voltage will range from 1 to 5V.

To comply with this scheme, the monitoring circuitry must meet certain criteria. It must be able to accommodate the 4-mA offset without losing any resolution to the loop. The ability to adjust the zero and the full-scale range independently is also essential. The ability to detect an open-loop circuit condition is another useful capability: Long 4- to 20-mA loops can easily be cut in industrial applications.

Normally, you'd have to trim out offset and gain errors to achieve true 12-bit performance.

Fig 2 shows a circuit that meets these requirements. Rather than directly monitoring a voltage drop across a sense resistor, the circuit bleeds a fraction of the loop current (nominally 25%) into a current mirror based around IC₁. IC₂ then sums the mirrored current with a 1-mA fixed offset current. IC₂'s output voltage ranges from 0 to 5V as the loop current changes from 4 to 20 mA. As a result, the dynamic range of the AD7582 matches the dynamic range of the loop current.

Calibration is a 2-step process: The zero-scale range needs adjustment before the full-scale point. For the zero adjustment, you drive a current of zero scale plus 1 LSB (20 mA+3.9 μ A) into the loop while the AD7582 continuously converts channel $A_{\rm IN0}$. As you read the conversion results, adjust R_6 until the AD7582's LSB flickers with all other bits off. You adjust the full-scale point with a loop current of full scale minus 1 LSB (4 mA-3.9 μ A) flowing in the loop. Repeatedly converting and reading the $A_{\rm IN0}$ results, you vary R_8 until the AD7582's LSB flickers with all other bits on. The system is now calibrated.

The input structure in **Fig 2** effectively eliminates a phenomenon known as resistor self-heating, a problem that plagues conventional detectors which simply moni
Text continued on pg 136




Fig 2—To simplify 4- to 20-mA loop detector monitoring, this circuit bleeds a fraction of the loop current into a current mirror based around IC₁. IC₂ then sums the mirrored current with a 1-mA fixed offset current.

EDN March 4, 1987





Fig 3—You can perform an initial calibration by sampling the potentiometer voltage at the two extremes of the manipulator joint movement (a). The 12-bit D/A converters provide the sample/hold function (b). DAC #1 holds V_{LOW} data, and DAC #2 holds data for V_{HIGH} .

IC ₂	IC ₁	CHANNEL SELECTED	MEASUREMENT FUNCTION
0	0	Aino	SHA, VLOW
0	1	A _{IN1}	SHA, VHIGH
1	0	A _{IN2}	MONITOR, VOUT
1	1	A _{IN3}	RATIOED INPUT



tor the voltage change across a 250Ω resistor. Because every resistor has a finite thermal resistance, its actual value is affected—via its temperature coefficient (TC)—by the heat it dissipates. The greater the thermal resistance and the greater the TC, the greater the problem. For example, a standard ${}^{1}\!\!/4W$, 250Ω metal-film resistor might have a thermal resistance of $120\,^{\circ}$ C/W and a TC of 50 ppm/ ${}^{\circ}$ C. As the loop current varies from 4 to 20 mA, the sense resistor value can change by 0.06%. In a 12-bit system, this change is equivalent to $2{}^{1}\!\!/_{2}$ LSBs of full-scale error.

Note that the self-heating effect is proportional to a current-squared term, and thus its contribution is nonlinear over the full-scale change. One solution to the problem is to spread the power dissipation over a number of resistors. By paralleling four similarly constructed 1-k Ω resistors to form a composite 250 Ω resistor, you achieve a fourfold reduction in the size of the resistance change. The circuit in Fig 2 actually monitors only a fraction of the loop current, so the problem of input-resistor self-heating disappears.

The four input resistors in Fig 2 bleed off one-quarter of the loop current, and resistors R_5 , R_6 , and R_8 experience a 4-mA current flow change as the loop current varies from 4 to 20 mA. It's important that R_5 and R_6 track each other to avoid any problems caused by their self-heating. You could use a potentiometer for R_6 , but a potentiometer's TC varies according to wiper position and thus is unlikely to match the TC of R_5 .

Two are better than one

In practice, you'll achieve better stability if you use two series resistors rather than one variable resistor for both R_6 and R_8 . Specify R_{6A} slightly smaller than the correct value for R_6 , and make up the difference with R_{6B} during zero-scale calibration. Fig 2 shows a value of 1.22 k Ω for R_{8A} —slightly less than the value required for R_8 . You can choose resistor R_{8B} to make up the difference during the full-scale range calibration.

To further minimize self-heating effects, you should use precision metal-film resistors for both R_{8A} and R_{8B} . If your resistors each have a thermal resistance of 120°C/W and a TC of 50 ppm/°C, the result over the 4-to 20-mA loop current range is that the full-scale endpoint changes by approximately ½ LSB. As an alternative, you can replace the composite series resistor R_8 with a T network made up of two 500 Ω resistors in series and a 1-k Ω resistor to ground. With the T network, self-heating is negligible.

You can use the A_{IN1} channel of the A/D converter to

directly monitor the signal voltage across the composite 250Ω resistor, which is quite helpful for fault-detection purposes. If the loop should open, then $A_{\rm IN1}$ will read 0V. Furthermore, if you're using a thermocouple, the thermocouple conditioner or the 4- to 20-mA transmitter can detect this burnt-out thermocouple and reduce the loop current to 0 mA: a fault condition. Note that, because of signal conditioning, the signal from $A_{\rm IN0}$ won't indicate a fault condition. The 10V varistor in Fig 2 protects the circuit from voltage or current spikes on the line.

Under certain circumstances, the AD7578 is also suitable in another application: position sensing. For any cost-sensitive application, a potentiometer is still the best choice for indicating the position of an object or shaft. Rotary potentiometers are particularly useful in robot manipulators for measuring joint coordinates as an instructor moves the robot arm to the desired locations in the correct sequence. A monitoring system based on an A/D converter has an output resolution that's directly dependent on the resolution of the converter. Higher-resolution converters will obviously increase resolution but will also increase system cost.

A full-scale output change from the A/D converter requires a full 360° rotation. For many applications, the swept-angle of a robot arm will be much less than 360°. For instance, in an application where a robot arm moves repeatedly between two points, a particular joint might sweep through at most 30°. A 12-bit A/D converter would monitor this angle in approximately 340 steps, which is between 8- and 9-bit resolution.

Fig 3a's circuit maintains 12-bit resolution over limited electrical travel, and it accommodates any arbitrary electrical angle with a simple calibration routine. This capability is very useful in situations where a robot manipulator has been taught to perform different repetitive tasks.

As Fig 3a shows, you perform an initial calibration by sampling the potentiometer voltage at the two extremes of the manipulator joint movement. This sampling produces two voltage levels: $V_{\rm HIGH}$ and $V_{\rm LOW}$. The difference between these levels produces a full-scale signal ($V_{\rm HIGH}-V_{\rm LOW}$) that's constant and equivalent to the swept electrical angle through which the joint rotates. As the joint moves, the low limit is also subtracted from the present reading to provide a signal ($V_{\rm OUT}-V_{\rm LOW}$) that ranges from 0V to full scale. The ratio of these two signals varies from 0 to 100%. When you properly scale the divider block to translate its ratioed output into a 0 to 5V analog signal suitable for

When monitoring 4- to 20-mA loops, you must be able to adjust zero and full-scale range independently.

the AD7582, the system provides 12-bit resolution over the swept angle.

This resolution has a significant impact on circuit performance. For instance, if the 4096 steps of the 12-bit ADC are scaled to cover a swept angle of 45° (one-eighth of the basic 360°), the LSB size will equal 0.01°, which is equivalent to 15-bit resolution. The practicality of this resolution depends on the output smoothness of the potentiometer wiper signal.

Contactless potentiometers, based on a magnetoresistive material, are completely free from sliding noise. When exposed to a magnetic field, the electrical resistance of this material increases. Rotating a permanent magnet, which is attached to a shaft close to two magneto-resistors in series, produces a potentiometric voltage divider. Contactless potentiometers have a number of disadvantages, but they are capable of monitoring movements as small as 1 μ m.

ADCs provide S/H functions

In the more detailed diagram of Fig 3b, the 12-bit D/A converters, loaded directly from the AD7582, provide the sample/hold-amplifier (SHA) functions. (The $A_{\rm IN0}$ and $A_{\rm IN1}$ channels are dedicated solely to this purpose.) Under μP control, address lines A_1 and A_2 select an SHA channel and the corresponding D/A converter that requires updating. DAC #1 holds data corresponding to $V_{\rm LOW}$, and DAC #2 holds data for $V_{\rm HIGH}$. To update an SHA channel, the potentiometer rotates as far as its respective limit will allow, and the \overline{WRADC} is pulsed low to begin a conversion. When the conversion is complete, the μP executes a read instruction to the same channel.

Because the A/D converter's \overline{RD} is also the D/A converters' \overline{WRDAC} signal, the conversion results are transferred from the A/D converter into the respective D/A converter. And, because of the 8+4 format of the A/D-converter data, you need two \overline{RD} instructions to transfer the full conversion results.

The AD7548 converters are configured to accept the right-hand-justified 8+4 data of the AD7582. The μ P's A₀ address line selects and controls the transfer of the low and high byte from the A/D converter to the correct D/A-converter register. Op amps IC₄ and IC₅ perform the subtraction, and the AD538, a monolithic computational circuit capable of providing analog multiplication, division, and exponentiation, performs the precision rationg. The VY input of the AD538 provides output scaling for the VZ/VX ratioed signal (the A_{IN3} input of the AD7582). The A_{IN3}'s 12-bit conversion result repre-

sents the swept angle that the wiper of the precision potentiometer moves through.

Initial system calibration is straightforward. The 100Ω trimming potentiometers (R_1 and R_3) in series with the voltage reference input of each DAC compensate for gain errors in the DACs themselves, as well as any gain errors in the ADC and subtracting amplifiers IC_4 and IC_5 . The fact that you can use the DF/\overline{DOR} and CTRL inputs to override the DAC registers of the AD7548 with all ones or all zeros simplifies the calibration.

To start, you set $V_{\rm HIGH}, V_{\rm LOW}$, and $V_{\rm IN}$ at full scale and adjust the trimming potentiometers to achieve 0V at the outputs of the subtracting amplifiers. Calibrate the $V_{\rm HIGH}-V_{\rm LOW}$ channel first. For a correct adjustment, $V_{\rm LOW}$ must be exactly 5V full scale. You accomplish adjustment by driving the DF/ $\overline{\rm DOR}$ input of DAC #1 to a logic low and then adjusting R_1 for a 5V output on IC₂. Maintaining these conditions on DAC #1, you now drive the noninverting input of IC₁ with $V_{\rm REF}$. Carry out a single conversion on $A_{\rm IN1}$ and use a read instruction to transfer the results to DAC #2. You then adjust R_3 until IC₅'s output equals 0V.

You calibrate DAC #1 in a similar manner. Carry out a single conversion on A_{IN0} and transfer the results to DAC #1 (data override input DF/ \overline{DOR} is now at a logic high). Then, adjust R_1 until the output of IC_4 is 0V.

The AD538 denominator has a wide 1000:1 dynamic range, and the divider's input offset voltage becomes increasingly important as the denominator gets smaller. If you restrict the dynamic range of the denominator to 10:1, you won't need to do any trimming to achieve a divider accuracy of 0.5%. Under these conditions, the system will accommodate a lower limit of approximately 36° for the swept angle.

Sample/hold amplifier can stand alone

In yet another application with few design headaches, you can use the AD7578 ADC and some additional logic to develop a stand-alone sample/hold system that requires no μP control (Fig 4a). In fact, you need only one control input: the conversion-start signal. You drive the ADC clock input from a 74HC-compatible source at 140 kHz. In Fig 4a, the ADC and DAC are both configured for bipolar operation, which allows the circuit to sample and hold over a $\pm 5V$ input signal range. Because the same 5V reference is applied to both the ADC and DAC, a 1:1 correspondence exists between the input and output in terms of signal magnitude and polarity. The ADC's output code is offset-





Fig 4—Combining some additional logic with the AD7578, you can develop a stand-alone sample/hold system that requires no μ P control (a). A conversion begins on the falling edge of WR (b) and runs for 100 μ sec. At the end of the conversion, the rising BUSY signal initiates an automatic data transfer between the ADC and the DAC.



EDN March 4, 1987

When cost is crucial, the potentiometer still represents the best solution for position-sensing applications.

binary; the LSB size equals 2.24 mV.

In the timing diagram of Fig 4b, the circuit samples the analog signal by pulsing the \overline{WR} input of the AD7578 low for 100 µsec. From the falling edge of \overline{WR} , a conversion begins and runs for 10 µsec. At the end of the conversion, the rising \overline{BUSY} signal initiates the automatic data transfer between the ADC and the DAC.

The data bus of both converters is eight bits wide, and thus the 12-bit conversion results are transferred in two bytes: first the eight LSBs, and then the four MSBs. If you need a digital representation of the analog input (and DAC output) elsewhere in the system, you can also load the conversion results into additional latches during the data transfer.

You must select input resistors R_1 and R_2 so that they match within 0.01%; they should be the same type (preferably metal film) and from the same manufacturer so that their TCs match. The same is true for R_3 , R_4 , and R_5 . It's best to use two resistors in series to make up both R_3 and R_4 . Specify R_{3A} and R_{4A} slightly less than the values needed for R_3 and R_4 , and make up the difference with the small-value resistors R_{3B} and R_{4B} during calibration. For optimum performance over temperature, you should use metal-film devices rather than potentiometers for these padding resistors.

The AD7548's data-override facility makes calibration uncomplicated. First, calibrate negative full scale

by pulling both override inputs (DF/ \overline{DOR} and CTRL) to a logic low. This calibration loads the DAC register with all zeros, generating 0V at the output of IC₂. You then select R_{3B} to develop -5V at the output of IC₃. For positive full scale, keep the DF/ \overline{DOR} input low and return CTRL high. This action loads all ones into the DAC register. You then select R_{4B} to develop a 4.9976V output. This process calibrates the endpoints of the transfer function.

To complete calibration, you must make sure that a 0V input yields a 0V output. For this adjustment, return both data-override inputs to a high level to allow normal operation. You then apply a −1.22-mV analog input voltage (½ LSB) to V_{IN} and set the AD7578 to perform continuous conversions. Next, adjust the input offset voltage of IC₁ until the ADC output flickers between 0111 1111 1111 and 1000 0000 0000. You can easily confirm a correct adjustment by monitoring IC₃'s output with a scope and trimming until you see a square wave that flickers between −2.44 mV and 0V.

Satisfy speech analysis/synthesis needs

Finally, the AD7578 is well adapted to speech applications, thanks to its 100-µsec conversion time and 12-bit resolution. Most of the energy in speech is below 2 kHz, so 4 kHz is the minimum acceptable sampling rate for intelligible speech. Of course, this sample rate minimum assumes that you are using an almost-ideal




Fig 5—Before being quantized by the AD7578, the input signal in this speech system goes through some signal-conditioning circuitry and a lowpass filter. The 12-bit data is compressed to four bits for storage in ROM.

antialiasing filter. To ease filter design and enhance speech quality, most designs employ an 8-kHz sampling frequency.

The ADC's resolution also directly affects speech quality. Insufficient resolution results in too coarse a reproduction, and thus influences intelligibility. More bits means better S/N ratio and better overall fidelity. Ultimately, the amount of memory normally constrains the upper limit. A 12-bit A/D converter, operating at an 8-kHz sampling rate, will fill up 64k bytes of memory in just over five seconds. For an 8-bit A/D converter, it's eight seconds.

Fortunately, voice waveforms contain a lot of redundant information and don't require such high bit rates. Signal-processing routines and dedicated devices introduced in recent years transmit and store voice signals much more efficiently.

One of these, the MSM5218RS speech analysis/synthesis IC from OKI Semiconductor (Sunnyvale, CA), uses an adaptive differential pulse-code modulation (ADPCM) method of data compression. It condenses 12-bit PCM samples into three or four bits. The MSM5218RS also contains a synthesis stage, which expands the 3- or 4-bit ADPCM data to 12-bit PCM data. In addition, it has an onboard 10-bit D/A converter, which you can use to reconstruct the speech signal. You can use an external DAC to provide 12-bit resolution, too.

Taking a slightly more in-depth look at ADPCM will help your understanding. PCM defines the output code of an ADC after quantization. An S/H amp freezes the speech input while an ADC performs the quantizing operation. In differential PCM, the current code is subtracted from the code immediately preceding it, and the result is the new DPCM code. This subtraction significantly reduces the data-transfer rate because, compared with the actual PCM value, the differential PCM value requires fewer bits.

Distortion may occur, though, if the difference between samples is greater than the DPCM encoding value. This difference is called a compliance error. To solve this distortion problem, you must reduce the input-signal bandwidth. ADPCM minimizes the compliance error by adaptively changing the DPCM quantizer step size to suit the waveform being digitized. If the difference between successive samples is great, it increases the step size, and vice-versa, reducing the overall data rate and keeping the compliance error to a minimum. The MSM5218RS uses an ADPCM technique based on the characteristics of speech waveforms. It

isn't suitable for triangular waves, square waves, or other such waveforms.

Fig 5 shows a typical speech system. Before being quantized by the AD7578, the input signal goes through some signal-conditioning circuitry and a lowpass filter. The digital data is then compressed from 12 to 4 bits before being stored in ROM. To reproduce the data, the MSM5218RS expands the data, and an AD7543 reconstructs the analog speech input.

To evaluate the system, you can configure the MSM5218RS to operate simultaneously in an analysis/synthesis mode (Fig 6). Except for the ROM storage capabilities, this circuit contains all the necessary components and interface details of a complete digital-speech system. Evaluating a speech system isn't simple because no well-defined tests or instrumentation exist that provide verifiable measurements. You can make a reasonable evaluation by listening to the reproduced speech with an impartial ear. If you've ever carried out such a test, you'll have to agree that eight bits is more than adequate for speech intelligibility.

Nonetheless, increasing the resolution to 12 bits yields a marked improvement in speech quality and naturalness of sound. Because the MSM5218RS's data output rate is the same for 8 and 12 bits, the IC offers these improvements without any memory-capacity penalty. Overall, the system in Fig 6 provides an efficient means of storing voice inputs, and it reproduces a high-quality speech output that's hard to distinguiush from the original input.

The input signal passes through buffering and lowpass-filtering circuitry before reaching the AD585 S/H amp's input. All the analog stages are ac coupled. Resistor R_3 ensures that the input signal covers the full dynamic analog input range of the AD7578. The MSM5218RS provides timing and control, generating a start conversion (SCON) pulse every 125 $\mu sec.$ SCON triggers an AD7578 conversion, which the AD7578 acknowledges by bringing its \overline{BUSY} output low. \overline{BUSY} asserts the \overline{HOLD} input of the AD585 S/H amp and freezes the analog input.

In any sampling circuit, it's important that the samples occur at equal intervals. The equidistant SCON pulses, derived from the MSM5218RS clock, ensure such performance. The same clock provides the clock input for the AD7582 via the resonator, which oscillates at 384 kHz. This clock rate is divided by 3 before being applied to the AD7578. The division process increases the conversion time slightly (to 110 µsec), but the 15 µsec available is more than ample time for the circuit to





Fig 6—Except for ROM storage accommodations, this circuit contains all the necessary components of a complete digital speech system. It reproduces a high-quality output hard to distinguish from the original input.



QUICK.

Name the company that makes the fastest high-density CMOS and bipolar PROMs on the market.

(You're probably wrong. See page 210.)

read the A/D-converter data and for the S/H amp to acquire the next sample before the next conversion. Note that the AD7578 doesn't require a symmetrical clock. The divide-by-3 circuitry establishes a 2:1 work/space ratio—more than adequate for the AD7578 clock input.


Between SCON pulses, the S/H amp has to acquire the speech signal. In the same time frame, the AD7578 digitizes the input signal, and the 74C74 dual flip-flop and two CD4014 shift registers transfer the previous conversion result to the MSM5218RS. The AD7578 data bus is byte oriented, and the 12 bits of data from the AD7578 load into the CD4014 shift registers in two bytes at the end of the conversion cycle. When the MSM5218RS is configured for an external D/A conversion, its Sock output pin generates 12 pulses. This output serially clocks the CD4014 data in the MSM5218RS input shift register during conversion.

EDN

POWER YOUR DISPLAYS FROM LOW DC VOLTAGE!

DC-DC Converters & Smart Force™ DC-AC Inverters to power:

- Electroluminescent Lamps,
- Plasma Gas Discharge,
- Vacuum Fluorescent,
- TFEL Displays, and More!



FREE Data Packet includes:

- CROSS REFERENCE INDEX matches ERG converters to various plasma and VF displays.
- EL SOURCE LIST helps source EL Lamps, LCDs, membrane switches, etc.

Call today for complete product information and pricing:



Endicott Research Group, Inc.

2601 Wayne Street P.O. Box 269 Endicott, NY 13760 607-754-9187 TWX 510-252-0155

FAX: 607-754-9255 \$\times 1986 ERG, Inc.



Authors' biographies

John Reidy is an applications engineer at Analog Devices in Limerick, Ireland. In this capacity, he provides technical support to the sales force. He has an Electronic Bachelor of Engineering degree from the National Institute for Higher Education in Limerick. In his spare time, John enjoys badminton, guitar, softball, and reading.




John Wynne, a senior applications engineer for the company, also provides technical support to the division's sales force. He holds a degree in electronics from Kevin St College of Technology and is a graduate member of the Institute of Electronic and Radio Engineers. In his spare time, John listens to music, reads, and plays squash.




Article Interest Quotient (Circle One) High 476 Medium 477 Low 478

PMI PRESENTS: PRECISION PERFORMANCE AT 20µA MAX.



Vos = 150μV MAX TCVos = 2μV/°C MAX





Introducing PMI's micropower OP-90, featuring OP-07 precision at 1/200 the power.

Input and output ranges include ground, allowing zero-in, zero-out capability in single-supply applications.

The OP-90 delivers 5mA, but draws only 20μ A quiescent current. Eliminate power-hungry op amps and still get the DC performance you require.

	OP-90E	
V_{SY}	+1.6 to $+36$	V Min/Max
VOUT	0 to $(V_{SY} - 0.8V)$	V
I_{SY}	20	μA Max
I _{OUT}	5	mA Min
VOS	150	μV Max
A_{VO}	700	V/mV Min

For more information on PMI's precision OP-90, please circle the inquiry number. Or, call us. 1-800-843-1515. In California, call 1-800-826-9664.

Precision Monolithics Inc. A Bourns Company Santa Clara, California, USA 408-727-9222

FRANCE: 01-40 03 35 93; GERMANY: 0711-22 93 0; NETHERLANDS: 070-87 54 04; SWITZERLAND: 042-33 33 33; UNITED KINGDOM: 01-572 65 31; HONG KONG: 0-4992888; JAPAN: (03) 234-1411; ARGENTINA: 46-5776/0628/0864/2214; AUSTRALIA: (02) 439-465 5; AUSTRIA: 0222-43 26 39; DENMARK: 02-98 63 33; FINLAND: 90-75 06 00; INDIA: 222-939; ISRAEL: (972) 3-922 39 88; ITALY: 02-569 57 46; KOREA: (02) 244-7492; NORWAY: 02-83 02 20; SINGAPORE: 747-6188; SPAIN: 01-405 42 13; SWEDEN: 08-768 05 60; TAIWAN: (02) 752-2200; YUGOSLAVIA: 041-42 37 46

CIRCLE NO 105



The precision solution.

Wyse takes the high cost out of high resolution.



At \$999, the WY-700 Graphics Subsystem is easily affordable. And its 1280 x 800 resolution makes the best of software packages like these:

DESKTOP PUBLISHING

Ventura Publisher PageMaker/PC Frontpage DeskSet Pagemaster Rim System Compound Document Processor

Display Ad Make-up System AdvanTex

GENERAL PC SOFTWARE

Lotus 1-2-3 Symphony PC-Paintbrush COMPUTER-AIDED DESIGN

AutoCAD Cadvance In-A-Vision Generic CADD VersaCAD ADVANCED Workview Procad PC

P-CAD Systems

GRAPHIC SYSTEM TOOLS

MS-Windows **GEM** MetaWindows HALO KEE PC

Wyse raises the standards for high resolution graphics, while lowering the cost.

Now you can have high resolution and full IBM software compatibility.

So Desktop publishing applications can get the screen treatment they deserve. You can run spreadsheets like Lotus

1-2-3 with four times more data displayed on the screen. Computer-Aided Design packages can deliver their full potential. And Graphicsbased pc environments finally have the high res-

You can do it all on the WY-700. A complete system, monitor and board, for just \$999. With a large 15-inch display, full tilt and swivel, and a crisp 1280 x 800 pixel resolution.

The WY-700. It's your best solution for high resolution.

Write Wyse Technology, Attention: Marcom Dept. 700, 3571 N. First Street, San Jose, CA 95134. Or call toll-free, today, for more information.

Call 1-800-GET-WYSE

YOU NEVER REGRET A WYSE DECISION.







ntil now, you expected to get what you paid for. Bruning's new ZETADRAF 900 E-size, single sheet plotter gives you *more*.


How? We've designed and engineered a totally new E-size plotter to the point where it outperforms every other plotter of its type.

And at the same time, we reduced the price!

The drawing quality is superb. And, when you consider 6 g's acceleration, 45 ips chart speed and 8-pen color capability, it's unmatched.

Of course our faster plot speed means your output is higher than ever. ZETADRAF 900 could cut the plot time for your most dense design in half.

ZETADRAF 900 supports all major CAD software packages and



is compatible with most computers. Interfaces include RS232, IEEE-488, GML and HPGL.

No prior plotter experience is required, even for liquid ink. ZETADRAF 900 has two levels of operation—novice and advanced. But *everyone* appreciates features such as the angled, LCD control panel and the ability of the plotter to store even complex user-designed configurations.

Sorry CalComp and HP. We just didn't realize when we started out that we could produce so much plotter for so little money. But we did. Get all the facts about ZETADRAF 900 or our other ZETA drafting plotters by calling (415) 372-PLOT or write:

Bruning Computer Graphics 777 Arnold Drive Martinez, CA 94533 TWX 910-481-5951



CIRCLE NO 57



Introducing the ZETADRAF 900 for \$7,950. We just raised the performance level for single sheet, E-size plotters. We also lowered the price!

Does your product require good, low cost



Meet the IMP-24, a tough, reliable little printer that you can afford to add to almost any application. It will record almost anything a microprocessor can store.

There are hundreds of applications. You can log test data, record coin counting activity, and verify security checks. The IMP-24 has proven ideal for many OEM needs.

It is miniature in everything except its capabilities. It measures only 4" x 4½" x 2," so it fits almost anywhere. An Epson dot matrix head prints on standard 2¼" adding machine paper and the ribbon cartridge is replaceable.

You can program your own format, print you own logo, get a battery pack, panel mounting or even choose your own color. The IMP-24 interfaces with RS-232 Serial, Parallel, or TTL Serial.

Cost? As low as \$135 each and less in quantities over 100.


Call IMP Printer Sales at (507) 238-4461 or send in the coupon below. Do it today. We'll have further information on the way to you within 24 hours.

Fill in the coupon of what it can do.	for the IMP-	-24's spec	c's and an actua	l sample
NAME			TITLE	
COMPANY				
ADDRESS				
CITY	STATE	ZIP	PHONE	EDN 3487




Weigh-Tronix, Inc. 1000 Armstrong Drive Fairmont, MN 56031

© 1985



POWER MANAGERS™ FOR LABORATORIES & SYSTEMS

Linear programmable...unipolar & bipolar...conventional & high speed... low, medium, & high voltage.



OEM, PROGRAMMABLE LINEAR & FERRORESONANT MODULES



OEM SWITCHING MODULES

Single & multi output.... a-c to d-c and d-c to d-c... PC Card, L-chassis, and fully shielded.



CUSTOM POWER ASSEMBLIES

You design them with Kepco's free Power Supply Template Design Kit. Kepco builds them for you.



KEPCO

THE POWER SUPPLIER



HEAVY DUTY
INDUSTRIAL
SWITCHING
POWER SUPPLIES




POWER MANAGEMENT SYSTEMS™

Kepco Digital Programming Interfaces integrated with Kepco Power Managers

For our 144-page Applications Handbook/Full-Line Catalog #146-1457, write Dept. JJF-12 or phone for a demonstration.

KEPCO. INC. • 131-38 SANFORD AVENUE • FLUSHING. NY 11352 USA • (718) 461-7000 • TWX #710-582-2631 • FAX: (718) 767-1102



Higher density, lower profile SIMM sockets from AMP. We've covered all the angles.



AMP is a trademark of AMP Incorporated

Get the styles you need with AMP SIMM Sockets, and get the well-thought-out design and reliability you can always expect from AMP.

Our single and dual slanted versions tighten parallel board spacing, shrink real estate requirements with .400 or .500 side stack centers. Single and dual verticals mount on .300 centers.

All are designed for uncomplicated, straight-in module insertion, with no clearance requirements from adjacent components. Housings provide polarization, with a separate mechanical latch for module retention.

All utilize our exclusive highnormal-force "floating" contact system, too—positive wipe gastight interface, with complete independence from housing materials for long-term integrity.


And all are designed for compatibility with industrystandard processing equipmentwith high-temperature materials, close-tolerance soldertail positioning, closed-bottom housings, robotic pick-up details.

All the details, in fact, that make AMP worth remembering for SIMM Sockets.

Call (717) 780-4400 and ask for the SIMM Socket Desk. AMP Incorporated, Harrisburg, PA 17105-3608.

AMP Interconnecting ideas





High-pressure tin-to-tin contacts provide reliable performance. Contacts with select gold plating also available.

EDN March 4, 1987

CIRCLE NO 33

Save Space, Time and Trouble.



With NEC's Chip Tantalum Capacitors.

Now you save three ways with NEC's chip tantalum capacitors. First, our surface mount packages save valuable board space. Second, our chips cut assembly time because they come in standard 8 or 12mm tape supply formats designed for automatic placement. And finally, NEC caps are 100% burned-in to minimize reliability problems while increasing MTBF.

NEC offers 96 different types of chip tantalum caps. With capacitance ranging from 0.01 to 68μ F and working voltage from 4 to 35VDC. They're all available for immediate shipment.

Contact your local NEC representative today and discover 96 ways to save space with surfacemount tantalum caps.

μF^{V}	4	6.3	10	16	20	25	35
0.01							A
0.015							A
0.022							A
0.033							A
0.047							A
0.068							A
0.1							A
0.15							A
0.22							A
0.33						A	A
0.47					A	A	B•B2
0.68				A	A		B•B2
1			A	A			B•B2
1.5		A	A	A		B•B2	С
2.2	A	A	A	В	B•B2		С
3.3	A	A	В	B•B2		С	C•D
4.7	A	В	B•B2	С	С	С	D•D2
6.8	В	B•B2	С	С	С	D•D2	D•D2
10	B•B2	С	С	C•D	D2	D•D2	
15	С	С	-C•D	D2	D•D2		
22	С	С	D•D2	D•D2			
33	С	D•D2	D•D2				
47	D•D2	D•D2					
68	D•D2						

			(Inch)
A case	1.6 (.063)	3.2 (.126)	1.6 (.063)
B2 case	2.8 (.110)	3.5 (.138)	1.9 (.075)
B case	2.6 (.102)	4.7 (.185)	2.1 (.083)
C case	3.2 (.126)	6.0 (.236)	2.5 (.098)
D case	4.3 (.169)	7.3 (.287)	2.8 (.110)
D2 case	4.6 (.181)	5.8 (.228)	3.2 (.126)
For further		please contac 6000. TWX: 91	
■ USA ■ Europe	W. Germany		0-379-6985
	Tel:0211-650	302. Telex:858	9960 NE D.
	The Netherl Tel:040-445- Sweden	302. Telex:858 ands 845. Telex:519	
	The Netherl Tel:040-445- Sweden Tel:08-732-8 France	302. Telex:858 ands 845. Telex:519	23 NEC B NL. 39 NECSCAN.
	The Netherl Tel:040-445- Sweden Tel:08-732-8 France Tel:1-3946-9 Italy	302. Telex:858 ands 845. Telex:519 200. Telex:138 617. Telex:699	23 NEC B NL. 39 NECSCAN.
	The Netherl Tel:040-445- Sweden Tel:08-732-8 France Tel:1-3946-9 Italy Tel:02-67091 UK	302. Telex:858 ands 845. Telex:519 200. Telex:138 617. Telex:699 08. Telex:3153	23 NEC B NL. 39 NECSCAN. 499 NEC EF.
■ Asia	The Netherl Tel:040-445- Sweden Tel:08-732-8 France Tel:1-3946-9 Italy Tel:02-67091 UK Tel:0908-691 Hong Kong	302. Telex:858 ands 845. Telex:519 200. Telex:138 617. Telex:699 08. Telex:3153	23 NEC B NL. 39 NECSCAN. 499 NEC EF. 55 NEC EIT I.
	The Netherl Tel:040-445- Sweden Tel:08-732-8 France Tel:1-3946-9 Italy Tel:02-67091 UK Tel:0908-691 Hong Kong Tel:3-755-90	302. Telex:858 ands 845. Telex:519 200. Telex:138 617. Telex:699 08. Telex:3153 133. Telex:826	23 NEC B NL. 39 NECSCAN. 499 NEC EF. 55 NEC EIT I. 5791 NEC UK G.
	The Netherl Tel:040-445- Sweden Tel:08-732-8 France Tel:1-3946-9 Italy Tel:02-67091 UK Tel:0908-691 Hong Kong Tel:3-755-90 Taiwan Tel:02-522-4 Singapore	302. Telex:858 ands 845. Telex:519 200. Telex:138 617. Telex:699 08. Telex:3153 133. Telex:826	23 NEC B NL. 39 NECSCAN. 499 NEC EF. 55 NEC EIT I. 5791 NEC UK G. 51 HK NEC HX. 72 HK NEC TP.



■ Oceania Australia
Tel:03-267-6355. Telex:AA38343 NEC BCD.

Interface various IC technologies to CMOS arrays

Many times you have no choice as to what device types your CMOS designs must work with. You need not despair: The key to interfacing devices made from dissimilar technologies lies in a simple analysis of each technology's voltage and current requirements.

Mark Stansberry, National Semiconductor Corp

Designs based on CMOS standard and semicustom cells must interact with devices that are fabricated in a wide variety of technologies. In communication systems, for example, high-speed data is often processed using fast bipolar circuitry and then sent on to slower CMOS systems. Old products that have not reached the end of their useful lives often employ TTL and metal-gate technologies, and these systems also must interface with CMOS circuitry. You can handle the interface problem easily by addressing a few simple voltage and current considerations.

The input- and output-voltage switching levels of two distinct technologies must be compatible, the current sourcing and sinking capability of the two technologies must mesh, and absolute voltage and current levels for the technologies must not be exceeded. In addition, you must examine timing requirements very carefully—especially if your design must drive such highly capacitive loads as a 3-state bus.

One important initial consideration with any circuitry is noise—both signal-line and power-line noise. Schmitt trigger inputs, which are available on standard cells, increase immunity to signal-line noise. You can also choose from a variety of output-power options to minimize switching transients that appear on the power lines. These methods of handling noise problems impose no restrictions on your attempts to render compatible the input-voltage switching levels of different technologies.

CMOS-cell arrays present very few problems to other technologies as far as input parameters are concerned. CMOS's input drive requirements are typically on the order of 1 μA for both I_{IH} and I_{IL} . If you decide to include a pullup or pulldown resistor in an input cell, then the input current will increase to approximately 50 μA for I_{IL} (pullup resistor) or I_{IH} (pulldown resistor). Even at 50 μA , devices fabricated in any technology can drive many CMOS devices with ease.

The only major problem you will encounter when you drive CMOS circuitry with devices of another technology is that of matching switching levels. TTL devices typically require $V_{\rm IH}$ to be 2V min, which is unacceptable as a high-level input for CMOS circuitry operating from a 5V supply. You can overcome this incompatabil-

EDN March 4, 1987




Fig 1—Voltage and current characteristics of p-channel (a) and n-channel (b) transistors reveal the drive capability of output cells and thereby the fan-out associated with the cells.

ity simply by adding a pullup resistor between the CMOS input and the 5V line, thus driving the input to a higher voltage.

Not only do you need to translate other technologies' logic levels into CMOS levels; you must also make sure that the CMOS inputs are driven higher than 4V and lower than 1V, in order to avoid power-consumption penalties. Between 1 and 4V, the input transistors operate in the linear region and therefore require an inordinate amount of current—2 to 30 mA.

How many outputs can you drive?

Fan-out is a concern in CMOS-cell-based designs only with respect to the output drive capability of the cell array. The input drive current required by an input cell is typically 1.0 μ A—low enough that any other logic family would have no trouble driving a multitude of gates. Fig 1 displays the voltage and current characteristics of n-channnel and p-channel transistors used in the construction of CMOS standard cells. Using these graphs and Table 1, you can determine the fan-out that a standard-cell-based design will have when it's interfacing with various technologies.

If, for example, you intend to drive TTL devices with a 4-mA output cell, first look at **Table 1** and determine what the specifications for $V_{\rm IH}$, $V_{\rm IL}$, $I_{\rm IL}$, and $I_{\rm IH}$ are (2V, 0.8V, 1.6 mA, and 40 μ A, respectively). Because $I_{\rm IL}$ is orders of magnitude greater than $I_{\rm IH}$, and the p-channel and n-channel transistors of the cell array can source and sink comparable amounts of current, $I_{\rm IL}$ is the parameter that determines fan-out in this case.

Now look at the voltage and current curves of Fig 1; you can see that when the n-channel transistor sinks 16 mA (assuming that $V_{\rm GS}{=}5V$), its voltage drop ($V_{\rm DS}$) is approximately 0.8V. The fan-out in this case is therefore 10 TTL devices, because $I_{\rm IL}{=}1.6$ mA, and because $V_{\rm DS}$ must be 0.8V or less (the latter condition follows from the stricture that a valid low input to a TTL gate must be 0.8V or less).

Be mindful of timing requirements

Besides dc considerations, there are, of course, timing concerns related to interfacing various technologies with CMOS. Package, trace, and circuit capacitances of externally driven devices present an ac load to driving devices. Package capacitance is the predominant factor, and if you regard it as the sole contributor to the ac load, you'll obtain a close approximation of the total capacitance. Most packages present between 5 and 15 pF of capacitive load. An output cell driving 10 external

CMOS-cell arrays present very few problems to other technologies as far as input parameters are concerned.

TABLE	1—VOLTAGE AND CURRENT REQUIREMENTS
	OF VARIOUS IC TECHNOLOGIES

1	I _{IH}	I _{IL}	V _{IH}	V _{IL}	V _{OL}	V _{OH}	I _{OL}	Іон
TIL	40 μΑ	-1.6 mA	2V	0.8V	0.4V	2.4V	1.6 mA	-400 μA
LTTL	10 μΑ	-0.18 mA	2V	0.7V	0.4V	2.4V	2/3.6 mA	-200 μA
LOW-POWER SCHOTTKY TTL	20 μΑ	-0.36 mA	2V	0.8V	0.5V	2.5V	4/8 mA	-400 μΑ
ADVANCED LOW-POWER SCHOTTKY TTL	20 μΑ	-0.2 mA	2V	0.8V	0.5V	V _{CC} -2V	4/8 mA	-400 μΑ
SCHOTTKY TTL	50 μA	-0.2 mA	2V	0.8V	0.5V	2.5V	20 mA	-1000 μΑ
ADVANCED SCHOTTKY TTL	20 mA	-0.5 mA	2V	0.8V	0.5V	V _{CC} -2V	20 mA	-2000 μΑ
ECL	-400 μA	0.5 μΑ	-1.95V	-1.63V	-1.63V	-0.92V	<u> </u>	- 1
CMOS	1 μΑ	1 μΑ	0.7 V _{SS}	0.3 V _{SS}	0.4V	4.6V	1 TO 12 mA	1 TO 12 mA

devices will therefore be driving a minimum of 50 pF.

When you drive capacitive loads, the following rules of thumb will help you determine the delays associated with output cells of different current capability. Expect delays of 0.12 nsec/pF for a 4-mA cell, 0.24 nsec/pF for a 2-mA cell, and 0.48 nsec/pF for a 1-mA cell. Using these numbers, you can see that a 50-pF load will add 6 nsec of delay to a 4-mA driver, 12 nsec to a 2-mA driver, and 24 nsec to a 1-mA driver. These added delays mean that, although a driver may be able to meet your dc current requirements, the delays may not measure up to your timing needs. Take care, then, to match your output cell's current capability with your ac load.

In addition to adhering to the minimum and maximum voltages specified for proper logic levels, you must adhere to the requirements for maximum and minimum safe operational voltages and for maximum allowable currents. The latch-up protection circuitry found on CMOS ICs sets the limit on both positive and negative input voltage swings. If you allow an input signal to exceed the supply voltage by more than 0.7V, or to go below ground by more than 0.7V, the input protection diode will turn on. The protection diode was designed into the IC to turn on in cases such as this, but it's meant to deal only with transient signals. If the diode is on for more than a few microseconds, the circuit may be destroyed. You can add a standard resistor-diode network to the input to limit the current.

CMOS devices that operate simultaneously from different supply voltages present one of the easiest inter-

face obstacles to overcome. You can use open-drain outputs with an external resistor tied to the voltage supply of the component you are attempting to drive. You should use external latch-up circuitry under these circumstances, because an internal latch-up diode will limit the output transition of the output cell to 0.5V above the supply voltage of your standard-cell design. You can also use a 3-state output cell to interface to a circuit that operates from a higher supply voltage; simply use the data to enable the cell or to put it into a high-impedance state. An external pullup resistor connected to the higher supply voltage will pull the signal up to the higher supply level when the cell is in the high-impedance state. The resistor must, in addition, restrict the current flow into the standard cell to a safe level.

The use of TTL parts to drive standard cells poses no special challenge, because CMOS input cells that are TTL compatible are readily available; just specify TTL-compatible input cells and the requirements for $V_{\rm IL}$ and $V_{\rm IL}$ are automatically met. Other means of interfacing TTL to CMOS include the previously mentioned pullupresistor technique and the use of dual-function level-translator/logic gates.

CMOS's output-voltage levels present no impediment to driving TTL circuitry, but you have to exercise caution with regard to TTL current requirements. Worst-case current requirements for TTL inputs generally restrict the fan-out of CMOS gates that drive TTL gates to 10.




Fig 2—You can interface telecomm signals, which operate at voltage levels of 0 and -48V, to CMOS arrays using this circuit.




Fig 3—You can use this circuit to drive 5V CMOS circuitry from 10V logic circuits.

If you want to interface CMOS to ECL, you can use TTL/ECL and ECL/TTL level translators. Once you have translated an ECL signal to TTL levels, you can tie the signal directly into a TTL-compatible input cell. You can drive a TTL/ECL translator directly from a CMOS output. Once again, though, you need to be aware of the fan-out restrictions associated with this driving configuration.

Telecommunications systems offer yet another interfacing challenge to designers of CMOS-cell-based circuitry (although many of the interfacing techniques described earlier apply here as well). Telecomm equipment often employs fast bipolar circuitry and operates at logic levels of 0 and -48V. Fig 2 illustrates a resistor-clamping diode network that allows you to interface CMOS devices to telecomm equipment.

When choosing the proper resistor values for this circuit, you must—as noted earlier—take care to prevent latch-up and ensure that the correct switching voltages are attained. To prevent latch-up, you must make sure that the input current to the array doesn't exceed 75 mA and that the interfacing circuit provides the correct switching voltages for a CMOS input— $0.3 \times V_{SS}$ and $0.7 \times V_{SS}$ for V_{IL} and V_{IH} , respectively. The external pullup resistor (R_{PU}) and the current-limiting

resistor (R₁) act in conjunction with internal input protection diodes to accomplish the level translation and input-current protection for the input buffer.

If the input signal is at -48V (logic zero), the input protection diode clamps the voltage at the input of the gate at -0.7V. If the input signal is at 0V (logic one), the input protection diode will pull the gate voltage up towards $V_{\rm SS}$. R_1 must limit the current to no more than $100~\mu A$. Consequently, the desired value of R_1 is

$$R_1 = \frac{48V - (-0.7)}{100 \ \mu A} = 473 \ k\Omega.$$

You can determine the value of R_{PU} from

$$V_{\rm IN} = V_{\rm SS} - \frac{R_{PU}(V_{\rm SS} - (\,-\,48V))}{R_{\rm PU} + R_{\rm I}}$$

for a logic zero and from

$$V_{IN} = V_{SS} - \frac{R_{PU}(V_{SS} - 0V)}{R_{PU} + R_1}$$

for a logic one.

For the problem of interfacing the telecomm signal to a CMOS gate, set $V_{\rm IN}{=}{-}1V$ for the logic-one state and $V_{\rm IN}{=}0.7{\times}V_{\rm SS}$ for the logic-zero state. Substituting these values into the above equations yields $R_{\rm PU}{=}60~{\rm k}\Omega$ and $R_{\rm 1}{=}470~{\rm k}\Omega$. These values provide the level translation and input protection needed.

You can use the circuitry shown in Fig 3 to interface higher-voltage (10V) signals to 5V CMOS standard cells. The blocking capacitor eliminates the dc component of the incoming signal. Once the capacitor is charged, the driving circuitry pumps no more current into the input. The diodes clamp the input signal, and the resistor serves as a current limiter.

Author's biography

Mark C Stansberry is a consultant who, since writing this article, has formed Datahouse Corp (Los Gatos, CA). In addition to conducting market research for the new concern, he does digital-logic-block and ASIC design. Mark acquired his BSEE from San Jose State University. He enjoys skiing, bicycling, wind-surfing, and illustrating in his spare time.

Article Interest Quotient (Circle One) High 479 Medium 480 Low 481

ROCKWELL SEMICONDUCTOR TECHNOLOGY SOLVES T-1/CEPT IMPLEMENTATION IN A CMOS CHIP.



Replace up to 100 MSI devices with the world's first single-chip PCM transceiver.

Designed for worldwide primary rate applications, the R8070 from Rockwell International is a telephony breakthrough. This singlechip solution accommodates all primary telephone carrier requirements in both North America and Europe. The R8070 T-1/CEPT operates with AT&T extended framing, Clear Channel, and European CEPT formats.

Save on power, design engineering and component costs.

As a single-chip, CMOS transceiver, the R8070 minimizes board space requirements with its VLSI implementation. It significantly reduces power consumption, saves on component costs and reduces engineering design investment as well. To find out how the R8070 can help you build your next generation T-1/CEPT communications system, talk to your Rockwell distributor or sales representative or send for complete technical literature today.

Semiconductor Products Division

Rockwell International, P.O. Box C, M.S. 501-300, Newport Beach, CA 92658-8902 (800) 854-8099. In California (800) 422-4230.



where science gets down to business

Aerospace / Electronics / Automotive General Industries / A-B Industrial Automation

CIRCLE NO 108

GE/RCA HC: Your clear path



into the world of CMOS.

Only GE/RCA has the broad line, unique parts and 25 years of CMOS experience to support you every step of the way.

Your venture into the world of high-speed CMOS can be very rewarding—if you travel with the right CMOS partner.

A logical first step.

We have been the leader in CMOS logic for more than two decades.

We pioneered with the 4000 series and followed with high-speed CMOS and ACL.

Today, we have more than 270 highspeed CMOS devices. And that number is growing fast, because every time we make a new HC device (and we have the industry's broadest line), we make the corresponding part in HCT, too.

A design engineer's dream.

This broad line includes quite a few unique parts (for a sample, see the box below). And we have extensive experience

in High-Rel, ASICs, memories and microprocessors, so we can help you get the most possible from this outstanding technology.

And a purchasing agent's, too.

There's more to good CMOS than good design. We have a track record of delivering competitively-priced parts on time. And we've invested millions of dollars to provide the production capacity and leading-edge technology you need.

Add to this a record for reliability that has truly withstood the test of time (after all, we invented CMOS), and you'll see why so many people have started successful journeys into CMOS with GE/RCA at their side.

Take a big step in the right direction, and call toll-free 800-443-7364, ext. 15. Or contact your local sales office or distributor.

Our unique high-speed CMOS analog switches are among the highest frequency, lowest distortion devices available today.

HC/HCT4016, 4066, 4316

- Low Ron, 125 ohm typically (4016, 4316),
 25 ohm typically (4066), Vcc=4 5V
- 25 ohm typically (4066), Vcc=4.5V.
 Frequency response of -3db down @ 180 MHz (4016, 4316), -3db down @ 200 MHz (4066), both driving a 75 ohm load.
- · Low distortion.
- Maximum control switching frequency to 35 MHz.
- Low "OFF" leakage current.
- Applications: Instrumentation, Direct Current to 50 MHz Switching Systems, Cable TV, Workstations.

HC/HCT4051, 4052, 4053, 4351, 4352, 4353

- Wide analog input voltage range: ±5.5V max.
- Low "ON" resistance: 70 ohm typ (Vcc-Vee = 4.5V), 40 ohm typ (Vcc-Vee = 9V).
- Low crosstalk between switches.
- Fast switching and propagation speeds.
- "Break-before-make" switching.
- Applications: Audio and Video Switches, Synch. Detection, Video Mixing, RF Frequency Switching, Data Multiplexing, Data Conversion, Data Transmission.

Our Phase-Locked Loop devices offer greater speed and linearity than any other CMOS PLL's...plus low power consumption.

HC/HCT4046A


- Operating frequency range up to 17 MHz (fc) at Vcc=4.5V.
- Built-in op amps for excellent linearity.
- Op-amp buffered demodulated output.
 3 phase comparators to choose from.
- Applications: FM Modulation/Demodulation, Frequency Synthesis, Frequency Multiplexing, Voltage to Frequency/Frequency to Voltage Conversion, Servo Control Systems, Data Synchronization, Manchester Coding/Decoding.

HC/HCT7046

- Operating frequency range up to 17 MHz (fc) at Vcc=4.5V.
- Built-in op amps for excellent linearity.
- Op-amp buffered demodulated output.
- A pin which indicates lock detect.
- 2 phase comparators to choose from.
- Applications: FM Modulation/Demodulation, Frequency Synthesis, Frequency Multiplexing, Voltage to Frequency/Frequency to Voltage Conversion, Servo Control Systems, Data Synchronization, Manchester Coding/Decoding.




EDN REPRINTS




A Designer's Guide to CMOS ICs

CMOS is fast becoming the chosen technology for developing integrated circuits. That's because CMOS ICs are able to implement ultra-complex system-level functions on a chip! Now you can meet the special challenges posed by this new breed of ICs with *A Designer's Guide to CMOS ICs*. You'll learn the advanced design and fabrication techniques required. Plus the latest linear and digital CMOS ICs available.



A Designer's Guide to Semicustom Integrated Circuits

Learn how to design a semicustom IC with A Designer's Guide to Semicustom Integrated Circuits. Based on EDN's own design experience, this nine-chapter booklet outlines the complete procedure used to design, fabricate, and test EDN 1, a chip with a 1200 equivalent-gate complexity. You'll not only learn the steps to take when creating ICs, but also the design/cost analyses and vendor-interface methods that lead to successful semicustom chips.



A Designer's Guide to Innovative Linear Circuits

As exciting as digital technology is, you still need analog circuitry to operate on signals from real-world sources. Now, EDN is offering a wealth of analog design information in *A Designer's Guide to Innovative Linear Circuits*. This 186-page collection of articles was developed by Jim Williams, one of America's foremost linear-circuit designers. It includes practical and efficient ways to use op amps, comparators, data converters, and other analog ICs, and discusses the theories behind all the design techniques presented.

Mail coupon to:

EDN Reprints EDN Magazine Cahners Building 275 Washington Street Newton, MA 02158-1630 Please print clearly. This is your mailing label.


275 Washington Street Newton, MA 02158-1630	NAME	
Please send the following Designer's Guide(s):		
copies of <i>A Designer's Guide to CMOS ICs</i>	- TITLE	
(BANK DRAFT ONLY) copies of A Designer's Guide to Semicustom Integrated Circuits	- COMPANY	
\$ 6.95 UPS \$ \$10.95 non USA (BANK DRAFT ONLY)	- ADDRESS	
copies of A Designer's Guide to Innovative Linear Circuits \$\Begin{array}{c} \\$14.95 \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \		TATE ZIP
Check or money order made out to EDN REPRINTS must accompany each order. No COD. Mass. residents add 5% sales tax.		EDN 3487

JOIN THE 1987 FA

AND DEVELO NEW PRODUCTS AND MARKETS IN THE FAR EAST

Hundreds in the electronics industry have taken advantage of Commerce Tours International's tours to the Orient. This year - our 11th year in the business - you, too, can develop new products, markets and sources in the Far East.

You'll attend major business seminars and electronics shows. Meet your foreign competitors in the Pacific Rim. Gather ideas. Exchange observations. It's truly a business opportunity you won't want to miss!



DATE: October 3-18, 1987

VISIT: Japan, Taiwan, Korea and

Hong Kong

Optional extensions:

A: Singapore

B: Canton and Beijing, China

PROGRAM HIGHLIGHTS:

VISIT ELECTRONICS SHOWS

- Japan Electronics Show
- Korea Electronics Show
- Taiwan Electronics Show
- Canton Trade Fair
- Singapore Electronics Show

ATTEND BUSINESS SEMINARS

- Electronics Technology Update Seminar
- Korea Business Opportunities Seminar
 Taiwan Business Opportunities Seminar
 China Business Opportunities Seminar
- Singapore Business Opportunities Seminar

PLUS

- · Visit factories and research facilities
- · Attend business meetings with foreign companies

DEPARTURE CITIES:

Departures will be available from major U.S., Canadian and European cities via regular flights.

PRICE:

\$3,130 from West Coast including airfare, hotel accommodations, daily American breakfast, five dinners, transportation to/from show grounds, airport/hotel transfers and all business programs as outlined above. Seminar fees are additional.

ORGANIZED BY:

Commerce Tours International, Inc.

FOR MORE INFORMATION. PLEASE CONTACT ONE OF THE FOLLOWING OR RETURN THIS COUPON

NAME COMPANY DEPARTMENT/TITLE _____ ADDRESS ___ CITY _____ STATE ___ ZIP ___ TELEPHONE __ TELEX ______FAX ___

IN U.S.A

Commerce Tours International 870 Market Street Suite 920

San Francisco, CA 94102 Tel: (415) 433-3072 Attn.: Bob Chang

IN CANADA

Plesman Publications 2 Lansing Square, #703 Willowdale, ONT M2J 4P8 Tel: (416) 497-9562 Attn.: Sharon Raspin

IN U.K.

JCT International Ltd. Hanover Court 5 Hanover Square London WIR 9 HE Tel: 01-499-6827 Attn.: Gordon MacFarland

IN NETHERLANDS

Nippon Express (Nederland) B.V. Postbox 7175 1007 JD Amsterdam Tel: 020-621387 Attn.: Errol Lafleur

Mil. Spec. IC decoupling

New MICRO/Q II capacitors conform with MIL-C-39014D, STD 202F. Molded construction seals out moisture and humidity. Available in capacitances from .01 μ F to .30 μ F. You achieve effective noise control and reduce noise spikes, in conditions from -55° C through +125 $^{\circ}$ C. Mount beneath DIP IC's to save up to 30% board space.



CIRCLE NO 111

Improve existing board performance

MICRO/Q capacitors can be retrofitted to solve noise problems on existing boards. Because MICRO/Q caps share mounting holes with existing IC pins, no board redesign is required. Effective decoupling becomes a matter of adding one insertion step.

CIRCLE NO 112

Simplify board layout and get a choice

MICRO/Q ceramic decoupling capacitors share board mounting holes with IC pins. You don't have to waste space on additional holes, as you do for standard caps. Simplifying board design opens up two very attractive options. Add more active devices with increased packaging density in the same space, or design the same

package on a smaller board. Either way, you win with MICRO/Q.

CIRCLE NO 113



Rogers MICRO/Q® decoupling capacitors reduce voltage noise spikes in IC's, often by as much as a factor of ten. And since they're easily mounted *underneath* the IC, MICRO/Q capacitors conserve valuable board real estate, too. A range of configurations makes MICRO/Q flat capacitors especially effective at reducing noise on:

- 64K RAMS
- Video RAMS
- **■** EPROMS
- Microprocessors
- Bus drivers/buffers
- Other IC's where noise spikes create performance problems
- Boards that need EMI/RFI fix
- CAD/CAM/CAE
- Telecommunications
- Minicomputers
- Printers and copiers
- Single-board computers

Find out how MICRO/Q capacitors reduce noise and provide better board density. Get the full story and a free sample. Call a Rogers MICRO/Q Product Specialist today, at (602) 967-0624.



Rogers Corporation Circuit Components Division 2400 South Roosevelt Street Tempe, AZ 85282

Distributed in the U.S. by the Genie Group; in Europe by Mektron NV, Gent, Belgium; in Brazil by Rogers Coselbra, São Paulo.

CIRCLE NO 115

Design noise out of PGA and LCC packages

PGA MICRO/Q capacitors provide effective solutions to noise problems with VLSI PGA packages and LCC sockets. Design effective decoupling on complex multi-layer board layouts by fitting PGA MICRO/Q capacitors under PGA or LCC sockets. They occupy no additional board space and provide the low-inductance, high-frequency decoupling required by today's VLSI packages. Available in a range of pinout configurations.





Partition Custom ICs along technology lines

Implementing analog circuitry on custom ICs can be a difficult task because such circuitry often uses a wide variety of device technologies. To divide your circuitry into the functional blocks appropriate for each IC technology, you must first know your system's requirements and the strengths and weaknesses of the various technologies.

Karl J Huehne, United Technologies Microelectronics Center

The rapid advancements in IC technology have made it possible to consider implementing entire systems on just a few custom or semicustom chips. In such systems, it's easy enough to implement the digital functions; one popular approach is to use gate arrays. However, implementing all the other (mostly analog) circuitry on chip can be much more difficult. Unlike the digital circuits, which generally are fabricated in the same technology, the analog circuitry is often a hodge-podge of components: integrated and discrete, active and passive, MOS and bipolar.

To integrate these analog functions on chip, you must first understand both your system's requirements and the strengths and weaknesses of the various IC technologies. Then you can divide your circuitry into the functional blocks appropriate for each technology. This scheme will let you get the best possible performance out of your IC in the smallest possible space.

Your first task in developing a custom analog IC is to understand the requirements of the system it will operate in. You need to know what the system will demand of your chip, regardless of whether the circuit design is a new one or an existing one. Both these situations can pose difficulties. For example, if your task is to place an existing board-level design on a single chip, you might find that the original requirements were poorly documented and are now lost. If you're designing your chip from scratch, your system requirements will tend to change as the design evolves.

When you start with an existing design, make sure you don't fall into the trap of specifying your IC merely in terms of the existing design's individual components. This approach is the easiest one for a systems house to take, and it can make a proposed design seem like a good risk, but it doesn't take into account the fact that the original circuitry probably consists of many disparate technologies, which will be difficult to integrate on a single chip.

A more serious problem with this approach is that the board designer had access to a number of low-cost, high-performance components, a luxury you won't have when you design your IC. The high-performance components were inexpensive in discrete form, and they took up no extra space. In integrated form, however, these components would use a lot of extra space to implement functions your chip simply doesn't need.

If you're putting an existing board-level design on a chip, don't specify your IC merely in terms of the design's individual components.

Therefore, specifying integrated versions of all the components on the original board would be counterproductive.

A discrete component as mundane as a 741 op amp, for example, offers high input impedance and output short-circuit protection, two features that might not be necessary to your system, yet would require complex circuitry were you to add them to your IC. In a design that calls for a 741, you could prevent this difficulty by specifying lower input impedance for your IC, thereby simplifying the design of the input stage. Alternatively, if the output will not be required to drive anything off chip, you can just avoid including the output short-circuit-protection circuitry.

Define the requirements

Even when you're working on a new design, it's critical for you to define the overall system requirements carefully. In this case, problems can arise when the system requirements are evolving along with the design. At some point during the IC-design process, you'll have to stop and define the system requirements. Your choices of custom-IC vendor, design methodology, and IC process will all depend on the device parameters you specify at this point.

Voltage levels, both normal and maximum, will be

one factor in determining what process you'll be able to use. For instance, you'll need to state in your IC specification whether your IC will have to drive high-voltage signals. If it will, you'll need to specify how: You could, for example, use open-drain or open-collector outputs. In each IC, you could incorporate a few output transistors having special characteristics, such as open drains.

Your specification should also include any voltage transients that you expect to see in your circuit. An IC must operate under well-defined bias conditions. When these conditions are violated, normal circuit operation can be disrupted and, in extreme cases, the IC can be destroyed. You can protect your IC from such problems by maintaining isolation between adjacent devices on a bipolar IC. To isolate the devices, make sure that the substrate is at the most negative voltage on the IC.

If you don't provide such external protection, a transient occurring on any IC line could drive a portion of the IC to a level more negative than that of the substrate. This condition, of course, would upset the delicate balance of the biasing scheme, and because parasitic transistors in the substrate could turn on, it could cause enough current flow to destroy the device.

Another factor you must consider is the amount of IC-performance degradation you're willing to tolerate.

IC resistors

The principle behind resistor design is that of a basic electrical parameter known as sheet resistance. The resistance from end to end of a square of material of uniform thickness and resistivity is a constant, independent of the size of the square. The resistance of a material is therefore characterized in terms of ohms per square.

When two of these squares are placed end to end (in series) between electrical contacts, the resistance between the contacts is twice the resistance that would be present if only one square were between the contacts. When two squares are

placed side by side (in parallel) between electrical contacts, their resistance is half that of one square.

Approximately, then, the re-

sistor you'll choose depends in part on the number of squares you need to use. If the base-diffusion material has a sheet resistance of 150Ω /square and you

TABLE A—TYPICAL VALUES ASSOCIATED WITH DIFFERENT TYPES OF IC RESISTORS

RESISTOR TYPE	OHMS/SQUARE	TYPICAL TOLERANCE	TC (PPM/°C)
BASE	150	25%	2000
EMITTER	5	30%	1500
E-B PINCH	5000	75%	5000
IMPLANT	1500	25%	3000
METAL	0.030	20%	6000
POLY	60	50%	1500
EPITAXIAL	1500	50%	8500
THIN FILM	1000	20%	200

You'll need to specify whether or not your device will have to operate continuously with unadulterated performance or whether the overall system can withstand some degradation on the part of your IC. If you can't relax your device's performance requirements, you may have to include thin-film or polysilicon resistors in your design. Both types of resistor offer dielectric isolation on the order of a few hundred volts but require extra process steps, which add to the cost of an IC.

Compare device technologies

One of the primary difficulties you face in recasting an existing design in silicon is that functions that aren't performed by the custom or semicustom digital ICs often use different technologies, such as MOS and bipolar technologies. Although you can mix MOS and bipolar technology on an IC, this approach is generally more expensive than using only one technology, and it often presents performance compromises, because it's difficult to optimize a process for both bipolar and MOS device performance. Standard IC products are fabricated around either the npn or the MOS transistor, but not both.

Achieving comparable performance for both device types on the same IC would require a prohibitive number of mask steps. In the mixed-technology pro-




Fig 1—Two implementations of an op amp's input stage illustrate how an IC op amp substitutes active circuitry for passive circuitry. The discrete-component implementation (a) uses resistors. The integrated version of the circuit (b) uses transistors in place of the resistors.

need a 1.5-kΩ resistor, the resistor will require 10 squares. To obtain a resistance of 15Ω, you'd also require 10 squares of this material, but you'd arrange it in parallel. To keep resistors to a reasonable size, you should limit the resistor values in your design to the range between ½0 and 10 times the sheet-resistance value of the resistor material you're using.

To obtain a wide range of resistance values, you might be tempted to use a variety of resistor types: base-diffusion, base-pinch, epitaxial, and epitaxial-pinch resistors (see **Table A**). The folly of this ap-

proach is that these resistors all use different processes, which will cause undesirable differences in both the resistors' absolute accuracy and their tracking, or matching, characteristics.

The absolute tolerances of IC resistors generally range between 20 and 50%. Absolute tolerance is determined by two primary factors. The first is the sheet resistance of the material, which is determined by the doping concentration and the junction depth. The second factor, the one you have more control over, is the definition of the resistor's length and width. The accuracy of these dimensions is

determined by the photolithographic tolerance. This tolerance is a fixed number, which is often on the order of a few microns.

Because the tolerance is a fixed number, you can make it as small as you like by increasing the size of the resistor. The catch is that when you make a resistor 10 times wider, thus improving its accuracy tenfold, it takes up 100 times more space, because you must increase the length by the same ratio in order to maintain the resistor value. As you can see, absolute accuracy exacts a heavy toll in IC area.

If your IC will drive high-voltage signals, you need to specify how: You could use open-drain or open-collector outputs, for example.

cesses that most custom-IC vendors use, a single mask step produces both device types on a chip, so the IC's performance is compromised. If your system is small enough to fit on a single chip, it may make economic sense for you to use mixed MOS/bipolar technology, but because of the performance compromises, it's generally best to choose one technology or the other.

If you decide that a mixed-technology device is not reasonable for your application, you must choose between the MOS and bipolar processes. Although MOS devices have traditionally been thought of as low-power devices that are unable to handle large amounts of current, the newer, more dense MOS circuits offer improved current-handling capabilities.

In addition to their reputation for low power capacity, CMOS devices are known for their low power consumption. In digital applications, in which a transistor acts as a switch, this reputation is well deserved. The MOS transistor requires very little power to maintain an on or off state. It consumes power mainly at intermediate states, when the devices are switching. If your design requires analog circuitry, you may wish to use bipolar technology, because bipolar and CMOS devices consume similar amounts of power at intermediate levels.

Analog switching or multiplexing functions are natural applications for CMOS technology, because MOS devices are inherent switches; the voltage-switching characteristics of bipolar devices aren't as good. On the other hand, bipolar voltage references are much better than MOS voltage references. If you plan on multiplexing analog signals into an A/D converter, for example, and you require an extremely accurate voltage reference, you'll want to use bipolar technology. To determine which process is most suitable for your design, you must carefully specify such switch parameters as speed, settling time, current capability, on-resistance, offset, signal-voltage levels, control-voltage levels, and isolation in the off state.

Important differences also exist between the performance of a circuit implemented in discrete components and the performance you can obtain in an equivalent IC. The designer of a board-level circuit can choose from a great number of transistors. Each of these transistors is optimized for a different characteristic, such as power, voltage, current, low noise, or frequency response. In contrast, you can't tweak an IC to improve it in one spec without making a tradeoff in another. Some variations are available to the IC designer—you can, for example, modify the geometry of a transistor-but

the basic limitations of its technology still remain.

Consider the npn transistor. The current-carrying capability of an npn transistor in an IC is limited by the fact that the current is forced to travel vertically through the emitter-base junction and the collector region. Then it must travel horizontally (the buried layer provides a reduction in resistance) and then vertically again through the epitaxial layer to the collector's contact area. However, because you don't have to isolate a discrete npn transistor from other devices, its entire current flow is vertical. Therefore, virtually its entire area is available for conduction, so it can carry much more current than can an integrated npn transistor. Further, the IC transistor has additional capacitance associated with its isolation and substrate junctions, so its frequency response is limited in comparison with that of a discrete transistor.

Although devices on an IC are constrained by the fact that they all operate from the same voltage, have approximately the same operating speed, and are restricted to the same threshold voltages, placing all the devices on the same substrate does have some advantages. Because these devices are produced with the same process steps and with the same material, you can achieve extremely close parametric matching and precise scaling. You can also design multiple-collector pnp and multiple-emitter npn transistors into an IC.

From weakness comes strength

With this knowledge, you can take some of an IC design's weaknesses and turn them into strengths. For example, although the absolute accuracy of a resistor in an IC may be off by as much as 30%, you can match resistor values to a very high degree. Both active and passive devices vary in a very similar fashion in response to environmental changes, so you can take advantage of the resistor matching by designing in differential circuits whenever possible. Differential circuits are little affected by the device-parameter changes that environmental changes cause.


The traditional design philosophy, which emphasizes the use of passive rather than active components, must be completely reversed when you design with ICs. Passive devices take up much more space in silicon than do active devices, so you'll want to favor active devices over passive ones. Indeed, modern IC op amps have a relative dearth of resistors. Fig 1, for example, shows a simple, single-stage amplifier designed first in the traditional way, with resistors, and then in the modern

EDN March 4, 1987

The \$50,000 RIDGE 3200 Design Analysis.

The state of the s

The \$400,000 VAX 8600 Design Analysis.



What's the difference??!!!

Until now, working with design programs like HSPICE, USPICE, ASPEC, HILO-3, SILOS, DRACULA, SUPREM, OMNIROUTE, and VTI Design Tools, meant you had to do one of two things. Spend about \$400,000 to get mainframe computing power. Or spend time waiting for your workstations to grind out the results.

Ridge Computers is changing all of that. The RIDGE 3200 gives you the 4 + MIPS of performance and up to 128 Mbytes of real memory at a price you can afford.

The 3200 is easily accessed from graphics terminals or through Apollo, SUN, IBM or Apple workstations and personal

computers over a local area network. With the power of the RIDGE 3200, complex tasks like design capture, analog and logic simulation, integrated circuit layout, design verification and database management, are fast and nearly routine.

Also, with designs running 10,000–20,000 gates and larger, cost-effective real memory availability becomes as important as CPU performance. Simulations today require at least 1 Mbyte of memory for each 1,000 gates

of design for efficient execution. The 128 Mbyte of real memory on the 3200 means that large designs are analyzed in memory and the overhead associated with input/output is significantly reduced. Analyses that have taken hours or days can now be done in minutes. Faster analysis provides the opportunity for more analyses and means fewer errors, lower manufacturing costs, faster product introductions, higher quality products. Success!

So remember, in addition to all of the performance and memory you would expect in a \$400,000 computer, the RIDGE 3200 gives you something else. About \$350,000 in change.

That's the Ridge difference!



2451 Mission College Blvd. Santa Clara, CA 95054 800-821-8975 In California 800-468-1848

CADscreen photo courtesy of ECAD Inc. HSPICE is a trademark of Meta-Software, Inc. USPICE is a trademark of Electronic Software Products. ASPEC is a trademark of Control Data Corp. HILO-3 is a trademark of GenRad, Inc. SILOS is a trademark of SimuCAD. DRACULA is a trademark of ECAD Systems. VAX is a trademark of Digital Equipment Corporation UNIX is a trademark of ATRE Bell Laboratories. Sun is a trademark of Sun Microsystems, Inc. Apple is a trademark of Apple Computer, Inc. OMNIROUTE is a trademark of Omnicad. SUPREM is a trademark of Stanford University. RIDGE 3200 is a trademark of Ridge Computers.

GUESS WHO

makes a 64K bipolar PROM that, at 35 nsec, is 30% faster than any other on the market?

(See page 210).



Precision switches are a snap!

One stop design shopping is yours with OTTO'S complete line of single and double break snap-

action switches. Sub-subminiature sizes for direct actuation and for integral or auxiliary lever, pushbutton and toggle actuators. Ratings from 8 amps to low level. OTTO'S patented high contact pressure design assures < 0.025 ohms contact resistance. If you don't see what you need as a standard, we'll customize a design for you. Commercial grades are UL listed and CSA certified. Military grades meet MIL-S-8805/4, /76, /101, /106 & /109.

Write or call for Catalog 103.

OTTO CONTROLS

OTTO means precision switches.

2 East Main St. • Carpentersville, IL 60110 • 312/428-7171 FAX: 312-428-1956 • TELEX: 72-2426 Resistors play a key role in many systems. Even systems that employ active devices often have an assortment of external resistors that set threshold, gain, hysteresis, or some other performance factor. For board-level systems, very accurate resistors are readily available. For integrated design, however, the selection of resistors is limited, and the resistance values have very poor accuracies. Fortunately, many applications require only accurate ratio control, an area in which integrated resistors easily outstrip their discrete counterparts (see box, "IC resistors").

Just as when you choose a device technology, you face a number of tradeoffs when you choose a design methodology. Custom and semicustom approaches each have their advantages and disadvantages. A custom aproach to implementation can result in the lowest cost per IC, as long as you can amortize the higher initial nonrecurring engineering (NRE) costs of this method over a large volume of chips. Linear arrays offer a lower NRE cost, because they can incorporate some building-block functions, such as op amps. The linear array, though, has not been able to match the utility of a digital gate array, because an analog design can't be reduced to a composition of 2-input-gate equivalent cells.

Standard cells provide higher-level functions than do linear arrays, but if you use these already-defined cells, you'll be making design compromises. Furthermore, analog standard cells, like their digital counterparts, are most often available in CMOS, so the standard-cell approach is geared mainly to applications that contain a lot of digital circuitry and require only limited linear performance.

Author's biography

When he wrote this article, Karl J Huehne was design manager of linear and smart power ICs at United Technologies Microelectronics Center. He is currently employed by Motorola Inc (Tempe, AZ), where he is design manager of telecommunications circuits. Karl obtained a BSEE from the University of Illinois and an MSEE from Arizona State University. His interests include astronomy, downhill skiing, and personal computers.



Article Interest Quotient (Circle One) High 473 Medium 474 Low 475

196 SYSTEM DMM

OHMS



SS

NO

POWER

MODIFIER 8 CAL ENABLE

VOLTS SENSE

□ 6½ digits, ±3,000,000 counts □ 100 nV, 1 nA, 100 μΩ sensitivity □ 30 ppm DCV accuracy ☐ Speed: up to 1000 readings/second ☐ Offset compensated or 4-wire ohms

☐ IEEE-488 and exclusive TRANSLATOR software ☐ \$1395, complete

Call or write Keithley for more information.

Product Information Center, Instruments Division, Keithley Instruments, Inc., 28775 Aurora Road, Cleveland, Ohio 44139, (216) 248-0400. CIRCLE NO 86



Only the Teddy Bear Can't Use Our Help...Yet



Priced as low as \$1.60 each, Avantek's silicon MMIC amplifiers and frequency converters provide outstanding gain-bandwidth per dollar.

Design engineers can simplify circuit designs, improve performance and lower overall system costs, as MODAMP™ MSAseries amplifiers and MSF-series frequency converters provide improved gain and bandwidth over hybrid components ... for less. These Monolithic Microwave Integrated Circuit (MMIC) components are designed for use in applications that listen, watch or talk ... from satellites, G.P.S. navigation receivers and fiber optic systems to police radar detectors, medical equipment and . . . even toys.

A Growing Family of MMICs to **Meet System Designer's Needs**

Since 1982, Avantek's silicon MMIC product family has grown to include more than 50 different models covering the frequency spectrum from DC to 8 GHz, with gains as high as 33 dB, noise figures as low as 2.5 dB and power outputs as high as 20 dBm (@ 100 MHz). The MSA- and MSF-series of products are available in a range of packages, from low-cost plastic to high-rel metal/ceramic.

Selected MSA & MSF Components

(Performance @ 1.0 GHz)

Model-	Max. Useable Frequency (GHz)	Gain (dB, typ.)	Noise Figure (db,typ.)	P _{1dB} (dBm, typ.)	Package Type	1000 Piece Price \$\$\$
MSA-0185	4.5	15.5	5.5	1.5	A A	1.60
MSA-0204	4.0	11.0	6.5	4.0	В	1.90
MSA-0370	4.5	12.5	5.5	10.0	C	16.10
MSA-0420	3.5	8.5	7.0	15.0	D	18.45
MSA-0635	4.0	16.5	3.0	1.5	E	4.85
MSA-0835	6.0	23.5	3.0	12.5	E	7.80
MSF-8870	8.0	20.0	N/A	9.0	C	29.75

A) 85 mil plastic B) 145 mil plastic C) 70 mil stripline D) 200 mil BeO. E) 100 mil ceramic

Avantek is a recognized leader in advanced, high-performance microwave semiconductors and MMICs for space and military applications. And, we deliver in quantity ... last year Avantek shipped more than 1,000,000 MMICs and built over

800,000 complex microwave components for more than 3,000 customers. So, when you need high performance low-cost MMICs — whether your system listens, watches or talks - you know Avantek can deliver ... in volume. Contact your nearest Avantek Distributor for additional information.

Applied Specialities, Inc., Baltimore, MD (301) 792-2211 Applied Specialities of Florida, Largo, FL (813) 531-2099 Component Distributors, Inc., Atlanta, GA (404) 441-3320 Component Distributors, Inc., FL (305) 724-9910 Sickles Distribution Sales, Lexington, MA (617) 862-5100 TMA/RF, Teterboro, NJ (201) 393-9330

Penstock Midwest, Palatine, IL (312) 934-3700 Thorson Distributing Co., Dallas, TX (214) 233-5744

West

Penstock, Inc., Los Altos, CA (415) 948-6552 Sertek, Inc., Tempe, AZ (602) 968-5132 Sertek, Inc., Westlake Village, CA (818) 707-2872



EDIF readers / writers handle data transfer between CAE systems

As you learned in the first three parts of this series, your CAE system can communicate with all CAE systems, ASIC foundries, and testers that can understand the Electronic Design Interchange Format (EDIF) data standard. To create a program that translates your system's data into and out of EDIF, get started with the simple programming steps described here in part 4.

Esther Marx, Hart Switzer, and Mike Waters, *Motorola Inc*

Any CAE system can read and write data in the Electronic Design Interchange Format (EDIF)—the growing standard among CAE systems and IC vendors—if you (or the CAE-system vendor) develop the necessary software to translate that data. By using the syntax rules of EDIF, you can create rudimentary EDIF writers and readers quickly. If you need a more sophisticated EDIF writer or reader (for such tasks as silicon compilation), you can add features to the program at a later time.

The first three parts of this series (see **Refs 1**, **2**, and **3**) described the rules for creating character strings that render your data in EDIF—that is, they described the content of an EDIF file. The reader and writer programs effect the interface between systems that will manipulate that data.

You can write an EDIF reader or writer in any language. For example, you can find EDIF readers and

writers in Fortran, Pascal, and C. Furthermore, EDIF readers and writers can run on any computer. EDIF readers and writers have been written for the Commodore 64, the Apple II, Apollo computers, DEC VAXs running VMS or Unix, Symbolics computers, and IBM CMS systems.

The recursive elements of EDIF give some languages an advantage over others. For example, a language like Lisp, which provides built-in recursion features, is easier to use than a language like Fortran. EDIF files resemble Lisp programs, particularly because EDIF and Lisp require extensive use of parentheses.

Several programs that interpret EDIF files are available to the public. (The box "For more information . . ." lists software that is either in the public domain or available for license.) However, although you can use one of these programs to help you develop an EDIF reader or writer, you can't simply copy a program and use it on your system. Each CAE system requires its own EDIF reader and writer, which you or your CAE vendor must develop. You should also contact the EDIF user group (below) for the most up-to-date information.

When you develop an EDIF reader, you must begin the program with a step that verifies the version and level of a file. EDIF files must begin with "edifversion" and "ediflevel" statements. The edifversion statement gives the version of EDIF that the file uses (for example, 100). The ediflevel statement specifies the level of data in a file.

EDIF lets you choose among three levels of data complexity. An ediflevel 0 file provides standard design data. In an ediflevel 1 file, you can associate parameters

EDN March 4, 1987

You can use a public-domain program to develop an EDIF reader or writer, but you can't simply copy a program.

with your data; this level lets you scale the size of devices in a cell. Ediflevel 2 files accept program statements instead of fixed data or parameters. Because ediflevel 2 provides so much flexibility in device descriptions, you can use this level to transfer designs to and from silicon compilers.

An EDIF reader can always read levels lower than the one you have built into it. However, an EDIF reader can't read a higher level than its built-in level. For example, an ediflevel 1 reader can read ediflevel 0 and ediflevel 1 files, but it can't read ediflevel 2 files.

You can arrange to have an EDIF reader read part of the files that are at a higher level or version than you have built into the reader. To handle more advanced edifversions or ediflevels, the reader must first identify instructions that it can't understand. Then the reader issues a warning statement and saves the unread data. Although the reader can't interpret the complete file, it can usually read most of the file. In many cases, you can translate the unread data manually and create a completely readable file.

EDIF readers and writers add "user" extensions to terms that aren't in the vocabulary of the standard EDIF specification. Words with user extensions form EDIF statements that use standard EDIF syntax but have no meaning within EDIF. The recipient of an EDIF file can understand user extensions only if you make prior data-transfer arrangements. However, even when an EDIF reader can't understand a user extension in a file, it can still preserve the file—that is, it won't garble the non-EDIF content.

Obviously you'll want to be able to transfer EDIF data between incompatible computer systems. Therefore, you can't have as much flexibility in transmitting your files as you could have if you were transferring data between compatible systems. For example, many systems prefix or append characters to their files. EDIF has no control over such extra characters, so you must instruct an EDIF reader to ignore them. The reader must therefore stop translating data after it receives the close parenthesis that matches that in the opening character string, "(EDIF...".

Because an EDIF reader must ignore all characters that follow this final parenthesis, you can't transfer two EDIF files as a single file. What's more, an erroneous extra parenthesis will end a file prematurely. Before you transmit an EDIF file, you must verify the syntax of your file. To help prevent syntactical errors, you must include a syntax checker in your reader and writer.

The EDIF file format, which is a character stream, can also create problems for the actual data transmission. Unlike card images or 80-byte records, character streams impose no overhead or restrictions on the content of a file, but unfortunately a character stream is incompatible with some computers. Stream-oriented operating systems, such as Unix, end lines with return characters, line-feed characters, or both. Computers that store data in 80-byte records, for example, will break each stream after every 80 bytes. Most programs assume that this break is the end of a line. Since EDIF uses end-of-line characters, it can't distinguish between the two conditions.

By defining blocks so that they are all the same size, you can arrange to have your EDIF reader recognize the end of a string simply by containing it within that block and adding extra spaces to fill the block. EDIF specifies that all strings be shorter than 256 bytes, so a block greater than or equal to 256 bytes can contain any EDIF string. This technique, however, is extremely wasteful of computer storage; most strings consume much less than 255 bytes, but you must use a whole block for each string.

Instead of setting all blocks to the same length, you can simply instruct your EDIF reader to ignore all record boundaries (such as 80-character records). When translating a CAE system's file into EDIF under such conditions, you specify that your EDIF writer convert all end-of-line characters to blanks. When an EDIF

For more information . . .

For more information on EDIF, for public-copies of EDIF Version 1 1 0, or for copies of public-domain software including parsers written by the University of California at Berkeley and the University of Manchester (UK), contact the EDIF User Group, 2222 S Dobson Rd, Bldg 5, Mesa, AZ 85202.

To obtain an EDIF interpreter licensed by the University of Waterloo, contact Professor M I Elmasry, VLSI Group, Department of Electrical Engineering, University of Waterloo, Waterloo, Ontario, Canada N2L 3G1.

To obtain a public-domain EDIF interpreter developed at the University of Manchester, contact Hilary J Kahn, Department of Computer Science, The University, Manchester, M13 9PL, United Kingdom.

reader receives a file, the reader restores the line feeds by converting all blanks to end-of-line characters. It makes no difference to EDIF syntax whether your character strings use line feeds or blanks. Right now, all EDIF readers use the technique of ignoring record boundaries. You can insert an end-of-line character by writing it in ASCII code if required, but as implied above, you don't need an end-of-line character in an EDIF file.

Some computers control files with periods and commas. In serial transmissions, moreover, many systems add extra characters that don't produce printed output. Most computers have a transparent mode, which sends data unchanged, but even transparent modes usually require extra characters for special file-handling procedures. Some high-security systems don't let you transmit binary files. Furthermore, different machines often use different binary codes for the same characters. In short, despite the existence of the ASCII standard, many character codes vary from machine to machine.

What's more, many systems can't read the full ASCII character set. In fact, the only universal characters are the 26 letters of the upper-case alphabet and the 10 digits. Because EDIF must run on all systems in order to be of maximum benefit, the format can use only a subset of the ASCII character set. All modern computer systems understand the subset of ASCII that EDIF does use.

Some older systems, however, can't even handle the EDIF subset of ASCII. You then have to translate one EDIF character into several system characters (such as an underscore to "+U"). As long as you translate each EDIF character into a unique character string, you can use older computer systems. You should assign a printable representation to every EDIF character, so that you can debug your files easily.

Your program must remove all the non-EDIF characters that a computer system adds to a file. While your software is removing the non-EDIF characters, it can also delete extra blanks, tabs, and line feeds.

You should certainly make your EDIF reader as generic as possible to ensure a clean transfer of data between dissimilar systems, but remember that EDIF itself doesn't provide any special capabilities for data transmission. To transfer data via a LAN or modem, you must establish or adopt existing network or file-transfer standards.

Although EDIF doesn't specifically handle datatransmission problems, you can transfer data only if you resolve such problems. For example, EDIF doesn't

GENERAL FUNCTION	SPECIFIC TASKS
LIST CONSTRUCTION	CREATE AN ATOM CREATE A LIST COPY PART OR ALL OF A LIST CONCATENATE TWO LISTS
ALTERATION OF EXISTING LIST	APPEND AN ELEMENT TO A LIST DELETE A LIST
RETRIEVAL FUNCTIONS	RETRIEVE A STRING FROM AN ATOM GET AN ELEMENT FROM A LIST GET A SERIES OF ELEMENTS FROM A LIST
QUERY FUNCTIONS	ASK IF AN ELEMENT IS AN ATOM ASK IF AN ELEMENT IS A LIST TEST ATOMS FOR EQUALITY ASK IF AN ELEMENT IS A MEMBER OF A LIST CHECK FOR EMPTY LISTS
AUXILIARY FUNCTIONS	COUNT THE NUMBER OF ELEMENTS IN A LIST COMPARE TWO LISTS DISPLAY THE DIFFERENCES BETWEEN TWO LISTS DELETE AN ATOM READ A LIST WRITE A LIST

provide data-error checking or parity checking. If you need these functions, you must add them yourself to your system's protocol-handling facility.

Once you have solved all the problems of structuring an EDIF reader or writer, you can develop the actual code. As you have seen in the earlier articles in this series, EDIF files consist of symbolic expressions enclosed by parentheses. In EDIF, these expressions are called lists. A list handler can simplify an EDIF-file reader or writer.

A list handler insulates users from the data structure and operations of EDIF. For example, a list handler places parentheses around lists, and users shouldn't have to count parentheses. A list handler also takes care of such chores as input, output, data-structure definition, and character-string manipulation.

Table 1 lists the functions that you must include in a list handler. Some of these functions are necessarily only for readers; other functions are specific to writers. A list handler that's a part of a reader only or a writer only doesn't, of course, need to include all of these functions. For example, an EDIF writer's list handler doesn't need the retrieval and logical operations a reader requires. A file reader's list handler, on the other hand, doesn't need the list-building functions a writer uses.

To create a simple list handler for a file writer, for example, you need the functions "create an atom," "create a list," "append an element to a list," and "write a list." Using these functions, your list handler can write such EDIF statements as

(DESIGN MOTO2500

(QUALIFY MOTO2500_LIBRARY MOTO2500_CELL)).

This list contains two atoms and another list, which

You can arrange to have an EDIF reader read files that are at a higher level or version than you have built into the reader.

contains three atoms. To create the larger list, your writer must first specify the atoms. These atoms are

DESIGN ← CREATE THE ATOM 'DESIGN'
DESIGNAME ← CREATE THE ATOM 'MOTO2500'
QUALIFY ← CREATE THE ATOM 'QUALIFY'
LIBRARYNAME ← CREATE THE ATOM 'MOTO2500_LIBRARY'
CELLNAME ← CREATE THE ATOM 'MOTO2500_CELL'.

Next, the list handler must create the "qualify_list":

QUALIFY_LIST ← CREATE A LIST.

The list handler then appends the keywords "qualify", "libraryname", and "cellname" to the qualify_list. It then creates the "design_list" and appends the remaining atoms to the design_list:

APPEND QUALIFY TO QUALIFY_LIST APPEND LIBRARYNAME TO QUALIFY_LIST APPEND CELLNAME TO QUALIFY_LIST.

DESIGN_LIST ← CREATE A LIST APPEND DESIGN TO DESIGN_LIST APPEND DESIGNAME TO DESIGN_LIST.

The list handler completes the statement by appending the qualify_list to the design_list and then writing the file:

APPEND QUALIFY_LIST TO DESIGN_LIST WRITE DESIGN_LIST TO OUTPUT FILE.

LISTING 1—INSERTING AN ELEMENT IN A LIST

SUBROUTINE INSERT_BEFORE (LIST, ELEMENT, NEW_ELEMENT)

If ELEMENT is a member of LIST then

Create NEW LIST

Create NEW__LIST

while not ELEMENTS_EQUAL (ELEMENT, Nth element of LIST) append Nth element of LIST to NEW_LIST

N ← N+1
append NEW ELEMENT to NEW_LIST
append Nth element of LIST to NEW_LIST
concatenate NEW_LIST and all elements of LIST after Nth element
LIST ← NEW_LIST

else

print error message

FUNCTION ELEMENTS_EQUAL (ELEMENT1, ELEMENT2)

ELEMENTS_EQUAL ← false

If ELEMENT1 is an atom and ELEMENT2 is an atom

ELEMENTS_EQUAL ← condition of ELEMENT1 equal to ELEMENT2

If ELEMENT1 is a list and ELEMENT2 is a list

ELEMENTS_EQUAL ← condition of difference between ELEMENT1

and ELEMENT2

By creating the atoms before creating the list, the list handler saves storage space. Instead of forming a keyword each time you use it, you can store the keyword and call it as often as you need it.

EDIF readers check syntax and read files

You can develop a list handler for an EDIF reader in the same way that you create a writer. To read the list that you just created, your reader must perform six of the tasks given in **Table 1**: "create an atom," "get an element from a list," "ask if an element is a list," "test atoms for equality," "count the number of elements in a list," and "read a list."

Your reader must first identify the atoms that it's reading. It then verifies that the sequence of atoms in the list obeys EDIF syntactical rules:

DESIGN ← CREATE THE ATOM 'DESIGN'
QUALIFY ← CREATE THE ATOM 'QUALIFY'.

On the basis of this verification procedure, the reader confirms that it's reading a list:

IS_LIST ← TRUE IF A LIST; IF FALSE, ABORT.

The reader then checks to see that the design statement contains two atoms and a 3-atom list, as EDIF requires.

$$\begin{split} & \text{HEAD_OF_LIST} = \text{DESIGN?} \leftarrow \text{IF FALSE, ABORT} \\ & \text{LENGTH_OF_LIST} = 3? \leftarrow \text{IF FALSE, ABORT} \\ & \text{IS_LIST (THIRD ELEMENT)?} \leftarrow \text{IF FALSE, ABORT} \\ & \text{LENGTH_OF_LIST (THIRD ELEMENT)} = 3? \leftarrow \text{IF FALSE, ABORT.} \end{split}$$


Finally, the EDIF reader reads the statement. The reader looks for "design_name" in the second atom of the design statement, and then it looks for "libraryname" and "cellname" in the third element of the design statement.

You can, of course, add other capabilities to your reader. Listing 1, for example, shows the code that enables a reader to insert an element in a list before the *n*th element.

After you complete your EDIF program, you should test it by actually using it. If you can transfer a file to another user and he can interpret the information correctly, then your program works reliably. Wherever possible, you should write both an EDIF reader and an EDIF writer, so you can test your programs against each other for consistency.

To verify your program adequately, you need a

Seven money saving ideas.



Take the long black strip of switches for example. It was the result of working together with a gaming machine manufacturer who needed to lower the cost of their product.

In addition to supplying less expensive basic switches that didn't compromise quality, we modified the switch terminals. Then we mounted the switches on a PC board, attached them to a connector, and assembled it all in a plastic housing. The result? A MICRO SWITCH idea designed to cut the

The start of many money saving ideas.

Together, we can find the answers.

customer's assembly costs in half.

Each one of the basic switch ideas you

see here has a money saving story of its own.

To find out what they are, or for other ways

we can work with you to reduce your total

costs, ask for our new brochure. Call us at

815-235-6600. Or write MICRO SWITCH,

Freeport, IL 61032.

MICRO SWITCH

a Honeywell Division **CIRCLE NO 93**

Stop By and Visit Us at Booth #1951 During Electro, NY

CAN YOU

name the company who makes a 64K CMOS PROM at 45 nsec using one-third the power of bipolar?

(See page 210.)

EDN NEWS



HOT NEWS OF PRODUCTS, TECHNOLOGY, AND CAREERS plotting package that accepts EDIF. The plotting package can be a fairly unsophisticated program, but the program should be able to interpret cell-protection frames, ports, the orientation of cells, and interconnections.

References


1. Marx, Esther, Hart Switzer, and Mike Waters, "EDIF format brings uniformity to CAE/CAD data," *EDN*, January 22, 1987, pg 153.

2. Marx, Esther, Hart Switzer, and Mike Waters, "Use an interchange format to port component libraries," *EDN*, February 5, 1987, pg 175.

3. Marx, Esther, Hart Switzer, and Mike Waters, "Use EDIF to create test vectors and verify your logic," *EDN*, February 19, 1987, pg 185.

Authors' biographies

Esther Marx is a senior software engineer at Motorola Semiconductor Product Sector's ASIC Division (Mesa, AZ). She received an MS from George Washington University (Washington, DC) and a BA from Oberlin College (Oberlin, OH). Before joining Motorola, Esther served for five years in the Air Force. She enjoys writing science fiction and collecting Star Trek memorabilia.



Mike Waters is a principal engineer and EDIF project manager at Motoro-la Semiconductor Products. He received a BS in computer science from Regent's College (New York, NY). Mike likes to exchange ideas with other EDN readers via his ham radio (license AA4MW) or his amateur packet radio.







Article Interest Quotient (Circle One) High 482 Medium 483 Low 484

ALLOTHERS PALE BEFORE US.

No other color graphics terminal can compare to the GR-1105. In fact, you'd have to spend an extra five or ten thousand dollars to get something even close.

The GR-1105's screen is brighter than anything else in its price class. It's also sharper. With three times the resolution of similarly priced terminals. And sixty times more addressable points (32K x 32K).

Plus the GR-1105 is perfect for people who hate to wait. It's twice as fast as its price competitors. And updates over one and a half times more data.


So look into the GR-1105. You'll see it's the one terminal that makes all others look pale.

Call Martin Nelson at (408) 943-9100 today.




CIRCLE NO 117

You're looking at an image on the GR-1105's 14", 1024 x 780, 60Hz non-interlaced monitor



A REAL BREAKTHROUGH IN SWITCHING REGULATORS.




Linear Technology delivers a new all-in-one punch with its complete family of easy-to-use, monolithic switching regulators. This group of devices includes the LT1070 (5A), LT1071 (2.5A), and LT1072 (1.25A).

There's no more worry about possible board burn-up or using a large area of space for external parts. The LT1070 series operates safely from 3 to 60 volts—while drawing a very low supply current of 6 milliamps. The LTC switching regulator family simplifies design and reduces the board space needed for most applications because they contain all switching, protection and control circuitry (including the power transistor) on a single chip.

The LT1070 family packs a real wallop by delivering load power up to 100 watts, with no external power devices, yet are extremely efficient even at low power levels. By utilizing current-mode switching techniques, these devices provide excellent AC and DC load and line regulation. They operate in nearly all switching topologies. And in the

Boost Converter (5V to 12V)



LINEAR TECHNOLOGY

TOUGH PRODUCTS FOR TOUGH APPLICATIONS.

CIRCLE NO 88

shutdown mode, the ICs draw only 50 μ A supply current.

This highly versatile family operates over an extremely broad range of input voltages, load currents and switching configurations. Switching configurations include: buck, boost, flyback, forward, inverting, and "Cuk."

These regulators offer many unique features not found on vastly more difficult-to-use low-power control chips on the market. All devices use an adaptive, antisaturation circuit for high switching efficiency and fast switching times. The LT1070 (and the LT1071/72 versions) are available in either standard 5-pin TO-3 or TO-220 power packages.

Take the sweat out of switching regulator design with the new LTC1070/71/72 family. Pricing for LT1070CT is \$7.45 each in quantities of 100 (LT1071CT is \$5.70 ea./100). The LT1072 will be available in the first quarter of 1987. For additional technical details, contact: LINEAR TECHNOLOGY CORPORATION, 1630 McCarthy Blvd. Milpitas, CA 95035. (408) 942-0810.

DESIGN IDEAS

EDITED BY TARLTON FLEMING

Linear load dissipates constant power

Horace T Jones
Penril Datacomm, Gaithersburg, MD

The Fig 1 circuit presents a constant-power load to the input voltage $V_{\rm IN}$. For the component values shown, the circuit provides a 4W load at a nominal $V_{\rm IN}$ of 13V and maintains this power level within $\pm 0.2\%$ for input voltages of 9 to 17V. Potentiometer R_{10} lets you adjust the constant-power level.

Select R_4 and R_5 to produce a voltage V_{CONTROL} of approximately 6V at the inverting input of IC_{1A} . Op amps IC_{1A} and IC_2 form a pulse-width modulator whose output duty cycle (X) is a linear function of V_{IN} (X equals $V_{\text{CONTROL}}/V_{\text{CC}}$). The modulator's nominal 33-kHz operating frequency (f) decreases as V_{IN} varies above or below its nominal value:

$$f = \frac{X \cdot R_3(1-X)}{R_2 R_1 C_1}$$
.

The modulator's output signal (pin 6 of IC₂) drives the analog switch IC₃, which in turn drives the linear current source formed by op amp IC_{1B} and MOSFET Q₁. Consequently, $I_{\rm IN}$ is inversely proportional to $V_{\rm IN}$, so the load power $P_{\rm IN}$ is constant:

$$P_{\rm IN} {=} V_{\rm IN} I_{\rm IN} {=} \frac{V_{\rm CC} V_{\rm REF}}{R_{\rm 11}} \! \bigg[1 {+} \frac{R_4}{R_5} \bigg]. \label{eq:pin}$$

Filter components R_8 and C_3 suppress voltage ripple introduced by the switching action of IC_3 . This switching action also limits the control loop's 3-dB bandwidth to about 480 Hz.

To Vote For This Design, Circle No 746




Fig 1—Developed for testing the rectifier/filter section of switching power supplies, this circuit provides a constant 4W load ($\pm 0.2\%$) for V_{IN} in the 9 to 17V range.

Bounds checker has DSP applications

Brian Case Advanced Micro Devices, Sunnyvale, CA

Fig 1's circuit dynamically limits the range of 12-bit data at the front end of a digital signal-processing system. The bounds checker (IC_2) contains a separate 16-bit register/comparator combination for the upper and lower thresholds. You store the desired values in IC_2 via the data bus; the chip then compares the A/D converter's output D with each threshold.

The outputs CO_L (low when $D \le lower$ threshold) and CO_U (low when $D \ge upper$ threshold) control a 12-bit, 4:1 digital multiplexer. Accordingly, the multiplexer passes to its output one of the following values: the lower threshold value, the upper value, or, when D is within

bounds, the A/D converter's output. The bounds checker can handle signed or unsigned numbers (pin 28 high or low, respectively). Similarly, different connections to pins 14 and 15 configure the device for various types of threshold comparisons ("greater than" vs "greater than or equal to," for example).

By connecting a counter to IC₂'s out-of-bounds output (pin 6), you can tally the number of A/D conversions outside the desired range. By connecting the converter output to several bounds-checker/counter combinations in parallel, you can create a histogram of the converter's output data.

To Vote For This Design, Circle No 749





Fig 1—This circuit screens data from the A/D converter. Data within a predetermined range passes to the output, and data outside the range is blocked. The bounds checker substitutes an upper or lower threshold value for the blocked data.

PLD controls a RAM-based LIFO memory

Chris Jay Monolithic Memories Inc, San Jose, CA

A LIFO memory lets you write in a sequence of data and then read it out in reverse order. You can construct such a memory from arrays of registers, but Fig 1 shows a more economical and flexible approach. IC_1 includes all the addressing and control logic necessary to supervise the static-RAM chip IC_2 . (Ed Note: To prepare the device, you can obtain the necessary Palasm program from the author.)

IC₁ contains a binary up/down counter for generating



Amplifier Arsenal

50KHz to 2000MHz, 100mWoutput Gain Controlled From \$69.95

Our ZFL-2000 miniature wideband amplifier hit a bulls-eye when we introduced it last year. Now we've added more models to offer you a competitive edge in the continuing battle for systems improvement.

The ZFL-2000, flat from 10 to 2000MHz, delivers +17 dBm output and is still priced at only \$219.

Need more output? Our ZFĹ-1000H, flat from 10 to 1000MHz, delivers +20 dBm output.

Variable gain important? Our ZFL-1000G, flat from 10 to 1000MHz, delivers +3 dBm output with 30 dB gain control while maintaining constant input/output impedance.

Searching for a high-quality, low-cost amplifier? Our ZFL-500 flat from 50KHz to 500MHz, delivers 10 dBm output for the unbelievably low price of only \$69.

One week delivery . . . one year guarantee.

Gain the competitive edge...specify Mini-Circuits RF/IF signal-processing components.

SPECIFICATIONS

OI LOII IOMITORO				
Model No.	ZFL-500 0.05-500 20 ±1.0	ZFL-1000G	ZFL-2000	ZFL-1000H
Freq (MHz)		10-1000	10-2000	10-1000
Gain (dB), Min.		17	20	28
Gain Flatness (dB) Max.		±1.5	±1.5	±1.0
Max. Power (dBm) (1dB compression) NF (dB) typ. 3rd order	+10	+3	+17*	+20
	5.3	12.0	7.0	5.0
Intercept pt (dBm) Current at 15V dc Price \$ qty.	+18	+13	+25	+33
	80mA	90mA	100mA	150mA
	69.95	199	219	219
	1-24	1-9	1-9	1-9

For complete specs on these and our 1- and 2-W models refer to 1985-86 Gold Book or Microwaves directory.

*+15 dBm below 1000MHz

finding new ways ... setting higher standards



P.O. Box 166, Brooklyn, New York 11235 (718) 934-4500 Domestic and International Telexes: 6852844 or 620156

C101 REV. B

DESIGN IDEAS

addresses and a state-machine sequencer for controlling write or read operations during active push (write) or pop (read) cycles. The 2k-byte×8-bit RAM gives you a 2-chip, 128-byte×8-bit LIFO memory, and additional RAM chips in parallel can expand the LIFO memory to 16, 24, or 32 bits wide. Unused address lines should be grounded, but if you want to build a deeper LIFO structure, you can connect those unused address lines to a second device, programmed as a cascadable counter.

To push data onto the LIFO, drive IC1's Push input

high while presenting valid data to the RAM. IC_1 increments its address counter and sets \overline{WR} low, then writes the data by driving \overline{CS} low (Fig 2a). You initiate a pop operation by driving the PAL's Pop input high. IC_1 then decrements its address counter, drives \overline{CS} low, and obtains the data by driving \overline{WR} high (Fig 2b). EDN

To Vote For This Design, Circle No 750




Fig 1—This 2-chip, 128-byte×8-bit LIFO memory consists of just a CMOS RAM chip and a controller chip.





Fig 2—These diagrams illustrate the control-timing relationships for push and pop operations in the Fig 1 circuit.



The most powerful, cost-effective single-chip MCU anywhere.

The Super8™ family of 8-bit MCUs gives you higher performance than a lot of 16-bit processors... and opens the door to a whole new realm of

Technology

Serial I/O

Program Memory

20MHz

External Memory up to 128K of RAM

0, 8, 16K ROM

1 down count only

1 full-duplex UART

single-chip designs.

Super 20MHz speed.

No other 8-bit MCU comes close to the 20MHz Super8. You'll always have plenty of performance to accomplish your software tasks – with CPU time to spare.

Super ROM memory.

Memory's no problem either, with up to 16K of internal ROM, up to 128K of external RAM or ROM, and 325 registers-272 general-purposewith dual register pointers for fast register access and context switching.

The Super8 offers you 40 interrupt sources and 600-nanosecond response time to each of the

8 priority levels – the fastest reaction time in the single-chip MCU world.

6	8052	8 prio
bit	8-bit	fastes
0S	NMOS	
1Hz	12MHz	the si
K ROM	0, 8K ROM	world
byte general- pose, 26 mode/ trol	32 byte general- purpose, 26 mode/ control, 224 Indirect RAM	Supe

up to 64K of RAM

1 full-duplex UART,

	OI HOM AND S	OI HOW	OI TION
DMA	Single-channel with 16-bit pointer and count register	None	None
I/O Lines	40 programmable with 2 handshake channels	26 programmable 12 fixed input 2 fixed output	32 programmable
Counter/Timers	3 16-bit: 2 up/down- count with bivalue	2 16-bit up-count only with 4 high-	3 16-bit up-count only

up to 64K of RAM

NM

121

Selection of	up to 2.5 Mb/s	ap to 0.2 Mo/3	1-bit bus
Interrupts	40 sources, 16 vectors, 8 programmable priority levels, minimum response 0.6 microsecond		6 sources, 8 vectors, minimum response 6 microseconds
	microscond		

ers for fast register s and context thing.

Price (100) \$4.95 \$24.75 \$7.60

The choice is clear.

Super bottom line.

The Super8 gives you all this unmatched performance-and a whole lot more. Off the shelf. Backed by Zilog's proven quality and reliability. At a price that leaves the competition even further behind. Contact your local Zilog sales office or your authorized distributor today. It's time to see how "super" your designs really can be.

Right product. Right price. Right away.

ZILOG SALES OFFICES: CA (408) 370-8120, (714) 432-9971, (818) 707-2160, CO (303) 494-2905, FL (813) 585-2533, GA (404) 451-8425, IL (312) 885-8080, MA (617) 273-4222, MN (612) 831-7611, NJ (201) 288-3737, (609) 778-8070, OH (216) 447-1480, TX (214) 231-9090, CANADA Toronto (416) 673-0634, ENGLAND Berkshire (44) (628) 39200, W. GERM. Munich (49) (89) 612-6046, JAPAN Tokyo (81) (3) 587-0528, HONG KONG Kowloon (852) (3) 723-8979. U.S. AND CANADA DISTRIBUTORS: Hall-Mark Elec., Schweber Elec., Western Microtech., Anthem Elec., JAN Devices, Inc., Bell Indus., Lionex Corp., Graham Elec., Alliance Elec., CANADA SEMAD, Future Elec.

Zilog
an affiliate of
EXON Corporation

MAC functions as a counter or divider

Steve Lubs

Department of Defense, Washington, DC

Bypassing the multiplier section of a multiplier-accumulator (MAC) chip lets you form a flexible counter or

divider. In this example, the TDC1008J MAC saves circuit-board area by replacing four or five cascaded counters and associated circuitry.

Tie the LSB of one input port (port Y in this example) to logical one, and tie the remaining Y port




Fig 1—This multiplier-accumulator chip can serve as a counter or divider when you bypass its multiplier section.

You're not gambling with quality when you buy low-cost T70 relays

Quality at just 77 cents

from P&B.

UL recognized and CSA certified, Potter & Brumfield's T70 relay switches from 1 milliamp through 10 amps, resistive, on printed circuit boards. All with the same reliability and performance that have made P&B relays the industry standard. And the T70 costs as little as 77 cents in 25,000 piece quantities.

Broad range of ratings

Gold-plated fine silver or silver-cadmium oxide contacts are available in a single pole, double throw configuration. Contacts of either material are UL recognized to switch motor loads up through 1/4 horsepower at 120 volts AC. Silver-cadmium oxide contacts are also rated for 5 amp tungsten lamp loads at 120 volts AC, while silver is rated 3 amps tungsten.

Reliability? Of course!

The T70 relay features simplified construction that enhances reliability while holding cost down. A sealed version is designed for immersion cleaning, and a plastic dust cover model is also available.

Off-the-shelf service

With 20 different T70 models available from stock at P&B, the unit you need is probably available off-the-shelf. Your P&B distributor or sales representative will gladly help you select the model that's just right for your application. Call toll-free 1-800-255-2550 for the name of an authorized Potter & Brumfield distributor or sales representative serving your area. Or call your P&B regional office.

Write for free sample

Write us on your company letterhead, briefly describing your potential application for T70 relays, and we'll rush you a free sample and Please send note into mation about 28 to relays complete specifications. Potter & Brumfield, A Siemens Company, 200 South Richland Creek Dr., Princeton, Indiana 47671-0001.

Regional Sales:

Braintree, MA, (617) 848-6550; San Juan Capistrano, CA, (714) 493-4503; Princeton, IN, (812) 386-2130: Bristol, England, (0454) 616263.

Potter & Brumfield A Siemens Company

CIRCLE NO 100

8701

DESIGN IDEAS

bits to logical zero. Apply an 8-bit digital value M to the other input port (port X in this example). The resulting frequency f_{OUT} on any of the 19 output pins (P_N) is

$$\mathbf{f}_{\mathrm{OUT}} = \frac{\mathrm{M}\mathbf{f}_{\mathrm{C}}}{2^{\mathrm{N}+1}}.$$

This circuit accepts values of M from 1 to 255 and $f_{\rm C}$ to 15 MHz. For higher clock rates, you should select a CMOS MAC. Different combinations of M and $P_{\rm N}$ provide a wide range of clock frequencies.

Alternatively, you can use all of the output pins or a subset of them as a counter that counts in units of M. Switch S_1 sets the count direction. Note that, following closure of S_2 , the chip requires two rising edges of the clock before it loads the output register (Fig 2). **EDN**

To Vote For This Design, Circle No 748




Fig 2—The multiplier-accumulator chip requires two rising edges of f_C in order to clear before it loads the output register.

Pulse-delay circuit has dual-edge trigger

S Murugesan ISRO Satellite Centre, Bangalore, India

In Fig 1, a single monostable multivibrator delays a pulse train by a variable amount; nonetheless, this amount can be no less than the minimum allowed pulse width t_w . This approach simplifies an earlier Design Idea (EDN, June 26, 1986, pg 225) by lowering the parts count.

The exclusive-OR gate IC₁ generates a short pulse following every leading or falling edge of the input

waveform. These pulses cause one-shot IC_2 to produce a negative-going pulse with a duration equal to the desired time delay t_D , which you set by adjusting the potentiometer (R). Flip-flop IC_3 then creates a delayed replica of the input pulse by latching the $\overline{\mathbb{Q}}_1$ output of IC_2 between positive-going transitions. You can independently control the output-pulse duration by cascading a second one-shot with the first.

To Vote For This Design, Circle No 747




Fig 1—This circuit delays the input pulse train by a time interval to, which is less than or equal to the minimum pulse width tw.

Ah, the big idea. Everyone has one. But not everyone can afford a plotter to plot one on. Which got us thinking. What if there was an HP quality plotter so reasonably priced you could afford to hook one up to every PC CAD workstation in the office?

Presenting the HP DraftPro Plotter. For only \$5400 any architect, engineer or designer can create perfect plots time after time. Consider what the DraftPro can do:

It can draw straight lines, smooth arcs and perfectly-formed characters. All on C and D-size drafting film, paper or vellum, using eight different pen colors.

Furthermore, it works with

just about any PC, such as the HP Vectra PC and IBM PC's. As well as popular PC CAD programs like VersaCAD and AutoCAD.

If the idea of having HP reliability with a low price tag makes sense to you, call us now. For a brochure and sample plot, call 1800 367-4772, Ext. 215J.

The HP DraftPro Plotter: high-quality drafting for only \$5400.*


The drawing shown below was produced on the HP DraftPro with VersaCAD software.



VersaCAD is a registered trademark of T & W Systems. AutoCAD is a registered trademark of AutoDesk, Inc. *Suggested U.S. list price.

CIRCLE NO 79

How to pull off a fantastic HP plot for only \$5400.



Me and My Smart Scope!



Looking for a 50 MHz scope that's right for today and ready for tomorrow?

Then take a good look at the PM 3055.

Featuring complete microprocessor control, it has an

Autoset facility, advanced 16 kV CRT, fast GPIB hook-up and versatile triggering up to 100 MHz.

So it's just as smart in performance as it is in looks.


In operation, too, the PM 3055 is very





smart. An LCD panel clearly indicates status and settings, up/down controls simplify fast input of amplitude and time settings, and softkey function selection makes operation fast, simple and logical.

So join the smart set with the PM 3055 smart scope from Philips.



Test the difference

Product credibility in technology, technique, quality and service is assured because the PM 3055 smart scope is backed by the resources of one of the world's largest electronics companies.



Test the difference and you'll also agree that Philips wins on price and performance!

Write to: Philips I & E, T & M department, Building HKF70, 5600 MD Eindhoven, The Netherlands or call your local supplier: Austria (222) 629141; Belgium (2) 5256692/94; Denmark (1) 572222; Finland (0) 5257225; France (1) 48301111; Germany (561) 5010; Great Britain (0223) 358866; Ireland (1) 693355; Italy (39) 3635 240/8/9; Netherlands (40) 782808; Norway (2) 680200; Portugal (1) 683121; Spain (1) 4042200; Sweden (8) 7821800; Switzerland (1) 4882211



Test & Measurement

PHILIPS



FOR THOSE WHO DEMAND PEAK PERFORMANCE.

As the first name in enclosures, Schroff delivers performance second to none.




NEW PRODUCTS

INTEGRATED CIRCUITS

MEMORY MODULE

- Contains multiple static-RAM chips
- 100-nsec access time is standard

Suitable for space-sensitive military applications, the 1M-byte VMS-10A24 memory module comes in commercial and military (MIL-STD-883, Class B and S) versions having access times of 100, 150, or 200 nsec. The device includes four 32k×8-bit static RAMs in DIPs, decoder circuitry, and decoupling capacitors, all of which are mounted on the top and bottom surfaces of a 40-pin ceramic substrate with a standard JEDEC pinout. Normally configured as 64k×16 bits, the module also comes as a 64k×8-bit or a



128k×8-bit device. An EEPROM version is also planned. VMS10A24S-150C, \$350; -150B, \$510.

Vitarel Microelectronics Inc, 3572 Corporate Ct, San Diego, CA 92123. Phone (619) 292-8353.

Circle No 351

32-BIT μP

- Has mathematically proven design for enhanced reliability
- Automatically halts when internal errors are detected

The Viper µP is targeted for use in safety-critical applications. Its design is mathematically verifiable at gate level to ensure consistent performance. The processor operates on 32-bit data, and it has 20-bit addressing and an additional control output to divide memory operations from I/O operations. It includes three 32-bit general-purpose registers and a single-bit condition code register. Registers for indexed addressing are automatically checked for overflow beyond the µP's 20-bit address capability. The instruction set is deliberately limited to 16 ALU instructions and 16 comparison operations to avoid ambiguity in the interpretation of each function. An illegal output from the ALU or an invalid address automatically halts the processor. The µP doesn't have any interrupt capability or any support for a hardware stack because

both of these are unacceptable sources of program failure in safety-critical systems. Fabricated in 5V CMOS, it costs £250.

Marconi Electronic Devices Ltd, IC Div, Doddington Rd, Lincoln LN6 3LF, UK. Phone (0522) 688121. TLX 56380.

Circle No 352


Marconi Electronic Devices Inc, 80 Smith St, Farmingdale, NY 11735. Phone (516) 420-8378.

Circle No 405

COMPANDER IC

- Processes documents to nearest bit or pixel
- Achieves 30:1 compression ratio

This 1-chip compression/expansion processor allows you to process documents for transmission to the nearest bit or pixel. Model Am7971 is an intelligent processor that achieves typical compression ratios of 30:1. It contains two programmable registers for bit-boundary control. The device compresses and expands 2-tone, bit-mapped documents in ac-



cordance with CCITT recommendations T.4 and T.6 for Groups III and IV facsimile equipment. Its coding options are 1-dimensional modified-Huffman run-length coding, and 2dimensional modified-Read relative coding. The chip can operate in lineby-line, fractional, and full-page modes. Equipped with an on-chip error-detection mechanism, the device detects all possible data corruptions by checking for illegal codes, negative run lengths, and incorrect line lengths. The IC operates at 5 MHz. Prices for devices in 68-lead PLCCs and LCCs are \$119.05 and \$142.86 (100), respectively.

Advanced Micro Devices Inc, Box 3453, Sunnyvale, CA 94088. Phone (408) 982-7445.

Circle No 353

A FULL DECK OF STATICS MAKES CENTS

It's no secret Hyundai makes a quality product that passes along substantial user savings. And now — a full line of SRAMs offering you a variety of speeds from 25ns to 150ns - plus the opportunity to reduce system costs.

Volume produced in state-of-the-art CMOS technology with standard DIP packaging, Hyundai's static RAMs will face up to meet all your system needs from fast access times to low power operation.

At Hyundai, we believe in helping you design a winning hand with high performance alternatives that help take the bite out of your budget.


Call one of our sales offices listed below for pricing, literature and samples.



Product	Part No.	Orgn.	Access Time (ns)	Packaging
16K SRAM	HY6116	2Kx8	100,120,150	24-pin DIP (600)
16K SRAM	HY61C16A	2Kx8	25,35,45,55,70	24-pin DIP (300/600)
16K SRAM	HY61C67	16Kx1	25,35,45,55,70	20-pin DIP (300)
16K SRAM	HY61C68	4Kx4	25,35,45,55,70	20-pin DIP (300)
16K SRAM	HY61C69	4Kx4	25,35,45,55,70	22-pin DIP (300)
64K SRAM	HY62C64	8Kx8	100,120,150	28-pin DIP (600)
64K SRAM	HY62C64A	8Kx8	35,45,55,70	28-pin DIP (600)
64K SRAM	HY62C87	64Kx1	35,45,55	22-pin DIP (300)
64K SRAM	HY62C88	16Kx4	35,45,55	22-pin DIP (300)
256K SRAM	HY62C256	32Kx8	55,70,90	28-pin DIP (600)



• REGIONAL SALES OFFICES: CALIFORNIA (408) 986-9800 ILLINOIS (312) 860-6406 MASSACHUSETTS (617) 239-8015 • REPRESENTATIVES: ALABAMA/GEORGIA/CAROLINAS/TENNESSEE, CSR Electronics (404) 396-3720 ARIZONA, Sanford Sales (602) 957-3570 CALIFORNIA, Straube Associates (415) 969-6060; Wiley Co. (213) 666-1611 COLORADO/UTAH, Elcom, Inc. (303) 337-2300 CONNECTICUT/MASSACHUSETTS, Gerald Rosen Co. (617) 481-9277 FLORIDA, EIR, Inc. (305) 660-9600 N. ILLINOIS/S. WISCONSIN, Heartland Technical Marketing (312) 577-9222 INDIANA/KENTUCKY/MICHIGAN/OHIO/W. PENNSYLVANIA, Giesting & Associates (513) 385-1105 IOWA, J.R. Sales Engineering (319) 393-2232 KANSAS/S. ILLINOIS/ MISSOURI/NEBRASKA, Advanced Technical Sales (913) 782-8702 MARYLAND, Walker-Houck Associates (301) 356-9500 MINNESOTA/DAKOTAS/N. WISCONSIN, P.S.I. (612) 944-8545 NEW YORK, Phase Four Technical Reps. (516) 482-1790; Labtronics, Inc. (315) 455-7314 E. PENNSYLVANIA, Denco Electronic Components (215) 630-8990 WASHINGTON/OREGON, Quest Marketing, Inc. (206) 747-9424 CANADA, Gidden-Morton Associates, Inc. (416) 671-8111.




7 REASONS WHY...

BICC-VERO MAKES THE BEST VME BACKPLANES

You've already invested quality time and budget in building the very best VME computer system for your application.

Now, interconnect your components with the very best backplane. Select from the full range of sizes and configurations offered by BICC-VERO.

BICC-VERO supports their VME Backplanes with a full line of card frames, enclosures, and connectors. Ask for the details.



Call us or your BICC-VERO Distributor for complete information.



BICC-VERO ELECTRONICS, INC.

1000 Sherman Avenue Hamden, CT 06514 (203) 288-8001 TWX: 510-227-8890

INTEGRATED CIRCUITS

DATA ACQUISITION

- Data-acquisition system comes in a 40-pin DIP
- Includes software-programmable instrumentation amp

The HS9414 is a self-contained, 12-bit data-acquisition system in a 2.1×0.8 -in., 40-pin DIP module. It includes a 4-channel, differential-input multiplexer and an instrumentation amplifier (IA) that has digitally programmable gains of 1, 10, 100, and 500. The module also includes a 10V reference, an S/H amplifier, and a 574-type A/D converter. The system's throughput ranges from 8.2k samples/sec (with 0.02% accuracy) at a gain of 500 to 24k samples/ sec (with 0.01% accuracy) at a gain of 1. You can improve the throughput by pipelining the selection of mux channels. The module's powersupply requirements are ±15 and +5V. It dissipates 980 mW typ, 1300 mW max. HS 9414C, \$119; HS 9414B, \$220. Delivery, six to eight weeks ARO.

Hybrid Systems Corp, 22 Linnell Circle, Suburban Industrial Park, Billerica, MA 01821. Phone (617) 667-8700.

Circle No 354



D/A CONVERTER

- Offers composite-video control functions
- Suitable for 2k×2k-pixel displays

Offering 300-MHz word rates and a low (45-pV·sec) glitch impulse, the Model AD9703 8-bit video D/A converter is suitable for displays having resolution as high as $2k \times 2k$ pixels. The device incorporates

blanking, composite-sync, 10% overbright, and reference-white control pins. The settling time to within ±0.4% of full gray-scale output is 6 nsec. Other specs include $\pm 0.2\%$ max integral and differential nonlinearity, ±2-mV max initial offset voltage, and guaranteed monotonicity. The converter's logic inputs are compatible with both 10KH and 100KH ECL systems; the output satisfies the RS-170 video standard and can drive a 75Ω line directly. The AD9703 comes in a 24-pin DIP, operates from a −5.2V ECL supply, and dissipates 1.1W. Nonhermetic BW-grade units operate over -25 to +85°C; hermetic BD- and TD-grade units operate over -55 to +125°C. The three grades cost \$42.60, \$47.20, and \$52.90 (100), respectively.

Analog Devices Inc, Literature Center, 70 Shawmut Rd, Canton, MA 02021. Phone (617) 329-4700. TWX 710-394-6577.

Circle No 355

DISCRIMINATOR

- Couples transducers to digital processors
- Identifies and measures motion

Model THCT2000, an LSI IC, provides an interface between mechanical devices and a data bus. It identifies and measures rotation or linear motion; the circuit determines the direction and displacement of mechanical devices, based on input signals from two transducers connected in quadrature. You can use the IC to measure the duration of a sensor-generated pulse by using a known clock rate, or to measure the frequency of a mechanical event over a known time interval. The discriminator IC also has a 16-bit read/load counter; you can use the counter separately or in cascade to provide accuracy greater than 16 bits. Offering TTL- and CMOS-compatible inputs, the device provides parallel 8-bit 3-state outputs. Clock frequency is 4 MHz max. Packaging

REAL TIME HARDWARE PC-PAL" PROGRAMMER The simple, fast and inexpensive way to program PALs in your PC or AT. Works with virtually all 20 and 24 pin devices from MMI, TI and NSC. Includes all the software needed to read, write and verify PALs. Works with JEDEC files and includes a compiler for MMI standard PAL types..... NUMBER SMASHER/ECM" Triples the speed of CAE and all applications on IBM PC, XT and compatibles! From \$599 12 MHz Accelerator Plus A

PC Magazine Editor's Choice

Megabyte

for DOS!

FastCACHE-286"

Real Time Software

87 SFL™ Very accurate and fast Scientific Function Libraries. 145 functions: 34 Elementary functions, 18 Probability and Statistical functions, 15 Random Number Generators and many more. Callable from FORTRAN, Pascal, BASIC and C. First module...........\$250 Each additional unit\$100

DCACHE™ Disk caching software that speeds up your I/O by storing repetitively used tracks in memory. The amount of memory used can be selected in 64 kbyte banks....\$49





You'll realize immediate cost savings in board production with the New CTS Series 207 AUTO-DIP™ Switch.

Because they are the same size as your IC's—these new Series 207 AUTO-DIP™ switches can be used in your automatic insertion equipment right along with IC's...without machine adjustment. You get economical high speed board production. You'll save significant board space as well! This new switch takes only 37% of the volume of a standard DIP switch allowing for closer board stacking and space savings.

Wave solderable! Board washable! The AUTO-DIP™ design eliminates bottom sealing. And, a lead frame housing construction with time-proven tape top seal keeps contaminants out of the switch through wave soldering and solvent or aqueous cleaning.

Reliability you can count on. During the fully automated assembly process, each Series 207 DIP Switch is 100% machine tested for continuity and contact resistance. In addition, statistical process control used in every step during manufacturing assures unvarying part quality and final reliability. Available in 2-position to 12-position switches.

WRITE TODAY for full technical data

on these new Series 207 AUTO-DIP™ switches. Contact: CTS Corporation,* Paso Robles Division, Electromechanical Group, 500 Linne Road, Paso Robles. CA 93446. Phone: (805) 239-0427

*In Calif. dba CTS Electronics Corporation

CIRCLE NO 61

CTS means Reliability

CTS CORPORATION • ELKHART, INDIANA

CIRCLE NO 62



Series CCXO-140 Leadless chip carrier crystal oscillator for surface mounting Phone: (815) 786-8411 **CIRCLE NO 63**




PC Boards Complex doublesided and multilayer. Phone: (415) 659-1770 CIRCLE NO 64



Surface Mount AUTO-DIP* Switches Process compatible. Series SM 207. Phone: (805) 238-0350

Switch reliability that is the best ever!



- Redundant gold inlaid contacts dramatically enhance contact reliability.
- 2 Positive wiping contacts assure low and consistent contact resistance. (.050" travel)
- 3 Detent function separated from contacts to optimize both designs.
- Gold contacts never abraded or contaminated by sliding over polymer surfaces. Contacts never touch a nongold surface
- 5 No contactor deflection for the life of the switch. Constant contact force eliminates overstressing of contacts for greater reliability.

CIRCLE NO 65



Surface Mount Resistor Networks Numerous package configurations and attachment choices. Phone: (219) 589-8220

INTEGRATED CIRCUITS

options include a 28-pin plastic or ceramic DIP and a 28-pin PLCC. \$7.20 (1000).

Texas Instruments Inc, Semiconductor Group SC-647, Box 809066, Dallas, TX 75380. Phone (800) 232-3200.

Circle No 356



D/A CONVERTER

- 14-bit deglitched device
- Comes in 32-pin flat pack

The DAC-02311 is a 14-bit, 10-MHz. deglitched D/A converter that comes in a 32-pin flat pack for surface-mount applications. It has a low-impedance voltage output specified for 12- or 13-bit linearity. You program the device's pins for one of five different ranges of output voltage. Using external potentiometers, you can trim the offset, gain, and pedestal errors to zero. The converter operates over the military temperature range and comes in versions screened to MIL-STD-883. \$245. Delivery, stock to eight weeks ARO.

ILC Data Device Corp, 105 Wilbur Pl, Bohemia, NY 11716. Phone (516) 567-5600. TWX 510-228-7324.

Circle No 357

QUAD OP AMP


- Exceeds precision specs of OP-07
- Draws 2.9-mA total supply current

On a per-amplifier basis, the Model OP-400GP quad op amp consumes less than one-fourth the power used by an OP-07, yet meets or exceeds the precision specs offered by a single OP-07 device. The maximum input-offset voltage and drift are 300

 μV and 2.5 $\mu V/^{\circ} C$, respectively. The voltage gain for each amplifier in the OP-400GP is 3,000,000 min. Other specs include a 7-nA max input-bias current, 11-nV/ $\sqrt{\rm Hz}$ typ voltage noise, 110-dB min CMR, and 105-dB min PSR. The four op amps can drive capacitive loads as high as 10 nF without oscillation. The device uses the industry-standard pinout for quad op amps. \$5.35 (100).

Precision Monolithics Inc, Box 58020, Santa Clara, CA 95052. Phone (408) 727-9222. TWX 910-338-0218.

Circle No 358



DIODES

- Feature fast recovery
- Rated at 1 and 3A

The 11DF and 31DF fast-recovery diodes come in axial-lead packages. Rated at 1A and 3A respectively, both the 11DF and 31DF come in 100 and 200V versions (0.98V forward-voltage drop, 35-nsec recovery) and 300 and 400V versions (1.25V forward-voltage drop, 30-nsec recovery). 11DF, \$0.60 (100); 31DF, \$0.68 (100). Delivery, six weeks ARO.


International Rectifier Corp, 233 Kansas St, El Segundo, CA 90245. Phone (213) 607-8837.

Circle No 359

GATE ARRAYS

- Accommodate Mentor workstations
- Use 2-µm CMOS processing

The manufacturer's 2-µm, highspeed, CMOS-processed gate arrays are now supported by Mentor work-



Data Analysis & Controls Software

DAL™ Data Analysis Language. A new scientific/engineering design and analysis software package. Performs matrix, statistical and data analysis along with signal processing and digital filter design... \$395

87 FFT™ Written in assembly language, 87 FFT performs forward and inverse FFTs on real and complex arrays occupying up to 512 K of RAM. Callable from most 8087 compatible compilers. The fastest PC FFT package available! \$200

87FFT-2[™] For two dimensional FFTs.....\$100

UNKELSCOPE™ Turns your A2D-160 into a digital oscilloscope and data-logger............\$549



And they're available now, to help your designs reach new peaks in performance.

Choose from a complete range of Sony 256K SRAMs, available in numerous speeds and data retention currents, in either DIP or SOP packaging.

For super-low data retention current, consider our CXK58256P-10LL/12LL, with just 10 µA data retention current. Or our soon to be released CXK58255P-45/55/70 at 5 μ A, and CXK58255P-45L/ 55L/70L at just 2.5 μ A.

SONY SRAM DEVICES					
PART NUMBER	ORGANI- ZATION	0	PACKAGE		
CXK5814P— 35L/45L/55L	2K x 8	35/45/55	300 mil DIP		
CXK5816PN— 10L/12L	2K x 8	100/120	600 mil DIP		
CXK5816M — 10L/12L	2K x 8	100/120	SOP*		
CXK5416P— 35L/45L/55L	4K x 4	35/45/55	300 mil DIP		
CXK5864AP— 70L/10L	8K x 8	70/100	600 mil DIP		
CXK5864AM— 70L/10L	8K x 8	70/100	SOP*		
CXK5864PN— 12L/15L	8K x 8	120/150	600 mil DIP		
CXK5864M — 12L/15L	8K x 8	120/150	SOP*		
CXK5464P— 45L/55L/70L	16K x 4	45/55/70	300 mil DIP		
*Small Outline Package					

No matter which SRAMs vou choose, you also benefit from our immediate delivery. Plus the quality, reliability and performance found in all Sony products.

By calling today, you'll get all the details-plus a free data

196

Sonys 256K SŘAMS are taking current retention to a new low.





book on our complete line of Sony SRAMs.

So call (213) 373-9425, or

	PERFORMANCE OF 32K X 8 SRAM					
	PART NUMBER	PROCESS	SPEED (ns)	PACKAGE	DATA RETE CURRENT (MAX)	ENTION CONDITION
	CXK58256P-10L/12L	MIX MOS	100/120	600 mil DIP	50 μA	0 to 70°C
	CXK58256MF-10L/12L	MIX MOS	100/120	SOP	50 μA	0 to 70°C
11665	CXK58256P-10LL/12LL	MIX MOS	100/120	600 mil DIP	10 μA	0 to 70°C
	CXK58255P-45/55/70	FULL CMOS	45/55/70	600 mil DIP	5 μΑ	-30 to 85°C
	CXK58255P-45L/55L/70L	FULL CMOS	45/55/70	600 mil DIP	2.5 µA	-30 to 85°C

write Sony Corporation of America, Component Products Division, 23430 Hawthorne Blvd., Suite 330, Torrance, CA 90505.

Sony SRAMs. Setting higher performance standards with lower data retention current.




INTEGRATED CIRCUITS

stations. Three levels of available support span the range from schematic capture to layout and backannotation of the devices. Using a Mentor Capture workstation, you can draw the schematic design and run a design-check package. With the addition of simulation software and the Mentor Idea workstation. you can perform logic simulation that includes fan-in, fan-out, processing delays, and user-defined resistance delays. Finally, by using Mentor's Gate workstation, you can place and route the design's macro cells. The three levels of support from the gate-array manufacturer cost \$1500, \$4000, and \$27,500, respectively.

Siliconix Inc, 2201 Laurelwood Rd, Santa Clara, CA 95054. Phone (408) 988-8000.

Circle No 360



A/D CONVERTER


- CMOS 4½-digit device
- Drives a multiplexed LCD

The TSC7129 is a CMOS 4½-digit A/D converter that directly drives a multiplexed LCD; you supply only a voltage reference and a few passive components. Package options include a 40-pin plastic or ceramic DIP and a 44-pin plastic leaded chip carrier or flat pack. The converter's successive integration technique provides resolution to 10 µV and a reading accuracy to 0.005% of full scale. The device is pin compatible

with the ICL7129 from Intersil, but eliminates the external RC network that's normally required by including phase compensation for the internal integrator amplifier. Drawing 500 μ A from a 9V battery, the chip includes circuitry for low-battery detection; overrange, underrange, and change-range outputs (for autoranging); and a latch-and-hold input (for snapshot readings). Chips, \$7; packaged parts, from \$9.95 (100). Delivery, 8 to 10 weeks ARO.

Teradyne Semiconductor, Box 7267, Mountain View, CA 94039. Phone (415) 968-9241.

Circle No 361



GaAs LOGIC ICs

- Can operate at speeds exceeding 2.4 GHz
- Compatible with ECL circuits

These three GaAs digital ICs can operate at speeds as high as 2.4 GHz. Model µPG700B is a masterslave D-type flip-flop that has set/ reset functions. Model µPG701B is a master-slave T-type flip-flop that also offers set/reset functions. Model µPG702B is a 3-input OR/NOR gate. Typical positive-supply current (I_{DD}) for the µPG700B and -702B is 70 mA; the μ PG701B's I_{DD} is 80 mA. Models μPG700B and -702B draw a 50-mA negative-supply current (Iss); the µPG701B draws 60 mA. In 16-pin hermetic ceramic packages, \$197 (100). Delivery, three months ARO.

California Eastern Laboratories, 3260 Jay St, Santa Clara, CA 95054. Phone (408) 988-3500.

Circle No 362

REAL TIME SERVICE

For five years, **MicroWay** has been the leader in 8087 support and accelerator board technology. People continue to buy our products for two reasons: one, they work and two, we support our products with one of the best technical support teams in the industry. Join those who know! Buy your 8087 support from **MicroWay**.



oscillator lets you increase your AT's

80286 speed in 5 MHz increments. Includes a 10 or 12 MHz 80287 clock and a system reset button.

Board only	\$149
With 80287-10	\$549
With 80287-12	\$629
Optional 80286-10	\$175

8087 Upgrades

8087	5 MHz	\$114
8087-2	8 MHz	\$149
80287-3	5 MHz	\$179
80287-6	6 MHz	\$199
80287-8	8 MHz	\$259
80287-10	10 MHz	\$395
NEC V20-8	8 MHz	\$16
NEC V30-10	10 MHz	\$30
64K RAM set	150 ns	\$10
256K RAM set	150 ns	\$27
256K RAM set	120 ns	\$39
128K RAM set	PC AT	\$49

8087 Software

87 BASIC™ A patch to the IBM Basic or MS QuickBASIC compiler that provides fast, USER TRANS-PARENT 8087 support \$150

MATRIXPAK™ A run-time package written in assembly language which accurately manipulates large matrices at very fast speeds. Includes matrix inversion and the solution of simultaneous linear equations. Callable from RM, IBM or MS FORTRAN, MS Assembler or 87 BASIC.....\$99

87 Verify™ For users that have to be absolutely sure of their results! This background task periodically performs an 8087 accuracy and stress test.....\$49

MICTO P.O. Box 79 Kingston, Mass. 02364 USA (617) 746-7341

NEW PRODUCTS

CAE & SOFTWARE DEVELOPMENT TOOLS



CAE WORKSTATION

- Uses 25-MHz 68020 and 20-MHz numeric coprocessor
- Provides 32k-byte, write-through cache with no wait states

The HP Series 9000 Model 350. available in six configurations, is based on the 25-MHz 68020 µP, supplemented by the 20-MHz 68881 numeric coprocessor. All configurations come with a 32k-byte, write-through cache that operates with no wait states; 8M bytes of RAM (expandable to 32M bytes); HP-IB (IEEE-488) and RS-232C interfaces; a high-speed disk interface; and a LAN interface conforming to the IEEE 802.3 standard. Configurations include a keyboard, a display, a mouse, and all necessary cabling. The operating system is HP-UX, the vendor's implementation of Unix. At the low end of the line is the 350SPU, a stand-alone unit that can act as a network server or multiuser processor. At the other end is the 350SRX workstation, which provides a graphics resolution of 1280×1024 pixels and is equipped with a 19-in. color display that can have as many as 24 color planes. The 350SRX is capable of executing complex applications such as 3-D mechanical design, molecular modeling, modeling of solids, geophysical engineering, and earthstrata analysis. According to the vendor, this model has four times the computational power of a VAX-11/780. Prices range from \$21,900 for the 350SPU to \$54,900 for the 350SRX.

Hewlett-Packard Co, 1820 Embarcadero Rd, Palo Alto, CA 94303. Phone local office.

Circle No 381

VLSI ANALYSIS

- Runs on vendor's VLSI-verification systems
- Lets you characterize a VLSI device at the prototype stage

Meta-Shmoo is an enhancement of the operating software of the vendor's Topaz design-verification systems for VLSI devices. It lets you automatically plot the performance of a device by means of a Shmoo (safe modes of operation) plot. You can plot time vs voltage, time vs time, voltage vs time, or voltage vs voltage, both for thorough characterization of a device and for automatic measurement of parameters, such as propagation and setup times. The program lets you select the parameters to be plotted, the pins on which the system will take measurements, maximum and minimum test values, and incremental values at which tests are to be conducted. You can display the test results on the screen or direct them to a dot-matrix printer. During operation, the Topaz system runs the entire vector set at each incremental point on the plot, thereby allowing the program to display the worst-case pass/fail condition for each set of Shmoo parameters. \$2500.

HiLevel Technology Inc, 18902 Bardeen, Irvine, CA 92715. Phone (800) 445-3835; in CA, (714) 752-5215. TLX 655316.

Circle No 382



PC-BOARD CAD

- Enhanced features include zoom, pan, and scroll
- Autorouting speed of original product increased by 100%

Enhancements to the Artworker 3000 pc-board CAD system increase its overall speed by as much as 20% and add high-speed zoom, pan, and scroll facilities. You can zoom in or out of a layout using as many as four different predefined magnification factors. Additional enhancements include a 100% speed improvement in the autorouting operation, with

Looking for a job doesn't have to be one.

EDN's Career Opportunities section keeps you informed of current job openings from coast-to-coast



some improvement in the quality of the routing. The system allows you to generate schematics incorporating as many as ten 100×100-in. sheets, and to perform interactive placement. The system comes with all necessary hardware and software; prices for the enhanced Artworker 3000 start at approximately £12.000.

Wayne Kerr Datum Ltd, Jenner Rd, Crawley, West Sussex RH10 2GA, UK. Phone (0293) 549011. TLX 87201.

Circle No 383

BASIC INTERPRETER

- Runs on all Apollo computers
- Provides a superset of ANSI Basic X3.60 plus other dialects

This Basic interpreter, formerly available only for the Apollo DN300 and DN320, now runs on all Apollo computers, including DN3000 machines. The interpreter embodies a

superset of ANSI Basic X3.60, plus several existing Basic dialects, which allows it to accept many programs that run on other Basics. It recognizes variable names containing as many as 255 alphanumeric characters, and it allows dynamically evaluated data statements. It also supports user-defined functions; multiple statements per line; and integer, real, and string variables. You can write your Basic program to trap execution errors. The interpreter compiles the program into executable pseudo machine code, and it can operate in both interactive and batch modes. It sells for less than £500 (single-user license).

Lattice Logic Ltd, 9 Wemyss Pl, Edinburgh EH3 6DH, UK. Phone 031-225 3434. TLX 72465.

Circle No 384

Lattice Logic USA, 3333 Bowers Ave, Suite 199, Santa Clara, CA 95954. Phone (408) 748-9797.

Circle No 406



PC-BOARD CAD

- Based around an IBM PC/ATcompatible computer
- Links to Cadat and Spice simulation packages

The KAD-286 is a CAD workstation that allows you to perform schematic capture, simulation, and layout generation for pc-board or hybrid-component designs. It consists of the company's IBM PC/AT-compatible computer equipped with a graphics processor board (1024×780-pixel resolution), a 20-in. color (or 17-in. monochrome) moni-

WHO DO YOU THINK

makes 16K and 32K PROMS that are 20% faster than anyone else's?

(See page 210).



YOU LIKE TO WRITE, RIGHT?

Then EDN wants you, providing you also have an EE degree and at least two years' circuit-design experience. We seek individuals who want to be Boston-based technical editors for this top electronics publication.

To qualified individuals, EDN offers an attractive salary, industry-wide recognition, high job satisfaction, and the ability to keep abreast of...

- Advanced Technology
- Exciting New Products
- State-of-the-art circuit and system-design techniques

If you thrive on meeting challenges head-on...

If you are an effective, technical communicator...then send your resume and salary requirements in strict confidence to: Roy Forsberg, Editorial Director, **EDN**, Cahners Building 275 Washington St., Newton, MA 02158-1630, 617/964-3030

An Equal Opportunity Employer

CAE & SOFTWARE DEVELOPMENT TOOLS

tor, and an 11×11-in. digitizing tablet. The system's graphics editor features menu, function-key, or cursor-controlled data entry. You can organize schematics into as many as 200 pages and produce single-page or global net lists and component listings from them. Selectable net-list formats allow you to pass net-list data to Cadat or Spice simulation software, and you can modify net lists during the simulation or routing phases. Post-layout processing allows you to perform design-rule checks and to compare and verify layout and schematic net lists. Post-layout software is available, including drill-tape generation and plotting capabilities for pen, photo, impact, laser, and thermal plotters. The workstation, including software, sells for around DM 40,000. The software is also available separately.

Kontron Messtechnik, Oskarvon-Miller-Strasse 1, 8057 Eching/ Munich, West Germany. Phone (08165) 77551. TLX 526719.

Circle No 385

Kontron Electronic Inc, 630 Clyde Ave, Mountain View, CA 94039. Phone (415) 965-7020.

Circle No 407

CD ROM RETRIEVER

- Lets you prepare documents for transfer to CD ROM
- Lets you use an IBM PC to retrieve data from a CD ROM

SilverSmith is a document-preparation and indexed-retrieval program that conforms to the Association of American Publishers (Washington, DC) standard for document markup, using the Standard Generalized Markup Language (SGML). The SGML is defined by ISO standard 8879 (available from the American National Standards Institute, New York, NY), and it's currently being considered by the National Information Standards Organization as a candidate for the standard for data interchange on CD ROM media. The

complete package consists of a build (preparation) module and a search-and-delivery module. The build module allows you to create an SGML index for a document that you have prepared with your usual word processor and SGML tags. You can use the search-and-retrieval module with floppy disks, hard disks, or optical disks; it lets you

perform a search at a speed that is independent of file size, and then retrieve data that meets your search criteria. At the start of a search session, you can set the boundaries for the search (eg, paragraph, chapter, book), and a window displays the SGML tags used in the document. You can select the tags by entering them from the keyboard,



or by using the cursor to highlight the desired tags. You can use the Boolean text-search operators AND and NOT in your query. To run either module, you need an IBM PC or compatible equipped with at least 128k bytes of RAM and MS-DOS 2.1 or later. Complete package, \$595; search-and-delivery module only, \$100.

Taunton Engineering Inc, 505 Middlesex Tpk, Suite 11, Billerica, MA 01821. Phone (617) 663-3667.

Circle No 386

GRAPHICS TOOL KIT

- Implements the proposed ANSI and ISO extensions to GKS
- Lets you add light sources to highlight 3-D images correctly


Visual:3D is a modular, 3-dimensional graphics library based on the internationally accepted GKS (Graphics Kernel System) standard. The vendor has enhanced the basic

GKS standard with extensions required by many 3-D applications. Some of these extensions implement the guidelines set forth in the GKS-3D draft proposal (also known as ISO DP 8805); these include drawing primitives for boxes, spheres, cylinders, cones, prisms, ovals, and rounded rectangles. More advanced extensions include solid shading, facet shading with hiddensurface removal, smooth shading, and global shading by ray tracing. The tool kit provides solid-surface attributes that include multiple light sources of different types, reflectivity and translucency, and antialiasing. The package includes a graphics-device-management system that provides device independence by letting you describe the environment's capabilities and constraints in an ASCII text file. The system analyzes the graphics requirements and produces the required control stream or invokes the

appropriate system calls. From \$1500 to \$8000, depending on the system-hardware configuration.

Visual Engineering Inc, 2150 N First St, Suite 600, San Jose, CA 95131. Phone (408) 922-2800.

Circle No 387




PLC DESIGN

- Provides predrawn symbols for many ladder-logic devices
- Runs on IBM PCs and compatibles

PLC-Ladder is a drawing tool for

THINKING DIN?



Our complete line of DIN 41612 compatible connectors meet all IEC 630-2 and MIL-C-55302 requirements.

STANDARD AND REVERSE MOUNT 3 amps; 64, 96 or more positions; optional mate first/break last ground contacts.

POWER AND MIXED POWER 5.5, 15 and 5.5/15 amp.

INSULATION DISPLACEMENT CONNECTOR (IDC) 3 amps, 96 position insulator fitted with 64 and 96 contacts.

MODULAR BACKPLANE INTER-CONNECTION (MBI) 3 amps, 96 position cable connector or 21 position modules.

MODULAR FRONT-EDGE INTER-

CONNECTION (MFI) 3 amps, 21 position modules.

Special connectors.

Our Engineering Dept. designs connectors for specialized applications and environments. Just one more reason why you should think Souriau when you're thinking DIN.

the ladder-logic diagrams used in the design of relay logic and programmable-logic controllers. The program runs on any IBM PC or compatible machine and allows you to call up logic symbols from a library and place them in a cellular grid that accommodates as many as 256 rungs. The package includes a graphics font editor that lets you create nonstandard symbols and store them in the library. You can copy, move, insert, or delete complete rungs by means of simple commands. Wire-management routines automatically handle interrung connections and provide for manual or automatic renumbering of the rungs after an insertion or deletion. Drawings are stored on disk; you can obtain hard copy by directing them to an inexpensive dot-matrix printer. Because the program is dedicated to the creation of ladder diagrams, the vendor claims, it is faster to use for this application

than standard CAD programs are. The company also maintains that a user requires less than one hour of self-training time to become competent in the program's use. \$495.

Simon Industries Inc, 2901 Hoover St, Orange, CA 92667. Phone (714) 639-9436.

Circle No 388

C COMPILER


- Runs on PC/AT and compatibles
- For 80386 processor

The C 386 compiler and the RLL 386 relocation, linkage, and library tools package are 80386 software-development tools that run on the IBM PC/AT or compatibles. The C 386 compiler implements the full C language. It generates code that is compatible with the vendor's other 80386 languages, so you can link modules written in different languages on different hosts. The com-

piler also provides facilities for symbolic debugging. The RLL 386 package consists of a linker, a builder, a mapper, and a librarian. The linker integrates program modules that have been separately compiled on a PC, VAX, or Xenix system into larger files or complete programs. The builder assigns absolute addresses to files created by the linker, to allow these files to be placed in nonvolatile memory. The mapper generates a program memory map to aid in debugging and software documentation. The librarian manages the program modules so that they can easily be accessed by all members of your programming team. C 386 compiler, \$900; RLL 386 package, \$600.

Intel Corp, Literature Dept, 3065 Bowers Ave, Santa Clara, CA 95052. Phone local office.

Circle No 389



NEW PRODUCTS

COMPUTERS & PERIPHERALS

A/D BOARDS

- Data-acquisition boards for IBM PC/AT and for Multibus II
- Sample rates of 250 kHz available

The DT2821-G analog I/O board provides single-board data acquisition for the IBM PC/AT and compatible computers. The DT2401 Series analog I/O boards, on the other hand, are directed at Multibus II applications. The DT2821-G gives you 12-bit resolution for 16 singleended or eight differential analog inputs, programmable gain, two 12-bit deglitched DACs, a channelgain list, a programmable clock, and support for interrupts and DMA transfers. The board can acquire data at a sustained rate of 250 kHz. (At present, however, the only PC that can run at this rate is the Compag 386; other PCs can sustain 180 to 235 kHz, depending on their clock speed.) The DT2401 Series features two 12-bit, 50-kHz D/A

converters, 32 lines of digital I/O organized as two 16-bit ports, and an onboard programmable clock that can start A/D conversions or control off-board events. DT2821-G board, \$2995; DT2401 Series, \$1695 to \$2960.


Data Translation, 100 Locke Dr, Marlboro MA 01752. Phone (617) 481-3700. TLX 951646.

Circle No 363

CRT CONTROLLER

- For VME Bus systems
- Available in ruggedized military versions

The SVME-676, a VME Bus-compatible alphanumeric CRT controller, offers serial and parallel I/O, a timer, and a real-time clock/calender with battery backup. It provides RS-170-compatible video output with nonserrated vertical synchronization for alphanumeric displays. The board generates the video timing signals and refresh



memory addressing. The module has a memory-mapped video refresh memory and attribute memory, the combination of which provides multilevel gray-scale, underline, blink, and reverse video. It also features software-selectable screen formats and programmable cursor-blink rates. The board provides 20 bits of parallel I/O and a 24-bit timer on board. It offers two channels of serial I/O, providing an optional RS-422 or RS-423 interface. Ruggedized military versions are also available. \$1690.


DY-4 Systems Inc, Suite 202, 1475 S Bascom Ave, Campbell, CA 95008. Phone (408) 377-9822.

Circle No 364

PRINTERS

- Two additional models to printer line
- Both come with Roman and sans serif NLQ fonts

The FX-86e (80-column) and FX-286e (136-column) dot-matrix printers are 9-pin dot-matrix printers that provide Roman and sans serif near-letter-quality (NLQ) fonts as standard features. The printers support pica, elite, proportional, italic, and condensed printing modes. Double-height and doublewidth characters are also available. You can select draft or NLQ and normal or condensed modes via front-panel buttons. Automatic single-sheet feed is standard on both models. In draft mode, both units print at 240 cps and 12 characters per inch (cpi); in NLQ mode, they



print at 48 cps and 12 cpi. Each printer operates either in conjunction with Epson's standard code for printers (ESC/P) or in IBM printer emulation mode. Optional accessories for the printers include a single-bin sheet feeder, a 32k-byte data

buffer, and the company's 81xx Series of serial interface boards. FX-86e, \$549; FX-286e, \$799.

Epson America Inc, 2780 Lomita Blvd, Torrance, CA 90505. Phone (213) 539-9140.

Circle No 365

NEED HELP WITH COOLING DESIGN PROBLEMS?



air-moving application problems.

Comprehensive test-laboratory facilities, and over 40 years of design experience have established our reputation for technical leadership in custom blower design for the electronics cooling, business machine, aerospace and military markets.

flow blowers, mixed-flow blowers, cabinet blowers and vane-axial fans.

As part of Fasco Industries, we are now uniquely positioned to provide you with country-wide sales coverage, dedicated design and sampling capabilities on both East and West coasts, in-house availability of electric motors and cost-effective manufacturing through Fasco.

Call on us when your air-moving requirements exceed the ordinary. Our product line is limited only by your imagination.

TORIN ENGINEERED BLOWERS



FASCO INDUSTRIES, INC.

MOTOR DIVISION HEADQUARTERS 500 Chesterfield Center Suite 200 St. Louis, MO 63017 314-532-3505 / Telex: 44-7455

TWO GREAT WAYS TO GET INTO PROGRAMMABLE LOGIC.



ONE LOW PRICE.

For just \$2495, Data I/O® now offers two easy ways to put the power of logic in your designs. The LogicPak™, with the generic adapter, transforms your 19, 29A, or 29B Universal Programming System into a sophisticated logic programming tool that supports virtually all programmable logic devices (PLDs). Or, if you don't already own one of our universal systems and want to program the popular PLDs, choose the 60A Logic Programmer.

Data I/O has set device programming standards for more than 15 years. So whichever programmer you choose, you can feel confident that you'll have the most reliable, up-to-date device support available today.

THE POWER OF LOGIC FOR JUST \$2495. Call us now at **1-800-547-4000**, Dept. 501. We'll send you a complete information packet on our logic programmers.

DATA I/O

COMPUTERS & PERIPHERALS

DISPLAY CONTROLLER

- Supports a variety of monitors
- Video-output section is on a piggyback module

The Intelligent Graphics Controller (IGC) is a modular graphics-controller board with which you can program your own graphics primitives. The board is designed around the TI34010, a 32-bit graphics-controller chip that uses software to form graphics primitives. Compatible with the IBM PC, the board supports 640×480- to 1280×1024-pixel monitors. You can choose the appropriate video-output stage for your application from three piggyback modules, which address low, medium, and high levels of monitor performance. You can display 16 to 256 colors from palettes of 4096 or 16.8 million colors. The board provides 512k bytes of RAM for storing command software for the graphics system's processor. The Direct Graphics Interface Specification (DGIS) is the standard interface for the IGC. Model 10 comes with 512k bytes of video RAM; 640×480-, 960×720-, and 1024×768-pixel resolution; and 16 available colors from a palette of 4096. Model 20 comes with 1M byte of video RAM; 640×480-, 960×720-, and 1024×768-pixel resolution; and 256 available colors from a palette of 4096. Model 30 comes with 1M byte of video RAM; 1024×1024- and 1280×1024-pixel resolution; and 256 available colors from a palette of 16.8 million. Model 10, \$1499; Model 20, \$1999; Model 30, \$2499.


Emulex Corp, Persyst Div, Box 6725, Costa Mesa, CA 92626. Phone (714) 662-5600.

Circle No 366

VME RAM BOARD

- Board can be configured with 2M or 4M bytes of RAM
- Error detection and correction corrects single-bit errors

The DRAM-5 board offers a choice of 2M or 4M bytes of dynamic RAM



for VME Bus applications and is corrected for all single-bit errors. The DRAM-5 also detects and reports to the host all double-bit errors. LEDs on the front panel signal all detected errors. Both versions of the board use ZIP 256k×1-bit RAMs for space savings. The boards are 32 bits wide in both data path and address path, and they employ a 64-bit-wide internal cache that enhances access time for sequential read operations. Read-access time is 140 nsec with a cache hit. Worst-case access time of 280 nsec occurs when read access misses the cache. Write time for the boards is 120 nsec. The DRAM-5 contains a control and status register, implements all VME Bus data-transfer modes, and provides support for unaligned and read-modify-write transfers. For 24- or 32-bit-address operation, you can access memory in 64k-byte blocks in conjunction with a mode jumper. DRAM-5A (2M bytes), \$2095; DRAM-5B (4M bytes), \$2895.

Force Computers Inc, 727 University Ave, Los Gatos, CA 95030. Phone (408) 354-3410.

Circle No 367

RLL CONTROLLER

- Run-length-limited controller for 3½-in. disk drive
- Attaches to two ST506/412 or two ST412R drives

The OMTI 3127 3½-in. disk-drive controller incorporates run-length-limited (RLL) encoding and attaches as many as two ST506/412- or two ST412R-compatible fixed or removable Winchester drives to computer systems using the SCSI host

Finally. A breaker handsome enough to mount on your panel.

New VisiRocker® On/Off Switching and Circuit Protection.

Get the convenience of over-current protection and on/off switching in one attractive package. Unique two-color actuator can be specified to indicate "tripped" mode or "on" mode. Various molded-in legends are available. High quality alloys and efficient arc suppression keep contact resistance low and service life high.

Available up to 3 poles with one actuator. Delay curves range from instantaneous to long, including high inrush. U/L recognized, CSA certified, with ratings up to 50 amps.

For a free VisiRocker sample, send us your specs and a description of your application on your letterhead. Or call for the location of your nearest distributor or sales representative. Carlingswitch, Inc., 60 Johnson Ave., Plainville, CT 06062-1156. (203) 793-9281. Toll Free: 1-800-243-8160.

CARLINGSWITCH MNOVATION BY DESIGN



COMPUTERS & PERIPHERALS

interface. The drive supports 1:1 interleaving and a buffering scheme that helps to generate a 7.5M-bps data-transfer rate. The RLL algorithm can increase the storage capacity of the disks by as much as 50%. A 48-bit polynomial is used for error detection and correction. The drive consumes 0.75A. \$129 (OEM qty).

Scientific Micro Systems Inc, 339 N Bernardo Ave, Mountain View, CA 94043. Phone (415) 964-5700.

Circle No 368

PROTOTYPING BOARD

- Allows you to prototype an intelligent VME Bus slave board
- Communicates with other bus processors via shared memory

The TSVME431 prototyping card for the VME Bus features a 68010 10-MHz μP and a VME Bus interface that occupy one-half of the double-Eurocard card, which is adjacent to the VME Bus P1 connector. The other half of the board, adjacent to the P2 connector, has a 110×160 -mm, 0.1-in.-pitch wirewrapping area and provision for the installation of a P2 connector. The wire-wrapping board detaches from the processor section via a 96-pin

DIN-41612 connector, which carries a buffered extension of the 68010's data and address bus. It also carries interrupt and interrupt-acknowledge lines, control lines, and a decoded address line that indicates the internal memory space reserved for the user. The μP has 60k bytes of onboard, dual-ported RAM, 4k bytes of local memory, two sockets for a maximum of 128k bytes of EPROM, two sockets for RAM/EPROM/EEPROM, and two RS-232C interfaces. Approximately Fr fr 8000.

Thomson Semiconducteurs, 45 Ave de l'Europe, 78140 Velizy, France. Phone (1) 39469719. TLX 204780.


Circle No 369
Thomson Components-Mostek
Corp, 7950 E Redfield Rd, Scottsdale, AZ 85260. Phone (602) 9512900.

Circle No 370

CPU CARD

- OS9/68000 operating system provides support
- Based on an 8-MHz 68008 µP


Supported by the OS9/68000 OS, the SC008 CPU card for STE Bus systems suits real-time or operating-system environments. The



board runs an 8-MHz 68008 µP and has 16k bytes of RAM, four memory sockets for RAM or EPROM, two serial I/O ports, and a counter-timer/real-time clock. The CPU can operate as a single STE Bus master, or it can provide bus-access arbitration alongside other STE Bus CPUs. It supports nonvectored-interrupt handling for the STE Bus and one interrupt for onboard devices. The CPU can access the full 1M-byte STE Bus address space as well as 4k bytes of I/O space. £275.

Arcom Control Systems Ltd, Unit 8, Clifton Rd, Cambridge CB1 4WH, UK. Phone (0223) 242224. TLX 817114.


Circle No 371



Design Digest of Electronic Reliability

Designing a high-performance electronic product is only half the battle. Protecting it is the other half. Demand our high-reliability protective

materials and you have won. Here is what we mean:



For thermal dissipation that protects perfomance, choose new SYLGARD® Q3-6605 thermally-conductive elastomer. It is especially useful as a thermally-conductive adhesive to bond ceramic hybrid circuit packages to heat sinks. Other uses include bonding or potting power supplies, coils, heavy-duty relays, and similar units. Primerless, too.

Protective silicone gels relieve stress and improve reliability.

When you encapsulate components in a silicone gel, you protect them against hostile environments, temperatures as low as -80° C and more. DOW CORNING® silicone gels also cushion components against stress and vibration. We offer a broad choice of one component and two component materials, for room temperature and heat cure processes.

Coating makes repairs on PC boards easier.

A PC board coating simply has to be reliable. And with DOW CORNING® 1-2577 conformal coating you get more: easy repairability when components need replacing. Add superior protection in extreme environments, versatile processing with dipping or spraying, and you have all the reasons major automotive and military electronics

Companies choose
DOW CORNING
1-2577.

Fast-cure coat-

ing for fiber optics.

OPTIGARD® optical fiber coating

UV-cures in just 0.3 seconds—5 to 20 times faster than thermal-curing coatings. And it protects against moisture and "micro-bends" better than acrylate coatings. It's part of the OPTIGARD family which includes fiber optics grade SiCl₄ core and cladding and OPTIGARD cable filler.

Life insurance for semiconductors.

Stress. Moisture. Ion contamination. Voltage linkage. Alpha particles. All are killers of your devices, robbers of reliability. Now you have a defense against them. HIPEC® coatings protect semiconductors and hybrids through a wide range of temperatures and environments. They're available in a variety of forms from gel to firm elastomer and resins. And HIPEC coatings are easier to process than other high-performance materials.

There's more.

There's also our unique team of experts whose only mission is to develop and customize coatings, adhesives, dispersions, sealants, and components specifically for you. Supported by dedicated research and manufacturing facilities, we will help you meet tomorrow's challenges today. Ask about our Specialty Elastomers, Group.

Write Department 7013, Midland, MI 48686-0994.



Dow Corning, Sylgard, Optigard and Hipec are registered trademarks of

Dow Corning Corporation.

Surprise. But the fact is, we do have the fastest high-density CMOS and bipolar PROMs in the industry. With more coming along all the time. In the last year, we've added at least one device for every density—from 1/4K to 64K.

We also have a large selection of surface mounted devices in both

PLCC and SO.

Volume quantities are available now. Call 800-227-1817, ext. 965D for more information.

For free on-line information, dial 1-800-345-PEEK with any 80-column ASCII terminal or PC and a 300 or 1200 baud modem (EVEN or IGNORE parity, 7 data bits, 1 stop bit). At "Enter Response Code," type HSPROMS. In Conn. dial 1-203-852-9201.



3/4

965

NEW PRODUCTS

COMPONENTS & POWER SUPPLIES

STEPPING MOTORS

- Torque ratings to 142 oz-in.
- Class B insulation standard

The 1.8° full-step angle motors in the D34D62-22 Series of stepping motors operate at 200 steps/revolution and provide holding torque ratings ranging from 26 to 142 oz-in. Phase-current ratings range from 1 to 4.7A in unipolar operation, and from 0.33 to 6.6A in bipolar operation. Rotor inertia ratings range from 0.28 to 1.8 oz-in², and detenttorque ratings spec at 4 to 14 oz-in. Bipolar models have four AWG-22 leads that are 12 in. long; the six models that run in both bipolar and unipolar modes have eight leads. Standard insulation for these motors is Class B. The motors operate over a -20 to +50°C ambient range; the recommended case temperature is 100°C max. From \$69.

Stock Drive Products, 2101 Jericho Tpk, New Hyde Park, NY 11040. Phone (516) 328-3330.

Circle No 372

MOSFETs

- Qualified to MIL-STD-19500/ 543B
- Power dissipation equals 150W

The 2N6768 and 2N6770 military-qualified MOSFETs are rated for 400 and 500V, respectively. The two devices are qualified to MIL-STD-19500/543B and listed under QPL-19500 for JANTX and JANTXV levels. The 6768 is a 15A unit with an on-state resistance of 0.3Ω . The 6770 is rated for 12A and has a 0.4Ω on-state resistance. The units are available in TO-204AA metal packages and operate over -55 to $+150^{\circ}$ C. The total power dissipation at 25°C is 150W. \$20 to \$45.

Fairchild Semiconductor Corp,


4300 Redwood Hwy, San Rafael, CA 94903. Phone (800) 554-4443; in CA, (415) 499-4416.

Circle No 373

DELAY LINES

- Delay times range as high as 1000 nsec
- Buffered input and outputs


EP8300 Series TTL-compatible active delay lines provide 10 equally spaced output delays. The 28 units in the family offer total delay times of 50 to 1000 nsec, $\pm 5\%$ or 2 nsec, whichever is greater. The delay-line input and the 10 output taps are buffered by a Schottky TTL inverter. The rise time specs at 4 nsec



max for 50- to 500-nsec delay models, and 5 nsec max for 550- to 1000-nsec models. In a 14-pin DIP, the lines are compatible with automatic-insertion equipment. The operating range spans 0 to 70°C. EP8301 50-nsec model, \$4 (1000). Delivery, stock to six weeks ARO.

PCA Electronics Inc, 16799 Schoenborn St, Sepulveda, CA 91343. Phone (818) 892-0761.

Circle No 374



DISPLAY SYSTEM

- Offers 1200 to 9600 band rates
- 100,000-hour display life

The VF-0640-01 is a 6-line×40-character vacuum-fluorescent display subsystem that features 0.2-in.-high characters. The display brightness specs at 175 fL, and data rates range from 1200 to 9600 baud. The unit displays several fonts: 96-characters.

acter standard ASCII, ECMA, Katakana, scientific, European, and custom. Built-in software features include dimming, scrolling modes, and blinking characters. The system accepts both TTL-level parallel or serial ASCII input data. Operation spans 0 to 55°C, and the viewing angle is 130°. The display life specs at 100,000 hours. High refresh and data-entry rates prevent flickering.



A **SEALED** I/R TOUCH DISPLAY MODULE SO FAR ADVANCED YOU HAVE TO SEE







FULLY INTEGRATED 512x256 MATRIX EL DISPLAY MODULE INCLUDES I/R SEALIOUCH AND GRAPHICS/TEXT TERMINAL CONTROLLER.

- One-piece molded I/R frame and integral bezel/ filter
 - Flush mounts in your front panel cutout.
 - Sealable from moisture and dirt antiglare, scratch-resistant, polarized filter included.
- Low power requirement 20 Watts typical, requires only +5, +12 vdc input.
- Minimum footprint, compact cube.
 - I/R touch frame fits within display panel frame outline.
 - Ultra-compact module occupies minimum space. See dimensions above.
 - Flat display screen and flat touch plane eliminates parallax.

ENHANCED OPERATIONAL FEATURES ASSURE MAXIMUM PERFORMANCE AND DESIGNER EASE!

- NEW "FTS" GRAPHICS:
 - Dual processor architecture gives highest graphics performance in the industry.
 - Fast 2400 vectors/sec., 4 million pixels/sec. (block fill).
 - Convenient interfaces serial, parallel, raster, DMA, keyboard.
 - ASCII encoded.
- VT100* TERMINAL EMULATION:
 - VT100* based text capability.
 - No hand-shaking required at 19.2K baud.

THE DISPLAY INNOVATORS



- EXPANDED TOUCH SOFTWARE:
 - High resolution.
 - Automatic button draw and button pages.
 - · Pop-up menus.
 - Enter, exit and track touch modes.
 - Software compatible with earlier DeeCO systems.
 - Callable on-screen ASCII keyboard.

CALL NOW FOR A FREE DEMONSTRATION (415) 786-0520.

See Us At Southcon '87-Booth 948

DIGITAL ELECTRONICS CORPORATION

26142 Eden Landing Road • Hayward, CA 94545 • (415) 786-0520
Telex: 172073 DIGELEC HYWD • Facsimile: (415) 786-1040
*VT100 is a Trademark of Digital Equipment Co.

EDN March 4, 1987 CIRCLE NO 70 213

The display comes with an onboard μP controller; an RS-232C input is available as an option. \$776 (99).

Babcock Display Products Inc, 1051 S East St, Anaheim, CA 92805. Phone (714) 491-5116.

Circle No 375



PANEL METER

- 1-µV/count resolution
- Serial BCD output optional

Model 2002-S is a 41/2-digit panel meter designed for strain-gauge, load-cell, and torque-monitoring applications. Standard features include a jumper-programmable differential preamp, which provides resolution down to 1 µV/count; an adjustable, electrically floating 10 to 24V dc bridge-excitation supply; and independent bridge-balance, zero, and span adjustments for direct readout in engineering units. The display spans $\pm 19,999$ counts with 99.98% accuracy. The 2002-S fits a standard 1/8-DIN panel cutout. Options include serial BCD output and a splash-proof lens cover that conforms to NEMA-12 requirements. \$279.


Newport Electronics Inc, 630 E Young St, Santa Ana, CA 92705. Phone (714) 540-4914. TWX 910-595-1787.

Circle No 376

DC MOTORS

- Feature integral shaft-tachometer or -encoder fixture
- Ironless rotors for low inductance

These cylindrical-collector, ironlessrotor dc motors now offer a choice of




a dc tachometer, a frequency tachometer, or a fixture that accepts a shaft encoder. These options make them suitable for variable-speed, constant-speed, and position-control applications, respectively. The 66-mm-diameter motors are available with supply voltages of 12 or 30V nominal. They operate at approximately 2000 rpm, have a torque of 120 mNm (milli-Newton-meters), and feature a mechanical time constant of 17 msec. The sample price is around \$46. Delivery, 12 weeks ARO.

Philips Elcoma, Box 523, 5600 AM Eindhoven, The Netherlands. Phone (040) 757005. TLX 51573.

Circle No 377

Airpax, Cheshire Industrial Park, Cheshire, CT 06410. Phone (203) 272-0301.

Circle No 378



SWITCHING SUPPLIES

- Typical efficiency equals 75%
- Meet FCC/VDC, level A specs for EMI

The QX Series of switching power supplies includes units that have output capabilities of 250 to 325W, with as many as five outputs, including a 50A main output. All models have fully regulated outputs for re-

duced soft-error rates, jumper-programmable input-voltage range selection, and input surge-current limiting; protective features include brownout, overload, overvoltage, and reverse voltage. The typical efficiency is 75%. Standard features include a 20-msec holdup time, remote sensing, and remote inhibition. Options include a power-fail signal, an EMI safety cover, remote on/off. thermal-shutdown and switches. The supplies have UL, CSA, and TUV approvals and meet FCC/VDC, level A specifications for EMI. \$299 to \$338 (100).

Cherokee International Inc, 8 Autry, Irvine, CA 92718. Phone (714) 951-9679. TWX 510-101-0493.

Circle No 379



FET DRIVER

- Patented photovoltaic IC provides fast turn-off
- Housed in an 8-pin DIP

Offering a significant reduction in drive-circuit complexity, board space consumed, and cost, the FDA200 converts a TTL- or CMOSlevel current input into a 12 or 14V output that drives discrete MOS-FETs. This driver incorporates a patented photovoltaic IC that includes a gate-clamping circuit for fast turn-off. You can operate the unit's two optically isolated outputs in series, in parallel, or independently; this operation drives ac or dc loads. The driver performs over a -40 to +85°C range and comes in a standard 8-pin DIP. \$4.20 (1000).

Theta-J Corp, 107 Audubon Rd, Wakefield, MA 01880. Phone (617) 246-4000.

Circle No 380

Anritsu Presents Spectrum Analysis That's Simply Unforgettable



MS710C Spectrum Analyzer

No more writing down results. No more sketching waveforms on paper. No more grease pencil graphics on the CRT grid. Why?

Because Anritsu's new MS710series Spectrum Analyzers actually remember display screens for you — up to nine of them, in fact. Each one complete with waveforms and comprehensive alphanumeric information such as frequency, level, etc. Each one ready for recall to the CRT at the push of a button. Check and recheck, contrast one with another, even compare the current real-time waveform to a standard in memory. It's like having a file of waveform information always at your fingertips. Frequency range is wide, too; for instance, our new MS710C covers the range from 10kHz to 23GHz (or up to 140GHz with an external mixer). It offers signal search functions, along with an ergonomic front panel that puts every control right where it's needed. A special display lists key functions right on the screen: it's virtually a built-in operator's manual!

Can't get the MS710C out of your mind? Contact Anritsu for further details.

Spectrum Analyzer	Frequency Range	Frequency Stability (6.5GHz)	Frequency Range with External Mixer
MS710C	10kHz~30MHz, 100kHz~23GHz	30kHz	18~140GHz
MS710D	100kHz~23GHz	1 MHz	18~140GHz
MS710E	100kHz~23GHz	30kHz	-
MS710F	100kHz~23GHz	1 MHz	-



ANRITSU CORPORATION 10-27, Minamiazabu 5-chome, Minato-ku, Tokyo 106, Japan Phone: 03-446-1111 Telex: 0-242-2353 ANRITU J ANRITSU AMERICA, INC. 15 Thornton Road, Oakland, NJ 07436, U.S.A. Phone: 201-337-1111 Sales & Service 1-800-255-7234 Telex: 642-141 ANRITSU OKLD ANRITSU EUROPE LIMITED Thistle Road, Windmill Trading Estate, Luton, Beds, LU1 3XJ, U.K. Phone: (STD0582)418853 Telex: 826750 ANRSEU G ANRITSU ELEKTRONIK GmbH Grafenberger Allee 54-56, 4000 Düsseldorf 1, F.R. Germany Phone: (0211) 679760 Telex: 8584904 ANRI D ANRITSU ELETRÔNICA S.A. Av. Passos, 91-Sobrelojas 203/205-Centro, 20.051-Rio de Janeiro-RJ, Brasil Phone: 221-6086, 224-9448 Telex: 2131704 ANBR BR

EDN March 4, 1987 CIRCLE NO 51 215

NEW PRODUCTS

TEST & MEASUREMENT INSTRUMENTS



PROGRAMMERS

- Program 1M-bit and one-timeprogrammable devices
- Implement EPROM manufacturer's recommended algorithms

These EPROM/EEPROM programmers, Models E8B, E9C, E12B, and C41, are now capable of programming 28- and 32-pin 1M-bit devices. They can now also program Intel one-time-programmable devices using Intel's Quick-Pulse Programming algorithm. Using the E8B or E9C, you can now program as many

as eight 27512, 27513, or 27011 EPROMs while still performing automatic access-time testing of the devices. Also available is the A32, a 28- to 32-pin adapter that allows programmers with 28-pin sockets to program and verify the 32-pin 27010, 27C001, and 27C101 1M-bit devices. Upgrades start at £150.

Elan Digital Systems Ltd, 16-20 Kelvin Way, Crawley, West Sussex RH10 2TS, UK. Phone (0293) 510448. TLX 877314.

Circle No 390



DC POWER SUPPLY

- Stores 200 settings internally
- Supplies 0 to 32V at 1A

The LPS-2801 programmable dc power source supplies 0 to 32V at 1A. You can program output-voltage changes in 10-mV increments

over time periods ranging from 10 msec to 99.99 sec. The device's slew rate ranges from 100 $\mu V/{\rm sec}$ to 3200V/sec. You can control the device manually or over the IEEE-488 bus. The source stores as many as 200 settings internally; you can program each setting to produce either a steady dc voltage or a ramp. \$1940.

Leader Instruments Corp, 380 Oser Ave, Hauppauge, NY 11788. Phone (800) 645-5104; in NY, (516) 231-6900. TWX 510-227-9669.

Circle No 391

EMULATORS

- Plug into IBM PC
- Versions available for 8- and 16-bit μPs

The ERX Series μP emulators each comprise a board set and a personality module for a specific μP . The board set consists of either two boards for 8-bit μPs or three boards for 16-bit μPs . The boards plug into IBM PC slots or slots in the company's Boxer computer. Personality modules are currently available for the Hitachi 6301 and 64180 and the Zilog Z80. An 8-bit board set costs \$2995; each personality module is \$2995.

Zax Corp, 2572 White Rd, Irvine, CA 92714. Phone (800) 421-0982; in CA, (714) 474-1170.


Circle No 392



CALIBRATOR

- Handheld instrument weighs
 14 oz
- Unit generates stimulus and measures output

The CL-2241 frequency calibrator is a handheld unit. It generates test signals having frequencies ranging from 0.3 to 163 Hz. The instrument also measures signals ranging from 0.1 Hz to 200 kHz, 4 cpm (cycles per minute) to 2k cpm, and 20 cph (cy-



TOUGH SOLEF JACKETING FOR AN INFINITY OF USES.

Your most cost-effective choice for state-of-the-art jacketing material is Solef fluorocopolymer. It meets the stringent smoke and flame retardant requirements of the Steiner tunnel test—a necessity for telecommunication and data transmission plenum cable constructions. And it has a myriad of uses in the demanding environments of the electronics, aerospace and com-

munications industries. That's why so many cable manufacturers are now using Solef resin for their jacketing needs.

Solef 11010-0003, which carries UL classification 910 for low smoke and flame spread, and a 150°C rating, gives you a jacket that's as tough as it is easy to work with. Elongation is outstanding. Abrasion resistance is excellent. Plus, Solef jacketing has

a high resistance to both thermal aging and chemical attack.

For more information about Solef fluorocopolymer's infinity of uses and competitive price, call Bill Mould or Chuck Glew at 1-800-231-6313 (in Texas, 713/522-1781). Soltex Polymer Corporation, P.O. Box 27328, Houston, Texas 77227.



Come where the power is.



Broadband capability from some very powerful amplifiers. Power from one watt to ten kilowatts. Frequencies from 10 kHz to 1 GHz. Gain that's flat and reliable.

For example, our Model 2000L, shown above, delivers 2000 watts minimum cw saturated power over a bandwidth of 10 kHz to 220 MHz. In pulse mode you can almost double that rated output.

We rate most of our amplifiers by minimum power—users can be certain that their 10-watt or 2000-watt amplifier will always deliver at least its rated output at any point in its frequency band.

AR amplifiers are unconditionally stable, immune even to worst-case load mismatch without damage or shutdown. The full bandwidth is instantly available—there's no need for tuning or bandswitching.

Send for our booklet, "Your guide to broadband power amplifiers."



160 School House Road Souderton, PA 18964-9990 USA Phone 215-723-8181 TWX 510-661-6094

8288

TEST & MEASUREMENT INSTRUMENTS

cles per hour) to 20k cph. The unit measures $6\times3\times2$ in. and weighs 14 oz. It operates from a 9V battery or an ac adapter. \$475.

Rochester Instrument Systems Inc, 255 N Union St, Rochester, NY 14605. Phone (716) 263-7700.

Circle No 393




RS-232C ANALYZER

- Converts band rates
- Captures message streams to 32k bytes

The Datamon portable RS-232C analyzer weighs 7 lbs, including accessories and a standard carrying case. You can record message streams as long as 32k bytes and view them in several formats on a dumb terminal. The device provides status LEDs for RS-232C lines and baud-rate conversion. \$795.

Standard Logic Inc, Box 2319, Corona, CA 91720. Phone (714) 735-8610.

Circle No 394



8051 EMULATOR


- Emulator runs at a 12-MHz clock speed
- Qualifies breakpoints by address range, data, and cycle

The 8051/31 in-circuit emulator for 8051-family single-chip µPs runs at clock rates as high as 12 MHz. It works with either a dumb terminal or an IBM PC. The emulator has

128k address breakpoints, a 2k-sample trace buffer, and 64k bytes of mappable program memory. The emulator also has an 11-bit event counter, an external-trigger input, and an internal-trigger output. The emulator's command monitor provides single stepping, in-line assembly and disassembly, and control of the μ P's internal registers. You can qualify breakpoints by address or address range, data, program-cycle type, and external inputs. \$3195.

IAM, Box 2545, Fair Oaks, CA 95628. Phone (916) 961-8082.

Circle No 395



PORTABLE SCOPES

- Display four traces
- Accept references for ratiometric measurements

The SS-6122 100-MHz and SS-6611 60-MHz portable oscilloscopes each have a 6-digit reciprocal counter. Each of the 4-channel scopes also has four on-screen cursors. The cursors can automatically track the 10 to 90% excursions of a waveform. Besides displaying the usual measurement readouts, the screen can show comments, such as the measurement setup, the contents, and the operator's name. The comments can be as long as 80 characters. The screens also show the date and time. The scopes can display ratiometric measurements referenced to previously entered voltage and time values. SS-6122, \$2295; SS-6611, \$1795.

Iwatsu Instruments Inc, 430 Commerce Blvd, Carlstadt, NJ 07072. Phone (201) 935-5220.

Circle No 396

Precision High Voltage Resistors and Resistor Networks from CADDOCK for high performance, high voltage systems.




Type TG Low TC Precision High Voltage Resistors with a TC of 25 PPM/°C from -55°C to +125°C and resistance values to 1,000 Meg.

Constructed with Caddock's Tetrinox® resistance films to achieve exceptional temperature and loadlife stability, the Type TG high voltage resistors are ideal for the precision circuitry of TWT power supplies, electron microscopes, X-ray systems, high resolution CRT displays and geophysical instruments.

The Type TG resistors deliver this outstanding combination of performance specifications:

 Temperature Coefficient of 25 PPM/°C from -55°C to +125°C



- Resistance range from 1 Meg. to 1000 Meg.
- Resistance Tolerances from 1.0% to 0.1%.
- Loadlife Stability of 0.25% per 1000 hours.
- Voltage ratings up to 48,000 volts.
- Max. Continuous Operating Temp. of +225°C.
- Exclusive Non-Inductive Performance.

plus - Matched Resistor Sets with Low Ratio Temperature Coefficient Tracking Performance.

The Type TG resistors can be used in combination with the low TC of Caddock's Type TK Low TC Precision Radial-Lead Resistors to achieve 30 PPM/°C Ratio TC without special matching.

With special matching, a Ratio TC of 10 PPM/°C can be achieved.

• For Type TG data, circle Number 101.




Type THV Thin-Profile 10 KVDC Precision Resistor Voltage Divider Networks with Ratio TCs to 10 PPM/°C from -55°C to +125°C.

Caddock's advanced high voltage resistor technology combines our high stability Tetrinox® resistance films with laser-generated V-Notch Geometry (Pat. Pend.) to produce this compact high voltage divider network.

The performance of these high stability networks includes these special features:

- Standard Input Resistance of 100 Megohm with custom resistances available.
 Standard Voltage Division Ratios of 1,000:1 or
- 100:1 with custom ratios available.
- Ratio Tolerances of 0.25%, 0.5%, 1.0% or 2.0% at 10 KVDC.
- Ratio Temperature Coefficients of either 10 PPM/°C or 25 PPM/°C from -55°C to +125°C.
- Non-Inductive Performance.
- Thermal coupling between the resistors in this single-substrate network provides excellent Ratio Temperature Coefficient stability.



- The thin-profile and 1.5 inch body length provides for easy packaging in spacesensitive designs.
- For Type THV data, circle Number 102.



Type MG Precision High Voltage Resistors with extended resistance range to 10,000 Megohm and a TC of 80 PPM/°C.

For greater **design flexibility**, Caddock's 'family' of Type MG resistors has been expanded with additional models and now includes 23 models that permit designers to select the optimum resistor size, power rating and voltage rating for each application, as illustrated by the four models of 4,000 volt, 1-inch long resistors shown here:



The Type MG high voltage, high stability resistors include all of these performance specifications:

- Standard Temperature Coefficient of 80 PPM/°C.
- Resistance values to 10,000 Megohm.
- Resistance Tolerances from 1.0% to 0.1%.
- Loadlife Stability better than 0.8% per 1000 hours.
- Voltage ratings up to 48,000 volts.
- Max. Continuous Operating Temp. of +225°C.
- Exclusive Non-Inductive Performance

Most models of these high voltage resistors are manufactured with Caddock's Exclusive Non-Inductive Design for improved per-



formance in high frequency, pulse and wide-band circuits.

• For Type MG data, circle Number 103.

Caddock's new 28-page General Catalog describes over 200 models of standard and custom precision and ultra-precision resistors and resistor networks. For your personal copy, call or write our main offices at –


Caddock Electronics, Inc., 1717 Chicago Avenue, Riverside, California 92507 ● Phone (714) 788-1700 ● TWX: 910-332-6108



HIGH PERFORMANCE FILM RESISTORS

CIRCLE NO 104

PCB Switches... and a lot more!



Switch with confidence... Switch to JAE!

For reliable PCB switches, switch to JAE Electronics—a leading manufacturer of electronic components for over 30 years. JAE PCB switches are available in three different versions—all with gold-plated wiping contacts:

Machine-Insertable DIP Switches—51D Series

- Reliably sealed for automatic soldering and cleaning.
- Truly machine-insertable with standard IC handling equipment.

Binary Coded Rotary DIP Switches—41/42J Series

- Bit designated terminals are shorted automatically for each setting.
- Switches have reliable seal for automatic soldering and cleaning.

PCB-Mounted Thumbwheel Switches—22J Series


- Larger size of these switches allows for thumb, as well as screwdriver actuation.
- All mounting orientations available.
- Bases are sealed for automatic soldering.


Switch with confidence. Switch to JAE. Call or write today for more information on JAE's PCB switches, lighted pushbutton switches, miniature pushbutton switches, keylock switches, and flat panel keyboards, plus a complete line of connector and fiber optic products.

JAE Electronics, Inc. 1901A E. Carnegie Avenue Santa Ana, CA 92705 (714) 250-8770 Telex 681-438 (JAE US) (800) JAE-PART (523-7278) Toll free except in California and Alaska



JAE Electronics, Inc.







51D Series

220

CIRCLE NO 85

EDN March 4, 1987

EDN PRODUCT MART

This advertising is for new and current products.

Please circle Reader Service number for additional information from manufacturers.

9-Track Tape Subsystem




Now you can exchange data files between your IBM PC/XT/AT and any mainframe or minicomputer using IBM compatible 1600 BPI 9-Track tape. Unit can also be used for disk backup and archival storage. Transfer rate is one megabyte per minute on PCs and 100% compatibles. Subsystems include 7" or 10 ½" streaming tape drive, tape coupler card and DOS compatible software. and DOS compatible software. Prices start at \$3,555.

JUALSTAR

9015 Eton Ave., Canoga Park, CA 91304 Telephone: (818) 882-5822

CIRCLE NO 325



PRODUCTION PROGRAMMER "Very Fast" 16 at-a-time in Gang MODEL 828 \$2350.

digelec PROM & LOGIC — PROGRAMMERS —

QUALITY - RELIABILITY - USER SUPPORT

 Typical program & verify speeds: 16 ea 2764A 15 seconds 16 ea 27128A 28 seconds 16 ea 27C256 58 seconds

· No adapters, no modules

• Programs 2716 to 27512 & equivalents

Stand-alone operation & UPGRADEABLE
 PHONE 201-493-2420
 DIGELEC, Inc.
 1602 Lawrence Ave., Ocean, NJ 07712

CIRCLE NO 327

EPROM PROGRAMMER \$349



The EP-1 is a great value, here's why:

- IBM PC Software included or RS-232 to any computer
- ASCII Command driven operation; All intelligence in unit Reads, Programs, Copies over 150 types from 2716 to 27512

- P. Reads, Programs. Copies over 150 types from 2716 to 27512

 Optional Intel microcontroller programming head

 Menu-driven Chip Selection; No Personality Modules

 Past, Slow, Cluck-Pulse Programming Algorithms

 Intel (8080 & 8680, Motorola, Tekhex, Straight Hex Files

 Splits Files by Base Address and Odd/Even (16 bit systems)

 Gold Textool ZIF (Is Goocket

 Feel Checksums

 Over-Current Protection

 8 Baud Rates 300 to 38,400

 WK.ROSYSTEMS


 OR881 Haddington, #190/ Houston, TX 77043

 (713) 461–9430

 (800) 225-2102

(713) 461-9430 (800) 225-2102

CIRCLE NO 328



GR MINI-INDUCTOR

AIE Magnetics introduces a new miniature inductor, for use in .1 to 1 amp switching regulators, that offers a lower cost and smaller size than previous units. They also provide higher efficiencies as well as high inductance and increased current levels. The units are self-shielding for less radiated noise and sealed for compatibility with all types of cleaning systems. AIE Magnetics, 701 Murfreesboro Road, Nashville, Tennessee 37210, 615/244-9024.

CIRCLE NO 329



SPACE-SAVING SUBMINIATURE JOYSTICK


The Model 462 subminiature force operated joystick offers high performance in a small package. This two axis proportional control is only 3/8 inch in diameter with a back of panel depth of less than 1/2 inch making it ideal where space is an important factor. It performs positioning and tracking tasks fast and accurately, and provides high resolution, with

continuous output and no dead zone.

Measurement Systems, Inc., 121 Water
Street, Norwalk, CT 06854 (203) 838-5561.

CIRCLE NO 330

To advertise in Product Mart, call Joanne Dorian, 212/576-8015



DIP ISOLATOR. Isolate any pin of a socketed DIP IC. Test points on both sides of each isolation switch allow monitoring or connection. Ideal for prototype debugging. Models available from 8 to 40 pins. Choose gold hi-rel or ZIF socket.

BETA AUTOMATION INC.

3541 Old Conejo Rd. Newbury Park, CA 91320 805/499-5785


CIRCLE NO 331



EPROM PROGRAMMER

MODEL EP-2B-79 with software MS-DOS, CP/M, Apple, Atari Pet, AIM-65, SYM-1, VIC-20, C-64, H-8, H-89, SS-50, TRS-80 (1&3), and S-100. Programs 2708, 2716, TMS2716, 2732, 2732A, 2532, 2764, 2564, 27128, 27128A, 27256, 27512 and MCM68764 EPROMs; 2816A, 2864A, EEPROM; 8751, 38E70 8748 MPU Price \$179 with personality modules \$17 to \$35, Software \$21 to \$40.

Optimal Technology Earlysville, VA 22936 804-973-5482 CIRCLE NO 332



FREE DEMO DISK

SCHEMA is a complete, integrated schematic drawing software package for IBM Personal Computers. Use SCHEMA with your PC to draw schematics and automatically generate design documentation such as Wire and Net Lists, Bills of Materials, Design Rule Checks, etc. SCHEMA is \$495 and supports most common PC hardware configurations. Call or write today for a free demo disk and brochure.

OMATION INC.

1701 N. Greenville Ave., Suite 809 Richardson, TX 75081 (214) 231-5167

CIRCLE NO 333



Atonly \$9/5, no electrical enginee can afford to be without this end-to-end circuit design, simulation and PCB layout tool.

You can pay up to 15 times more and still not get all the features offered by EE Designer—Schematic Capture...Circuit Simulation...PCB Layout.

30 day money back guarantee. Full purchase price refunded if not completely satisfied.

Call 1-800-553-1177 today to order your package. Bank cards welcome.

343 Gibraltar Drive Sunnyvale, CA 94089

CIRCLE NO 334

NEED CIRCUIT PROTECTION?



E-T-A has "THE RIGHT STUFF!"

- Commercial, Mil & Low Cost Types Magnetic or Thermal ● 0.05 to 400 A, 250V AC or 28V DC
- ON/OFF Switch/Breaker Combination
 PC Board & Snap-in Mounts

E引心 CIRCUIT BREAKERS

7400 North Croname Road, Chicago IL 60648 • 312/647-8303

CIRCLE NO 335


A Lot For A Little

Reach 137,000 specifiers of electronics components, equipment, and systems for only \$725.

EDN Product Mart

CIRCLE NO 336

Simulator/Debugger for IBM-PC for 8048 - 8051 - 8096 µCs




Execute and debug code for popular single chip microcomputers on your IBM PC. Dynamic display with windows for source code, control flow, registers, flags, memory, commands, and more! Set breakpoints, traps, etc. Crossassembler & EPROM programmers, too.

| Solution | Solution

CIRCLE NO 337

6800/6809 Micro Modules



dedicated control and monitoring. Interfaces for sensors, transducers, analog signals, solenoids, relays, lamps, pumps, motors, keyboards, displays, IEEE-488, serial I/O, floppy disks.

WINTEK

Millek Corp. 1801 South Street alfoyette, IN 47904 117-742-8428 300-742-6809

CIRCLE NO 338

EPROM/PAL Prog. LOGIC/DATA Analyzer

TEM PC

 EPROM PROGRAMMER
 \$350

 2716 Through 271024
 \$250

 PAL OPTION
 \$250

 20 and 24 Pin Pals
 \$100

 MP OPTION
 \$100

 8741/42/48/49/51

 BIPOLAR OPTION
 \$350

16, 18, 20 & 24 Pin Proms HITACHI/INTEL

50 MHZ. 8 Channel expandable to 32

EPROM SIMULATOR\$395

FREE DEMO DISK

2780 S.W. 14th Street Pompano Beach, FL 33069

1-800-9PC-FREE 1-305-975-9515

CIRCLE NO 339



- portable, independent, easy-to-use development system works under MS-DOS, PC-DOS, VMS, Micro-VMS,
- UNIX, and XENIX.

 SLICE source langage in-circuit emulation nonintrusive symbolic de-bug package for C and assembly
- level code.

 universal supports various families: 8086, 8088, 80186, 80286, 68000, 68010, 68020, 68008.
- extremely powerful breakpoints, triggering, and trace capabilities on C, assembly, and bus cycles

 on-line HELP available.

It's the world's best microprocessor development system. Challenge us to prove it. Call 1-800-435-5001 or 617-769-2980.

EMULOGIC

One Edgewater Drive, Brookside Park Norwood, MA 02062

CIRCLE NO 340



5 Watt surface mounting DC/DC Converter Are you still looking for a 5 watt industrial standard DC/DC converter featuring,

Wide input voltage range Constant high efficiency Input reflected ripple according CEPT No opto couplers in feedback loop MTBF 235,000 hours Surface mount technology
TPI can now offer you the PSCM Series.

Total Power International, Inc. 418 Bridge St., Lowell, Ma. 01850 (617) 453-7272

CIRCLE NO 341

Waterproof **Potentiometers**




Cermet and wirewound panel potentiometers. All-Metal . High-Quality 100% Checked for Water-Tightness 1/2", 5/8", 3/4" Diameters Panel and PC Board Mounting Linear and Log Tapers, 1-3 Watt Ratings Normal cycle life - 25,000 operations

WILBRECHT ELECTRONICS, INC

(612) 222-2791 240 E. Plato Bivd. • St. Paul, MN 55107

Call for prompt quotation

CIRCLE NO 342



Send for our new Engineering Design Guide. It contains the do's and don'ts for designing with welded wire. And it is loaded with tips for using steel wire construction to replace sheet metal,

plastic or castings. E.H. Titchener & Co., 28 Titchener Place. P.O. Box 1706, Binghamton, NY 13902, Phone: 607-772-1161.

CIRCLE NO 343




CIRCLE NO 344



5W .375" PROFILE DC/DC CONVERTERS

50 Models available in 2" x 1" x .375" pkg. w/fully regulated outputs. State-of-the-art design and packaging insures high performance and reliability. Inputs range from 5 to 48VDC. Outputs are 5, 12, 15, \pm 5, \pm 12, \pm 15V at 5W typ. Dual Isol. outputs also avail. Other specs include; Vin accy ±10%, Vout accy ±1% 200KHZ switching freq. Prices from \$65 (1-9) Conversion Devices, Inc., 101 Tosca Dr., Stoughton, MA 02072. Call for tech. data 617/341-3266.

CIRCLE NO 345



NEW PGA MICRO/Q® CAPACITORS

Reduce voltage noise spikes, achieve effective decoupling on complex multi-layer PC boards. Low-impedance, low-inductance decoupling for VLSI PGA packages and LCC sockets. Available in a range of pinout configurations. Rogers Corp., 2400 S. Roosevelt St.,

Tempe, AZ 85282, 602/967-0624. **CIRCLE NO 346**



IEEE-488 CONTROL FROM YOUR PC.

- □ Emulate hp and Tektronix controllers.
- ☐ Fast and easy-to-use. Thousands sold.
- ☐ Program in BASIC, C, FORTRAN, or Pascal
- ☐ Hardware and software \$395 complete.



Capital Equipment Corp. 99 South Bedford St. Burlington, MA. 01803 Call today 617-273-1818

CIRCLE NO 348

CIRCLE NO 347

To advertise in Product Mart, call Joanne Dorian, 212/576-8015



smARTWORK® Circuit-Board-Artwork Software. For only \$895, smARTWORK® lets the design engineer create and revise printed-circuit-board artwork on the IBM Personal Computer. Forget the tedium of taping it yourself or waiting for a technician, draftsman, or the CAD department to get to your projects. With **smARTWORK®** you keep complete control over your circuit-board artwork from start to finish. Call or write to Wintek Corporation, 1801 South Street, Lafayette, IN 47904-2993. (317) 742-8428, (800) 742-6809.


CIRCLE NO 349



12 BIT HIGHLY ISOLATED DAC

Combines all features for harsh or noisy industrial environment. Modular 12 bit, w/serial or parallel inputs and 500VDC max. isolation between inputs-tooutputs. Unip. or bipolar 5 output voltage ranges @ 3 µsec settling, 2 current outputs and bi-directional current loop of ± 20mA. Internal DC/DC converter w/5VDC input need. Size 3" x 2" x .375". Price \$239 (1-9). Conversion Devices, 101 Tosca Dr., Stoughton, MA 02072. Call for tech. data 617/341-3266.

CIRCLE NO 350



- For IBM-PC/AT/XT and compatibles
- •Dual RS-422/RS-485 interface
- Differential drivers to 4000 ft.



478 E. Exchange St. Akron OH 44304 (216) 434-3154 TLX: 5101012726

CIRCLE NO 751

or all your telecom equipment design needs:

- Call Progress Tone Detectors & Generator CMOS detectors for telephone system tones (dial tone, ringback, busy, special information); CMOS generator for standard call progress
- DTMF Receivers High quality receivers for all applications.
- MF Receivers & Generator CCITT R1 & R2 receivers; CMOS generator IC.
- DC Signalling Products Line sense relay; Dial pulse counter & hook status monitor IC; Binary input pulse dialer IC.

TELTONE

10801-120th Avenue NE, Kirkland, Washington 98033

1-800-824-4246

CIRCLE NO 752



Flow Charting II+ The New Plus for Fast Flowcharting

FLOW CHARTING is new! It's now

Flow Charting II+, with more speed + more functions + more printing options;

· 10 text fonts; 26 shapes; · Line mode can stop at a shape; * Backspace key can erase a line to its origin; * Free text entry anywhere, or select auto-centering; * Vertical or horizontal printing; one chart or multiple charts.

Used by Fairchild, Bechtel and more than 500 other major corporations. Edit quickly and accurately — even major edits — with Flow Charting II+, the Specialist. See your retail store or call:

PATTON & PATTON

800/672-3470, ext. 897 California

800/538-8157, ext. 897 National 408/629-5044 International)


CIRCLE NO 753

Join Forces

Combine your larger ads with EDN Product Mart ads for a total marketing program.

EDN Product Mart


CIRCLE NO 754



A powerful control computer based on the new Hitachi 6303Y and high level language Forth. 100mm×72mm. 30K bytes RAM, 16K dictionary RAM/PROM, 256 bytes EEPROM, 16K Forth. You can attach 64 key keyboard, LCD and 1²C bus peripherals. Built in are interrupts, multitasking, time of day clock, watchdog timer, full screen editor and symbolic assembler. 32 parallel and two serial ports. Single power supply and low power 3mA OPERATIONAL mode. Buy direct from England. \$295 inc airmail. Phone +44-1-520-0442.

Triangle Digital Services Ltd 100a Wood Street, London E17 3HX

CIRCLE NO 755



SAVE SPACE WITH Q/PAC® COMPONENTS

- Provide built-in capacitance
- · Eliminate decoupling capacitance
- · Gain 4-layer board quietness with 2-layer economy
- · Vertical or horizontal mounting

Send for Rogers Q/PAC® Application Bulletin.

Rogers Corp., 2400 S. Roosevelt St. Tempe, AZ 85282

CIRCLE NO 756

602/967-0624



NEW ENGINEERING SOFTWARE

Filter designs active filters up to order 30. Bessel, Filter designs active filters up to order 30. Bessel, Butterworth, Chebyshev, Allpass; High, Low Bandpass and Bandstop. Fully menu driven, Filter designs, plots, and selects component values for any filter in seconds. LSAP analyzes linear systems producing Bode, Nyquist, Impulse, Step Response and Root-Locus plots. Micro-CSMP simulates control and servo systems with full support for nonlinear behavior. Filter is \$750, LSAP is \$450, Micro-CSMP is \$900 for the IBM PC.

California Scientific Software

1159 North Catalina Ave, Pasadena, CA 91104 (818) 798-1201

CIRCLE NO 757

To advertise in Product Mart, call Joanne Dorian, 212/576-8015

Applications information for data communications

This catalog establishes the applications that are appropriate for Series II and Bump protocol-conversion hardware. The publication lists the types of devices and protocols that the hardware and firmware connects to, and covers such modes of communication as LANs and X.25 satellites.

Datagraf Inc, 8305 Highway 71 West, Austin, TX 78735.

Circle No 397

Guide to Macintosh software

The winter edition of *MacGuide* contains an up-to-date listing of more than 2000 programs that are available for the Apple Macintosh. For each software package, the publication includes product name, vendor name, suggested retail price, and program description. \$4.95; \$1 for shipping and handling.

Menu, 1520 S College Ave, Fort Collins, CO 80524.

Circle No 398

Wall chart depicts PLDs

This wall chart provides a convenient reference to all types of programmable semiconductor devices. It's divided into sections that tabulate all PLDs, EPLDs, GALs, bipolar and CMOS PROMs, EPROMs, EEPROMs, and microprocessors. The information listed includes programmable-array size, the number of pins, and the company's identifier code for each device.

Stag Microsystems Inc, 3 Northern Blvd, Amherst, NH 03031.

Circle No 399

Data sheet details fault-tolerant computers

This preliminary data sheet covers 200/400XR Series fault-tolerant computers and how they bring fault tolerance into the supermicrocomputer and minicomputer price range. Along with block diagrams

and a black-and-white photo, the 6-pg publication gives an overview of system operation, lists optional communications interfaces, describes the different configurations, and devotes an entire page to complete specifications.

Parallel Computers Inc, 3004 Mission St, Santa Cruz, CA 95060.

Circle No 400



Catalog presents interconnect devices

This 84-pg catalog features the company's line of interconnection products. The sockets and adapters are available in SIPs, DIPs, zig-zag configurations, and over 150 low-insertion-force, pin-grid-array footprints. In addition, you can order them with standard glass-filled molded polyester, high-temperature Rynite, and FR-4 fiberglass epoxy; vou can order the Peel-A-Way terminal carriers in Mylar or Kapton. The catalog covers such new products as hybrid sockets with surfacemounted components, single- and dual-beam connectors, multilaver wire-wrapped boards, and surfacemount decoupling capacitor sockets. Request Catalog #7.

Advanced Interconnections, 5 Energy Way, West Warwick, RI 02893.

Circle No 401

Test-and-measurement accessories cataloged

Publication No 5954-0193D describes this company's test and measurement accessories that are available in the US by phone order for same- or next-day shipment. The

catalog is organized into four sections: accessories and cables, rack mounts and cabinets, supplies, and instruments. It lists products alphabetically, numerically, and by equipment reference. The catalog also contains selection guides, flow diagrams, and compatibility charts to help you find the right products for a particular application.

Hewlett-Packard Co, 1820 Embarcadero Rd, Palo Alto, CA 94303.

Circle No 402

Directory for software

A group of software publishers have cooperated in putting together this 16-pg newspaper. It describes each business-oriented software package with enough detail to make a purchasing decision. Participants include the following companies: Turner Hall Publishing, Software Concepts, Polytron, Rocky Mountain Software Systems, Spectre Technologies, North Edge Software, Permar & Associates, DGH Software, Bruce & James, Olympus Software, and Maxthink.

Cooperative Software Catalog, 1641 S Lansing St, Aurora, CO 80012.

Circle No 403

Newsletter covers µP development system

A quarterly newsletter discusses topics of interest to users of microprocesser development systems (MDSs) for 64180, 6301, and 8051 μP projects. This 6-pg issue features an article comparing the cost and performance of PC-based MDS tools vs traditional mainframe MDSs. In addition to including selected application notes, the paper lists and briefly describes other application notes available upon request.

Ashling Microsystems Inc, 542 Lakeside Dr, Suite 2, Sunnyvale, CA 94086.

Circle No 404

Using the CAE and CAD design tools of a variety of companies

—just as you would, if you could, in your workplace—

we've made the links, set-up the interfaces

necessary

for a complete, end-to-end circuit and systems design



Data Flow Chart

Central Processor Workstation Local area networking

Local area networking File storage/management Data formatting/translation Application processing DIGITAL EQUIPMENT CORP. Ethernet and TCP/IP

System Design Workstation

Workstation
Definition of functional system
requirements
Data flow modeling
Mapping of detailed
system structure

Circuit Design Workstation

Workstation
Creation of circuit
library elements
Hierarchical circuit
definition
Schematic capture
Circuit simulation/

analysis

Test Simulation/ Programming Workstation

Fault coverage analysis IC test program generation PC board test program generation IC Layout Workstation

Creation of device/ cell library clements Physical chip autolayout Electrical/design rule check PG postprocessing PC Layout


Workstation
Creation of
component
library elements
Auto-layout of
circuit board
Design rule check
Documentation
Artwork/NC
postprocessing

Testing Workstation

C device testing PC board testing Assembly Design Workstation

Assembly layout Thermal/ mechanical stress analysis Documentation Outputs Workstation

Pattern/artwork generation Layout checkpots Detailed drawing generation



Large-screen projection systems provided by Electrohome, Ltd. - Ontario, Canada

Come, see, question and discuss at...

||||||Automated |||||Design and March 31-April 2, 1987 Anaheim Convention Center North Hall

Anaheim, California

Exhibit Hours: 8:00 a.m.-5:00 p.m. Tues. & Wed. 8:00 a.m.-4:00 p.m. Thurs. Sponsored by:

ED

Endorsed by: Electronic Business Electronic Packaging and Production Design News Semiconductor CEG"

A Member of:

Cahners Exposition Group 1350 E. Touhy Ave.


P.O. Box 5060 Des Plaines, Illinois 60017-5060 Phone: (312) 299-9311 Telex 256148 CEGCGO DSP

©1987 Reed Holdings, Inc.

PROFESSIONAL ISSUES

A study in contrasts: US engineers recall their visit to Japan

Deborah Asbrand, Associate Editor



While on a fellowship in Tokyo, Anderson Howard, a US graduate student in electrical engineering, attended a conference of Japan's Institute of Electrical and Communications Engineers. He expected it to be similar to large American technical conferences that he had attended. But what Howard found at the Japanese conference surprised him. Instead of presenting a program of about 200 presentations, each lasting 30 to 45 minutes, the Japanese conference featured 2800 presentations. each lasting 15 minutes.

The goal of Japanese professional societies at their technical conferences, Howard discovered, is to give attendees a broad sample of ongoing technical research. American conferences, on the other hand, generally cover a narrower range of technology in greater detail.

This dissimilarity between the American and Japanese engineering communities was just one of the differences Howard noted during his stay in Japan three years ago. Howard's 8-month visit was sponsored by the American Electronics Association's Japan Fellowship Program, a 3-year-old venture that sends American students to work for Japanese companies. With few other programs offering similar opportunities, the AEA fellows who subsequently enter the US electronics workforce become members of a small group: US engineers with firsthand knowledge of Japanese engineering practices.



PROFESSIONAL ISSUES

The members of the first AEA-sponsored contingent, which included Howard and five others, currently work for such American electronics concerns as Hewlett-Packard, Apple Computer, Daisy Systems, and Westinghouse Electric. Having now worked two years for their US employers, they can attest to differences between the two countries' engineering education, industry training, and job responsibilities. But the greater distinctions, they say, lie in each country's cultural nuances.

What prompted the AEA to initiate the program was not a need to explore cultural nuances, but a need to address serious economic problems between the US and Japan, and to offer a way to ease the resulting tensions. In 1983, with trade between the US and Japan climbing to record imbalances in Japan's favor, concern about the trade deficit was increasing among US electronics companies. The AEA, which represents more than 2800 US electronics companies, decided that a cooperative venture between US and Japanese companies would be a welcome gesture towards smoother relations between the US and Japan, says Pat Hill Hubbard, the AEA vice president of engineering

and management education.

A deficit of another kind also was a factor in the association's decision to sponsor a fellowship program. "The Japanese were sending about 400 engineering students each year to study in US universities, while the US was sending about seven students to study in Japan," Hubbard says. "They were learning all about us and we weren't learning anything about them." The real goal of the fellowship program, Hubbard says, became one of introducing more US engineering students to Japanese culture.

An important aspect of learning about Japan's culture, Hubbard believed, included studying the complex Japanese language. Hubbard says that some supporters of the program chafed at this proposal, noting that the study of English is a requirement in Japanese schools, and that, as a result, most Japanese workers have at least a passing familiarity with the English language. Consequently, the AEA fellows would be able to communicate with their Japanese counterparts well enough to get by with no special training. Hubbard, however, disagreed.

"As we began to research the program, one of the problems we saw

was the differences in the cultures. Culture is reflected in language. We wanted the students to establish long-term relationships with their coworkers that would be above trade politics." Hubbard's persistence has paid off: Before leaving for their Japanese assignments, AEA fellows spend nine weeks in an intensive Japanese-language class at Cornell University. There, they spend six hours each day listening to native Japanese speakers, participating in conversation drills, and learning the intricacies of the language. To keep up with the class, they usually spend several hours each night reviewing the day's lessons.

The students' experiences in Japan bore Hubbard's theory out. The nine weeks of language study were rigorous, they say, but provided them with "survival level" language skills. They were able to ask directions, ride the subway, order food, and hold simple conversations. More important, though, their attempts to speak Japanese favorably impressed their hosts.

"The Japanese assume Americans and Europeans know nothing about the culture and speak no Japanese," recalls Bruce Gaya, who was developing a compiler for a new architecture as part of his graduate work at Carnegie-Mellon University when he went on the fellowship. "Having a little bit of [language] background made them accept me more. They appreciated it and were surprised by it." Gaya now works as a software engineer for Apple Computer's product-development group in Cupertino, CA.

Once the students were settled into their Japanese living quarters—which in most cases was a company dormitory—the students were briefed on the work they'd be doing for their host companies. The projects on which the students worked were varied: artificial intelligence, manufacturing automation, and analog-to-digital conversion.

At Oki Electric in Tokyo, Gaya

How the Japan Fellowship Program operates

The American Electronics Association Japan Fellowship Program has sponsored 26 students since its inception in 1984. The program is open to all US graduate students in electrical and computer engineering or computer science. Once selected as fellows, the students are matched with Japanese host companies based on mutual technical interests. Students work for their Japanese hosts for nine months to one year.

The program is jointly funded by American and Japanese electronics companies. American companies' contributions pay for the students' tuition and expenses while enrolled in an intensive 9-week language class at Cornell University. The Japanese host companies, which have included Sony Corp, Fujitsu, Hitachi, and Oki Electric, pay for the students' travel, housing, food, books, and research materials, and they offer a monthly stipend. In addition, a grant from the National Science Foundation matches contributions from US supporters.

PROFESSIONAL ISSUES

worked with Japanese engineers on an artificial-intelligence research project. Gaya's colleagues were intent on learning more about software, an area to which they ceded American superiority. "They felt that in the area of chips and hardware, Japan was better," he says. "But they felt American software and artificial intelligence were far superior. They wanted to work hard to catch up and develop an artificialintelligence capability at Oki."

Education and training

The engineers with whom Gaya worked were technically astute, he says, but their training differed from that of most American engineers. "My group wasn't trained as engineers," he says. "They were trained as scientists, and they came to Oki and learned [engineering] there. [My coworkers'] software skills weren't that great. Japan as a whole is lacking good software."

Because of their scientific backgrounds, Japanese engineers are less specialized than American engineers, says Jeff Funk, a senior engineer at Westinghouse Electric's research and development laboratory in Pittsburgh, PA. "In Japan, the university education is generalized. When they join a company, Japanese engineers receive a great deal of training. Their responsibilities are broader than American engineers'. When Japanese engineers design a product, for example, they're forced to talk to manufacturing people when they're designing." Funk traveled to Japan upon completion of his doctorate degree in engineering and public policy at Carnegie-Mellon University in Pittsburgh. In Japan, he studied factory automation and visited the factories of 15 companies.

Anderson Howard's association with Japanese engineers dispelled for him the notion that Japanese technology is secondhand. "Before I went over, I had the impression that the Japanese just copy Americans and don't do basic research," he

says. "But it's apparent that they conduct a lot of basic research now. They're sensitive to the feeling that their technology is inferior, and they hate being thought of as copycats. They want to be thought of as world-class leaders in technology."

Howard adds that competition among Japanese companies is intense. A likely cause of such rivalries is the nation's seemingly tireless interest in electronics, evident serve the employer. Your own desires and wishes are nothing compared to what's good for the company." Now working in Silicon Valley, Gaya marvels at the different credo he finds among the valley's workers: "Here, people stay with the job as long as it's good for them. There's little loyalty to the company, only to yourself."

At NEC, where Howard worked while in Japan, the work environ-

Japanese engineers "felt that in the area of chips and hardware, Japan was better. But they felt American software and artificial intelligence was far superior."

in the akihabara, the section of Tokyo where hundreds of consumerelectronics vendors line the storefronts. Howard, too, succumbed to the excitement of the district, purchasing a pair of stereo speakers and a Walkman radio while he was there.

Mastering Japanese etiquette

The greatest differences between American and Japanese engineers, the men noted, were in their relationships with their respective employers. In Japan, the boundaries of acceptable and unacceptable behavior are rigid by comparison with US standards.

Gaya inadvertently discovered the importance of remaining within those boundaries. Interested in extending his stay in Japan, he began negotiating with his supervisors at Oki Electric. He soon found that, among his engineering peers, his engagement in a time-honored American custom—haggling over salary—was a faux pas by Japanese standards.

"I had one colleague come up and say 'How could you ask for more money? This is terrible!" Gaya remembers. "There's a whole feeling that the company is like your mom and dad. If the company says something, you do it. They feel they must ment combined a measure of flexibility with rigid guidelines. To help employees better accommodate their family's schedules, the company allows them the choice of beginning work each day at 8:30, 9:00, or 9:30 am. Yet arriving even one minute late exacts a stiff penalty upon employees: They owe the company one half hour of overtime as compensation. As a result, Howard says, "It wasn't uncommon to see people running from the train station in their suits to arrive at work on time."

Japanese Bandstand

Company-sponsored festivities, however, were common. strengthen the family-like bonds between the company and its employees, attendance at company parties is limited to employees—no family members are welcome. Invited to one such party after working at NEC for just one month, Howard was asked to make a speech and sing before the 50 celebrators in attendance. He was reluctant to address the crowd but aware that the invitation was an honor and not to be declined. Gamely, he gave a short speech and then sang "Yesterday" by the Beatles. When his coworkers called for an encore, he followed with a rendition of a song

Buy DIRECT and SAVE!

Global \$199 LTC-2 Logic Test Analysis Kit

- High speed
- Includes LP-3, DP-1, LM-1 and more
- · Storage/carrying case

You'd expect to pay \$300 or more for a logic test analysis kit with the LTC-2's capabilities and performance features. But for a limited time we're offering this special price—\$30 off our already low catalog price of \$229—to introduce you to the incredible bargains you'll find in solderless breadboarding products, logic analysis equipment and test and measurement instruments in our new Global Direct Catalog.

Call TOLL-FREE

1-800-345-6251
(1-800-445-6250 in Connecticut)

To order your LTC-2 at this special price simply call our toll-free order line, mention this ad and have your Visa or MasterCard ready. Or send your check with the coupon below.

There's a lot in our new catalog that will interest you. Send in the coupon below and we'll put you on our mailing list.

FREE Catalog



- □ Enclosed is my check for the LTC-2.

 (CT and CA residents include state sales tax.)
- □ Please send your new Global Direct Catalog.

Name

Company

Address

City

State Zip



Global Specialties Mail Order Division P.O. Box 1405 New Haven, CT 06505

ISSUES

popular with many Japanese, "I Left My Heart in San Francisco."

Now employed by Hewlett-Packard as a development engineer, Howard continues to correspond with Japanese friends, and last year he was visited by three NEC researchers. To maintain his language skills, he watches a local Japanese television news broadcast each night. He has given talks on his experiences in Japan for Hewlett-Packard and for the AEA. In his talks, he says, "I've helped to open

The Japanese are "sensitive to the feeling that their technology is inferior, and they hate being thought of as copycats. They want to be thought of as world-class leaders in technology."

people's eyes about what Japan is like. I've encouraged them to study the language."

Indeed, his study of the language has provided him with a distinct professional advantage: Now able to read Japanese, he can explore Japanese electronics journals for research and development information. And it's this type of reciprocation that may bring a greater understanding between the two cultures: Gaya reports that the Japanese engineering community has long recognized the importance of reading English. At Oki Semiconductor, his engineering group had two translators whose only job, he says, was to "search through American journals and cut out articles for the engineers to read." Turnabout is fair play.

Article Interest Quotient (Circle One) High 518 Medium 519 Low 520

See Who Really Won the 32-Bit Shoot-Out!

Get your own copy of the 4 hour, "Shoot-Out at the 32-Bit Corral" held in the heart of Silicon Valley on September 18, 1986.

Watch 6 top vendors present their 32-bit product line and see how 12 demanding systems designers interrogated, explored, and provoked full disclosure with no holds barred.

Vendors:

- AT&T
- Motorola
- Fairchild
- National SemiNEC
- Intel •

Don't miss this unique opportunity to actually see the presentations, as they were given by each of the vendors.

Use this handy coupon to order your copy.



Electronic Trend
Publications
12930 Saratoga Avenue
Suite D1
Saratoga, CA 95070
(408) 996-7416

- Yes! Please send me _____ copies of the 4 hour, 3 VHS video tapes at \$195 per set.
- Please send me information on the "Shoot-Out" report and "The Impact of the 32-Bit Microprocessor on Computer Systems."

Name	
Title	
Firm	
Division	
Address	
City	
State	_ Zip
Phone	
Signature	

CIRCLE NO 35

CAREER OPPORTUNITIES

1987 Editorial Calendar and Planning Guide

Issue Date	Recruitment Deadline	Editorial Emphasis	EDN NEWS
Apr. 15	Mar. 26	Microprocessor Technology; Software Development; Digital ICs	
Apr. 30	Apr. 9	Communications Special Issue; ASICs; Test & Measurement	Closing: Apr. 2 Mailing: Apr. 23
May 14	Apr. 23	Analog Technology Special Issue; ICs; Test & Measurement	-
May 28	May 7	Computer Peripherals; Software; Power Sources/Devices	Closing: Apr. 30 Mailing: May 21
June 11	May 21	Math ICs; CAE; Computers	
June 25	June 4	ASIC (Semicustom ICs) Directory; Analog ICs; Surface-Mount Technology	Closing: May 28 Mailing: June 18
July 9	June 18	Product Showcase-Volume 1; ICs & Semiconductors; Software	Closing: June 25
July 23	July 2	Product Showcase-Volume II; Computers & Peripherals; Test & Measurement Instruments	Mailing: July 16
Aug. 6	July 16	Computer Boards; Digital Signal Processing; Test & Measurement; Top Ten Reader Vote Contest	Closing: July 23
Aug. 20	July 30	Military Electronics Special Issue; Fiberoptics; Software	- Mailing: Aug. 13

Call today for information.

East Coast Janet O. Penn (201) 228-8610 West Coast Dan Brink (714) 851-9422 National Roberta Renard (201) 228-8602

ENGINEERING (HW/SW)

Top Producer in the largest personnel network system currently has openings for ALL Engineering and computer professionals. Over 200 offices through the U.S. and Canada. All fees, interview and relocation expenses are borne by our client companies. Please call or submit your resume to:

RIKER PERSONNEL

8790 Purdue Road, Suite E Indianapolis, IN 46268 (317) 875-9911





First in Readership Among Design **Engineers and Engineering** Managers in Electronics

Massachusetts and Northeast

- Software
- Hardware
- Microwave
- Radar
- Circuits
- OC/Reliability
- Manufacturing

COMMERCIAL & DOD

We specialize in EE's, ME's and CS Software Engineers. Send resume to

HAMPSHIRE PERSONNEL SERVICE 241 KING ST., P.O. BOX 988 NORTHAMPTON, MA 01061 413-586-0088

Motorola **Opportunities**

VLSI ENGINEERS

Our Ft. Lauderdale, Florida Applied Research Organization has immediate opportunities for individuals with a BSEE or equivalent and a minimum of 5 years experience in the design and simulation of full-custom VLSI ICs.

The qualified individuals will explore new CMOS circuit applications for low power communications equipment, characterize emerging new semiconductor technologies and work with the latest computer-aided engineering tools to develop more productive design methods for Analog and Digital CMOS chips.

Motorola provides excellent salaries and benefits and relocation assistance to our beautiful South Florida location. For immediate consideration. please forward your resume with salary history to: Alan Waters, Professional Staffing, MOTOROLA, 8000 W. Sunrise Blvd., Ft. Lauderdale, FL 33322. We are an equal opportunity/affirmative action employer.



Share Our Success.

Digital's storage systems groups in Colorado Springs are committed to continued leadership in storage technology.

We have constructed one of the most advanced hi-tech design and manufacturing facilities in the country. And it is surrounded by acres of open land at the foot of Pike's Peak.

Disk Drive Design ELECTRICAL ENGINEERING SUPERVISORS

Supervise a technical staff of 6 to 8
Servo & recording channel experience
Analog & microprocessor experience
R/W channel PLO & AGC applications

SERVO ENGINEERS

Control theory expertise
Analog and microprocessor implementation
Positioners/actuators
Power amplifiers
Spindle drivers

READ/WRITE ENGINEERS

Recording channel development Head/media test & evaluation Head/media parametric optimization Standard setting and control

HDA MECHANICAL DESIGN ENGINEERS


Read/disk assemblies Positioners Actuator motors Spindles Air filtration systems

To share our commitment to success, send your resume and salary requirements to: Jerri Jason, Digital Equipment Corporation, Department 0215 7820, 301 Rockrimmon Boulevard South, CXO1-1/Q21, Colorado Springs, CO 80919.

We are an affirmative action employer.



E-SYSTEMS



YOU can make the difference at E-Systems.

How do we keep the edge that's made us the nation's number one developer and producer of electronic strategic and tactical deterrent systems? People.


And you, as a member of the E-Systems team, would work in an environment that inspires creativity and technical excellence — using the industry's most advanced computerized resources and sharing the expertise of the best engineers in America. We are constantly pushing America's leading-edge technologies across new and exciting frontiers.


Creative engineers can work wonders given the right conditions. So we've taken away much of the administrative paperwork to let our engineers concentrate on engineering — and they do just that.

E-Systems has pioneered and produced a broad array of electronic systems and products in the areas of intelligence and reconnaissance systems, command and control, specialized aircraft modification, guidance, navigation and control, communications and data systems.

We have immediate openings for experienced engineers in electronic design and analysis, EMI, specialized receiver design, and full-scale multi-array systems design, definition and integration.

If qualified and interested, submit resume to: Staffing Manager, E-Systems, Inc., Greenville Division, PO. Box 1056, CBN 81, Dept. EDN-0387ES, Greenville, Texas 75401. "Remember, you can make the difference."





TEST THE LIMITS OF COMMUNICATIONS TECHNOLOGY. THEN BREAK THEM.

At Xetron, new breakthroughs in communications technology take shape day after day. That's because we give our engineers the freedom to explore. And that's why you'll have the chance to break new ground, too.

As an engineer with Xetron, you'll contribute to one-of-a-kind communications systems for all types of military platforms. And you'll help us produce highly specialized components for these systems — from jam-resistant miniature micropower transceivers to frequency agile multicouplers and multiplexers, adaptive vehicular antenna, co-site filters, and more. In short, you'll define communications systems that work . . . in the lab and in the field.

If you're looking for a fast-growing company that lets you do what you do best, look to Xetron. We have immediate positions available for the following:

RF/ANALOG ENGINEER

Participate in the design, development, and manufacturing of HF/VHF/UHF microwave receiver and transmitter equipment. Requires BSEE plus four or more years design experience, including experience with tunable filters, VCO synthesizers, demodulator

and modulator (PSK, QAM, etc.) IF circuitry and audio circuitry.

ANTENNA DESIGN ENGINEER

Must have BSEE plus two or more years hands-on design and analysis experience with all types of antenna with a frequency range from VLF through MW.

LEAD ENGINEER

Supervise 6-10 engineers and technicians in developing RF system PRU, including: evaluating SRU designs, leading PRU design and interface efforts, monitoring schedule and budget performance, participating in monthly reviews, making presentations to customers, and leading SRU and PRU testing efforts. Requires BSEE plus at least five years of RF design experience, including experience in a leadership role. Excellent communications skills are a must.

RF DESIGN ENGINEER

Design, develop, and test RF circuits and subsystems to include: analyzing specifications; breadboarding and testing designs; developing engineering documentation; writing component specifications; guiding circuit layout; working with packaging designers,

vendors, and customers; and supervising/instructing technicians. Requires the ability to work independently in a lab or office, BSEE, and two or more years RF experience.

ELECTRICAL ENGINEER (RF)

Provide technical proposal support. Must possess solid analytical and practical experience in the development and analysis of RF systems (transceivers, filters VLF through UHF) and thorough knowledge of computer design and analysis software. In addition, you must have a BSEE along with strong oral and written communications skills and excellent leadership potential.

Break the limits of technology at Xetron. You'll find the technical challenge you need along with the rewards of our rapid growth, excellent compensation, and comprehensive benefits. To apply, please call or send your resume to Debbie O'Toole, Human Resources:

Xetron Corporation

40 W. Crescentville Road Dept. EDN 03-04 Cincinnati, Ohio 45246 (513) 671-5220

An Equal Opportunity Employer. U.S. citizenship required.



Subsidiary of Westinghouse Electric Corporation We make the right things happen.

SONAR & RADAR ENGINEERS

GE's Government Electronic Systems Division has outstanding opportunities available now for talented radar and sonar engineers. Located in Syracuse, New York, we offer low cost of living combined with excellent school systems and terrific recreational facilities. We've been a leader in the development of sonar and radar systems since the 1950's and we're continuing our growth into the 1990's.

The Following Opportunities are Available Now:

Systems Engineers—Radar/Sonar, with experience in:

- Large scale systems analysis, design, and development
 Specification development (including B-5
- specs)
 Algorithm development
- Performance monitoring/fault detection/ failover analysis
- Sensor systems design and development
 Signal/data processing design

Software Engineers/Managers—Radar/Sonar, with experience in:

- Real time software development in a VAX environment
- Top down structured design applying CMS-2/2M, ADA, Fortran, and other military languages
- Configuration management/customer documentation requirements under MIL-STD-483
- Software quality assurance/design review under MIL-S-52779
- Design of embedded programmable processor subsystems

Field Engineers—Radar/Sonar, with experience in:

- · Installation, check-out, and alignment of radar or sonar systems
 • Installation and check out of MOD and ECP kits

- Troubleshooting to component/replaceable level Graduate of a military electronics training school

Technical Training Specialists, with experience in:

- Defining courseware specifications for technical instruction in radar/sonar operation/maintenance
- Proficiency in several computer languages (must include PASCAL) and experienced in Computer Aided Instruction (CAI)
- · Platform training in a military environment

Your Background All positions require a B.S. degree or higher in one of the following disciplines: EE, Computer Engineering, Math, Physics, or Computer Science with at least 2 years of related experience. A.S. degrees with experience will be considered for field engineering positions—especially if you've graduated from military training schools.

Act Now For guaranteed immediate response, just send your resume. We'll do the rest. Write to us directly at: GE-Government Electronics Systems Division, Code ADEDN26, P.O. Box 309, Liverpool, New York 13088

U.S. Citizenship Required—Minorities, females, handicapped and Vietnam Era Veterans encouraged to apply No agencies please



The Future Is Working At General Electric



General Electric has been selected to lead a multi-year program to design a new generation of Test Instrumentation & ATE Systems

We are now entering the full scale development stage of this potential \$2 billion project.

GE Automated Systems Department

CASS (Consolidated Automated Support System) will be a totally integrated system incorporating new hardware and software specifically designed to standardize and consolidate test instrumentation systems for naval aircraft and shipboard systems. To accomplish our objective, General Electric's Automated Systems Department in Huntsville, Alabama will be recruiting technical professionals who are ready to design and develop a whole new generation of integrated test instrumentation and ATE hardware and software systems.

The Positions

Test Instrumentation Design Engineers – Perform circuit design on a wide range of RF, analog and digital instrumentation. You will also participate in the development of requirements specifications, technical concepts and plans for instrument designs. Requirements include a BSEE (or equivalent education/experience), previous exposure to CAE/CAD systems and extensive design experience with any of the following: Spectrum Analyzers, Vector Voltmeters, Digital Multimeters, Digital/Analog Oscilloscopes, Logic Arrays, Signal Processing Hardware, Network Analyzers, Synthesizers, Waveform Recorders, Pulse Generators, Custom Bipolar/CMOS and ECL.

Senior ILS Analysts- Applicants should possess a BS in Logistics Engineering, Electrical Engineering or another relevant technical discipline and a minimum of 5 years logistics engineering experience. Familiarity with U.S. Navy (preferably NAVAIR) logistics requirements would be a significant asset.

Software Quality Assurance Engineers – These positions will involve you in the development and implementation of software test/quality assurance plans and in the preparation of test procedures and specifications for systems and test program sets. Requirements include a BS in a relevant technical discipline, a minimum of 3 years experience with software engineering and/or software quality assurance, and a working knowledge of QA MIL-STDs.

TPS Development Engineers - Perform test requirements analysis of electronic assemblies, prepare test flow diagrams which specify automatic tests for electronic assemblies, and design analog, digital, and RF interface devices. Requirements include a BSEE and several years relevant ATE or analog/digital circuit design experience.

Huntsville Facts & Figures

These positions are available at General Electric's Automated Systems Department in Huntsville, Alabama. For those of you unfamiliar with Huntsville, you might be interested in a few facts. Huntsville, Alabama is home to more Fortune 500, advanced technology firms than many of America's largest cities. Yet, our cost of living (approx. 80% of most metro areas), our educational and cultural facilities, and the general quality of life in Huntsville makes our community one of the most "liveable" in the nation.

General Electric offers a competitive salary and benefits package, relocation assistance, and continued opportunities for both management and technical development. For immediate consideration, please forward your resume, including salary requirements, to: General Electric Automated Systems Department, 110 Wynn Drive, Huntsville, AL 35805, Attn: Dept. BN-10. U.S. Citizenship is required.

The future is working at General Electric.



NOW YOUR TWO FAVORITE TABLOIDS COME TOGETHER IN ONE HOT NEWSPAPER...



EDN NEWS

EDN Product News and EDN Career News, EDN's two tabloid editions, have merged to form EDN News...bringing you all the hottest news of products, technology, and careers. EDN News mails once a month to EDN's U.S. and Canadian circulation. Which means that EDN News and EDN magazine together give you near-weekly coverage of the electronics industry!

HOT NEWS OF PRODUCTS

The focus of EDN News is on hot products that will have the most powerful impact on the way you do your job. EDN News covers the best products on the market, how they evolved, and why. Plus, it now covers the industry events that drive product technology and hence product introductions.

HOT NEWS OF CAREERS

In a separate section, EDN News keeps you abreast of professional developments and job openings in the electronics field. It carries editorial aimed at your career and professional growth. Editorial that will help you find a job and keep it.

EDN News. Hot News of Products, Technology, and Careers

EDN March 4, 1987

0	EDN Databank	0
0	Professional Profile	0
0	Announcing a new placement service for professional engineers!	0
0	To help you advance your career. Placement Services, Ltd. has formed the EDN Databank. What is the Databank? It is a computerized system of matching qualified candidates with Service is nationwide. You'll be "The computer never forgets. When your will periodically be reviewed with you by a PSL professional placement person." Service is nationwide. You'll be "We hope you're happy in your current posi-"	0
0	positions that meet the applicant's professional needs and desires. What are the advantages of this new service? considered for openings across the U.S. by PSL and it's affiliated offices. by PSL and it's affiliated offices. Your resume this new service? this new service? this new service? That's why it makes sense for you to register	0
0	 It's absolutely free. There are no fees or charges. is carefully screened to be sure it will not be sent to your company or parent organization. with the EDN Databank. To do so, just mail the completed form below, along with a copy of your resume, to: Placement Services, Ltd., Inc. 	0
0	IDENTITY PRESENT OR MOST RECENTEMPLOYER	0
	Name Parent Company Home Address: Your division or subsidiary:	
0	City State: Zip: Location (City, State)	0
	Home Phone (include area code):Business Phone if O.K. to use:	
0	EDUCATION Major Field GPA Year Degree College or University Degrees (List)	0
0	Dagrees (List)	0
0	POSITION DESIRED	0
\circ	EXPERIENCE Present or Most Recent Position From: To: Title:	0
O	Duties and Accomplishments: Industry of Current Employer:	O
0		0
0		0
	Reason for Change:	
0	PREVIOUS POSITION:	0
_	Job Title:	0
O	Division: Type of Industry: Salary: Salary:	0
0	COMPENSATION/PERSONAL INFORMATION	0
_	Years Experience Base Salary Commission Bonus Total Compensation Asking Compensation Min. Compensation	_
O	Date Available I Will Travel I own my home. How long? I rent my home/apt.	0
0	Light Moderate Heavy	0
	Level of Security Clearance U.S. Citizen Non-U.S. Citizen My identity may be released to: Any employer All but present employer	
0	☐ WILL RELOCATE ☐ WILL NOT RELOCATE ☐ OTHER	0
0	EDN Databank	0
0	A DIVISION OF PLACEMENT SERVICES LTD., INC.	0

BUSINESS/CORPORATE STAFF

F Warren Dickson Vice President/Publisher Newton, MA 02158 (617) 964-3030 Telex 940573 Diann Siegel, Assistant

Peter D Coley Associate Publisher/ Advertising Sales Director Newton, MA 02158 (617) 964-3030 Stacey Vorias, Assistant

NEW ENGLAND Bob Sommer, Regional Manager 199 Wells Ave Newton, MA 02159 (617) 964-3730

STAMFORD 06904 George Isbell, Regional Manager 8 Stamford Forum, Box 10277 (203) 328-2580

ROSELAND, NJ 07068 Daniel J Rowland, Regional Manager Chris Platt, Regional Manager 103 Eisenhower Parkway (201) 228-8619 (201) 228-8620

PHILADELPHIA AREA Steve Farkas, Regional Manager 999 Old Eagle School Rd Wayne, PA 19087 (215) 293-1212

CHICAGO AREA Clayton Ryder, Regional Manager Randolph D King, Regional Manager Cahners Plaza 1350 E Touhy Ave, Box 5080 Des Plaines, IL 60018 (312) 635-8800

DENVER 80206 John Huff, Regional Manager 270 St Paul St (303) 388-4511

DALLAS 75234 Don Ward, Regional Manager 13740 Midway, Suite 515 (214) 980-0318

SAN JOSE 95128
Walt Patstone, Regional Manager
Bill Klanke, Regional Manager
Philip J Branon, Regional Manager
Mark Holdreith, Regional Manager
3031 Tisch Way, Suite 100
(408) 243-8838

LOS ANGELES 90064 Charles J Stillman, Jr Regional Manager 12233 W Olympic Blvd (213) 826-5818

ORANGE COUNTY/ SAN DIEGO 92715 Jim McErlean, Regional Manager 18818 Teller Ave, Suite 170 Irvine, CA (714) 851-9422

PORTLAND, OREGON 97221 Pat Dakin, Regional Manager Walt Patstone, Regional Manager 1750 SW Skyline Blvd, Box 6 (503) 297-3382

UNITED KINGDOM, THE NETHERLANDS, SCANDINAVIA Jan Dawson, Regional Manager 39A Bowling Green Lane London EC/1R/OBJ UK 44-1-278-2152 Telex: 28339

BELGIUM/FRANCE Robert Broekman American Publishers Representatives 4 Rue Robert de Flers 75015 Paris, France 33-1-46099595 Taley: 270F60

GERMANY/SWITZERLAND Wolfgang Richter Sudring 53 7240 Horb/Neckar West Germany 49-7451-7828; TX: 765450

Igal Elan Elan Marketing Group Neutor g 2, Box 84 1013 Vienna, Austria 43222-663012, 638461 SOUTHERN EUROPE Igal Elan Elan Marketing Group 13 Haifa St, Box 33439

13 Haifa St, Box 3343 Tel-Aviv, Israel Tel: 972-3-268020 TX: 341667

FAR EAST Ed Schrader, General Manager 18818 Teller Ave, Suite 170 Irvine, CA 92715 (714) 851-9422; Telex: 183653

TOKYO 160 Kaoru Hara Dynaco International Inc Suite 1003, Sun-Palace Shinjuku 8-12-1 Nishishinjuku, Shinjuku-ku Tokyo 160, Japan Tel: (03) 366-830 Telex: J2322609 DYNACO

TAIWAN
Owen Wang, Gen Mgr
Ace Marketing Inc
Box 26-578 Taipei, Taiwan
Republic of China
86-2-703-4272
Telex: 14142

KOREA Korea Media Inc Rm 110, A-11 Bldg 49-4, Hoihyundong 2-Ka, Chung-Ku CPO Box 2314, Seoul, Korea Tel: 82-2-755-9880 Telex: K26249

SINGAPORE Cheny Tan Associates 1 Goldhill Plaza No 02-01 Newton Rd Singapore 1130 Tel: 2549522 Telex: RS 35983 CTAL

PRODUCT MART Joanne Dorian, Manager 475 Park Avenue South New York, NY 10016 (212) 576-8015

CAREER OPPORTUNITIES/ CAREER NEWS Roberta Remard National Sales Manager 103 Eisenhower Parkway Roseland, NJ 07068 (201) 228-8602

Janet O Penn Eastern Sales Manager 103 Eisenhower Parkway Roseland, NJ 07068 (201) 228-8610

Dan Brink Western Sales Manager 2041 Business Center Dr Suite 109 Irvine, CA 92715 (714) 851-9422

Diann Siegel Boston Sales Representative Newton, MA 02158 (617) 964-3030

Maria Cubas Production Assistant (201) 228-8608

Cahners Magazine Division William Platt, President Terry McDermott, Executive Vice President Frank Sibley, Group Vice President Tom Dellamaria, VP/Production & Manufacturing

Circulation Denver, CO: (303) 388-4511 Sherri Gronli, Group Manager Eric Schmierer, Manager

Reprints of EDN articles are available on a custom printing basis at reasonable prices in quantities of 500 or more. For an exact quote, contact Joanne R Westphal, Cahners Reprint Service, Cahners Plaza, 1350 E Touhy Ave, Box 5080, Des Plaines, IL 60018. Phone (312) 635-8800.

New Instruments

(GP-IB) Programmable Amplitude and Frequency



Model 4503

The Model 4503 was designed for many applications such as meter calibration, audio frequency simulation, low level amplifier testing, strain gauge simulation and testing, transducer calibration, and frequency meter calibration.

Some of the major features are: All functions programmable via the IEEE-488 (GP-IB) BUS.

All functions can be manually controlled.
Outputs from 1 mVac to 120 Vac in five ranges.
Plus optional auxiliary 1000 Vac amplifier.
Resolution 1 ppm or six decades.
Microprocessor-assisted which simplifies the programming procedures.
Frequency bandwidth 30 Hz to 120 kHz.
Amplitude accuracy 0.04%.
Distortion better than 0.1%.

A 1000 Vac amplifier, Model 4200, is available as an add-on chassis.

Size: 3½ inches high and weighs only 15 pounds. Rack mounting is standard. Price: \$3,995 Availability: 60 days ARO

Engineering Contact: Bob Ross Tel: (617) 268-9696 CIRCLE NO 36

1000 Volt AC Amplifier



Model 4200

Very low cost AC voltage amplifier with a fixed gain of 100. Can be used to extend the output range of the EDC Model 4503, 100 Vac Calibrator, or used with AC voltage calibrators of most other manufacturers.

Specifically designed to use for the calibration of digital multimeters, digital and analog meters.

Range: 100 V to 1100 Vac, rms Input Voltage: 10 Vac, rms Fixed Gain: 100 Gain Accuracy: 0.05% Frequency Band: 40 Hz to 30 kHz Distortion: 0.2% of setting Dimensions: 7.0H x 19.0W x 13.8D inches Weight: 40 lbs.

Price: \$1995 Availability: 60 days ARO

Engineering Contact: Bob Ross
Tel: (617) 268-9696
CIRCLE NO 37
ELECTRONIC DEVELOPMENT CORP.
11 Hamlin St., Boston, MA 02127
Tel: (617) 268-9696
TLX: 951596 (ELECDEVCO BSN)

ADVERTISERS INDEX

Acopian Corp*
Advance Power Supplies Inc* 98
Advanced Micro Systems Inc 221
Advanced Microcomputer
Systems Inc
AIE Magnetics
Altera Corp
American Automation 78
AMP Inc150-151
Amplifier Research
Anritsu Corp
Avantek
Beta Automation
BICC-Vero Electronics Ltd 192
BP Microsystems
Bruel & Kjaer Instruments 21
Bruning Computer Graphics 147
Caddock Electronics Inc 219
Cahners Exposition Group 226
Calcomp54
California Scientific Software 224
Capital Equipment Corp
Carlingswitch 207
Catalyst Semiconductor Inc
Cherry Electrical Products Inc 23
Chomerics Inc 201
C&K Components Inc 6
Conversion Devices Inc 223, 224
Converter Concepts Inc 102, 103
CTS Corp
Cybernetic Micro Systems 222
Cypress Semiconductor
Daisy Systems Corp 64-65
Dale Electronics Inc
Dale Electronics Inc
Dale Electronics Inc
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209 DSP Development Corp 104
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209 DSP Development Corp 104 E H Titchener & Co 223
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209 DSP Development Corp 104 E H Titchener & Co 223 EIE Electronic Industrial
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209 DSP Development Corp 104 E H Titchener & Co 223 EIE Electronic Industrial Equipment** 130
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209 DSP Development Corp 104 E H Titchener & Co 223 EIE Electronic Industrial Equipment** Electronic Development Corp 239
Dale Electronics Inc
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209 DSP Development Corp 104 E H Titchener & Co 223 EIE Electronic Industrial Equipment** Electronic Development Corp 239 Electronic Trend Publications 230 Emulogic Inc 223 Endicott Research Group 144 E-T-A Circuit Breakers 222 Ferranti Integrated Circuits** 98 Ferranti ULA** 49 Force Computers Inc 28-29 4C Electronics 82 Fujitsu America Inc/Storage Products 121 Fujitsu Components of America Inc* 32 Fujitsu Microelectronics Inc* 14-15
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209 DSP Development Corp 104 E H Titchener & Co 223 EIE Electronic Industrial Equipment** Electronic Development Corp 239 Electronic Trend Publications 230 Emulogic Inc 223 Endicott Research Group 144 E-T-A Circuit Breakers 222 Ferranti Integrated Circuits** 98 Ferranti ULA** 49 Force Computers Inc 28-29 4C Electronics 82 Fujitsu America Inc/Storage Products 121 Fujitsu Components of America Inc* 32 Fujitsu Microelectronics Inc* 14-15 GE/Intersil 16-17
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209 DSP Development Corp 104 E H Titchener & Co 223 EIE Electronic Industrial Equipment** Equipment Corp 239 Electronic Development Corp 239 Electronic Trend Publications 230 Emulogic Inc 223 Endicott Research Group 144 E-T-A Circuit Breakers 222 Ferranti Integrated Circuits** 98 Ferranti ULA** 49 Force Computers Inc 28-29 4C Electronics 82 Fujitsu America Inc/Storage Products 121 Fujitsu Components of 32 Fujitsu Microelectronics Inc* 14-15 GE/Intersil 16-17 Grayhill Inc 187
Dale Electronics Inc
Dale Electronics Inc
Dale Electronics Inc 1 Data I/O Corp 206 Data Translation Inc 41 Detoronics 223 Digelec Inc 221 Digital Electronics Corp 213 Dow Corning 209 DSP Development Corp 104 E H Titchener & Co 223 EIE Electronic Industrial Equipment** Equipment Corp 239 Electronic Development Corp 239 Electronic Trend Publications 230 Emulogic Inc 223 Endicott Research Group 144 E-T-A Circuit Breakers 222 Ferranti Integrated Circuits** 98 Ferranti ULA** 49 Force Computers Inc 28-29 4C Electronics 82 Fujitsu America Inc/Storage 121 Fujitsu Components of 32 America Inc* 32 Fujitsu Microelectronics Inc* 14-15 GE/Intersil 16-17 Grayhill Inc 187 Hewlett-Packard Co
Dale Electronics Inc

Hyundai Electronic Industries Ltd 191
Industrial Devices Inc 208
Inmos Corp
In Power**
Intel Corp
International Recitifer
Interplex Technologies
ITT Pomona Electronics
JAE Electronics Inc
Kepco Inc
Kepco Inc
Ledex Inc
Linear Technology Corp
Marconi Instruments*
MathSoft Inc
Measurement Systems Inc
MicroSim Corp96
Micro Switch
Micro Ware
Micro Ware
Mini-Circuits
Laboratories 3, 4, 24-25, 181
Monolithic Memories Inc
Motorola Microcomputer MCD 92-93
Motorola Semiconductor
Products Inc 76-77, 101, 111
National Machine Systems
National Semiconductor Corp 44-45
NEC Corp152
NEC Electronics Europe**
Nova Tran Corp
Omation Inc222
Optimal Technology222
Otto Controls
Patton & Patton
Performance Semiconductor Corp 75
Philips Test & Measuring
Instruments Inc63
Philips Test & Measuring
Instruments Inc*
Dhiling Toot 9 Magazina
Instruments Inc**
Potter & Brumfield 185
Precision Monolithics Inc 145
Qua Tech Inc
Qualstar Corp
Raytheon Semiconductor Div 57
RCA Solid State Div 42-43, 158-159
Ridge Computers
Robinson-Halpern
Rockwell International
Rogers Corp 162, 223, 224
Rohde & Schwarz
Samtec Inc
SBE Inc
Scanbe, Div of Zero Corp
Schroff
Seiko Instruments
Siemens Components Inc* 199
Siemens Munich** 61
Signal Transformer Co Inc C4
Signetics Corp 144, 168, 176, 200,
210-211
Silicone Systems Inc90-91
Soltex Polymer 217

Sony Corp	. 196
Souriau	2-203
Spectrum Software	39
Sprague Electric Co30, 3	1, 73
Stag Microsystems Inc	18
Summit Electronics	33
Sunrise Electronics Inc	56
Switchcraft	. 127
Switchcraft	3-88
Teltone Corp	. 224
Texas Instruments Inc	. 126
Thomson	
Components-Mostek* 48-49, 6	30-61
Torin Engineered Blowers	. 205
Toshiba America Inc	26-27
Total Power Int Inc	. 223
Triangle Digital Equipment	. 224
Triplett/Penril	. 107
Universal Data Systems	C3
Valid Logic Systems Inc	66
Vectrix	. 119
Viking Connectors Co	. 109
Visionics Corp	. 222
Weigh-Tronix	. 148
Wilbrecht Electronics Inc	. 223
Wintek Corp222	, 224
Nyse Tech	. 146
Zilog Inc	. 183
Recruitment Advertising	

Digital	236
Dunhill of Indianapolis	
EG&G Special Projects	. 237
E-Systems Greenville	. 233
GE Federal & Electronic Systems.	. 232
GE Military Electronic Systems	. 235
Hampshire Personnel Service	. 231
Motorola Portable Products	. 231
Riker Personnel	. 231
Xetron Corp	. 234

*Advertiser in US edition

This index is provided as an additional service. The publisher does not assume any liability for errors or omissions.

^{**}Advertiser in International edition

LOOKING AHEAD

EDITED BY GEORGE STUBBS

Annual growth rate is 10.2% for rectifier market

The US market for diode rectifiers, a market valued at \$521.7 million in 1985, is expected to grow at an average annual rate of 10.2% for the next five years, according to the market-research company Venture Development Corp (VDC) of Natick, MA. By 1991, the value of US shipments of these products will be \$932.7 million. VDC cautions, however, that this market growth is contingent upon improvements in diode-rectifier technology.

Specifically, manufacturers are focusing on improvements in packaging. The performance levels of many rectifier products—particularly standard and fast-recovery types—are essentially similar and meet the needs of large OEMs. Ease of mounting, power dissipation, reliability, size, spacing, thermal characteristics, hermeticity, total device cost—all these factors are predominantly determined by the package.

Plastic packages are most popular in low- and medium-current applications, and, in 1985, rectifiers housed in plastic or epoxy packages accounted for 45% of all rectifier sales. These packages often cost less, consume less board space, and are easier to mount than other package types. Manufacturers are continuing to improve the reliability and power dissipation of plastic, and VDC expects rectifiers in plastic packages to continue making gains in market share through the rest of the decade.

Glass-packaged axial-lead rectifiers offer greater current-carrying capacity than plastic axial-lead types, and metal-packaged studmounted rectifiers dissipate more power and are more reliable. The former will see healthy growth into the next decade, though cost is an important limiting factor. The latter are bulky and difficult to mount, and growth in that market segment will be sluggish.

MILESTONES IN THE DEVELOPMENT OF MOLECULAR ELECTRONIC TECHNOLOGY

1990	DEMONSTRATION OF MOLECULAR-SCALE SWITCHES AND MEMORY ELEMENTS. COMPUTER MODELING OF MOLECULAR-SCALE CIRCUITS.
1991	DEVELOPMENT OF TECHNIQUES FOR PREDICTING THE 3-DIMEN- SIONAL STRUCTURE NEEDED TO MAKE MOLECULAR-SCALE DEVICES USING A POLYPEPTIDE SEQUENCE FOR A SPECIFIC FUNCTION.
1994	SOLUTION OF THE CONNECTOR PROBLEM (LINKING A KEYBOARD TO AN INDIVIDUAL MOLECULE).
1998	CONSTRUCTION OF A MOLECULAR-SCALE ELECTRONIC CHIP OR 3-DIMENSIONAL ARRAY.
2000	INITIAL SALES OF MOLECULAR ELECTRONIC DEVICES AND COMPUTERS.
2010	SALES OF MOLECULAR ELECTRONIC DEVICES AND COMPUTERS REACH \$1 MILLION.
2020	SALES OF MOLECULAR ELECTRONIC DEVICES AND COMPUTERS CONSTITUTE 1% OF THE TOTAL COMPUTER MARKET.
2050	SALES OF MOLECULAR ELECTRONIC DEVICES AND COMPUTERS CONSTITUTE 10% OF THE TOTAL COMPUTER MARKET.

(SOURCE: SEAI TECHNICAL PUBLICATIONS)

Molecular electronic devices to be commercial by 2000

According to several experts in molecular electronic technology, the development of that technology will yield computer modeling of molecular-scale circuits by 1990 and commercially available devices by the year 2000. The survey responses, collected and analyzed by Professor M Todd Jarvis of the Mississippi State University Department of Engineering and published by SEAI Technical Publishing (Madison, GA), also include predictions that sales of molecular electronic devices and computers will constitute approximately 1% of the total computer market by 2020.


Researchers in molecular electronics are seeking ways to significantly improve both computational densities and speeds. Some investigators believe that proposed chromophore chains for molecular chips could attain spacing improvements above the upper limits of silicon by a factor of 40. Other researchers see molecular electronics as issuing a new breed of analog computers for such applications as pattern recognition, correlations, and context-de-

pendent decisions. Another potential approach combines molecular technology with biosensors for such medical applications as bionic implantations.

Scientists are investigating two principal approaches to the construction of molecular electronic circuitry. One approach would employ synthetic materials, such as polymers or charge-transfer salts. The other approach would use biological polymers—primarily proteins. Whichever approach proves more feasible, the experts polled seemed to think, molecular-scale ICs would be available at a much lower cost per element than today's ICs.

The actual device structures proposed thus far look astonishingly like their counterparts rendered now in silicon. Beyond the visual similarities, however, the construction of molecular-scale electronic devices poses some special challenges and difficulties: In one area, for example, scientists will have to face problems associated with the use of different materials, and in another, they may even have to consider new methods of signal transport.

We're bringing down the price of moving up.



"VMEbus boards are just too damned expensive."

Tom Andersen CEO, SBE, Inc.

New price/performance for VME. If you're building VMEbus systems, or thinking about moving up to VMEbus systems, this is good news: SBE is entering the VMEbus market-place with two new boards. And new

price/performance standards for the industry.


SBE VCOM-8. A 10 MHz, MC68000-based communication board with eight RS-232-C serial ports. VCOM-8 is designed to handle data transfer rates up to 38.4K baud and to take over many of the tasks usually handled by the host operating system. VCOM-8 can function as either a terminal cluster controller for small to large systems, or, as a data concentrator for VMEbus systems. What's more, it's one of the few VME boards to fully meet the VME C.1 spec. The price? \$795 in 100's.

SBE VMEM-4. 4 Megabytes of dynamic RAM for VME. At a price that's more than simply competitive. This new VME memory board from SBE works equally well with 16-bit and 32-bit processors and supports

8-bit, 16-bit and 32-bit aligned transfers. Plus, 32-bit unaligned transfers that free programmers from boundary alignments, greatly simplifying program design. **A note on price:** Presently, 256K RAM prices are extremely volatile. We're quoting stable bare-board prices plus RAM at our lowest spot price. Call for quotes.

Aggressive volume discounts. When it comes to "build-or-buy," you'll find that SBE lowers the "build" boundary. Our experience in the manufacture of board-level products and tight in-plant cost controls allow us to remain a competitive supplier well into your volume production.

Better support. Our hardware and software engineers work with you to build better systems on better schedules. And we deliver within 30 days ARO.



No compromises. That's our company policy. No compromise in engineering design. No compromise in software support. No compromise in price/performance ratio. That's been our policy in Multibus boards. And now, it's our policy in VME.

Thinking VME? Call us. Today, we're your source for high performance VMEbus memory and communication boards. At highly competitive prices. Tomorrow, we could be your strategic partner in the design and implementation of next-generation VMEbus systems.

SBE, INC.
MICROCOMPUTER BOARDS AND SYSTEMS

2400 Bisso Lane, Concord, CA 94520 Toll Free: (800) 221-6458 In Calif.: (800) 328-9900 TWX: 910-366-2116 (SBE CNCD)

SBE, Inc. is a public company traded on the NASDAQ National Market System

How to get from dial tone to CTS with UDS' new 224A/D




Here's a new user programmable, full duplex 2400 bps modem that can handle the entire auto-dial and log-on sequence with a single keystroke! It's the UDS 224A/D - the intelligent version of our 224

It has all the advantages of our original 224, including V.22bis compliance at 2400 bps and Bell-compatible fallback rates of 1200 and 300 bps. In addition, it offers battery-backed

memory storage for 10 numbers and their logon sequences, keyboard or automatic dialing (pulse or tone), call progress monitoring and an impressive array of built-in test functions.

For detailed specifications, contact Universal Data Systems, 5000 Bradford Drive, Huntsville, AL 35805.

Phone 205/721-8000: Telex 752602 UDS HTV. NEW!



Universal Data Systems



MOTOROLA INC.

Information Systems Group

UDS modems are offered nationally by leading distributors. Call the nearest UDS office for distributor listings in your area. DISTRICT OFFICES: Apple Valley, MN, 612/432-2344 • Atlanta, GA, 404/998-2715 • Aurora, CO, 303/368-9000 • Blue Bell, PA, 215/643-2336 • Boston, MA, 617/875-8868 • Columbus, O, 614/895-3025 • East Brunswick, NJ, 201/238-1515 • Glenview, IL, 312/998-8180 • Houston, TX, 713/988-5506 • Huntsville, AL, 205/721-8000 • Issaquah, WA, 206/829-9600 • Livonia, MI, 313/522-4750 • Mesa, AZ, 602/820-8611 • Milwaukee, WI, 414/273-8743 • Mission Viejo, CA, 714/770-4555 • Mountain View, CA, 415/969-3323 • Richardson, TX, 214/680-0002 • St. Louis, MO, 314/434-4919 • Silver Spring, MD, 301/942-8558 • Tampa, FL, 813/684-0615 • Uniondale, NY, 516/222-0918 • Van Nuys, CA, 818/891-3282 • Willowdale, Ont, Can, 416/495-0008

CIRCLE NO 140

Created by Dayner/Hall, Inc., Winter Park, Florida

Imitation. The sincerest form of flattery.

We call Signal "The American Original." And we must be doing something right because our design innovations are being copied around the world.

While this imitation may be flattering to us, it could be extremely risky for you. After all, just because a transformer looks like Signal's doesn't mean it will perform like Signal's.

Our innovation, creativity and reliability are one-of-a-kind. We pioneered the high isolation split bobbin design.

Now our exciting new International Series takes another leap forward with a dual, high-temperature bobbin and insulating shroud that provides significantly better performance at lower costs than ever before. One-4-All™ and More-4-Less™ transformers are so reliable they meet – or surpass – every important international specification (UL, CSA, VDE and IEC).

We also introduced low-profile Flathead™ plug-in transformers. Our latest series, available in five sizes, is arguably the best in the industry. The innovative non-concentric windings eliminate the need for an electrostatic shield and feature



hum-bucking construction.

Beyond that, Signal has a full line of superior low power PC board transformers, as well as smaller-than-ever "2-4-1" Series, competitively-priced rectifier power transformers, chokes and industrial-grade step-up and step-down power isolation transformers.


We maintain significant levels of our stock transformers and sell direct – without a middleman to slow things down – or mark prices up. Even better, we can ship to you in quantity within just 48 hours. We call it our PRONTO service... and it's unique in the industry.

Just let our competition try to play "follow the leader" with that!

Of course, if we don't have a standard stock item that fits your needs, our custom engineering department will gladly quote your specific requirements. *PRONTO*.

But for you, it's easy to follow our lead. Simply send for our complete, free catalog by contacting: Signal Transformer, 500 Bayview Avenue, Inwood, NY 11696.

(516) 239-5777



Signal Transformer.

The merican Original.

An Insiko Company